Terms and Conditions of Use of Digitised Theses from Trinity College Library Dublin

Copyright statement

All material supplied by Trinity College Library is protected by copyright (under the Copyright and Related Rights Act, 2000 as amended) and other relevant Intellectual Property Rights. By accessing and using a Digitised Thesis from Trinity College Library you acknowledge that all Intellectual Property Rights in any Works supplied are the sole and exclusive property of the copyright and/or other IPR holder. Specific copyright holders may not be explicitly identified. Use of materials from other sources within a thesis should not be construed as a claim over them.

A non-exclusive, non-transferable licence is hereby granted to those using or reproducing, in whole or in part, the material for valid purposes, providing the copyright owners are acknowledged using the normal conventions. Where specific permission to use material is required, this is identified and such permission must be sought from the copyright holder or agency cited.

Liability statement

By using a Digitised Thesis, I accept that Trinity College Dublin bears no legal responsibility for the accuracy, legality or comprehensiveness of materials contained within the thesis, and that Trinity College Dublin accepts no liability for indirect, consequential, or incidental, damages or losses arising from use of the thesis for whatever reason. Information located in a thesis may be subject to specific use constraints, details of which may not be explicitly described. It is the responsibility of potential and actual users to be aware of such constraints and to abide by them. By making use of material from a digitised thesis, you accept these copyright and disclaimer provisions. Where it is brought to the attention of Trinity College Library that there may be a breach of copyright or other restraint, it is the policy to withdraw or take down access to a thesis while the issue is being resolved.

Access Agreement

By using a Digitised Thesis from Trinity College Library you are bound by the following Terms & Conditions. Please read them carefully.

I have read and I understand the following statement: All material supplied via a Digitised Thesis from Trinity College Library is protected by copyright and other intellectual property rights, and duplication or sale of all or part of any of a thesis is not permitted, except that material may be duplicated by you for your research use or for educational purposes in electronic or print form providing the copyright owners are acknowledged using the normal conventions. You must obtain permission for any other use. Electronic or print copies may not be offered, whether for sale or otherwise to anyone. This copy has been supplied on the understanding that it is copyright material and that no quotation from the thesis may be published without proper acknowledgement.

DESIGN AND FABRICATION OF A WAVEGUIDING ORGANIC DOUBLE HETEROSTRUCTURE LIGHT-EMITTING DEVICE

*A Milestone in the Development of an
Electrically Pumped Polymer Laser*

by

Colin Belton

A thesis submitted in partial fulfilment for
the degree of

Doctor of Philosophy

Trinity College Dublin

July 2002

DECLARATION

I declare that the work in this thesis has not been previously submitted as an exercise for a degree to this or any other university. The work described herein is entirely my own, except for the assistance mentioned in the acknowledgements and the collaborative work mentioned in the list of publications. I agree that Trinity College Library may lend or copy this thesis on request.

Colin Belton

Colin Belton

**PHYSICS DEPARTMENT
TRINITY COLLEGE DUBLIN**

Abstract

**DESIGN AND FABRICATION OF A WAVEGUIDING ORGANIC
DOUBLE HETEROSTRUCTURE LIGHT-EMITTING DEVICE**

*A Milestone in the Development of an Electrically
Pumped Polymer Laser*

by Colin Belton

Supervisor :

Professor Werner J. Blau
Department of Physics

The development of an electrically pumped polymer laser fabricated using simple solution processing would revolutionise the optical data storage and communications industry. In order to achieve this, a research strategy, aimed at producing a waveguiding double heterostructure device, is developed whereby the relevant physical properties of a large number of conjugated polymers are investigated. The measurement of the optical constants of a series of spin cast conjugated polymer and thermally evaporated small molecule films on silicon substrates was carried out. The optical constants are measured, by spectroscopic ellipsometry, from 0.75eV up to just below the bandgap of each polymer. The optical constants are then obtained by fitting a homogeneous Cauchy model to the ellipsometric data. The excited state absorption features of the polymers are also measured using Photo-induced absorption in tandem with doping of polymer solutions with FeCl_3 . Using the optical constant data the waveguiding behaviour of a double heterostructure device with edge emission is modelled using the well-established Beam

Propagation Method (BPM). The waveguide loss of double heterostructure devices is modelled for various device geometries and across the emission band of an experimentally prepared light emitting, waveguiding double heterostructure organic device. The emission characteristics of the experimental device compare favourably with results of the simulation based on the measured optical constants. These results have important implications for the design of future electrically pumped organic laser devices.

TABLE OF CONTENTS

1	INTRODUCTION	1
1.1	THE DAWN OF ORGANIC ELECTRONICS	3
1.1.1	<i>Technological Advantages of Organic Materials</i>	4
1.1.2	<i>Production of Organic Materials</i>	5
1.1.3	<i>Commercial Advantages of Organic Materials</i>	5
1.2	MOTIVATION FOR A POLYMERIC LASER	6
1.2.1	<i>Device Tunability</i>	7
1.2.2	<i>Power Savings</i>	7
1.2.3	<i>Broad Range of Emission Wavelengths</i>	7
1.2.4	<i>Integrated Polymer Communications Systems</i>	8
1.3	RESEARCH STRATEGY	9
1.3.1	<i>Waveguiding Double Hetero-structure devices</i>	9
1.3.1.1	Proposed Device Structure.....	10
1.3.1.2	Measurement and Utilisation of Material Properties	11
1.3.2	<i>Overview of Experimental Measurements</i>	12
1.3.2.1	Measurement of the Optical Constants.....	12
1.3.2.2	Excited State Absorption Measurements.....	13
1.3.2.3	Design and Fabrication of Double Hetero-structures.....	13
2	OVERVIEW OF OPTICAL PROPERTIES RELEVANT TO POLYMERIC AND MOLECULAR ORGANIC MATERIALS	17
2.1	POLYMERIC MATERIALS	19
2.2	NON-CONJUGATED POLYMERS.....	19
2.3	CONJUGATED POLYMERS	20
2.4	PHOTO-PHYSICS OF MOLECULAR ORGANIC MATERIALS.....	21
2.4.1	<i>Absorption</i>	21
2.4.2	<i>Relaxation</i>	24
2.4.3	<i>Luminescence</i>	25
2.4.3.1	Fluorescence	26
2.4.3.2	Phosphorescence	26
2.4.3.3	Delayed Fluorescence	27
2.5	PHOTO-PHYSICS OF POLYMERIC MATERIALS	27
2.5.1	<i>Absorption</i>	28
2.5.2	<i>Relaxation-Stokes Shift</i>	30
2.5.2.1	Spectral Relaxation	30
2.5.2.2	Structural Relaxation.....	31
2.5.2.3	Synopsis.....	31

2.5.3	<i>Luminescence</i>	32
2.6	ELECTRON LATTICE COUPLING - HUANG RHYS FACTOR	33
2.6.1	<i>Huang Rhys Factor</i>	33
2.6.2	<i>Strength of Electron-Lattice Coupling</i>	36
2.6.3	<i>Electron Lattice Coupling –Synopsis</i>	38
2.7	EXCITED STATES	38
2.7.1	<i>Singlet Exciton</i>	38
2.7.2	<i>Triplet Exciton</i>	39
2.7.3	<i>Polarons and Bipolarons</i>	40
2.8	ELECTRON-ELECTRON INTERACTION –THE MOLECULAR PICTURE	42
2.9	SU-SCREIFFER-HEEGER MODEL:- THE BAND PICTURE	45
2.9.1	<i>Degenerate Ground State Models</i>	45
2.9.2	<i>Non-degenerate Ground State Models</i>	47
2.10	VIBRONIC STRUCTURE AND DISTRIBUTION OF CONJUGATED SEGMENTS - SIGNATURES OF IMPROVED ORDER	50
2.10.1	<i>Signatures of Improved Order</i>	50
2.11	CONJUGATED POLYMERS AS LASER MATERIALS	51
2.11.1	<i>Definition of a Laser</i>	52
2.11.2	<i>Four Level Systems</i>	52
2.11.3	<i>Stimulated Emission Cross-section of Organic</i>	53
	<i>Materials</i>	53
2.11.4	<i>Tunability of Disordered Systems</i>	54
3	INTRODUCTION TO THE MATERIALS UNDER STUDY IN THIS WORK	59
3.1	INTRODUCTION TO SYNTHESIS OF CONJUGATED POLYMERS	61
3.2	GENERAL SYNTHESIS OF PPV'S	61
3.2.1	<i>Precursor Routes</i>	61
3.2.2	<i>Soluble PPV Derivatives</i>	62
3.3	SAMPLE PREPARATION – FILM FORMATION	64
3.3.1	<i>Spin Coating</i>	65
3.3.2	<i>Thermal Evaporation</i>	68
3.3.2.1	<i>Organic Layer Deposition</i>	68
3.3.2.2	<i>Metal Electrode Deposition</i>	69
3.3.3	<i>Sputtering of Metal Contacts</i>	69
3.3.4	<i>Film Thickness Measurement</i>	70
3.4	INTRODUCTION TO THE JENA PPV DERIVATIVES	71
3.5	OTHER MATERIALS FOR STUDY	77
4	SPECTROSCOPIC ELLIPSOMETRY OF CONJUGATED POLYMERS	81
4.1	INTRODUCTION.....	83

4.2	OVERVIEW OF SPECTROSCOPIC ELLIPSOMETRY	83
4.3	POLARISATION OF LIGHT AND THE OPTICAL ELEMENTS IN ELLIPSOMETRY	87
4.3.1	<i>Jones Vectors - Polarisation States of Light</i>	88
4.3.2	<i>Jones Matrices – Representing Optical Elements</i>	91
4.3.3	<i>Jones Matrix of the Sample</i>	94
4.3.3.1	Coordinate systems	95
4.3.3.2	The Fresnel Reflection Coefficients	98
4.3.3.3	Isotropic Bare Surface Index Calculation.....	102
4.3.3.4	Thin Film Reflection Coefficients	103
4.3.3.5	Multiple Film Reflection Coefficients.....	106
4.4	THROUGH THE ELLIPSOMETER –EXTRACTING USEFUL DATA	107
4.4.1	<i>Intensity Modulation of Light in the Ellipsometer</i>	107
4.4.2	<i>Measured Parameters in Ellipsometry - α and β</i>	108
4.4.3	<i>Extracting the Optical Constants</i>	110
4.4.3.1	Isotropic Cauchy Model.....	112
4.4.3.2	Uniaxial Model.....	114
4.4.3.3	Models to Interpret Surface Roughness or Inhomogeneous Films	116
4.4.3.4	Model for Interpreting Composite Films.....	116
4.5	ISOTROPIC MEASUREMENTS OF REFRACTIVE INDEX OF POLYMERIC MATERIALS	117
4.5.1	<i>Modelling of the Substrate</i>	119
4.5.2	<i>Modelling of Polymer Thin films</i>	119
4.5.3	<i>Inversion of the HT73 Polymer Data</i>	128
4.5.4	<i>Discussion of Isotropic Fitting Results</i>	129
4.6	UNIAXIAL MEASUREMENTS OF REFRACTIVE INDEX OF PMPV	132
4.7	OPTICAL CONSTANTS OF PMPV-CARBON NANOTUBE COMPOSITE THIN FILMS	133
4.8	CONCLUSIONS	141
5	EXCITED STATE ABSORPTION IN CONJUGATED POLYMERS.....	145
5.1	INTRODUCTION TO EXCITED STATE ABSORPTION	147
5.2	POLARON PAIRS IN CONJUGATED POLYMERS	147
5.2.1	<i>Formation of Inter-chain Polaron pairs</i>	148
5.2.2	<i>Recombination of Inter-chain Polaron pairs</i>	149
5.2.3	<i>Energy Transfer</i>	150
5.3	POLARON ABSORPTION IN DPOP-PPV - A CASE STUDY	152
5.3.1	<i>Photo-physics of DPOP-PPV in Solution and solid state</i>	153
5.3.1.1	Experimental Measurements of Photo-luminescence of DPOP-PPV	153
5.3.1.2	Discussion of Photoluminescence of DPOP-PPV	154

5.3.2	<i>ASE measurements on DPOP-PPV</i>	156
5.3.2.1	Waveguide Characterisation and ASE Experiment	156
5.3.2.2	Absence of ASE in DPOP-PPV	157
5.3.3	<i>Excited State Absorption in DPOP-PPV</i>	158
5.3.3.1	Photo-Induced Absorption Experiment	159
5.3.3.2	Temporal Response of PA Experiment	160
5.3.4	<i>Results of Photo-induced Absorption Experiment</i>	162
5.3.4.1	Polaron Pair Absorption Peaks in DPOP-PPV	162
5.3.4.2	Lifetime measurements of polarons in DPOP-PPV	163
5.3.5	<i>Discussion of experimental results on DPOP-PPV</i>	164
5.3.6	<i>Summary of the Case Study on DPOP-PPV</i>	165
5.4	POLARON ABSORPTION IN OTHER CONJUGATED POLYMERS	165
5.4.1	<i>Absorption due to doping of Polymers with FeCl₃</i>	165
5.4.2	<i>Doping Induced Absorption Measurements</i>	168
5.4.3	<i>Discussion of doping results</i>	173
5.4.4	<i>Summary of the Doping Induced Absorption Measurements</i>	182
5.5	CONCLUSIONS	183
6	DEVELOPMENT OF ORGANIC DOUBLE HETERO-STRUCTURE WAVEGUIDING DEVICES	187
6.1	INTRODUCTION	189
6.2	OVERVIEW OF ELECTROLUMINESCENCE IN CONJUGATED POLYMERS	189
6.2.1	<i>Charge Injection</i>	189
6.2.1.1	Electrical Contacts and Formation of Schottky Barrier	190
6.2.1.1.1	Neutral Contacts	192
6.2.1.1.2	Ohmic Contacts	192
6.2.1.1.3	Blocking Contact	193
6.2.1.2	Electrode Limited Current Flow	194
6.2.1.2.1	Thermionic Emission	194
6.2.1.2.2	Fowler Nordheim Tunnelling	195
6.2.2	<i>Charge Transport</i>	197
6.2.2.1	Physical Models for Electronic Conductivity in Organic Materials	197
6.2.2.1.1	Variable Range Hopping	198
6.2.2.1.2	Fluctuation Induced Tunnelling	202
6.2.2.1.3	The Poole-Frenkel Effect	202
6.2.2.2	Current Flow in Organic Devices	204
6.2.2.2.1	Limitations on Current Flow in Organic Materials	204
6.2.2.2.2	Unipolar Space Charge Limited Conduction	205
6.2.2.2.2.1	Trap Free Solids (Ideal case)	206
6.2.2.2.2.2	Traps Confined to Discrete Levels	207

6.2.2.2.3	Trap Distributions.....	209
6.2.2.2.3	Bipolar Space Charge Limited Conduction.....	210
6.2.3	<i>Exciton Formation</i>	211
6.2.3.1	Langevin electron-hole capture.....	211
6.2.3.2	Singlet-Triplet Ratio	212
6.2.4	<i>Exciton Recombination in Organic Devices</i>	213
6.2.4.1	Electro-luminescence Efficiency	214
6.2.4.2	Quenching of Luminescence in Organic Devices	214
6.3	REVIEW OF RECENT RESULTS FROM THE LITERATURE	216
6.3.1	<i>Electrically Pumped Lasing in Single Crystal Devices</i> ...	216
6.3.2	<i>Singlet Triplet Ratio in Organic Devices</i>	218
6.4	OPTICAL MODELLING OF HETEROSTRUCTURES	220
6.5	ELECTRICAL MEASUREMENTS ON ORGANIC MATERIALS	225
6.5.1	<i>Experimental Set up for Low Current Measurements</i>	225
6.5.2	<i>Important Considerations for Low Current Measurements</i>	226
6.5.3	<i>Unipolar Current Voltage characteristics</i>	228
6.5.3.1	Current Voltage Measurements for Electrons.....	228
6.5.3.2	Current Voltage Measurements for Holes	232
6.5.3.3	Discussion of Unipolar Current Voltage Measurements.....	236
6.6	WAVEGUIDING ORGANIC DOUBLE HETEROSTRUCTURE.....	239
6.6.1	<i>Fabrication</i>	240
6.6.2	<i>Device Characteristics of Heterostructure</i>	240
6.6.3	<i>Spectral emission from edge of device</i>	241
6.6.4	<i>Discussion of the Heterostructure Characteristics</i>	243
6.7	CONCLUSIONS	245
7	DISCUSSION OF PROSPECTS FOR POLYMERIC LASING	251
7.1	REVIEW OF RESEARCH CARRIED OUT IN THIS THESIS	253
7.1.1	<i>Refractive Index Measurement</i>	253
7.1.2	<i>Excited State Absorption of Polymers</i>	254
7.1.3	<i>Waveguide design and Hetero-structure Emission</i>	255
7.2	PROBLEMS TO BE OVERCOME	255
7.2.1	<i>Solvent Orthogonality</i>	256
7.2.2	<i>Polaron Absorption</i>	256
7.2.3	<i>Low Carrier Mobility</i>	257
7.3	SUGGESTIONS FOR FUTURE RESEARCH	258
7.3.1	<i>Deposition Techniques</i>	258
7.3.1.1	MAPLE.....	259
7.3.1.2	Crystal and Epitaxial Film Growth	260
7.3.2	<i>Device Structures to circumvent polaron absorption</i>	261
7.3.3	<i>Design of future polymers</i>	263

7.4 CONCLUSIONS	264
-----------------------	-----

APPENDICES

APPENDIX I – PROGRAM FOR MODELLING OF ELLIPSOMETRY RESULTS AND NONLINEAR REGRESSION	267
APPENDIX II – ANALYSIS OF UNCERTAINTY.....	281
APPENDIX III – LIST OF PUBLICATIONS	285

LIST OF FIGURES

Figure 1.1 Graph showing the increase in efficiency for Organic small molecule and polymer LEDs (yellow lines) versus their inorganic counterparts (blue lines). The dots show the colour of the emission from the devices. Also shown for comparison is the efficiency for some common lighting sources.....	3
Figure 1.2 (a) An example of a polymeric display fabricated in Trinity College Dublin. (b) Organic devices are mechanically flexible and can assume almost any shape. (Universal Display Corporation) (c) Organic devices are easily tuneable and even white light LEDs can be fabricated. (Vladimir Bulovic and co-workers, Princeton University).....	5
Figure 1.3 Schematic for the proposed organic double heterostructure waveguide emission device.	10
Figure 2.1 Schematic of sp^3 hybridisation. This results in a tetrahedral structure with a bond angle of 109.5° . Polyethylene is a saturated polymer made up of entirely sp^3 hybridised carbon, which results in its disordered morphology.	20
Figure 2.2 Schematic of sp^2 hybridisation. This results in a planar structure with a bond angle of 120° and a p_z orbital perpendicular to σ bonds in PPV. This allows a more ordered morphology and the delocalisation of π -electrons along the polymer backbone.	21
Figure 2.3 The $\pi-\pi^*$ transition in a carbon double bond is allowed since there is a change in the dipole moment. The electron is moved from the bonding π level to the anti-bonding π^* level. Lightly shaded area is positive wave-function while heavily shaded areas are negative wavefunction.	22
Figure 2.4 Schematic outlining Absorption process in organic materials. Optical Transitions take place vertically. The intensity is determined by the spatial overlap of the wavefunctions. Note the lattice distortion ΔQ upon excitation.	24
Figure 2.5 Photo-physics of Organic molecules. Upon excitation relaxation occurs down the ladder of vibrational levels until the zero point energy is reached. Radiative or non-radiative recombination occurs with the emission of fluorescence. Intersystem crossing to the triplet level can also occur, resulting in phosphorescence.....	25

Figure 2.6 DOS for free electron gas in materials of 0-D (quantum dot), 1-D (quantum wire), 2-D (quantum well) and 3-D. Note how the steps of a 2-D quantum well follow the 3-D band as shown. Typical polymeric absorption is shown with 1-D bandstructure.....	29
Figure 2.7 Relative intensities of different electronic-vibrational transitions change with increasing S. Oscillator strength is removed to peaks of increased phonon energy at the expense of the 0-0 transition. Bandshapes become smoother and more symmetrical at high S. Figure modified from (<i>Henderson and Imbusch</i>) pg 202.	34
Figure 2.8 Absorption spectra for several alkali-halides, showing increasing Huang Rhys factor. The Huang Rhys factor is least for LiF and greatest for NaCl. KCl and KBr have intermediate electron-lattice coupling. Data from (<i>Palik</i>).	35
Figure 2.9 Calculated PL spectra of PPV for $\lambda=0.15$ and $\lambda=0.20$. Note that oscillator strength is removed from 0-0 transition to lower energy peaks for increased electron-phonon coupling. Also shown is the experimental PL for PPV. All curves are normalised so that area under under each curve is the same. Figure modified from <i>Bronold et al.</i>	37
Figure 2.10 Schematic showing singlet and triplet excitons and the transitions associated with them. Note that the triplet energy level difference is smaller than the singlet energy level difference due to the exchange interaction.	39
Figure 2.11 a) Representation of the lattice distortion due to a single polaron charge on a polyacetylene chain. b) Representation the lattice distortion due to an exciton.....	41
Figure 2.12 Schematic showing the possible polaron and bipolaron energy levels and their associated transitions. +/- denotes the charge character of the species.....	41
Figure 2.13 <i>Trans</i> -Polyacetylene is an example of a degenerate ground state polymer. When the single and double bonds are interchanged the molecules energy remains unchanged ie. the molecule has two ground states and is known as being degenerate.....	46
Figure 2.14 PPV is a non-degenerate ground sate polymer. When the single and double bonds are interchanged the quinoid structure is produced. This structure has a higher energy associated with it.....	48
Figure 3.1 The sulphonium polyelectrolyte precursor route to PPV. Polymer 2 is spin cast onto the surface before thermal conversion to polymer 3.....	62

Figure 3.2 (a) 2,5 phenyl substituted PPV. This substitution has a limited effect on the backbone conformation. (b) PPV substituted on the Vinylene bond in the α and β positions. This substitution has a considerable effect on the backbone conformation.	64
Figure 3.3 Film Formation by Spin Casting process. 1. A substrate is affixed to the vacuum chuck 2. Polymer solution is pipetted onto the substrate. 3. Chuck is rotated at high speed, forming a polymer film on the substrate. 4. Sample is baked at 60°C in a vacuum oven.....	66
Figure 3.4 Surface profile, from phase contrast microscope, of a film spin cast from PVK in DCM (20g/l) on a silicon substrate.	66
Figure 3.5 Surface profile, from phase contrast microscope, of a film spin cast from a PVK in Chlorobenzene (20g/l) on a silicon substrate.	67
Figure 3.6 DPOP-PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem TM	72
Figure 3.7 HT73 absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem TM	73
Figure 3.8 HT94 absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem TM	74
Figure 3.9 MEH-DOO-PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem TM	75
Figure 3.10 Thianthrene PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated by Hyperchem TM	76
Figure 3.11 PFO absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem TM	77
Figure 4.1 A schematic diagram of a rotating polariser ellipsometer. The linearly polarised light, E_y , is rotating with angular frequency Ω (see red arrows). This means the resulting elliptical polarisation is also rotating with angular frequency Ω , which results in a linear polarisation, with oscillating amplitude E_d , when it passes through the analyser. It is the resulting modulated intensity, which is directly measured by the detector.....	85
Figure 4.2 (a) Generation of linearly polarised light from two orthogonal polarisations. (b) Generation of linearly polarised light from two orthogonal polarisations, by inducing a phase shift of $-\pi/2$ in the x -component of the polarisation.....	89

Figure 4.3 Schematic of the reflection of light from a surface, showing the coordinate systems for the laboratory, the incident light, and the reflected light.....	95
Figure 4.4 Schematic diagram of reflection and refraction of s & p-polarised light, showing the directions of the electric and magnetic fields for the incident, reflected, and refracted light.	98
Figure 4.5 (a) The Fresnel Reflection and Transmission coefficients, for a dielectric, as a function of angle of incidence. The point where the <i>p</i> -reflection coefficient passes through zero is known as the Brewster angle. (b) The nature of the phase change upon reflection Δ for dielectrics and for materials of increasing absorption.	101
Figure 4.6 (a) Multiple reflections of light in a single thin film. The index of refraction of the incident medium is n_1 , that of the film is n_2 , and that of the substrate is n_3 .(b) Schematic of two films stacked on a surface, including the various rays that must be taken into account to solve the problem by multiple reflections.....	103
Figure 4.7 Integrated signals actually measured in ellipsometric measurements. Signal is divided into four time “bins” of duration $\frac{1}{8}$ a polariser revolution.	108
Figure 4.8 Schematic showing the interaction of p-polarised light with the optical indicatrix of a spin-cast polymer film.	114
Figure 4.9 Ellipsometric and Regression results from a bare silicon substrate.....	119
Figure 4.10 Two separate measurements of $\tan\psi$ and $\cos\Delta$ for Thianthrene PPV are used to determine the standard deviation of ellipsometric measurements. The subtraction of the two measurements, away from significant features, are plotted as $\delta\tan\psi$ and $\delta\cos\Delta$ and the standard deviation of this determined.	120
Figure 4.11 Residuals of the fitting to $\tan\psi$ and $\cos\Delta$ Note that the value for χ^2 is inordinately high. There is still functionality remaining to be modelled in the ellipsometric data.	121
Figure 4.12 Ellipsometric Data and results from regression of the proposed models for Alq ₃	122
Figure 4.13 Ellipsometric Data and results from regression of the proposed models for DPOP-PPV.	123
Figure 4.14 Ellipsometric Data and results from regression of the proposed models for HT94.....	123
Figure 4.15 Ellipsometric Data and results from regression of the proposed models for MEH-DOO-PPV.....	124

Figure 4.16 Ellipsometric Data and results from regression of the proposed models for PFO.	124
Figure 4.17 Ellipsometric Data and results from regression of the proposed models for PBD doped into PMMA in a ratio of 3:1.	125
Figure 4.18 Ellipsometric Data and results from regression of the proposed models for Thianthrene PPV.	125
Figure 4.19 Ellipsometric Spectra for HT73. It was not possible to obtain a unique solution with the standard modelling procedure. Inversion with a film thickness of 66nm produces the optical constant spectra shown here. A curve smoothing procedure was used to remove the noise from the data. Note the appearance of an absorption band in the IR part of the extinction coefficient.	128
Figure 4.20 Ellipsometric Data and results from regression of a uniaxial model without absorption for PmPV. The ordinary (n_{ord}) and extraordinary (n_{ext}) are shown in red. The uncertainty in the refractive index is omitted here for the sake of clarity, although it may be calculated from the uncertainty in the Cauchy coefficients.	132
Figure 4.21 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (9% mass fraction) composite.	134
Figure 4.22 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (11% mass fraction) composite.	134
Figure 4.23 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (14% mass fraction) composite.	135
Figure 4.24 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (20% mass fraction) composite.	135
Figure 4.25 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (25% mass fraction) composite.	136
Figure 4.26 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (33% mass fraction) composite.	136
Figure 4.27 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (50% mass fraction) composite.	137

Figure 4.28 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (66% mass fraction) composite.	137
Figure 4.29 Refractive Index and Extinction coefficient of the guest nanotube inclusions, as measured from the 66% mass fraction sample.	139
Figure 4.30 Measurement of volume fraction of nanotubes in spin cast polymer films against the mass fraction of nanotube soot in original solutions.	140
Figure 5.1 (a) The photoluminescence of DPOP-PPV in various solvents. (b) Plot of integrated PL intensity against solvent viscosity for DPOP-PPV. The quantum yield for emission increases with solvent viscosity.	154
Figure 5.2 Experimental set up for determining (a) Waveguide Loss from a film on Fused Silica and (b) ASE detection from a similar waveguide on a thermally oxidised silicon wafer.	156
Figure 5.3 (a) Determination of waveguide loss in a DPOP-PPV waveguide on fused silica. (b) Example of edge emission from a DPOP-PPV waveguide pumped at $8.5 \times 10^5 \text{ W/cm}^2$ in the ASE experiment. No spectral narrowing is observed.	158
Figure 5.4 Experimental Set-up for Photo-Induced Absorption Experiment.	159
Figure 5.5 In-Phase and Quadrature Photo-induced Absorption Signals. A Doping Induced Absorption signal has been included for comparison.	162
Figure 5.6 Frequency Response of the In-Phase and Quadrature PA signals with theoretical fits for lifetime determination using equation 5.10.	163
Figure 5.7 Schematic showing the transitions present in a doped polymer with counter-ions in close proximity to the polymer chains.	166
Figure 5.8 (a) Doping Induced Absorption spectra for DPOP-PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.	168
Figure 5.9 (a) Doping Induced Absorption spectra for HT73 upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.	168

Figure 5.10 (a) Doping Induced Absorption spectra for MEH-DOO PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.....	169
Figure 5.11 (a) Doping Induced Absorption spectra for Thianthrene PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.....	169
Figure 5.12 (a) Doping Induced Absorption spectra for HT94 upon successive addition of FeCl_3 . (b) The polaron intensity increases in a step-like manner with the addition of FeCl_3 . This indicates the FeCl_3 molecules are breaking down polymer aggregates before doping the polymer chains.....	170
Figure 5.13 (a) Doping Induced Absorption spectra for PFO upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases with a power law dependance with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.....	171
Figure 5.14 (a) Doping Induced Absorption spectra for PmPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases with a power law dependance with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.....	172
Figure 5.15 (a) Doping Induced Absorption spectra for a 12.5% PmPV nanotube composite upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.....	172
Figure 5.16 (a) Overlap of Polaron absorption with the PL for DPOP-PPV. (b) Overlap of Polaron Absorption with PL for HT94.....	180
Figure 6.1 (a) Schematic of the band diagram for a neutral contact.....	191
Figure 6.2 Trap States in a semi-conducting polymer. This is the origin of hopping transport in conjugated polymers. Electrons “hop” between trap states of various distances or energies. Note transition A is of a higher energy change and shorter hopping distance whereas transition B is of lower energy change and longer distance.	198
Figure 6.3 The Poole-Frenkel Effect for a Coulomb Trap in a semiconductor. Under the application of an electric field the potential barrier for freeing a trapped electron decreases, allowing it to escape by thermal excitation, or tunnelling, for high applied fields.....	203

Figure 6.4 Schematic showing how Beam Propagation Method calculates the field at different points E_z on the grid. Also shown are the boundary conditions that the Helmholtz equation must satisfy due to changes in the refractive index.....	221
Figure 6.5 Optical Loss map for Heterostructure waveguide on gold as a function of guiding layer and cladding layer thickness. Calculations performed on cladding layer of $n=1.4537$ and guiding layer of $n=1.7142$ at a wavelength of 630nm.	222
Figure 6.6 Lossy Waveguide; Cladding layers are 100nm thick and guiding layer is 150nm thick.....	223
Figure 6.7 Low Loss Waveguide; Cladding layers are 0.6 μ m thick and guiding layer is 0.5 μ m thick.	224
Figure 6.8 Leaky Waveguide; Cladding layers are 0.6 μ m thick and guiding layer is 0.4 μ m thick.....	224
Figure 6.9 Schematic showing the Experimental Setup for Current-Voltage characterisation of Unipolar devices and Organic LED's (OLEDs). Luminance and Spectral Measurements are also taken for OLEDs.	226
Figure 6.10 Schematic showing the structure of a six-fingered device. Also shown is the Transverse emission which is normally measured as well as the edge emission which is measured from Double Heterostructure Waveguide devices in section 6.5.....	227
Figure 6.11 Log-log current voltage characteristics for Alq ₃ . Also included is the appropriate fitting to the data.....	228
Figure 6.12 Log-log current-voltage characteristics for DPOP-PPV. Also included is the appropriate fitting to the data.....	229
Figure 6.13 Log-log current voltage characteristics for HT73. Also included is the appropriate fitting to the data.....	229
Figure 6.14 Log-log current voltage characteristics for HT94. Also included is the appropriate fitting to the data.....	230
Figure 6.15 Log-log current voltage characteristics for MEH-DOO PPV. Also included is the appropriate fitting to the data.....	230
Figure 6.16 Log-log current voltage characteristics for Thianthrene PPV. Also included is the appropriate fitting to the data.....	231
Figure 6.17 Log-log current voltage characteristics for DPOP PPV. Also included is the appropriate fitting to the data.....	232
Figure 6.18 Log-log current voltage characteristics for HT73. Also included is the appropriate fitting to the data.....	233
Figure 6.19 Log-log current voltage characteristics for HT94. Also included is the appropriate fitting to the data.....	233

Figure 6.20 Log-log current voltage characteristics for MEH-DOO PPV. Also included is the appropriate fitting to the data.....	234
Figure 6.21 Log-log current voltage characteristics for PVK. Also included is the appropriate fitting to the data.....	234
Figure 6.22 Log-log current voltage characteristics for Thianthrene PPV. Also included is the appropriate fitting to the data.....	235
Figure 6.23 (a) The Current-Voltage characteristic for the ITO:PEDOT:HT73:Alq₃:Al device. (b) The transverse emission spectrum from the device, showing the overlap between the emission and the spectral response of the human eye. Also shown in the table are the values of the current density, luminance and device efficiency at 30 V.....	241
Figure 6.24 Graph showing the Edge and Transverse Emission from the Heterostructure waveguide. Also shown is the quotient of the Edge PL Intensity divided by the Transverse PL Intensity. Peak occurs at 655nm. Simulation Predicts Peak at ~630nm.....	242
Figure 6.25 Graph showing the Intensity of emission versus azimuthal angle for the edge emitted light from the heterostructure device.	243
Figure 7.1 Experimental Setup for Maple Deposition Technique. A UV laser pulse evaporates a frozen polymer solution from a rotating target. The evaporated polymer then diffuses onto the substrate, while the solvent is pumped away. (Copied from the Industrial Physicist, 6, 5 pg.20).....	259
Figure 7.2 Schematic showing the proposed device structure for a small area diode pumped channel waveguide; a possible structure to achieve an all-polymer laser device using current materials.	262

ACKNOWLEDGMENTS

If you know me, this is probably the first page that you've immediately turned to, to see if I've mentioned you or if I'm going to reveal any scandals that I may have learnt about you over the years. However, since this thesis is going to be added to the Trinity College library, I'm just going to adhere to standard practice and thank the people without whom this work would not have been completed, so Keith and Rob your secrets are safe!

I owe a debt of gratitude to my supervisor Prof. Werner Blau, who advised and supported me, while allowing me the freedom to follow my own lines of research. Dr. Paul Lane and Ashley Cadby, of Sheffield University, also deserve special mention for their help with Photo-induced absorption measurements. Dr. Eric Toussaere and Dr. Gerald Kranzelbinder, of ENS Cachan, were invaluable for their assistance in performing ellipsometry measurements. In Trinity College Dr. Diarmuid O'Brien and Kevin Kretsch also had an immense impact on the direction of my research. Sean O'Flaherty's assistance with the modelling of polymer structures in Chapter 3 is very much appreciated. Thanks must also go to Prof. Hans-Heinrich Hörhold, Anna Drury and Martin Cadek for providing materials as well as answering my interminable questions about Chemistry. Dr. Jonathon Coleman and Dr. Takeyuki Kobayashi also deserve my thanks for their contribution during the proof reading process. I must also thank the executive staff of the Physics Department for all their efforts on my behalf over the years.

Looking back over the last four years the best thing that I can say is that overall, I've had a sizzling good time. Much of the reason for this is due to the friends that I've picked up along the way:- The members of Group Bu (who never stopped asking "Is it done yet?"); Adam, Anna, Bernd, Brian, Catriona, Gavin, Grace, David (I had to break the alphabetical order here to keep Jean away from Grace!), Jean, Johnny, Kev, Manuel, Martin, Patrick, Rebekah,

Rob, Rory, Sakina, Sandy, Sean, Stef Hold, Stef Maier, Stephen (Slipper), Takey:- I hope you all stay in touch; My fellow coffee drinkers Keith, James, Adam and John (soon to be releasing a book of short lessons in Physics as written on paper napkins!); The Knights of the PMX (Padraig, Donal, Naoise and Theo) who had to live with me while I was writing up.

Finally, I must thank my parents for all of their support so far throughout my career.

DEDICATION

For my parents

*“Just because something doesn’t do what you planned it to do doesn’t mean it’s
useless”*

Thomas Alva Edison

- *“Why don’t you just go with the flow?”*
- *“What goes with the flow?”*
- *“I don’t know”*
- *“Dead Fish?”*

A conversation between Jason MacAteer and Roy Keane the day before Keane was sent home from the World Cup “in disgrace” by Irish team manager Mick McCarthy. (22 May 2002.)

Chapter 1

INTRODUCTION

1.1 The Dawn of Organic Electronics

Organic Materials are poised to transform the opto-electronic industry. Major electronics firms such as *Philips* and *Pioneer*, and smaller companies such as *Cambridge Display Technology*, *Universal Display*, and *UNLAX*, are investing heavily in these emerging materials to produce low cost and sometimes surprisingly high performance organic electronic and opto-electronic devices.

Organic electronics have already entered the commercial world. Multicolor automobile stereo displays are now available from the Japanese electronics company, *Pioneer* while *Sony* has recently produced a 13" OLED full colour display. It is possible that soon, portable and lightweight roll-up OLED displays will cover our walls, replacing the bulky and power-hungry cathode ray tube that has been the television standard for 50 years.

The momentum behind this industrial development is being driven by considerable advances made by academic and research teams around the world. Prototype polymer and small molecule LEDs are rapidly approaching

Figure 1.1 Graph showing the increase in efficiency for Organic small molecule and polymer LEDs (yellow lines) versus their inorganic counterparts (blue lines). The dots show the colour of the emission from the devices. Also shown for comparison is the efficiency for some common lighting sources.

the efficiencies of their in-organic counterparts (see Figure 1.1). Progress has not been limited to the field of display and lighting technology. Currently, photo-detectors (*Yu et al.*), photo-voltaic cells (*Sariciftci*), sensors (*Chen et al.*) and field effect transistors (*Sirringhaus et al.*; *Bao*) have all been demonstrated. The motivation for this work is that organic materials hold significant advantages over inorganic materials including technological, production and commercial aspects.

1.1.1 Technological Advantages of Organic Materials

Organic LED (or OLED) displays are made in much the same way as one makes LCDs. Starting with a glass substrate, a transparent conductor (typically Indium Tin Oxide (ITO)) is deposited. Any necessary patterning is carried out using industry-standard photolithographic techniques, followed by the deposition of organic layers and the cathode (which may also need to be patterned) using thermal evaporation. Finally, the display is encapsulated to prevent degradation by external attack from oxygen. The equipment required for these steps can be obtained directly from LCD industry sources. Polymeric LEDs (or PLEDs) are even easier to fabricate where the polymer layer is formed by spin casting from a polymer solution. Such solution processability is far simpler to carry out when compared to the epitaxial growth schemes currently incorporated in the fabrication inorganic optoelectronic devices.

According to the European Energy Agency Report of the 30 May 2002 “Energy consumption levels rose by 1.1% every year between 1990 and 1999 and are expected to continue increasing beyond 2010”. About 20% of the total power consumption is used for lighting. By the year 2020, electricity used for lighting could be cut by 50%, if solid-state alternatives replace current incandescent and fluorescent bulbs. Such a decrease in power consumption would lead to both energy and environmental savings. Initially inorganic devices are earmarked to fulfil this demand. However, OLEDs have some

significant advantages over in-organic devices due to their mechanical flexibility and the possibility of fabrication of white light emitting diodes (see Figure 1.2 (c)). However, considerable work still needs to be done with regard to device efficiency and lifetime.

1.1.2 Production of Organic Materials

Various chemical companies like *DuPont Chemicals*, *Bayer* and smaller start-up companies like *Covion*, are now producing conjugated polymers and organic molecules in quantities suitable for industrial use. This provides the basis of a symbiotic relationship between these companies and major electronics companies in the future where the development of products based on organic electronics becomes one of the dominant forces in industry. Materials can then be tailor made to suit specific opto-electronic requirements, making the development of new devices possible.

1.1.3 Commercial Advantages of Organic Materials

The equipment required to fabricate modern LCDs is quite expensive because of the size of the substrate. The vacuum processing of large glass substrates

Figure 1.2 (a) An example of a polymeric display fabricated in Trinity College Dublin. (b) Organic devices are mechanically flexible and can assume almost any shape. (Universal Display Corporation) (c) Organic devices are easily tuneable and even white light LEDs can be fabricated. (Vladimir Bulovic and co-workers, Princeton University)

(1 mm thick and 1 m² on a side (estimated cost per unit area $\sim$ €10,000 m⁻²)) at high throughput rates is a cumbersome technological feat. The capital required for a typical start-up plant may amount to as much as €½ billion. If flexible substrates could be used, lithographic printing techniques could be used, where the substrate is unwound from one roll, passed through the process stations, and wound up onto another roll analogous to a newspaper printing process, the handling equipment becomes cheaper and the process much faster (estimated cost per unit area $\sim$ €1 m⁻²). The commercial potential of processing such displays at high volume is such that the display industry could be revolutionised by the development of such a product.

Apart from the improvements in processing techniques, polymeric displays would also hold significant advantages over current TFT flat panel displays in that they possess a larger viewing angle, are potentially brighter (brighter displays can be used for outdoor viewing in sunlight) and can be bent into any shape (see Figure 1.2 (b)).

1.2 Motivation for a polymeric laser

Notably absent from the list of electronic and optical devices (see section 1.1) that can be made from conjugated polymers, is one of the most important devices for modern technology, the diode laser. While photo-pumped lasing has been observed in the solid-state by many groups (*Hide et al.*), electrically pumped lasing has yet to be observed (*Tessler et al.*), despite intensive efforts. The question then arises:- Aside from the scientific achievement, why is the development of a polymeric laser desirable?

Apart from the advantages of solution processing of devices, mechanical flexibility and the cost savings that organic devices hold over their inorganic counterparts, a polymer laser would hold other considerable advantages over the current technology. Specifically these are the possibility of device tunability, significant power savings, a wide range of emission wavelengths and the possibility of creating integrated polymeric communications systems.

1.2.1 Device Tunability

For current communication and computer systems there is a need for high-volume data transfer. Metal wires cannot satisfy this need because of low transmission speed and small signal bandwidth (information-carrying capacity). Information transmission by using optical fibres, which transport pulses of light instead of electricity, increases the bandwidth by a factor of 1,000. The bandwidth can be increased still further by the incorporation of wavelength division multiplexing (WDM) systems where multiple wavelengths of light are propagated down the fibre at the same time. The number of wavelengths that can be used is limited by the dispersion of the fibre. Provided the propagation loss of the fibre is low enough the broader the spectral range of the multiplexing system the greater the bandwidth increase. This provides an opportunity to take advantage of the broad possible device tunability of an infrared organic or polymeric laser. The broad gain spectra of organic lasers would be a great advantage in designing WDM systems with a large number of transmission channels.

1.2.2 Power Savings

A conjugated polymer laser possesses another possible advantage over current inorganic devices. The effective stimulated emission cross-section for GaAs is $\sim 10^{-16} \text{cm}^2$ (Hwang), while for polymers the same quantity can be as high as $\sim 10^{-15} \text{cm}^2$ (McGehee and Heeger). The stimulated emission cross section is a particularly important figure of merit when comparing laser materials as it effectively represents the gain per excited state. The fact that polymers can possess a cross-section for stimulated emission that is one order of magnitude greater than their inorganic counterparts means that ten times less excited states have to be created in order to achieve a laser above the threshold condition. This could result in significant operational power savings for conjugated polymer lasers running at significantly lower threshold currents.

1.2.3 Broad Range of Emission Wavelengths

Although considerable progress has been made in the development of inorganic LEDs and blue and other visible laser diodes (e.g GaN 390nm,

InGaAlP 635-660nm) and emitting in the visible spectrum, difficulties remain with regard to device lifetime and fabrication costs. The primary difficulty is the issue of obtaining epitaxial growth on cheap readily available substrates. These issues are highlighted in the GaN system where lattice matching at the GaN/substrate interface results in thread defects, which give rise to heat buildup inside the devices. This results in the degradation of both the metal contacts and the internal structure of the GaN crystal (*Lammers et al.*). Lasers emitting in the blue-green emission region could give rise to higher density optical data storage and reading. The maximum achievable storage density is limited by the lateral size of the read/write laser spot, which is itself limited by the wavelength of the laser ($\sim \lambda^2/2$). It is deemed that the use of a 400nm laser would give rise to a four-fold increase in storage density when compared with current optical data storage systems, which utilise a ~ 780 nm laser for reading.

Since polymers have a wide variety of different chemical structures with a broad range of peak emission lengths the possibility of obtaining solid-state laser diodes, emitting at any desired wavelength across the visible is very attractive. Polymer laser diodes could easily fill the role currently occupied by GaAs lasers in optical storage data systems. The low processing costs and the possibility of obtaining higher data storage would allow the creation of a new polymer laser driven data storage device.

1.2.4 Integrated Polymer Communications Systems

A polymer laser would also find applications in future Local Area Networks (LANs) and Fibre to the Home (FTH) networks.). Current 1.3 μm and 1.5 μm telecommunications technologies are too expensive for these applications, where optical paths are typically shorter than a few kilometres and the use of ultra low loss fibres is unnecessary. Polymer fibres have already been earmarked for FTH applications, where propagation losses are low enough at various transmission windows in the 510-650nm spectral region to be useful (*Lambkin et al.*). It is possible that conjugated polymers fibres could be used for optical amplification. The development of a polymeric laser diode would

provide the possibility of using an all-polymer communications system, which would be cheap to fabricate, install and maintain.

1.3 Research Strategy

The basic goal at the beginning of this research was to try to create an electrically pumped diode laser fabricated using conjugated polymers, or other organic components. As a result, a research strategy was outlined to use waveguiding, within a double hetero-structure device, to attain a long path length and thus to achieve significant single pass gain from an active medium with a low gain coefficient. The condition that only a low gain is required means that the threshold number of excited states necessary to achieve lasing is diluted, and so possibly obtainable. This is by no means a new idea, as this was the same method used to operate the first GaAs lasers at room temperature. In the following, the proposed device structure, as well as the necessary experimental measurements needed to implement this research strategy are summarised, to provide the reader with an overview of the basic theme of the thesis.

1.3.1 Waveguiding Double Hetero-structure devices

In 1962, the demonstration of a semiconductor diode laser by three independent groups (Hall, R. N. (General Electric), Nathan, M. I. (IBM) and Quist, T. M. (MIT)) sparked major research into the development of diode lasers. The first diode lasers were made from forward biased GaAs pn junctions and operated in pulsed mode with a threshold current of $100\text{kA}/\text{cm}^2$ at 70K. This performance was later improved by using a hetero-structure to improve the trapping of charge carriers in the active region of the device. These devices operated in pulsed mode with a threshold current of $100\text{kA}/\text{cm}^2$ at room temperature. Finally, the use of a double hetero-structure device achieved Continuous Wave (CW) operation at room temperature with a threshold current of $1\text{kA}/\text{cm}^2$. The double hetero-structure device was effective in lowering the threshold because both the carriers and the optical field were confined within the active area with a combination of trapping and

waveguiding. This was achieved by sandwiching a material of lower bandgap between two transport layers of higher bandgap.

The development of an organic waveguiding double hetero-structure device is the primary aim of the research summarised in this thesis. It is hoped that by developing a low propagation loss waveguide structure, within the confines of metal electrodes, that stimulated emission can be observed, even if only small gain coefficients can be obtained by electrical pumping. This is because the spontaneously emitted photons will then have a large path length and so will be more likely to interact with another excited state. The use of such a device should significantly decrease the threshold currents necessary for obtaining stimulated emission.

1.3.1.1 Proposed Device Structure

The proposed device structure for an organic hetero-structure is shown in Figure 1.3. The device consists of three organic layers, which are prepared by an appropriate combination of spin coating (see section 3.3.1) and thermal evaporation (see section 3.3.2). The anode and cathode should be chosen to obtain the lowest possible contact potential barriers for charge injection. The ideal charge (Electron Transport Layer and Hole Transport Layer in Figure 1.3) transport layers must also function as effective cladding layers. This means that the requirement for these layers is that they must possess high

Figure 1.3 Schematic for the proposed organic double heterostructure waveguide emission device.

carrier mobility and a large bandgap. The Emissive Layer should have a high quantum yield and demonstrate stimulated emission. The emissive layer should also possess a high refractive index (lower bandgap) combined with balanced charge carrier mobilities.

It is by no means a trivial procedure to minimise the propagation loss of such a device. The primary loss mechanisms which must be eliminated for such a device to succeed are charge induced absorption and metal electrode absorption. The materials should not have charge induced absorption in the the same spectral region as the emission, and the device should confine the optical field within the emissive layer away from the electrodes as is shown in the inset of Figure 1.3.

1.3.1.2 Measurement and Utilisation of Material Properties

As has just been seen, the materials requirements for the successful operation of double hetero-structure devices are somewhat diverse, encompassing specific electrical and optical characteristics, for each layer within the device. Since the materials that are available for this research are essentially new materials (see section 3.4), a complete physical characterisation of these materials needs to be applied.

The proposed strategy for the identification of materials suitable for use in a hetero-structure device is as follows:-

- The complete characterisation of the physical properties (optical constants, excited state absorption and electrical properties) of a wide range of materials of diverse chemical structures.
- The identification suitable materials for each component of the hetero-structure.
- The utilisation of numerical simulation (using the measured optical constants) to ascertain the optimal layer thicknesses for a low loss waveguide.
- The fabrication and testing of a double hetero-structure device.

The fundamental aspect of this strategy is that the physical properties of a wide range of materials with varied chemical structures be determined. This will give the maximum possibility of obtaining the best possible materials for a specific function within the hetero-structure.

1.3.2 Overview of Experimental Measurements

At this point, the experimental research carried out in this thesis is summarised, with consideration of the broad research strategy that has just been outlined. The physical parameters that need to be determined are as follows:- Optical Constants, Excited State Absorption and the Electrical properties (carrier mobility and free carrier density). When these properties have been determined, the procedure for design and fabrication of an organic hetero-structure device can be carried out.

1.3.2.1 Measurement of the Optical Constants

The primary aim of this research is to design and optimise an organic hetero-structure waveguide device, incorporating novel conjugated polymers. In order to achieve this, the refractive index dispersion across the emission spectrum of the polymers, within the hetero-structure, needs to be measured. The refractive index mismatch between the cladding and guiding layers is the critical parameter, which determines optical confinement of the optical field away from the metal electrodes of the hetero-structure. It is very important to have accurate values of the refractive index when optimising a waveguide, so that the optical loss, due to absorption by the metal electrodes, can be minimised.

Spectroscopic ellipsometry is used to measure the optical constants of the range of materials under study. Spectroscopic ellipsometry was chosen over other techniques, such as prism-film coupling, so that the optical constants could be obtained across a broad spectral range, including the emission spectra of all the polymers studied here.

1.3.2.2 Excited State Absorption Measurements.

Of great importance for a material in an electrically pumped laser is the excited state absorption that becomes apparent under extreme pumping conditions. A case study of an initially promising material, DPOP-PPV, is carried out in order to highlight the difficulties in producing suitable materials for polymeric lasing. The excited state absorption due to polarons (see section 2.7.3) for a variety of materials is then observed. This is of great importance, since polarons are the most populous species in an electrically pumped device. From the trends observed in the polaron absorption spectra of the materials the possibility of decreasing the polaron absorption of future materials, by designing more rigid chemical structures, is discussed.

1.3.2.3 Design and Fabrication of Double Hetero-structures

The electrical properties, such as mobility and free carrier density, are also important when fabricating a double hetero-structure device. The intrinsic carrier density and mobility are obtained from simple single layer unipolar devices. It is then reasonable to consider the behaviour of these materials in multi-layer bipolar devices, where light emission occurs.

The geometry of such devices is also important if low loss waveguides are to be fabricated. Using the measurements of the refractive index from the spectroscopic ellipsometry experiment, simulations of the waveguiding behaviour within double hetero-structure devices are carried out. The geometry for low loss waveguiding devices is obtained. However, due to the low intrinsic mobility of conjugated polymers it is not possible to fabricate a low loss waveguiding hetero-structure. The emission behaviour of a high loss electrically pumped waveguiding hetero-structure is then observed and the prospects for electrically pumped polymeric lasing are considered.

References

Bao, Z. (2000). "Materials and Fabrication Needs for Low-Cost Organic Transistor Circuits." Advanced Materials **12**(3): 227-30.

Bayer. <http://www.bayer-echemicals.com>.

Cambridge Display Technology. <http://www.cdtltd.co.uk>.

Chen, L., McBranch, D. W., Wang, H.-L., Helgeson, R., Wudl, F. and Whitten, D. G. (1999). "Highly sensitive biological and chemical sensors based on reversible fluorescence quenching in a conjugated polymer." PNAS **96**(22): 12287-12292.

Covion. <http://www.covion.com/index.html>.

DuPont Chemicals. <http://www.dupont.com/displays>.

Hide, F., Schwartz, B. J., Diaz-Garcia, M. A. and Heeger, A. J. (1997). "Conjugated polymers as solid-state laser materials." Synthetic Metals **91**(1-3): 35-40.

Hwang, C. J. (1970). "Properties of Spontaneous Emission in GaSa Junction Lasers. I. Densities of States in the Active Regions" Physical Review B **2**(10): 4117-4125.

[Although it is not strictly correct to define a stimulated emission cross-section for a band-like material such as GaAs, using figures for the threshold carrier concentration in the active region ($\sim 10^{18} \text{cm}^{-3}$) and the optical loss within the cavity ($\sim 100 \text{cm}^{-1}$) an effective stimulated emission cross-section can be obtained for comparison with conjugated polymers. Since the gain, g , at threshold must exceed the losses ie. $g \geq 100 \text{cm}^{-1}$, the effective stimulated emission cross section can be given by $\sigma_{SE} = g/N$ where N is the exciton concentration. This gives rise to the value of $\sigma_{SE} \approx 10^{-16} \text{cm}^2$ quoted in the text.]

Lammers, D. (2002). "Race toward blue laser picks up speed." EETimes available at <http://www.eetimes.com/news/97/966news/bluelaser.html>.

Lambkin, J. D., McCormack, T., Calvert, T. and Moriarty, T. (2002). "Advanced Emitters for Plastic Optical Fibre." Firecomms technical paper available at <http://www.66.129.71.182/Technology/Default.aspx>.

McGehee, M. D. and Heeger, A. J. (2000). "Semiconducting (Conjugated) Polymers as Materials for Solid-State Lasers." Advanced Materials **12**(20): 1655-68.

Philips <http://www.research.philips.com/InformationCenter/Global/FArticleDetail.asp?lArticleId=2270&lNodeId=13>.

Pioneer (Car Stereo). <http://www.pioneerelectronics.com/Pioneer/CDA/Common/ArticleDetails/0,1484,912,00.html>.

Sariciftci, N. S. (1999). "Polymeric photovoltaic materials." Current Opinion in Solid State & Materials Science 4(4): 373-8.

Sirringhaus, H., Tessler, N. and Friend, R. H. (1998). "Integrated optoelectronic devices based on conjugated polymers." Science 280(5370): 1741-4.

Sony (Organic Display) <http://www.sony.co.jp/en/SonyInfo/News/Press/200104/01-0418E/>.

Tessler, N., Pinner, D. J., Cleave, V., Ho, P. K. H., Friend, R. H., Yahiolu, G., Le Barny, P., Gray, J., de Souza, M. and Rumbles, G. (2000). "Properties of light emitting organic materials within the context of future electrically pumped lasers." Elsevier. Synthetic Metals 115(1-3): 57-62.

UNIAX. <http://www.uniax.com>.

Universal Display. <http://www.universaldisplay.com>.

Yu, G., Wang, J., McElvain, J. and Heeger, A. J. (1998). "Large-area, full-color image sensors made with semiconducting polymers." Advanced Materials 10(17): 1431-4.

Chapter 2

2.1 Polymeric Materials

Organic polymers are long, interconnected, covalently bonded chains of repeating units, making them the primary structural component of many materials. They are typically found in solid, liquid, or gaseous states, depending on their molecular weight and intermolecular forces.

OVERVIEW OF OPTICAL PROPERTIES RELEVANT TO POLYMERIC AND MOLECULAR ORGANIC MATERIALS

The optical properties of polymers are determined by their molecular structure and the way they interact with light. This includes absorption, scattering, and emission. The morphology of the polymer, such as its crystallinity and the presence of defects, also plays a significant role in determining its optical behavior. Highly ordered polymers, for example, often exhibit strong dichroism, where the optical properties vary depending on the direction of light polarization.

The optical properties of polymers are also influenced by their chemical composition. Conjugated polymers, which have alternating single and double bonds, are known for their strong absorption in the visible and near-infrared regions. This is due to the delocalization of π electrons along the polymer backbone, which creates a series of energy levels that can absorb photons. On the other hand, saturated polymers, which lack conjugation, typically have higher bandgaps and absorb light primarily in the ultraviolet region. The presence of functional groups, such as carbonyl or amino groups, can also modify the optical properties of a polymer by introducing additional absorption bands or changing the refractive index.

2.2 Non-conjugated Polymers

Non-conjugated polymers are those that do not have a continuous system of alternating single and double bonds. They typically have a higher bandgap than conjugated polymers, meaning they absorb light at shorter wavelengths. However, they can still exhibit interesting optical properties, such as fluorescence or phosphorescence, if they contain chromophoric groups. The optical properties of non-conjugated polymers are also highly dependent on their morphology and the presence of impurities or defects, which can act as energy transfer sites or quenchers.

2.1 Polymeric Materials

Organic polymers are long, one-dimensional macromolecules, made up of repeating identical building blocks consisting mainly of carbon, hydrogen, oxygen, sulphur and nitrogen atoms. Polymers can be thought of as one dimensional lattice structures with the polymer repeat unit as a basis. The molecular shape (conformation) and the way the molecules are arranged (morphology) in the solid state are important factors when considering the properties of polymers. The morphology of polymers is generally semi-crystalline with a mixture of both amorphous and randomly orientated crystalline regions. Regularly ordered rigid polymers e.g. *m*LPPP and *trans*-polyacetylene tend to be more crystalline. Disordered, flexible polymers e.g. *atactic*-polystyrene tend to be more amorphous.

The inherent disorder prevalent in these materials gives rise to numerous defects in the material, which in turn cause trap states in the bandstructure. Chemical impurities such as dopants and missing hydrogen atoms also cause sub-gap states. Due to the fact that polymers are large molecules the band structure is described as having a Highest Occupied Molecular Orbital (HOMO) for the valence band and a Lowest Unoccupied Molecular Orbital (LUMO) for the conduction band. This terminology will be used from this point forward. Polymers can be divided into two broad categories, non-conjugated or saturated polymers and conjugated or un-saturated polymers.

2.2 Non-conjugated Polymers

Chains of carbon atoms, which are sp^3 hybridised form non-conjugated polymers (see Figure 2.1). Each carbon is σ bonded to carbons on the chain and to side groups such as hydrogen atoms as in polyethylene. Due to the geometry of σ bonds the electrons are highly localised between the carbon atoms and have little effect on the conduction process. It is this high degree of localisation that results in these materials having a large bandgap.

Figure 2.1 Schematic of sp^3 hybridisation. This results in a tetrahedral structure with a bond angle of 109.5° . Polyethylene is a saturated polymer made up of entirely sp^3 hybridised carbon, which results in its disordered morphology.

Moreover, because these σ bonds bind the chain together, any excitation to a higher energy state (a $\sigma-\sigma^*$ excitation) cleaves a carbon-carbon bond in the polymer chain. Hence, due to the high degree of localisation and lack of π orbital overlap, non-conjugated polymers display all the properties of excellent insulators.

2.3 Conjugated Polymers

An organic conjugated polymer is a chain of carbon atoms, which are sp^2 hybridised. Each atom is left with one electron in a p_z orbital perpendicular to the backbone of the polymer. These orbitals overlap to form an extended π -molecular system along the polymer chain. This is depicted pictorially in Figure 2.2. The extended π -electron system permits carrier delocalisation along the chain, and so is one of the criteria for a conductor.

Intrachain electronic coupling is much stronger than coupling between separate molecules, and so these materials are considered as quasi-one dimensional systems.

Figure 2.2 Schematic of sp^2 hybridisation. This results in a planar structure with a bond angle of 120° and a p_z orbital perpendicular to σ bonds in PPV. This allows a more ordered morphology and the delocalisation of π -electrons along the polymer backbone.

2.4 Photo-physics of Molecular Organic Materials

The laws of quantum mechanics govern the photo-physical properties of organic molecules. In this section, the behaviour of light interacting with the molecular orbitals of organic molecules will be explored. The behaviour of a molecule after excitation then determines its luminescent properties, which make organics ideal candidates for laser materials. Consequently molecular photo-physics can be separated into the following three processes:-

- Absorption.
- Relaxation.
- Luminescence.

In general, the simple concepts discussed here can be extended to explain the photo-physics of conjugated polymers. However, the morphology of polymers gives rise to some unique polymeric photo-physical properties.

2.4.1 Absorption

The most intense electronic transitions of electrons within atoms or molecules are those caused by the interaction of the electric component of an

Figure 2.3 The π - π^* transition in a carbon double bond is allowed since there is a change in the dipole moment. The electron is moved from the bonding π level to the anti-bonding π^* level. Lightly shaded area is positive wavefunction while heavily shaded areas are negative wavefunction.

applied electromagnetic field with a dipolar distribution of charge in the system. An example of such a transient dipolar event is shown in Figure 2.3 for a carbon-carbon double bond. The excitation of a π electron leads to a redistribution of charge density, here the transfer of a π electron from the bonding orbital to the anti-bonding orbital. This involves the electron moving further away from the axis of the bond (*Atkins*). Such a transition is known as being dipole allowed. Note that the electronic transitions can only take place between discrete energy levels.

Electric dipole transitions can also occur if a vibration accompanies the oscillation of an electric dipole. These transitions lead to absorption spectra having more than one peak associated with a given electronic transition.

Each electronic energy level is split into a series of vibrational sub-levels. These levels are the series of quantised vibrations dictated by the vibrational wavefunctions within the molecular potential energy well of the molecule (see Figure 2.4). The potential energy well is a function of the classical “force constant” of the bonds in a molecule. The schematic shown in Figure 2.4 may be considered as an average of all the vibrations within the molecule. If the

molecular potential is modelled as a harmonic oscillator the energy, ε_n , of these vibrations is given by:

$$\varepsilon_n = (n + \frac{1}{2})\hbar\omega_o \quad [2.1]$$

for $n = 1, 2, 3, \dots$ and where

$$\omega_o = \sqrt{\frac{k}{\mu}} \quad [2.2]$$

where k is the “force constant” and μ is the reduced mass of the molecule. Note this assumes that the potential well of the molecule is a perfect parabola. It can be seen from Figure 2.4 that this breaks down at high energies of vibration.

The typical energy separation between vibrational levels is 0.05eV. This means that the vast majority of electrons will reside in the ground state at 293K ($kT \sim 0.025\text{eV}$).

The Franck-Condon principle (see Figure 2.5) dictates the probability of a transition between the vibrational levels of different electronic states, when a molecule is photo-excited. It says that:-

Nuclei have much more mass than electrons, which means that when an electronic transition takes place, the nuclei in the molecule are effectively stationary.

For a transition to be dipole allowed the excited electronic state is spatially offset from the ground state (see Figure 2.54). This is because the excited state is less tightly bound than the ground state.

The most probable transition occurs vertically from the initial ground state vibrational wavefunction that yields the largest overlap to the vibrational state with the upper electronic state. The appearance and shape of a vibrational structure in the absorption spectrum depends on the relative displacement,

Figure 2.4 Schematic outlining Absorption process in organic materials. Optical Transitions take place vertically. The intensity is determined by the spatial overlap of the wavefunctions. Note the lattice distortion ΔQ upon excitation.

ΔQ , of the potential energy curves of the ground and excited states expressed by the Huang Rhys factor (see section 2.6.1). The transitions from the lowest vibrational (0) level of the ground electronic state to the manifold vibrational levels (0, 1, 2... n) are labelled as 0-0, 0-1, 0-2...0- n transitions as in Figure 2.4.

The onset of these vibrations may also be thought of in a classical manner. If the molecular dipole comes under the influence of the electric field of incident light 'the initially stationary nuclei suddenly experience a new force field. They respond to the new force by bursting into vibration, and swing backwards and forwards from their original separation- which was maintained during the rapid electronic excitation.' (*Atkins*).

2.4.2 Relaxation

After the incident radiation has caused an electron to jump into a given vibrational state in the excited state, it may lose its vibrational energy, if the surrounding molecules are able to carry away the vibrational quanta. These vibrational quanta are known as phonons, and are manifested by an increase in temperature of the surrounding environment (*Strauss and Seelert*).

Figure 2.5 Photo-physics of Organic molecules. Upon excitation relaxation occurs down the ladder of vibrational levels until the zero point energy is reached. Radiative or non-radiative recombination occurs with the emission of fluorescence. Intersystem crossing to the triplet level can also occur, resulting in phosphorescence.

With small molecules, the vast majority of the electrons relax to the ground vibrational state after excitation. This happens on very a fast time scale of the order of 10^{-13} s (*Turro*), which is faster than any luminescence decay mechanism.

2.4.3 Luminescence

Luminescence is the result of the emission of photons after excitation due to energy absorption (*Atkins*). Two possible decay mechanisms for luminescence are fluorescence and phosphorescence. It should be noted that the energy absorption does not necessarily originate from photo-excitation but also energy from chemical or biochemical reactions (chemi-luminescence or bioluminescence) (*Waldemar and Cilento*) and may even be thermally activated (thermo-luminescence) (*Ausin and Rivas; McKeever*).

In general fluorescence dies out almost immediately ($\sim$ ns) after the exciting radiation is removed while phosphorescence lasts orders of magnitude longer (ms up to hours).

2.4.3.1 Fluorescence

Fluorescence is the radiative decay of excited singlet states. After reaching the lowest vibrational level one of the following processes can occur:

- Non-radiative decay; the surrounding molecules (solvent, air, substrate, etc.) dissipate the electronic excitation energy.
- Radiative decay; the emission of a photon.

The dominant decay process depends on the interaction of the excited molecule and its surroundings – a strong interaction supports the non-radiative decay. This has been shown in solution where the fluorescence intensity of terphenyl and anthracene depends on the overlap of its Raman spectrum with that of the host solvent (*Dhote et al.*).

There may be vibrational structure in the luminescence spectrum as illustrated in Figure 2.9. The spacing of the vibrational levels provides information about the “force constant” of the molecule in its ground state while the vibrational level spacing of the absorption spectrum provides information about the “force constant” in the excited state. If the force constants are similar, the fluorescence and absorption spectrum resemble each other obeying the rule of mirror symmetry.

Note that if the potential wells were identical no vibrational transitions would be dipole allowed. Only if there is any difference in the shape of the potential energy well and/or atomic displacement ΔQ in Figure 2.4, can vibrational transitions occur (see section 2.6).

2.4.3.2 Phosphorescence

Phosphorescence is the radiative decay of the triplet excited state to the singlet ground state. In contrast to fluorescence, phosphorescence requires that a change in the multiplicity of the excited state occur. This is labelled inter-system crossing (ISC). ISC to a triplet state can take place if the vibrational deactivation is not too fast and there is a nearby state of the triplet

system – see Figure 2.5. This usually requires a heavy atom (e.g. Pt), with many electronic levels, to be present in the molecule so that spin-orbit coupling is promoted (*McMurry*).

After ISC the vibrational deactivation continues down the ladder of levels of the triplet state (*Atkins*). At the ground vibrational state the electron is trapped since the T_1-S_0 transition is forbidden by selection rules (*McMurry*). However, it is weakly allowed because ISC was initially possible indicating that there is enough spin orbit coupling to break down the selection rule. The resulting radiative decay is extremely long lasting (10^{-4} - 10^{-2} s) and is known as phosphorescence.

2.4.3.3 Delayed Fluorescence

In order to consider all decay mechanisms the phenomenon of delayed fluorescence will also be considered. This is often confused with phosphorescence, because delayed fluorescence displays a longer lifetime than fluorescence. However, the emitted light that is from S_1-S_0 transitions and not the T_1-S_0 emission. Delayed fluorescence is caused by some intermediate non-radiative or long-lived state. This state then decays to form a singlet, which then decays radiatively. Examples of such a phenomenon are:-

- The excited molecule spreads over two molecules to another molecule creating an excimer (S_0S_1)^{*} if the molecules are identical or an exciplex if the molecules are different. The excimer/exciplex then disintegrates with the emission of fluorescence.
- The collision of two molecules in their triplet state can repopulate, by electron transfer, the excited singlet state of one of the molecules at the expense of the other. The newly revived singlet state then decays radiatively with the emission of fluorescence.

2.5 Photo-physics of Polymeric materials

The photo-physics of polymeric materials is now considered. It is important to distinguish between the degree of polymerisation and the conjugation

length. The degree of polymerisation describes the mean length of polymer chains regardless of the number of defects within the chain. The conjugation length (*Kuhn*), l_c , describes the length of the chain without any distortion disturbing the conjugation. Even non-planarity leads to a shorter l_c (*Graupner et al.*) due to the weaker overlap of the π -electron wavefunction (less delocalisation). In general, an excitation on a conjugated polymer extends only over a few repeat units. This state can be thought of in a similar way to the molecular excitations that have just been explored. However, conjugated polymers are macromolecules, which are subject to various morphologies and disorder. They are also designed to be quasi one-dimensional semiconductors. Their photo-physical behaviour will now be examined in more detail with emphasis placed on the difference between the photo-physical properties of polymers and small molecules.

2.5.1 Absorption

The absorption profile of a material can be expected to follow the basic shape of the density of states. The density of states (DOS) for materials of different dimensionality can easily be calculated (*Kittel*). The expected DOS, which scales with the absorption profile for materials of different dimensionality, is shown in Figure 2.6. The DOS are:

- 0-dim.: A sharp line.
- 1-dim : A discontinuity at the band-edge followed by $\sim 1/\sqrt{\epsilon}$ dependence at higher energies.
- 2-dim : A step function.
- 3-dim : $\sim \sqrt{\epsilon}$ dependence above the band-edge.

Consequently, polymer chains approaching one dimensionality could initially be expected to exhibit an asymmetric line shape with a singularity at the band

Figure 2.6 DOS for free electron gas in materials of 0-D (quantum dot), 1-D (quantum wire), 2-D (quantum well) and 3-D. Note how the steps of a 2-D quantum well follow the 3-D band as shown. Typical polymeric absorption is shown with 1-D bandstructure.

edge. In reality the singularity is never observed because of the following reasons:

- Distribution of conjugation lengths: all materials possess some distribution of the chain lengths, which tends to broaden spectral features.
- Deviation from 1 dim: Single polymer chains are not truly one-dimensional since they have a finite chain length and finite axial dimensions (see section 2.8).
- Lifetime broadening yields a Lorentz line shape feature, although this is smeared out by inhomogeneous broadening effects, due to the random distribution of electronic levels in conjugated polymers.

Nevertheless, the asymmetry is observed and increases by approaching one dimensionality. The $\pi-\pi^*$ transition of most conjugated polymers in the visible and near UV regions appears as a featureless band. In many oligomers, and some polymers, (e.g. LPPP) the absorption reveals a few maxima (see Figure 2.9).

Whether such a structure appears or not depends on the distribution of conjugation lengths, which is rather narrow in the case of oligomers and some

polymers like LPPP. However, PPV type polymers tend to have a shorter, broader distribution of conjugation lengths. Hence, the vibrational structure in the absorption spectrum of PPV's is smeared out and remains unresolved in absorption spectra (see Figure 3.6).

2.5.2 Relaxation-Stokes Shift

Just as in the case of small molecules, polymers also relax with the emission of phonons to the ground vibrational state of the excited electronic state. However, in polymers, the relaxed electronic state is itself lower in energy than the initially excited state. This results in larger Stokes shifts for polymers than for small molecules.

A Stokes shift is defined as the energy separation between the 0-0 absorption and the 0-0 emission peaks. This is not necessarily the separation between the emission and absorption maxima (*Bredas et al.*). The Stokes shift essentially indicates that emission takes place from an electronic state that is different from the one involved in the absorption process. In the case of conjugated polymers a Stokes shift can appear due to several effects.

2.5.2.1 Spectral Relaxation

The inherent disorder of polymeric materials leads to a random distribution of conjugation lengths. Since the local energy gap is dependant on the conjugation length, the polymer can be thought of as having a gaussian distribution, $\rho(\epsilon_g)$, with variance, σ , of bandgaps throughout the sample.

$$\rho(\epsilon_g) = \sqrt{2\pi\sigma^2} e^{-\left(\frac{\epsilon_g^2}{2\sigma^2}\right)} \quad [2.3]$$

Absorption takes place across this entire distribution, which leads to inhomogeneous broadening of the absorption band.

The subsequent spectral relaxation occurs when the excited states diffuse along the chain and become 'trapped' on those chain segments with the

longest effective conjugated lengths i.e. the excited states become concentrated at the lower energies of the distribution, $\rho(\epsilon_g)$. Consequently, subsequent radiative recombination occurs mainly at lower energies resulting in an asymmetric line-shape in the emission (*Bässler*). The longer conjugation length also contributes to improved vibronic structure in the emission, just as larger molecules would in the molecular case.

Consequently, spectral relaxation, due to the distribution of conjugation lengths produces:

- A red shift of the emission compared to the absorption (Stokes shift).
- A more pronounced vibronic structure in the PL, because transitions occur over a less randomised distribution of energy levels.
- The emission peak is sharper than the absorption peak.

Therefore, a narrowing of the distribution will yield decrease in the Stokes shift.

2.5.2.2 Structural Relaxation

Excited state geometry calculations predict that the excited state has a strong tendency towards a more planar structure than the ground state (quinoid geometry in section 2.9.2). This strong dependence of the structure on the promotion of an electron into the excited state leads to the potential energy wells of the ground and the excited state being different. This change in the environment of the electron means that phonons are created and is taken into account by the Huang Rhys factor – see section 2.6.1. Hence, structural relaxation promotes the appearance of vibrational structure in the PL spectrum.

2.5.2.3 Synopsis

It has been established from spatially resolved photoluminescence spectra using NSOM *Nguyen et al.* that polymers emit preferentially from one or two

specific points on the polymer backbone. This is indicative of the migration of states to these specific low bandgap points on the lattice before they give up their energy as light. Consequently, spectral relaxation is the dominant contributor to the Stokes shift and the emission of light from polymers. However, the Stokes shift in site selective fluorescence methods is most probably due to structural relaxation (*Harrison et al.*).

2.5.3 Luminescence

The excited species produced in polymers are the same as for small molecules. Fluorescence is usually the only radiative decay route. Phosphorescence is strongly disallowed in organic polymers, as there is not enough spin orbit coupling to prohibit transitions involving a change of multiplicity. This is a considerable barrier for polymer electro-luminescence as 75% of the excitons produced in organic light emitting diodes are thought to be triplets.

The appearance of a vibrational structure in the photoluminescence (PL) is a consequence of the effect of spectral relaxation and structural relaxation of the excited species (see Section 2.5.2). The process of spectral relaxation ensures that the state from which photons are emitted is considerably lower in energy than that which was initially excited. This means that the Stokes shift in disordered polymers such as PPV is generally quite large. Consequently, the self-absorption in these polymers is minimised, because the 0-0 emission transition is red-shifted from the 0-0 absorption transition.

It should be pointed out that while vibrational structure in absorption spectra are the result of an averaging of the entire polymer, the vibrational structure in fluorescence spectra are the result of specific emitting sites in the material where the conjugation length is longest. While this tends to aid the resolution of vibrational structure in PL spectra, the disorder in the PPV's precludes real resolution of vibrational structure. Hence, the emission from disordered PPV derivatives is generally a broad feature-less band.

From measurements on finite polyenes (*Kohler and Samuel; Kohler and Woehl*) it is well established that the energy of the $\pi-\pi^*$ transition of molecules decreases with increasing conjugation length. Hence, a decreasing bandgap ε_g means a longer conjugation length, which can be derived from the energy gap by applying the simple relation (*Kohler and Woehl*):

$$\varepsilon_g = a + \frac{b}{l_c} \quad [2.4]$$

where a denotes the energy gap for infinite l_c and b is a fit parameter. In the case of the polyenes l_c corresponds to the number of phenyl rings.

2.6 Electron Lattice Coupling - Huang Rhys Factor

Inhomogeneous broadening by spectral relaxation does not on its own account for the spectral width of the absorption and PL of conjugated polymers. Only by considering the structural relaxation of the polymer in tandem with the inhomogeneous broadening can the photo-physics be fully explained. The lattice distortion, which is responsible for structural relaxation is, directly related to the electron lattice coupling, quantified by the Huang Rhys factor.

2.6.1 Huang Rhys Factor

If there is no lattice distortion during photo-excitation the Franck Condon overlap of the vibrational wavefunctions $\chi(n_i)$ form an orthonormal set (*Henderson and Imbusch*):

$$\langle \chi(n_i) | \chi(n_j^*) \rangle = \delta_{i,j} \delta_{n,n^*} \quad [2.5]$$

where i, j indicate the vibronic levels and n, n^* indicate the ground and excited levels.

Figure 2.7 Relative intensities of different electronic-vibrational transitions change with increasing S . Oscillator strength is removed to peaks of increased phonon energy at the expense of the 0-0 transition. Bandshapes become smoother and more symmetrical at high S . Figure modified from (Henderson and Imbusch) pg 202.

Accordingly, the optical transitions between the various vibronic energy levels of the excited state and the ground state are forbidden, only the 0-0 transition would be allowed. In the case of increased lattice distortion, during photo-excitation, the 0-0 transition becomes less dominant (see Figure 2.7). The normalised intensity distribution I_{n_i} , of the phonon transitions $0 \rightarrow n_i$, is (Bredas et al.):-

$$I_{n_i} = \left| \langle \chi(n_i) | \chi(0) \rangle \right|^2 = \frac{e^{-S_i} S_i^{n_i}}{n_i!} \quad [2.6]$$

where S is the Huang Rhys factor. This is the energy of relaxation in units of the phonon energy $\hbar\omega_i$ (Henderson and Imbusch):

$$S_i = \frac{\frac{1}{2} M_i \omega_i^2}{\hbar\omega_i} (\Delta Q_i)^2 \quad [2.7]$$

where $\hbar\omega_i$ is the vibronic level spacing (phonon energy) and M_i is the reduced ionic mass of the mode Q_i . For large values of S , I_{n_i} tends towards a

Figure 2.8 Absorption spectra for several alkali-halides, showing increasing Huang Rhys factor. The Huang Rhys factor is least for LiF and greatest for NaCl. KCl and KBr have intermediate electron-lattice coupling. Data from (Palik).

Gaussian line-shape of half-width $\hbar\omega\sqrt{2S}$ (Henderson and Imbusch). The Huang Rhys factor can be calculated from equation 2.7 using the intensity ratio of adjacent vibronic transitions:

$$S = (n+1) \frac{I_{n+1_i}}{I_{n_i}} \quad [2.8]$$

The total Huang Rhys factor is the sum of all appearing vibronic modes i :

$$S = \sum_i S_i \quad [2.9]$$

and so the actual relaxation energy is:

$$E_{rel} = \sum_i S_i \hbar\omega_i \quad [2.10]$$

Equation [2.7] states that S is the average number of phonons, which are involved in the electronic transition. In addition S can also be estimated directly from the absorption and PL spectra of the material by measuring Δ ,

the energy difference, between the absorption and fluorescence maxima. S is then obtained by applying the formula (Reddy *et al.*):

$$S = \frac{\Delta}{2\hbar\omega} \quad [2.11]$$

where $\hbar\omega$ denotes the average phonon energy of the dominating vibronic mode.

The calculated absorption is shown in Figure 2.7 for different values of S . The vibrational mode is the same while the number of phonons creating the absorption band increases with S . There is a shift of oscillator strength at the expense of the 0-0 peak upon increasing S . Hence the phonon peaks in materials enjoying a large S produce a more symmetric, Gauss broadened, smooth band-shape. However, a small S favours a more resolved structure with a more pronounced 0-0 peak, which tends to produce a narrower band. The absolute intensity decreases to preserve conservation of energy.

The optical absorption of several alkali-halides is shown at low temperatures Figure 2.8. The absorption band of NaCl (large S) consisting of many phonons is smeared out while the few phonons creating the LiF absorption (small S) can be resolved. KCl and KBr show the vibronic structure dying out as S increases.

2.6.2 Strength of Electron-Lattice Coupling

For a small molecule, the excitation of a single electron has a large effect on the local bond order influencing the geometry. Consequently, the largest lattice distortions are expected to take place when the excitation is confined on small molecules. For polymers, where the excited state wavefunction is delocalised over N atoms, the change in bond order would be of the order $1/N$. Accordingly, disordered polymers with a short conjugation length will suffer a greater lattice distortion, than polymers with an ordered structure and an increased conjugation length.

Figure 2.9 Calculated PL spectra of PPV for $\lambda=0.15$ and $\lambda=0.20$. Note that oscillator strength is removed from 0-0 transition to lower energy peaks for increased electron-phonon coupling. Also shown is the experimental PL for PPV. All curves are normalised so that area under each curve is the same. Figure modified from *Bronold et al.*

The effect of electron lattice coupling on the PL in PPV was studied by *Bronold et al.* using lattice relaxation theory, which is based on the non-degenerate ground state SSH like model Hamiltonian (see section 2.9) but taking into account multimode effects. They calculate the PL in terms of the electron-phonon coupling constant, λ , given by:-

$$\lambda = \frac{2\alpha^2}{\pi t_o K} \quad [2.12]$$

where α is the electron lattice coupling constant, t_o is the π -electron hybridisation energy, and K is the σ -bond compressibility.

The results are summarised in Figure 2.9 showing the calculated PL for a relatively weak coupling constant of $\lambda=0.15$ and a stronger coupling constant $\lambda=0.20$. The inset illustrates the experimental result. In both experiment and theory the 0-0 transition dominates and a vibronic structure is clearly visible although the $\pi-\pi^*$ energy transition has been miscalculated. In the calculated PL for $\lambda=0.20$ the oscillator strength is shifted from the 0-0 vibron to higher

phonons producing a more symmetric band-shape. This is in good agreement with the results described previously, from *Palik*.

2.6.3 Electron Lattice Coupling –Synopsis

To sum up, it may be expected that:

1. The appearance of a vibronic structure requires a lattice distortion upon photo-excitation ($\Delta Q \rightarrow S$). The observation of vibronic structure is a clear signature of a change between the equilibrium positions of the lattice ions in the excited state relative to that of the ground state.
2. A large S value creates a relatively small vibronic spacing, which can easily be smeared out (by e.g. inhomogeneous broadening or additional vibrons) to give a smooth, symmetrical band-shape.
3. A dominant 0-0 transition indicates a small change between ground and excited state (*Bredas et al.*) and hence, a weak electron phonon coupling. An initially dominant 0-0 transition decreases with increasing S .
4. Short conjugation length produces greater S values resulting in increased oscillator strength at higher energies to the expense of the low energy regime.
5. Increased conjugation length tends to reveal the vibronic structure.

2.7 Excited States

As has been said previously, conjugated polymers are quasi one-dimensional semiconductors. This means that these materials possess a bandgap (see section 2.9) of between 1-3eV. The excited states of conjugated materials possessing such a bandgap are shown in Figures 2.10 and 2.11.

2.7.1 Singlet Exciton

Intra-chain singlet excitons are thought to be the only species responsible for PL (*Conwell*) in conjugated polymers. PL arises from the transition of an electron between the first excited state and the ground state of the exciton.

Figure 2.10 Schematic showing singlet and triplet excitons and the transitions associated with them. Note that the triplet energy level difference is smaller than the singlet energy level difference due to the exchange interaction.

A singlet exciton is the equivalent of an excited state in large molecules and is responsible for fluorescence. The exciton is strongly confined, and therefore, extends over only one or two repeat units (see section 2.8). This produces quantum levels in the gap that lie close to the HOMO and LUMO band-edges (see Figure 2.10) (*Pope and Swenberg*). The intensity of the PL is linearly dependant on excitation intensity, I_{Exc} , indicating a mono-molecular, ie excitonic, decay route. At high excitation intensities, the PL depends on $\sqrt{I_{Exc}}$ (*Agranovich et al.*) indicating a bi-molecular or bi-excitonic decay mechanism.

Charged excitations are believed to act as quenching centres for singlet excitons (*Pope and Swenberg*).

2.7.2 Triplet Exciton

The photo-excitation of triplet excitons in polymers is quite poorly understood. Direct evidence for a photexcited triplet exciton was already found in 1968 in anthracene (*Pope and Swenberg*). The energy difference

between the triplet state and the first singlet excitation is a direct measure of the interaction strength.

However, there is no easy way to measure the energy difference between the triplet and singlet levels since phosphorescence is forbidden in most polymers. In PPV, as well as in anthracene, non-radiative decay vacates any excited triplet states (*Pope and Swenberg*).

Within electroluminescent devices, the spins of the injected charges have random spin orientations resulting in a ratio of 3:1 (*Gymer*) between triplet and singlet generation by Coulomb capture. On the other hand, photo-excitation creates geminate charges, which never have the same spin orientation. This results in singlet excitons, which are responsible for PL.

As a consequence of these simple considerations, the theoretical upper limit for the quantum efficiency of photoluminescence is 100% in contrast to 25% for electroluminescence. However, as will be seen in section 6.3.2 new experimental evidence has recently emerged that this simple argument may not hold true in conjugated polymers.

2.7.3 Polarons and Bipolarons

The origin of the term “polaron”, for charged quasi particles, can be found in classical polar crystals where the associated charge i.e. an electron repels nearby electrons while attracting nearby nuclei resulting in a polarisation and hence distortion of the lattice in the vicinity of the charge. Furthermore, this accompanying cloud of lattice distortion causes an increased effective mass while decreasing the charge mobility.

In the case of organic polymers charge is localised on part of the backbone with an accompanying local rearrangement of the lattice see Figure 2.11 (a) for *IPA*. This strong electron lattice coupling is responsible for the existence of the quasiparticles (polarons, bipolarons (two charges of the same sign)) in

Figure 2.11 a) Representation of the lattice distortion due to a single polaron charge on a polyacetylene chain. b) Representation of the lattice distortion due to an exciton.

conjugated systems. Polarons in conjugated systems can even change the nature of the bonds from σ to π and vice versa via excitation and while travelling along the backbone. Consequently, the excited state often yields a more rigid structure such as the quinoid configuration in e.g. PPV (Figure 2.11 (b)). Even the neutral excited state (ie. exciton) shows a similar structural reorganisation to that of the polaron (Figure 2.11 (b)), because it is two

Figure 2.12 Schematic showing the possible polaron and bipolaron energy levels and their associated transitions. +/- denotes the charge character of the species.

separate charges bound to each other. This sometimes leads to the exciton being referred to as a “polaron-exciton”.

Due to the lattice reorganisation in the vicinity of a polaron, the electronic levels shift from the HOMO and LUMO to form two sub-gap levels symmetrically displaced about the mid-gap (see Figure 2.12). In the case of a bipolaron, the two like-charges have a repulsive interaction, which lowers the confinement resulting in deeper quantum levels within the gap (see Figure 2.12). The greater degree of relaxation in the bipolaron in comparison to the polaron can stabilise the coalescence of two polarons (P) to form a bipolaron (BP) at high polaron densities.

The photo-generation of these charged excitations depends upon the separation of charges between the chains. This means that the most effective way to generate these species is to excite the polymer with a pump beam polarised perpendicular to the chains (*Townsend and Friend*). These longer living charged species are known to be defect stabilised (*Graupner et al.*) and so their density increases with the density of chain defects. The long lifetime of polarons and bipolarons means that it is most likely for them to be observed in steady state PIA experiments. Their motion is trap limited and therefore their recombination through bi-molecular collision is temperature dependant as experimentally observed by *Woo et al.*

2.8 Electron-Electron Interaction –The Molecular Picture

The electron-electron interaction is mediated by Coulomb forces between charges within the solid. This results in the formation of bound electron-hole pairs (excitons).

An organic small molecule has a finite size within which an exciton is localised. Evidence for this is the strong electron lattice coupling found in the

emission from organic molecules. Hence organic small molecules are usually associated with the appearance of strongly bound excitons (binding energy $> kT = 25\text{meV}$ at 300K). Intersite coupling is responsible for the formation of bands. Weak intersite coupling in conjunction with a low dielectric constant favours the generation of strongly correlated electron-hole pairs upon photo-excitation while strong coupling leads to the formation of uncorrelated electron hole pairs.

Within polymers, investigations involving electro-reflectance and photoconductivity have established the excitonic nature of the lowest allowed optical transition of e.g. crystalline polydiacetylene.

There are three types of excitons (*Pope and Swenberg*):

- Frenkel exciton: The extent is within one molecular unit.
- Mott-Wannier exciton: The extent is over many molecular units.
- Charge Transfer exciton: The excitation is over a few molecular units.

Clearly, an exciton on a small molecule is a Frenkel exciton. It is informative to apply Mott-Wannier theory to organic polymers to ascertain the localisation of excitons on polymer chains. The Mott-Wannier exciton may be considered as a hydrogen-like bound state of an electron and a hole, producing a series of energy levels given by

$$\varepsilon_{ex} = \varepsilon_g - \frac{\varepsilon_b}{n^2} \quad [2.13]$$

with $n=1,2,3,\dots$, where ε_g is the energy gap, n is the principle the number of the orbital and ε_b is the binding energy, which is given by:-

$$\varepsilon_b = \frac{\mu}{m_p \epsilon_r^2} R_H \quad [2.14]$$

where μ is the effective mass of electron and hole ($1/\mu = 1/m_e + 1/m_h$), m_p is the proton mass, ϵ_r is the relative permittivity and R_H is the Rydberg constant (13.6eV). This means the exciton radius r is:-

$$r = \frac{4\pi\epsilon_0\epsilon_r\hbar^2}{\mu e^2} n^2 \quad [2.15]$$

Eq. 2.15 is used ascertain whether Mott-Wannier theory can be applied, if μ and ϵ_r is known. If the exciton radius is greater than the intermolecular spacing the electron is delocalised between molecules and may be considered to be a Charge Transfer or Mott-Wannier exciton.

Gomes da Costa and Conwell have applied this theory to PPV with the parameters $\mu_{\parallel} = 0.0421m_e$, $\mu_{\perp} = 2.66m_e$, $\epsilon_{\parallel} = 8$, $\epsilon_{\perp} = 3$ parallel and perpendicular to the polymer chain. This gives $r = 2\text{nm}$ along the chain and 0.4nm transverse to the chain with an exciton binding energy of 0.4eV . The high binding energy and degree of localisation indicates a molecular character to the system, resulting in strong electron-hole coupling.

Calculations involving electron-electron coupling have been performed for PPV and it's oligomers (*Shuai et al.*; *Beljonne et al.*). They have predicted a considerably more localised triplet exciton than singlet exciton because of the reversed sign of the exchange energies. The triplet exciton has a binding energy of 0.65eV .

It is now established that the modelling of higher energy excitations is only realistic in models that include electron-electron interactions. Thus, the UV absorption spectrum of e.g. PPV can be described using configuration interaction methods (*Cornil et al.*) or by Pariser-Parr-Pople methods (*Chandross et al.*).

Excitons are mobile within the solid by hopping between sites and so transfer excitation energy without the movement of charge. Singlet Excitons may hop

either by tunnelling or by the resonant Forster energy transfer process (*Forster (1946 and 1948)*) whereas triplet excitons are restricted to the tunnelling mechanism (*Dexter; Ermolaev*).

Excitons can even form Bloch waves when interacting with adjacent molecules (exciton band). Significant electron phonon interaction can cause a loss of its coherence and hence restrict the motion of the exciton to the above mentioned hopping mechanism.

Photo-excitation into an excitonic state is supposed to reveal a symmetric lineshape – in contrast to the band picture where the absorption follows a $1/\sqrt{\epsilon}$ (see above). Actually there is a symmetric absorption for some molecules like e.g. polydiacetylene. However, many other important polymers reveal an asymmetric absorption band according to the band picture.

2.9 Su-Schrieffer-Heeger Model:- The Band Picture

In 2000, the Nobel Prize in Chemistry was awarded to Heeger, McDiarmid and Shirakawa. This was in essence for their work in bringing polymeric materials to the fore as semi-conducting materials for device applications. A large volume of this work was the development of a theoretical model, which concerns the appearance of a band-like structure in polymers. Due to the nature of quasi-particles in conjugated polymers, the theory predicts different results for degenerate and non-degenerate ground state materials.

2.9.1 Degenerate Ground State Models

A degenerate ground state polymer is one for which there are two possible chemical structures that have the same energy (see Figure 2.13). For the polymers described here any structure whose energy remains invariant when the single and double bonds are interchanged is considered to have a degenerate ground state.

In 1979 Su, Schrieffer and Heeger (*Su et al. (1979 and 1980)*) introduced a theoretical model (SSH model), which is able to describe a degenerate ground

Figure 2.13 *Trans*-Polyacetylene is an example of a degenerate ground state polymer. When the single and double bonds are interchanged the molecules energy remains unchanged ie. the molecule has two ground states and is known as being degenerate.

state one-dimensional carbon chain such as *trans*-polyacetylene within a single particle approximation.

The theory takes into account:

- Electron – phonon coupling

But neglects

- Electron-electron interaction

This early model predicts that a dimerisation, u_0 , (Peierls; Su et al. (1979 and 1980)) of the polymer chain results in the appearance of an energy gap:

$$\varepsilon_g = 8\alpha u_0 \quad [2.16]$$

where α is the strength of electron-phonon coupling. This appearance of an energy gap means that the polymer becomes a semiconductor.

Assuming a moderate electron-phonon interaction, electrons with energies close to the gap are generally involved in dimerisation. This allows a

linearisation of the energy curve yielding the continuum model (TLM) (*Takayama et al.*).

It emerged that the boundary conditions play a major role, which was first reported by *Kivelson and Heeger* in 1985. Solutions of this model predict two species:

- Solitons
- Polarons

Both species are deemed to be quasi-particles since they reveal a finite spatial extent according to their spatially restricted lattice distortion.

The creation of a soliton pair is associated with the appearance of an energy level in the middle of the band gap. These two soliton states are associated with non-bonding π states (*Heeger et al.*), which are manifested as a single state exactly halfway between the HOMO and LUMO bands. As has been seen a polaron produces a symmetric shift of two levels from the HOMO and LUMO band towards the centre of the gap. In contrast to the soliton level the polaron levels remain close to the band edges. Since the energy difference between these levels and the band edges is related to the confinement of the defect species by lattice deformation, a soliton is considerably more localised than a polaron. Both of these quasiparticles are mobile on the chain.

The minimum energy for the creation of a soliton pair is $2/\pi\epsilon_g$, which represents twice the energy of a single soliton. The creation energy of a single polaron $\sqrt{2}/\pi\epsilon_g$ is higher compared to that of a single soliton $1/\pi\epsilon_g$. Consequently solitons are energetically preferred to polarons in a degenerate ground state system.

2.9.2 Non-degenerate Ground State Models

A non-degenerate ground state polymer is one, which only has one chemical structure in its ground state. In contrast to degenerate ground state polymers,

Figure 2.14 PPV is a non-degenerate ground state polymer. When the single and double bonds are interchanged the quinoid structure is produced. This structure has a higher energy associated with it.

when single and double bonds are interchanged an increase in the energy of the polymer occurs. This can be seen in Figure 2.14 for PPV, which, upon bond interchanging yields the quinoid structure, with an increase in molecular energy.

A great disadvantage of early SSH models is that they were only applicable exclusively on degenerate ground state systems like *trans*-polyacetylene, which are very rare among conjugated polymers. Hence, in 1981, *Brazovski and Kirova* extended the theory to include non-degenerate systems by adding an external potential. The predictions of this improved SSH model do not alter the results concerning degenerate systems while the results in terms of the non degenerate systems are the appearance of

- Stable polarons.
- Stable bipolarons (doubly charged polarons).

Consequently, it is energetically favourable for model non-degenerate systems such as PPV, PPP and LPPP to exhibit polarons and bipolarons upon photo-excitation instead of the solitons, which are preferred in degenerate systems.

The existence of stable polarons and bipolarons accompanied by symmetric subgap states in non-degenerate ground state polymers was confirmed by the theoretical model (FBC) of *Fesser et al.*, using the FBC model. Both non-interacting electron continuum band models are not consistent with the observed relative transition probabilities (absorption intensities). This is known as the “intensity anomaly”.

Shimoi et al. have calculated the stabilities and the electronic transitions of polarons and bipolarons using a Peierls-Hubbard Hamiltonian (SAH model). This model takes into account both electron-phonon coupling and electron-electron interaction terms. According to this model, electron-electron interactions stabilise two polarons in comparison to one bipolaron. Bipolarons have been observed in conjugated polymers in contrast to this prediction.

In conclusion, it may be said that polarons as well as bipolarons are inherently stable in polymers of degenerate ground state while they are the only stable charged excitation in polymers of non-degenerate ground state.

The SSH Hamiltonian has been applied to PAs, Polythiophenes, PPVs, PPPs and LPPPs. While the overall picture of the optical properties of the quasi particles in polymers is becoming clearer, there remain some issues to be addressed:-

- The prediction of transition intensities.
- The stability of polarons with respect to bipolarons.

One aspect of conjugated polymers, which has yet to be incorporated into these models, is that of the disorder present in polymeric chains. It may well be that the trap distribution due to disorder may explain the anomalous predictions in current models.

2.10 Vibronic Structure and Distribution of Conjugated Segments - Signatures of Improved Order

When the potential curve of the excited state differs from the ground state the Huang Rhys factor is non-zero indicating electron-phonon coupling. As has been said the distribution of conjugated segments leads to a number of different gap values resulting in less sharp absorption. Therefore, a narrower distribution of conjugated segments results in a well-resolved vibronic structure in the absorption spectrum.

2.10.1 Signatures of Improved Order

In 1991 films of “improved PPV” were synthesised by *Holmes* using a new precursor mechanism. The PPV is termed ‘improved’ because it displays the following signatures of improved order over its predecessor (*Halliday et al.*; *Pichler et al.*):-

- A red shift of the absorption and a Stark Effect, which is five times greater in magnitude - both indicating a longer l_c .
- Electron diffraction measurements display ring like patterns, associated with diffraction from the randomly orientated microcrystalline regions within the polymer. The line broadening of the $0\bar{1}3$ ring reflection is associated with values for the intra-chain coherence length reaching $90\text{\AA}$ (cf. $50\text{\AA}$ for standard PPV) and inter-chain coherence lengths of $45\text{\AA}$ (cf. $60\text{\AA}$ for standard PPV).
- No bipolarons – indicating fewer defects since they are stabilised in the standard material by chain defects (*Woo et al.*).

Holmes used a precursor with rigid rod conjugated segments connected by flexible spacer groups to achieve a more ordered material which has a longer effective conjugation length due to the rigid frame structure. The final polymer was then formed after thermal conversion in the presence of acid.

The improved conjugation length of the PPV results in the following spectral information:-

- A well resolved vibronic structure- not only in emission (PL) but also in absorption.
- A dominant 0-0 transition in PL and absorption in strong contrast to standard PPV.

Another way to obtain PPV of increased order is by stretch orientation experiments as *Hagler et al.* achieved with blends of MEH-PPV and ultrahigh- molecular weight polyethylene (UHMWPE). They observed the following in their absorption and emission spectra at 80K:

- Sharpening of the vibronic structure
- Redistribution of spectral weight into the 0-0 phonon line
- A red shift of the absorption compared with the absorption of unorientated spin cast films.

The oriented MEH-PPV/UHMWPE blend loses its vibronic structure upon heating to 300K. There is also a clear blue shift in the absorption, indicating a shorter conjugation length. This is attributed to temperature activated phenylene ring torsional oscillations, which reduce the π -conjugation along the chain. At low temperatures, the fast transfer of vibronic energy to the surrounding molecules inhibits these phenylene ring oscillations, which favours an increase in the conjugation length and a better-resolved vibronic structure.

2.11 Conjugated Polymers as Laser Materials

Although the optical properties of polymers have now been examined in some detail, their suitability as laser materials has yet to be discussed. This will be done by defining what a laser is and then specifying the suitable properties of a material for lasing.

2.11.1 Definition of a Laser

A laser is an acronym for Light Amplification by Stimulated Emission of Radiation. This essentially summarises the operation of a laser. Light is amplified using stimulated emission as it passes through an excited volume of the laser material.

As well as the phenomenon of stimulated emission, it is necessary to provide a mechanism of *optical feedback* to generate laser output, by the use of a resonant cavity. This will also require a suitable path length through the material, to obtain the necessary optical gain, via stimulated emission and overcome the losses within the resonant cavity.

Unlike processes such as Amplified Spontaneous Emission, laser action requires a population inversion to be observed. Indeed, it is necessary to distinguish between the process of lasing and other processes of optical gain. A laser device will display all of the following properties;

- The presence of a well defined threshold pump power, before the onset of laser emission.
- Spatial Coherence as can be indicated by a diffraction limited output beam or speckle
- The presence of laser cavity modes, that may be explained from the geometry of the resonator
- Significant spectral narrowing of the fluorescence in the output beam.

2.11.2 Four Level Systems

The photo-physical properties of these polymers make them ideal candidates for laser materials. The fact that electrons undergo spectral and structural relaxation upon excitation and emission means that the energy levels of conjugated polymers forms a four level system. This is desirable for a laser material, as every electron that is excited relaxes to a new energy level, which

then decays to another unpopulated level, before relaxing to the ground state. This means that a population inversion, which is required to produce stimulated emission, can be obtained with minimum pumping (*Svelto and Hanna*).

2.11.3 Stimulated Emission Cross-section of Organic Materials

As has just been seen the singlet levels of conjugated polymers provide the environment for a four level laser system. To observe the phenomenon of lasing stimulated emission must occur within the laser gain medium. Stimulated emission occurs when a photon of resonant frequency encounters a chromophore in an excited state and induces the chromophore to emit a photon of the same frequency, propagation constant, polarisation and phase. This involves some mechanism whereby a large number of the emitting species within a material can be transformed into the excited state. This may be achieved by either optical or electrical pumping. The stimulated emission cross-section of these excited states is defined as;

$$\sigma_{se}(\lambda) = \frac{\lambda^4 E_f(\lambda)}{8\pi n^2(\lambda) c_o \tau_f} \quad [2.17]$$

where λ is the wavelength of emitted light, $E_f(\lambda)$ is the fluorescence quantum distribution, $n(\lambda)$ is the refractive index at λ , τ_f is the fluorescence lifetime and c_o is the speed of light in vacuum. The fluorescence quantum distribution $E_f(\lambda)$ is defined by the relation:-

$$\phi_F = \int_0^\infty E_f(\lambda) d\lambda \quad [2.18]$$

where ϕ_F is the fluorescence quantum yield, which is defined as the ratio between the total number of photons emitted to the total number of photons absorbed.

The important parameters of a material may now be assessed to achieve a large cross-section, which will be desirable in a laser medium. The short fluorescence lifetime and a large fluorescence quantum distribution are central to achieving large stimulated emission cross-sections. The high fluorescence quantum yield, and hence large fluorescence quantum distribution, and the fast radiative decay rates of fluorescent polymers contribute to making them ideal candidates for laser media with typical $\sigma_{se} \sim 10^{-15} \text{ cm}^2$. The λ^4 -dependence of the stimulated emission cross-section results in a greater likelihood of stimulated emission occurring at longer wavelengths. This results in maximum optical gain being red-shifted from the fluorescence emission peaks, characterised by the fluorescence quantum distribution. Note that decreasing the refractive index of the emitting species can increase the stimulated emission cross-section. This can be achieved by doping a fluorescent species into a host material such as polystyrene, which increases the possibility of stimulated emission and hence creates a more efficient emissive material.

2.11.4 *Tunability of Disordered Systems*

Due to the vibrational and inhomogeneous broadening present in conjugated polymers, there is generally a structureless broadband emission Stokes shifted away from the absorption band. This effectively eliminates self-absorption of laser light within the material. It also provides a material with a spectrally broad fluorescence quantum distribution $E_f(\lambda)$. This allows the possibility of having a broad stimulated emission cross-section, which means that the laser emission could be tuned over a broad wavelength distribution. A solid state device with such characteristics would have much to offer in information storage systems where wavelength multiplexing is proposed to increase data storage density.

References

- Agranovich, V. M., Efremov, N. A. and Zakhidov, A. A. (1980). "Exciton luminescence of molecular crystals at high excitation levels." Izvestiya Akademii Nauk SSSR Seriya Fizicheskaya **44**(4): 759-64.
- Atkins, P. W. (1998). "Physical Chemistry."
- Ausin, V. and Rivas, J. L. A. (1972). "Thermoluminescence and annealing of F-centres in KCl gamma irradiated at room temperature." Journal of Physics C: Solid State Physics **5**(1): 82-96.
- Bässler, H. (1998). Excitons in Conjugated Polymers. Primary Photoexcitations in Conjugated Polymers: Molecular Excitons versus Semiconductor Band Model. N. S. Sariciftci, World Scientific: 51-98.
- Beljonne, D., Shuai, Z., Friend, R. H. and Bredas, J. L. (1995). "Theoretical investigation of the lowest singlet and triplet states in poly(paraphenylene vinylene) oligomers." Journal of Chemical Physics **102**(5): 2042-9.
- Brazovski, S. A. and Kirova, N. N. (1981). "Excitons, polarons and bipolarons in conducting polymers." Pis'Ma V Zhurnal Eksperimental'noi i Teoreticheskoi Fiziki **33**(1): 6-10.
- Bredas, J. L., Cornil, J., Meyers, F. and Beljonne, D. (1998). Electronic Structure and Optical Response of Highly Conducting and Semiconducting Conjugated Polymers and Oligomers. Handbook of Conducting Polymers. T. A. Skotheim, R. L. Elsenbaumer and J. R. Reynolds: 1-27.
- Bronold, F. X., Saxena, A. and Bishop, A. R. (1993). "Radiative decay of polaron-excitons in poly(phenylene vinylene)." Physical Review B-Condensed Matter **48**(17): 13162-5.
- Chandross, M., Mazumdar, S., Jeglinski, S., Wei, X., Vardeny, Z. V., Kwock, E. W. and Miller, T. M. (1994). "Excitons in poly(para-phenylenevinylene)." Physical Review B-Condensed Matter **50**(19): 14702-5.
- Conwell, E. M. (1998). Intramolecular Excitons and Intermolecular Polaron Pairs as Primary Photoexcitations in Conjugated Polymers. Primary Photoexcitations in Conjugated Polymers: Molecular Excitons versus Semiconductor Band Model. N. S. Sariciftci, World Scientific: 99-114.
- Cornil, J., Beljonne, D., Friend, R. H. and Bredas, J. L. (1994). "Optical absorptions in poly(paraphenylene vinylene) and poly(2,5-dimethoxy-1,4-paraphenylene vinylene) oligomers." Chemical Physics Letters **223**(1-2): 82-8.
- Dexter, D. L. (1953). Journal of Chemical Physics **21**: 836.

Dhote, J., Kretsch, K. P., Davey, A. P., Blau, W. and Byrne, H. J. (1999). "Luminescent quantum yields and vibrational spectroscopy." Synthetic Metals **102**(1-3): 1529-30.

Ermolaev, V. L. (1967). Soviet Physics Doklady **6**: 600.

Fesser, K., Bishop, A. R. and Campbell, D. K. (1983). "Optical absorption from polarons in a model of polyacetylene." Physical Review B-Condensed Matter **27**(8): 4804-25.

Forster, T. (1946). Naturwissenschaft **33**: 166.

Forster, T. (1948). Ann. Phys.

Gomes da Costa, P. and Conwell, E. M. (1993). "Excitons and the band gap in poly(phenylene vinylene)." Physical Review B-Condensed Matter **48**(3): 1993-6.

Graupner, W., Eder, S., Mauri, M., Leising, G. and Scherf, U. (1995). "Excited states in PPP-type ladder polymers probed by photoinduced absorption." Synthetic Metals **69**(1-3): 419-22.

Graupner, W., Grem, G., Meghdadi, F., Paar, C., Leising, G., Scherf, U., Mullen, K., Fischer, W. and Stelzer, F. (1994). "Electroluminescence with conjugated polymers and oligomers." Molecular Crystals & Liquid Crystals **256**: 549.

Gymer, R. W. (1996). "Organic electroluminescent displays." Endeavour **20**(3): 115-120.

Hagler, T. W., Pakbaz, K., Voss, K. F. and Heeger, A. J. (1991). "Enhanced order and electron delocalization in conjugated polymers oriented by gel processing in polyethylene." Physical Review B-Condensed Matter **44**(16): 8652-66.

Halliday, D. A., Burn, P. L., Bradley, D. D. C., Friend, R. H., Gelsen, O. M., Holmes, A. B., Kraft, A., Martens, J. H. F. and Pichler, K. (1993). "Large changes in optical response through chemical pre-ordering of poly(p-phenylenevinylene)." Advanced Materials **5**(1): 40-3.

Harrison, N. T., Baigent, D. R., Samuel, I. D. W., Friend, R. H., Grimsdale, A. C., Moratti, S. C. and Holmes, A. B. (1996). "Site-selective fluorescence studies of poly(p-phenylene vinylene) and its derivatives." Physical Review B-Condensed Matter **53**(23): 15815-22.

Heeger, A. J., Kivelson, S., Schrieffer, J. R. and Su, W. P. (1988). "Solitons in conducting polymers." Reviews of Modern Physics **60**(3): 781-850.

Henderson, B. and Imbusch, G. F. (1989). "Optical spectroscopy of inorganic solids."

Kittel, C. (1996). "Introduction to Solid State Physics."

Kivelson, S. and Heeger, A. J. (1985). "First-order transition to a metallic state in polyacetylene: a strong-coupling polaronic metal." Physical Review Letters **55**(3): 308-11.

Kohler, B. E. and Samuel, I. D. W. (1995). "Experimental determination of conjugation lengths in long polyene chains." Journal of Chemical Physics **103**(14): 6248-52.

Kohler, B. E. and Woehl, J. C. (1995). "A simple model for conjugation lengths in long polyene chains." Journal of Chemical Physics **103**(14): 6253-6.

Kuhn, H. (1953). Fortschritte der Chemie Organischer Naturstoffe **16**: 169.

McKeever, S. W. S. (1985). "Thermoluminescence of solids."

McMurry, S. M. (1993). "Quantum Mechanics."

Nguyen, T.-Q., Schwartz, B. J., Schaller, R. D., Johnson, J. C., Lee, L. F., Haber, L. H. and Saykally, R. J. (2001). "Near-Field Scanning Optical Microscopy (NSOM) Studies of the Relationship between Interchain Interactions, Morphology, Photodamage, and Energy Transport in Conjugated Polymer Films." Journal of Physical Chemistry **105**(22): 5153-5160.

Palik, E. D. (1991). Handbook of Optical Constants of Solids II. London, Academic Press.

Peierls, S. R. (1955). "Quantum Theory of Solids."

Pichler, K., Halliday, D. A., Bradley, D. D. C., Friend, R. H., Burn, P. L. and Holmes, A. B. (1993). "Photoinduced absorption of structurally improved poly(p-phenylene vinylene)-no evidence for bipolarons." Synthetic Metals **55**(1): 230-4.

Pope, M. E. and Swenberg, C. E. (1982). Electronic Processes in Organic Crystals, Oxford University Press.

Reddy, N. R. S., van Amerongen, H., Kua, S. L. S., van Grondelle, R. and Small, G. J. (1994). Journal of Physical Chemistry **98**: 4729-4735.

Shimoi, Y., Abe, S. and Harigaya, K. (1995). "Theory of optical absorption in doped conjugated polymers." Molecular Crystals & Liquid Crystals **267**: 329-34.

Shuai, Z., Bredas, J. L. and Su, W. P. (1994). "Nature of photoexcitations in poly(paraphenylene vinylene) and its oligomers." Chemical Physics Letters **228**(4-5): 301-6.

Strauss, E. and Seelert, W. (1984). "Photocaloric determination of the fluorescence quantum efficiency: Cr^{3+} ions in amorphous and crystalline hosts." Journal of Luminescence **31-32**(1): 191-3.

Su, W. P., Schrieffer, J. R. and Heeger, A. J. (1979). "Solitons in polyacetylene." Physical Review Letters **42**(25): 1698-701.

Su, W. P., Schrieffer, J. R. and Heeger, A. J. (1980). "Soliton excitations in polyacetylene." Physical Review B-Condensed Matter **22**(4): 2099-111.

Svelto, O. and Hanna, D. C. (1989). Principles of Lasers. New York, Plenum.

Takayama, H., Lin-Liu, Y. R. and Maki, K. (1980). "Continuum model for solitons in polyacetylene." Physical Review B-Condensed Matter **21**(6): 2388-93.

Townsend, P. D. and Friend, R. H. (1987). "Photoexcitation in oriented polyacetylene." Synthetic Metals **17**(1-3): 361-6.

Turro, N. (1991). Modern Molecular Photochemistry, University Science Books.

Waldemar, A. and Cilento, G. (1982). "Chemical and biological generation of excited states."

Woo, H. S., Graham, S. C., Halliday, D. A., Bradley, D. D. C., Friend, R. H., Burn, P. L. and Holmes, A. B. (1992). "Photoinduced absorption and photoluminescence in poly(2,5-dimethoxy-p-phenylene vinylene)." Physical Review B-Condensed Matter **46**(12): 7379-89.

Chapter 3

INTRODUCTION TO THE MATERIALS UNDER STUDY IN THIS WORK

3.1 General Synthesis of PPV's

Polymers of poly(p-phenylenevinylene) (PPV) are a class of polymers with unique properties. They are synthesized by a variety of methods, including the Wittig reaction, the Horner-Wadsworth-Emmons reaction, and the McMurry coupling. The resulting polymers have a conjugated backbone, which gives them unique electronic and optical properties.

The synthesis of PPV's is a complex process, and the resulting polymers can have a wide range of properties. The properties of the polymers are determined by the synthesis method used, the purity of the starting materials, and the conditions of the reaction.

The synthesis of PPV's is a complex process, and the resulting polymers can have a wide range of properties. The properties of the polymers are determined by the synthesis method used, the purity of the starting materials, and the conditions of the reaction.

The synthesis of PPV's is a complex process, and the resulting polymers can have a wide range of properties. The properties of the polymers are determined by the synthesis method used, the purity of the starting materials, and the conditions of the reaction.

3.1.1 Precursor Routes

The most common method for the synthesis of PPV's is the precursor route. This involves the reaction of a precursor molecule with a vinyl compound to form the polymer. The precursor molecule is typically a substituted benzene ring, and the vinyl compound is typically a substituted ethylene. The reaction is typically carried out in the presence of a catalyst, and the resulting polymer is purified by precipitation.

3.1 Introduction to Synthesis of Conjugated Polymers

As has been seen, conjugated polymers consist of chains of alternating single and double bonds. The most basic conjugated polymer is polyacetylene (PA). However, PA has significant limitations such as:- extreme air sensitivity and lack of processibility. Consequently, great efforts have been made to discover new materials that display greater processibility and stability in ambient conditions. Poly(*p*-phenylene-vinylene) (PPV) has since emerged because of its promising non-linear optical behaviour (*Tsutsui et al.*) and the electroluminescent activity observed by *Burroughes et al.*. PPV has also shown itself to be less affected by oxidation and other external attack than PA.

3.2 General Synthesis of PPV's

Synthesis of conjugated polymers is hampered by the solubility of the polymer within solution. Both PA and PPV are insoluble, which results in the polymer falling out of solution at high chain lengths. Two strategies have been devised to circumvent this problem.

- Preparation of soluble precursor polymers, which can be thermally converted to PPV after film formation.
- Synthesis of soluble derivatives of PPV, incorporating soluble side-chains.

These two strategies for the exploitation of conjugated polymers using solution-processing techniques will now be examined in brief.

3.2.1 Precursor Routes

The use of conjugated polymers as the emissive layer in light emitting diodes (LEDs) by *Burroughes et al.* has been one of the most significant breakthroughs so far in the field of organic electronics. Such a step could

Figure 3.1 The sulphonium polyelectrolyte precursor route to PPV. Polymer 2 is spin cast onto the surface before thermal conversion to Polymer 3.

have been taken considerably earlier were it not for the problems with synthesis and processibility that have been outlined previously.

The PPV used by *Burroughes et al.* in their LED was developed at the University of Massachusetts and co-workers at Sumitomo Chemical Co. Japan (*Kanbe and Okawara*), using a sulphonium precursor. Previously, studies on PPV were limited to oligomeric powder samples prepared by de-hydrohalogenation or by Wittig condensation reactions. Due to the material becoming insoluble during polymerisation, it was not possible for these oligomers to exceed 9 to 11 monomer units per chain.

The synthesis route used by *Kanbe and Okawara* for the formation of high molecular weight PPV films by the use of a precursor material is outlined in Figure 3.1. The precursor polymer is formed by the base-induced polymerization of a *p*-xylylene-*bis*-(alkyl-sulphonium) salt (1 in Figure 3.1), usually in an aqueous solution. The precursor polymer (2 in Figure 3.1) is then used for solution processing in order to form films in LED architectures. PPV (3 in Figure 3.1) is then formed by the elimination of the alkyl-sulphonium-leaving group. The great advantage of such precursor methods is that they are the only known way of producing films of pure PPV, which can be use in device applications.

3.2.2 Soluble PPV Derivatives

Although precursor routes are successful in producing well-conjugated PPV with relatively high molecular weights, the method can often be cumbersome,

with the introduction of defects and impurities during the thermal treatment. Soluble PPV derivatives provide an alternative to this approach. Such materials can be purified in solution and avoid the need for thermal treatment. Moreover, the addition of different chemical substituents to the polymer backbone can be used as a method to chemically tune the properties of the polymer.

PPV-based polymers can be made soluble by substituting long flexible side-groups onto the phenyl ring, which gives rise to an increase in the entropic contribution to the free energy in solution. The use of dialkoxy substituents on the phenyl ring at the 2 and 5 positions is the most popular way of solubilising PPV (*Murase et al.*; *Antoun et al.*) (see Figure 3.2 (a)). The first soluble PPV derivative was poly(2,5-di-hexyloxy-*p*-phenylene-vinylene). This was synthesized by *Askari et al.* who added excess base to sulphonium precursor during polymerisation. *Swatos and Gordon* have suggested an alternative method, using a soluble chlorine leaving group precursor. The chlorine may then be eliminated by heating the precursor to 370 K.

The addition of asymmetric side-chains can further increase the solubility of PPV. *Wudl et al.* used this strategy when developing the polymer poly(2-methoxy-5-(2'-ethyl-hexyloxy)-*p*-phenylene-vinylene) or MEH-PPV, which has been used extensively for device applications (*Braun and Heeger*). The use of other substituents on the phenyl ring of the polymer backbone has been used to increase solubility of the polymer (*Gailberger and Bassler*). Here in Trinity College Dublin, *Maier* has carried out a full study of side chain substitution of PPV derivatives.

Substitution can also be used to alter the electronic properties of PPV and it is, in principle, possible to chemically tune the emissive properties of such polymers. *Greenham et al.* have used a cyano-substituted PPV for applications in LEDs. The cyano-groups are substituted on the α vinylic carbon next to the phenyl ring. The cyano-groups increase the electron

Figure 3.2 (a) 2,5 phenyl substituted PPV. This substitution has a limited effect on the backbone conformation. (b) PPV substituted on the Vinylene bond in the α and β positions. This substitution has a considerable effect on the backbone conformation.

affinity of the polymer and result in a marked red-shift in the emission from devices. Side-chain substitution on the α and β vinylene carbons (see Figure 3.2(b)) has a strong effect on the chain conformation and so is an effective method of tuning the emissive properties of the polymer.

The group of Prof. Hörhold in Jena have produced many PPV derivatives incorporating different side-chains on the phenylene and vinylene positions, as well as incorporating different chemical moieties into the polymer backbone, to tune the photo-physical properties. They have achieved these results using novel synthesis routes such as the modified Horner route outlined by *Pfeiffer and Hörhold* as well as through de-hydro-halogenation routes (*Hörhold and Helbig*). Many of the polymers studied in this work have come from this group. These materials are considered state of the art, since the synthesis routes have not yet to be implemented by commercial providers such as Covion.

3.3 Sample Preparation – Film Formation

There are three techniques used in this work for preparing organic and metallic thin films, for device and sample fabrication; Spin Coating, Thermal Evaporation and Sputtering. It will now be explained how these three preparation techniques have been used for thin film preparation in this thesis.

3.3.1 Spin Coating

Spin coating is a well-established, inexpensive method for producing high quality, homogeneous polymeric films. All of the spin-cast polymer films studied in this work were fabricated using a Convac 1001 spin coater. The samples were prepared in a laminar flow cabinet to ensure clean, particle free films. The ambient temperature is maintained between 17-20°C by air conditioning.

The preparation of polymer films by spin coating was carried out as follows (see Figure 3.3).

1. The substrate is held in place on the chuck by a rotary vacuum.
2. A uniform film of polymer solution is pipetted onto the whole of the substrate surface.
3. The substrate can then be rotated at frequencies between 200 and 10 000 rpm depending on the required film thickness. The thickness can then be estimated from the following equation (*Umeda*):-

$$t = kc^a \omega^{-b} \quad [3.1]$$

where t is the film thickness, c is the solution concentration, ω is the spin speed and k , a and b are empirical constants. These constants may be determined by fitting this formula to the film thickness resulting from solutions of different concentration spun at various spin speeds. These constants depend on numerous experimental conditions such as, substrate wettability, polymer chain length, solvent viscosity and ambient humidity and temperature. Approximate values for typical polymers are $k \approx 0.02$, $a \approx 1.6$ and $b \approx 0.5$ (*Umeda*).

Figure 3.3 Film Formation by Spin Casting process. 1. A substrate is affixed to the vacuum chuck 2. Polymer solution is pipetted onto the substrate. 3. Chuck is rotated at high speed, forming a polymer film on the substrate. 4. Sample is baked at 60°C in a vacuum oven.

Solvent choice plays a crucial role in the preparation of polymeric thin films. It is of great importance that the polymer solution wets the surface of the substrate in order to obtain good quality films from the spin coating process. Also of great importance is the volatility of the solvent. The rate at which the solvent evaporates during spin coating has a great effect on the surface roughness of the resulting film. *Wen-Li et al.* have attributed this formation of this surface roughness to turbulence at the solvent, air interface during the

Figure 3.4 Surface profile, from phase contrast microscope, of a film spin cast from PVK in DCM (20g/l) on a silicon substrate.

Figure 3.5 Surface profile, from phase contrast microscope, of a film spin cast from a PVK in Chlorobenzene (20g/l) on a silicon substrate.

spin-coating process. *Umeda* proposes that spin casting from solutions with a boiling point in excess of 120°C minimises the surface roughness, so that homogeneous, optical quality films may be prepared.

The effect of solvent volatility can be seen from Figures 3.4 and 3.5, where the surface profile of two poly-vinyl-carbazole (PVK) films spin cast from dichloro-methane (DCM) (b.p. 40°C) and chloro-benzene (b.p. 130°C) on silicon substrates. The film surface profile has been measured directly using a Zygo phase-contrast microscope. In this method, white light is reflected perpendicular to the plane of the film, and the surface is measured from the interference between the incident and reflected light. The surface roughness, R_a , is defined as the variance in the topology measured by the phase contrast microscope. For the DCM film R_a is 24nm while for the chloro-benzene film R_a is 8nm, which is approximately equal to the surface roughness of the silicon substrate.

The issue of solvent volatility affecting film quality is addressed by choosing *o*-xylene as the standard solvent for spin coating of the polymers in this work. Xylene has a boiling point of 130°C and dissolves all of the materials under study.

3.3.2 Thermal Evaporation

The process of thermal evaporation involves the heating of a material, beneath a substrate, in a vacuum chamber (glass bell jar). The material is heated until it reaches the gaseous phase, through either sublimation or evaporation. Once in the gas phase, the material diffuses outward until it reaches a cool surface where it forms a thin film. Provided the substrate is relatively small and is orientated tangentially to the gas flow direction a homogeneous thin film will form on the exposed surface.

All evaporated films were deposited at a pressure of approximately 2×10^{-6} mbar in an Edwards Auto 306 thermal evaporator using a tungsten resistive heating element. The substrate would typically be a distance of about 10cm from the heating element. The mean free path of any of the molecules evaporated in this work is of the order ~ 10 m, so interaction with molecules such as oxygen during the transfer to the substrate is unlikely. A shutter is initially positioned over the heating element to protect the substrate from any impurities that may be given off due to out-gassing etc. After a short time when it is apparent that the evaporation of the material has begun, the shutter is then opened and the rate of evaporation and film thickness are regulated using a film thickness monitor. The film thickness is estimated by measuring the change in the acoustic impedance and using the density of the metal to calculate the film thickness.

In this work, thermal evaporation has been used to deposit a variety of materials as thin films, such as organic charge transport layers and metal electrodes.

3.3.2.1 Organic Layer Deposition

For organic materials, a special heating element was used for the sublimation of molecular materials such as Alq₃. The organic material is placed in a ceramic holder, which is placed into a close-fitting tungsten heating element. Glass wool is then wedged into the ceramic holder on top of the material to

be evaporated. This acts to filter the material so that only small, pure particles can escape when the holder is heated and sublimation occurs. Typically, the evaporation is maintained at a rate of between $1\text{-}5\text{ \AA}\cdot\text{sec}^{-1}$ throughout the evaporation, to allow the film to grow as uniformly as possible over the surface of the substrate. For device fabrication typical layer thickness was between 30-50 nm, although much thicker samples $\sim 200\text{nm}$ were prepared for ellipsometry measurements.

3.3.2.2 Metal Electrode Deposition

Metallic (usually Aluminium) thin films are deposited in a similar manner to the organic thin films. Here a simple helical heating element is used for the evaporation of metals. The metals that are evaporated in Trinity College are supplied by Testbourne Ltd. in wire form and may be evaporated by placing a short length $\sim 2\text{cm}$ inside the helical heating element. When vacuum has been achieved, the heating element is then turned on, with the shutter closed, until the metal melts around the helical element. Once the metal has melted around the coil the element is cooled down and the shutter is opened. The coil is then reheated until evaporation of the metal commences. The rate of evaporation is very important to prevent penetration of the metal into the polymer. Typically, a rate of between $1\text{-}2\text{ \AA}\cdot\text{sec}^{-1}$ is used for the first 20 nm of film growth. Subsequently, the film can be grown at faster rates of $\sim 1\text{ nm}\cdot\text{sec}^{-1}$. It has been shown for OLEDs that metal electrodes fabricated in such a manner behave as well as electrodes grown at the slower rate throughout the growth of the entire film (*Fletcher*). Electrodes were typically grown to a thickness of $\sim 100\text{nm}$ for all OLEDs in this work.

3.3.3 Sputtering of Metal Contacts

Another method of depositing metal films is by sputtering. This method was used when a greater degree of control was desired for the rate of film deposition. Such a situation arises when bottom contacts for devices were prepared from Aluminium or Platinum in the uni-polar work in section 6.5.3.

All sputtered films were prepared under a vacuum of $\sim 1 \times 10^{-5}$ mbar. The sputtering rig used for this work is very similar in set-up to the evaporator described previously, except that the thermal heating coil is replaced with a sputtering target.

Sputtering involves the deposition of almost any target material (the material that is being deposited), onto almost any substrate material. The vacuum chamber is flooded with an inert gas (Argon). The Argon is ionised using a radio frequency power supply resulting in the formation of a plasma, over the target. The target is at a negative potential, resulting in the acceleration of the argon ions towards it. This causes the surface of the target to be bombarded by the argon ions and the target atoms are ejected away from the target. The target atoms then behave similarly to the evaporated atoms/molecules mentioned previously, with diffusion towards the sample surface and the formation of a thin film. A shutter is initially held in place to prevent surface impurities from the target reaching the substrate. This is removed after ~ 1 min sputtering. A crystal thickness monitor is used to regulate the rate of deposition and to estimate the film thickness.

Although usually used for bottom contact preparation top contacts were also prepared by sputtering. Ejected target atoms possess greater kinetic energy than evaporated atoms. Consequently when top contacts were sputtered directly onto polymer thin films the sputtering rate was initially maintained at very low deposition rates $\sim 0.1 \text{ \AA} \cdot \text{sec}^{-1}$ to prevent penetration of the metal into the polymer layer.

3.3.4 Film Thickness Measurement

The film thickness of both organic and metallic films can be measured using a computer controlled DekTak³ surface profilometer. The sample whose thickness is to be measured is scratched with a fine blade. The sample is then placed beneath the diamond tipped stylus of the DekTak. The tip is then lowered onto the surface and dragged over the scratch, while recording the

surface profile. The force applied to the surface is typically between 0.08-0.20mN. The resolution of the DekTak is $\sim 1\text{\AA}$ over the range of films measured in this work. However, the error in film thickness measurements is usually of the order $\sim 10\text{nm}$, due to the influence of film and substrate surface roughness. For film-thickness measurements, the measurement is carried out 10 times at random points on the film surface and the mean and variance of these measurements is then calculated.

3.4 Introduction to the Jena PPV Derivatives

As has been mentioned in section 3.2.2 the polymers developed by Prof. Hörhold's group in Jena have been developed using new synthesis techniques. Consequently, very little is known about the physical properties of these materials. Here the basic photo-physical properties (absorption and emission spectra, quantum yield and polymer conformation) of these new materials are presented along with the chemical structure of the polymers. Some acronyms for the polymer names will also be introduced, which will be used throughout the remainder of the thesis.

Absorption spectra were taken of solid films using a Shimadzu UV-Vis absorption spectrometer. Photoluminescence spectra were obtained using an Oriel 77400 spectrograph, connected to an Andor B401-UV CCD, using an Oriel 77863 liquid light guide to collect the emission. For photoluminescence, the films were excited using a UV LED with a peak emission at 370nm. The quantum yield, ϕ_{PL} , of the polymers is then determined from corrected photoluminescence spectra against a standard solution of quinine sulphate in 0.1M H_2SO_4 ($\phi_{PL}=54\%$).

The most likely chain conformation for each material was calculated using HyperchemTM over 8 repeat units (shorter chain-lengths are displayed in Figures 3.6-11 for clarity). HyperchemTM is a molecular modelling package, which uses a Metropolis Monte-Carlo simulation (Press) to calculate the

lowest energy single chain conformation. While this doesn't take account of inter-molecular interactions, it does shed some light onto how the chain conformation may affect the morphology of solid-state polymer films.

The chemical structure for the six novel conjugated polymers studied in this thesis is presented, along with the absorption and emission spectra, the optimised conformation in Figures 3.6-11. Also shown are relevant material parameters such as the molecular weight (M_w and M_n) as measured by Gel Permeation Chromatography (GPC), the quantum yield and the glass transition temperature, T_g , as measured by Differential Scanning Calorimetry (DSC). The measurement of T_g and M_w are important for device fabrication. A soluble material with a high M_w will usually form good quality films, which is important to fabricate OLEDs. A material with a high T_g will be more stable to the thermal stress present during charge transport.

The polymer, poly[1,4-phenylene-1,2-di(phenoxy-phenyl)-vinylene] (DPOP-PPV), was synthesised by reductive coupling (de-hydro-halogenation polymerisation) of appropriately substituted tetrachlorides (*Hörhold and*

Figure 3.6 DPOP-PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem™.

Helbig). As can be seen from the chemical structure in Figure 3.6, DPOP-PPV has large side chains (phenoxy-phenyl), which aid both solubility and increase the glass transition temperature ($T_g \sim 163^\circ\text{C}$). The polymer batch used for this work had a molecular weight (M_w) of $\sim 23,800$. The substitution of phenoxy-phenyl side-groups on the vinylene bond results in a highly disordered chain conformation. This produces a broadband emission and absorption spectrum combined with a high quantum yield of 68%, making this material an excellent candidate for a polymeric laser.

The polymer poly[(95%)-2,5-(methoxy-octyloxy)-1,4phenylene-vinylene]-co-[(5%)-1,4-phenylene-1,2-(di-phenylene)-vinylene] (HT73) was prepared by dehydro-halogenation of substituted xylene di-halides (*Hörhold et al.*). As can be seen from the chemical structure in Figure 3.7, HT73 has large side chains (octyloxy and phenyl), which aid solubility. The molecular weight (M_w) of the polymer batch used for this work was $\sim 261,000$. HT73 is a statistical copolymer made up of 95% alkyloxy substituted PPV and 5% phenyl substituted PPV. The introduction of the phenyl substituted PPV adds disorder to the ordered alkyloxy substituted PPV, although considerable order

Figure 3.7 HT73 absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using HyperchemTM.

remains within the material as evidenced by the presence of vibronic structure in the PL spectrum. The high quantum yield of 25% makes HT73 a good candidate for a polymer laser.

The polymer Poly[oxy-1,4-phenylene-1,2-(1-cyano)-ethynylene-2,5-dioctyloxy-1,4-phenylene-1,2-(2-cyano)-ethynylene-1,4-phenylene] (HT94) was synthesised by a step growth polymerisation using the Knoevenagel reaction between 2,5-di-alkoxy-terephthalaldehyde and ether-*bis*(acetonitrile) catalysed by potassium-*tert*-butylate at 110°C (Tillmann and Hörhold). As can be seen from the chemical structure in Figure 3.8, HT94 uses phenyl substituted octyloxy side-chains to increase solubility. There are cyano-groups substituted on the vinylene carbons giving this material a high electron affinity, offering the promise of good electron transporting properties. This is offset by the relatively low glass transition temperature of $T_g \sim 61^\circ\text{C}$, which would indicate significant degradation of the material under device conditions. The polymer batch used for this work had a molecular weight (M_w) of $\sim 21,500$. The polymer conformation is highly ordered, although the excited state is probably localised between the ether groups as can be seen from the

Figure 3.8 HT94 absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem™.

broad structure-less emission from this material. HT94 is a good candidate for a polymer laser as evidenced by the high quantum yield of 36%.

The polymer Poly[2-methoxy-5(2-ethylhexyloxy)-1,4-phenylene-vinylene-2,5(dioctyloxy)-1,4-phenylene-vinylene] (MEH-DOO-PPV) was synthesised by a modified Horner poly-condensation reaction of di-octyl-oxy-terephthalaldehydes in chloro-benzene at 130°C. (*Hörhold et al.*). As can be seen from the chemical structure in Figure 3.9, MEH-DOO-PPV has branched alkyloxy side chains (phenoxy-phenyl), which aid both solubility and act to prevent aggregation in the solid state. The molecular weight (M_w) of the polymer batch used for this work was $\sim 34,300$. The polymer backbone assumes an ordered linear rod-like conformation, although this will not be anchored by aggregation in the solid state, due to the branched alkyloxy sidechains. Some vibronic structure can be observed in the emission, although the vibronic peaks are some-what smeared out indicating that the polymer doesn't assume a highly ordered morphology. MEH-DOO-PPV is a good candidate for a polymer laser as evidenced by the high quantum yield of 19%.

The modified Horner synthesis route outlined by *Pfeiffer and Hörhold*, has been extended to the synthesis of the related co-polymer poly[2,7-

Figure 3.9 MEH-DOO-PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using HyperchemTM.

thianthrene-1-phenyl – vinylene - 2,5 - (dioctyl - oxy) - 1,4 – phenylene - 2 - phenyl-vinylene] (Thianthrene-PPV) (*Kreuder et al.*). Thianthrene-PPV (see Figure 3.10) has a thianthrene moiety substituted into a Poly-Arylene-Vinylene/Poly-*p*-Phenylene-Vinylene (PAV/PPV) backbone with octyloxy side chains, for solubility. The high glass transition temperature ($T_g \sim 151^\circ\text{C}$), makes this polymer a very good candidate for device applications. The polymer batch used for this work had a molecular weight (M_w) of $\sim 17,600$. The polymer conformation is highly ordered, although the Thianthrene group stays in a different plane to the remainder of the polymer backbone. This results in a localised excited state resulting in a broadband emission spectrum combined with a high quantum yield of 59%, making this material an excellent candidate for a polymeric laser.

The polymer poly[9,9-di-n-octylfluorenyl-2,7'-diyl] (PFO) is a commercial polymer obtained from the American Dye Source (product code ADS129BE). PFO is synthesised using a Palladium catalysed Suzuki coupling scheme of di-brominated and boron esters (*Charas et al.*). As can be seen from the chemical structure in Figure 3.10, PFO uses substituted di-octyl

Figure 3.10 Thianthrene PPV absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated by Hyperchem™.

Figure 3.11 PFO absorption and emission spectrum. Also shown is the chemical structure and the chain conformation as calculated using Hyperchem™.

sidechains for solubility. The polymer batch used for this work had a molecular weight (M_w) of $\sim 10,000$. PFO has a repeat unit of two phenyl rings, planarised by a ladder-type bond. However, two adjacent repeat units can rotate with respect to each other. This results in the di-octyl sidechains rotating to opposite sides of the polymer backbone resulting in the herring bone type conformation shown in Figure 3.10. The polymer backbone assumes a highly planar conformation, resulting in this material having a large amount of aggregation in the solid state, in this highly ordered fashion. This produces an emission showing a large amount of vibronic structure. PFO has a high quantum yield of 46%, making this material a good candidate for a polymeric laser.

3.5 Other Materials for Study

The Jena materials represent a wide variety of chemical structures for this study. However all these materials are soluble in non-polar organic solvents. This causes considerable problems, when fabricating multi-layer devices, due to the requirement that during the spin coating of a polymer layer, the solvent

must not dissolve the layer beneath the new polymer layer. Such behaviour between two polymer layers is termed orthogonal solvency.

Due to the lack of orthogonal solvency between the Jena materials, some established materials have also been added to this study, for the fabrication of heterostructure devices. PEDOT (Baytron P; Bayer), Alq_3 , as well as the polymer nanotube composite developed in TCD (*Curran et al.*), have also been used throughout this thesis. These materials, along with the Jena materials comprise the broad range of materials that will be studied, within the research strategy outlined in section 1.3. As a result, the optical constants, the excited state absorption, and the electrical properties of all of these materials will be assessed throughout the next three chapters of this thesis.

References

- Antoun, S., Gagnon, D. R., Karasz, F. E. and Lenz, R. W. (1986). Polymer Preprints **27**: 116.
- Askari, S. H., Rughooputh, S. D. and Wudl, F. (1989). "Soluble substituted-PPV conducting polymers: spectroscopic studies." Synthetic Metals **29**(1): 129-34.
- Braun, D. and Heeger, A. J. (1991). "Visible light emission from semiconducting polymer diodes." Applied Physics Letters **58**(18): 1982-4.
- Burroughes, J. H., Bradley, D. D. C., Brown, A. R., Marks, R. N., Mackay, K., Friend, R. H., Burns, P. L. and Holmes, A. B. (1990). "Light-emitting diodes based on conjugated polymers." Nature **347**(6293): 539-41.
- Charas, A., Barbagallo, N., Morgado, J. and Alcacer, L. (2001). "Synthesis and optical properties of poly(fluorene)-based alternating copolymers." Synthetic Metals **122**(1): 23-5.
- Curran, S. A., Ajayan, P. M., Blau, W. J., Carroll, D. L., Coleman, J. N., Dalton, A. B., Davey, A. P., Drury, A., McCarthy, B., Maier, S. and Strevens, A. (1998). "A composite from poly(m-phenylenevinylene-co-2,5-dioctoxy-p-phenylenevinylene) and carbon nanotubes: a novel material for molecular optoelectronics." Advanced Materials **10**(14): 1091-3.
- Fletcher, R. B. (1999). "Engineering of Optoelectronic Devices based on Conjugated Polymers." PhD. Thesis. Department of Physics and Astronomy. Sheffield, University of Sheffield.
- Gailberger, M. and Bassler, H. (1991). "DC and transient photoconductivity of poly(2-phenyl-1,4-phenylenevinylene)." Physical Review B-Condensed Matter **44**(16): 8643-51.
- Greenham, N. C., Moratti, S. C., Bradley, D. D. C., Friend, R. H. and Holmes, A. B. (1993). "Efficient light-emitting diodes based on polymers with high electron affinities." Nature **365**(6447): 628-30.
- Hörhold, H.-H. and Helbig, M. (1987). "Poly(phenylenevinylene)s - Synthesis and Redoxchemistry of Electroactive Polymers." Makromolecular Chemie, Macromolecular Symposium **12**: 229-58.
- Hörhold, H.-H., Tillmann, H., Bader, C., Stockmann, R., Nowotny, J., Klemm, E., Holzer, W. and Penzkofer, A. (2001). "MEH-PPV and dialkoxy phenylene vinylene copolymers. Synthesis and lasing characterization." Synthetic Metals **119**(1-3): 199-200.

Kanbe, M. and Okawara, M. (1968). Journal of Polymer Science Part A, Polymer Chemistry **1**(6): 1058.

Kreuder, W., Lupo, D., Salbeck, J., Schenk, H., Stehlin, T., Hörhold, H.-H., Lux, A., Teuschel, A. and Wieduwilt, M., Hoechst AG.

Maier, S. (1997). Diploma Thesis. Department of Pure and Applied Physics. Dublin, Trinity College.

Murase, I., Ohnishi, T., Noguchi, T. and Hirooka, M. Highly conducting poly(phenylene vinylene) derivatives via soluble precursor process. Synthetic Metals, vol.17, no.1-3, Jan. 1987, pp.639-44. Switzerland.

Pfeiffer, S. and Hörhold, H.-H. (1999). "Synthesis of soluble dialkoxy-substituted poly(phenylene alkenylidene)s by applying the Horner-reaction for condensation polymerisation." Macromolecular Chemistry and Physics **200**(8): 1870-8.

Press, W. H. (1992). Numerical Recipes in C : the art of scientific computing, Cambridge University Press.

Swatos, W. J. and Gordon, B. (1990). Polymer Preprints **31**: 505.

Tillmann, H. and Hörhold, H.-H. (1999). "Synthesis, optical and redox properties of novel segmented cyano-PPV derivatives." Synthetic Metals. **101**(1-3): 138-9.

Tsutsui, T., Murata, H., Kim, J. C. and Saito, S. (1992). Polyarylenevinylene films for third-order nonlinear optics. Nonlinear Optics. Fundamentals, Materials and Devices. Proceedings of the Fifth Toyota Conference on Nonlinear Optical Materials., Amsterdam.

Umeda, Y. (1993). Fabrication and Testing of Passive Polymeric Waveguides. Department of Pure and applied Physics. Dublin, Trinity College.

Wen-Li, W., Orts, W. J., van Zanten, J. H. and Fanconi, B. M. (1994). "Density profile of spin cast polymethylmethacrylate thin films." Journal of Polymer Science Part B-Polymer Physics **32**(15): 2475-80.

Wudl, F., Allemeand, P. M., Srdanov, G., Ni, Z. and McBranch, D. (1991). Materials for Nonlinear Optics: Chemical Perspectives. S. R. Marder, J. E. Sohn and G. D. Stucky. Washington D.C., American Chemistry Society. **455**: 683.

4.1 Introduction

Chapter 4

SPECTROSCOPIC ELLIPSOMETRY OF CONJUGATED POLYMERS

Spectroscopic ellipsometry is a highly sensitive technique for the determination of accurate values for the refractive index and thickness of thin films. It is a non-destructive technique that can be used to study a wide range of materials, including polymers, semiconductors, and metals. The advantages of using spectroscopic ellipsometry include its high accuracy, its ability to measure the thickness of films down to a few nanometers, and its ability to measure the refractive index of materials over a wide range of wavelengths. The disadvantages of using spectroscopic ellipsometry include its sensitivity to surface roughness, its sensitivity to the quality of the incident light, and its sensitivity to the quality of the detector.

4.2 Overview of Spectroscopic Ellipsometry

Ellipsometry is a sensitive optical technique for determining the refractive index and thickness of thin films. It is based on the principle that the reflection of light from a surface at an oblique angle is polarized. The degree of polarization is determined by the refractive index and thickness of the film. By measuring the degree of polarization, the refractive index and thickness of the film can be determined. Ellipsometry is a non-destructive technique that can be used to study a wide range of materials, including polymers, semiconductors, and metals. The advantages of using ellipsometry include its high accuracy, its ability to measure the thickness of films down to a few nanometers, and its ability to measure the refractive index of materials over a wide range of wavelengths. The disadvantages of using ellipsometry include its sensitivity to surface roughness, its sensitivity to the quality of the incident light, and its sensitivity to the quality of the detector.

Consider linearly polarized light of a specific wavelength incident at oblique incidence on a surface. The reflected light is then elliptically polarized. The shape and orientation of the ellipse depend on the angle of incidence, the refractive index of the material, and the thickness of the film. By measuring the shape and orientation of the ellipse, the refractive index and thickness of the film can be determined. Ellipsometry is a non-destructive technique that can be used to study a wide range of materials, including polymers, semiconductors, and metals. The advantages of using ellipsometry include its high accuracy, its ability to measure the thickness of films down to a few nanometers, and its ability to measure the refractive index of materials over a wide range of wavelengths. The disadvantages of using ellipsometry include its sensitivity to surface roughness, its sensitivity to the quality of the incident light, and its sensitivity to the quality of the detector.

4.1 Introduction

One of the main aims of this thesis is to design and optimise an organic heterostructure waveguide device incorporating conjugated polymers. In order to achieve this, a way of obtaining the refractive index dispersion across the emission spectrum of the polymers needs to be obtained. The refractive index is the critical parameter in increasing the optical confinement within a waveguide. It is very important to have accurate values of the refractive index when optimising a waveguide to minimise the optical loss due to absorption by the metal electrodes.

Spectroscopic Ellipsometry is a flexible technique, which allows the determination of accurate values for the refractive index ($\pm 10^{-3}$). Other information about the variation of the refractive index across a polymer layer may also be obtained, although this is of secondary importance for this work. The advantage of using spectroscopic ellipsometry over other techniques, such as prism-film coupling, is that it provides information across a broad spectral range, including the emission spectra of all the polymers studied here.

4.2 Overview of Spectroscopic Ellipsometry

Ellipsometry is a sensitive optical technique for determining properties of surfaces and thin films. There are various different ellipsometer configurations such as; null, rotating polariser, rotating analyser and polarisation modulation ellipsometers. In this chapter, all measurements were performed on a rotating polariser ellipsometer. While many aspects of the terminology discussed in this chapter translate to other forms of ellipsometry, all further discussion is based on the rotating polariser configuration.

Consider linearly polarised light of a specific orientation reflected, at oblique incidence, from a surface. The reflected light is then elliptically polarised. The shape and orientation of the ellipse depend on the angle of incidence, the direction of the polarisation of the incident light, and the reflection properties

of the surface. If the polarisation of the incident light is caused to rotate the polarisation of the reflected light is modulated accordingly. If the reflected light is then linearly polarised by an analyser at a fixed angle, the amplitude of this light is modulated, as a function of the incident beam's polarisation. From the detected signal the relative phase change, Δ , and the relative amplitude change, $\tan \psi$, introduced by reflection from the surface can be calculated.

The first experiments where thin films were characterised by the use of changes in the polarisation state of the light upon reflection were carried out by (*Drude*). Since the technique measures changes in polarisation it probably should have been given the name 'polarimeter'; however, at the time when the ellipsometer was named the term polarimeter was already in use as the name of an instrument for measuring the specific rotation of optically active materials, which is something different from the reflection properties of a film-covered surface. Since the general polarisation state of polarised light reflected from a surface is elliptical, the term ellipsometer was chosen by (*Rothan*).

The most important application of ellipsometry is to study thin films. In the context of ellipsometry a thin film is one that ranges from essentially zero thickness to several thousand Angstroms, although this range can be extended in some cases. If a film is thin enough, so that it shows an interference colour then it will probably be a good ellipsometric sample. The sensitivity of an ellipsometer is such that a change in film thickness of a few Angstroms is usually easy to detect.

Figure 4.1 shows a schematic diagram of the rotating polariser ellipsometer used in this work for determining the optical constants of polymers. The light source is a Xenon arc lamp, 75W, which provides an unpolarised emission of spectral range 210-2500nm. After the light source, there is a collimator to produce a highly collimated incident beam of small divergence.

Figure 4.1 A schematic diagram of a rotating polariser ellipsometer. The linearly polarised light, E_0 is rotating with angular frequency Ω (see red arrows). This means the resulting elliptical polarisation is also rotating with angular frequency Ω , which results in a linear polarisation, with oscillating amplitude E_d , when it passes through the analyser. It is the resulting modulated intensity, which is directly measured by the detector.

The polariser follows the collimator. This is a quartz ROCHON separator mounted in a holder that rotates about an axis that is parallel to the direction of the light beam. A DC motor rotates the polariser, at a frequency of 40Hz, and correspondingly modulates the polarisation of the resulting incident beam. This modulation allows extremely accurate measurements to be made under constant ambient room lights, without affecting the measurement.

Following the polariser there is an aperture. This ensures that the cross-sectional area of the incident beam is 2mm^2 . This is particularly useful for avoiding imperfections in polymer films due to dust or micro-crystallites. A glass slide is placed in the beam for visible and IR measurements to filter out UV radiation, which can cause sample degradation during the measurement.

The resulting collimated beam of modulated polarisation then reflects off the sample under study, into the analysing arm of the ellipsometer. This reflection induces a change in the polarisation state of the light so that the light is now elliptically polarised. The change in polarisation depends on the environment, structure and the optical properties of the sample. The sample should have a small flat uniform area of at least the size of the incident beam cross-section

that specularly reflects the incident light. Spin cast polymer films on silicon substrates usually provide films of suitable quality and large enough reflection coefficients to achieve consistent, reproducible, and meaningful ellipsometric data.

Following the sample is the analyser. This is a Glan-Taylor prism, which is mounted in a calibrated holder. The analyser angle, ϕ_A , is defined as the angle from the plane of incidence to the analyser transmission axis by an observer looking into the reflected beam. A stepper motor controls the holder and allows ϕ_A to be dynamically selected during a spectral measurement.

Finally, there is a light detector. This consists of an optical fibre, 200 μ m core, which transfers the optical signal to a spectrometer. Transmission through the fibre depolarises the light so that any polarisation sensitivity of the detector is removed from the detected signal. The spectrometer uses a double monochromator (prism/grating) driven by stepper motors and two detectors to achieve a spectral range of 185-1700nm. A photomultiplier tube is used for UV-Vis measurements (185-930nm) and a GaInAs photodiode is used for NIR measurements (900-1700nm).

When a measurement is made at a given wavelength two parameters are found: $\tan\psi$ and $\cos\Delta$. Therefore, two characteristics of the sample can be computed from these two numbers. One possibility would be the index of refraction and optical absorption of a clean optically absorbing sample. If there is a transparent film on a known substrate then the index of refraction and the thickness of the film can be deduced. If the sample consists of a thin optically absorbing film of unknown index of refraction and thickness on a known substrate then there are three unknown parameters that determine the reflection properties of the sample. It is not possible to determine the complex index of refraction and film thickness from a single measurement. This is sometimes called the fundamental problem of ellipsometry.

4.3 Polarisation of Light and the Optical Elements in Ellipsometry

In order to calculate the ellipsometric quantities $\tan \psi$ and $\cos \Delta$, the formalism for the representation and modification, by optical elements, of the polarisation of light, needs to be introduced. One way to calculate the polarisation state of light as it passes through an ellipsometer is by using the Jones calculus. The Jones vector representation for the polarisation state of light will first be described. Then the means by which the Jones calculus treats the changes in polarisation caused by polarising optical elements will be illustrated. This will allow the possibility of tracing the polarisation state of light through the ellipsometer using the Jones calculus.

Consider a beam of monochromatic light travelling in the $+z$ direction in an x - y - z coordinate system. A light wave consists of an oscillating electric field, E , and an oscillating magnetic field, H , which are mutually perpendicular to each other and to the direction that the light travels. The electric field of a monochromatic plane wave of angular frequency ω and travelling in the $+z$ direction can be written as $E = E_0 e^{i(\omega t - kz)}$, where E_0 may be a complex number. The real part of E represents the instantaneous electric field vector at a point z and a time t , and the magnitude of E_0 represents the amplitude of the oscillating electric field. The actual value of a field at any point in space and any instant of time is the real part of the complex field at that point in space and that instant of time.

The magnetic field of the wave, H , is perpendicular to E and the direction the light is travelling, and its magnitude is given by $n \cdot u \times E$, where n is the index of refraction of the medium and u is a unit vector in the direction the light is travelling. Since H can always be calculated from this relation if n , E , and the direction the light is travelling are known, the electric field, E , only needs to be retained to describe the light.

4.3.1 Jones Vectors - Polarisation States of Light

The nature of a completely polarised beam of light can always be completely described by a Jones vector. When light travels in the $+z$ direction in an isotropic material, E_o is a vector that lies in the x - y plane. There are therefore two perpendicular components of the electric field vector that are needed to represent light propagating in the $+z$ direction, one with its electric field oscillating in the x direction and the other with its electric field oscillating in the y direction. If the light is observed at $z = 0$ by looking into the beam then the electric field, E , can be represented by a two-element column matrix, known as a Jones vector, given by:-

$$E = \begin{bmatrix} E_{o,x} \\ E_{o,y} \end{bmatrix} e^{i\omega t} \quad [4.1]$$

The upper element of the matrix is the x component of the electric field and the lower element is its y component. The $e^{i\omega t}$ term can be omitted for the sake of economy provided it is replaced when necessary.

Consider linearly polarised light with the direction of the electric field at an angle θ to the x -axis of our coordinate system (see Figure 4.2 (a)). The components E_x and E_y are then in phase and the Jones vector for the light is given by:-

$$E = \begin{bmatrix} E_o \cos\theta \\ E_o \sin\theta \end{bmatrix} \quad [4.2]$$

where E_o is the amplitude of the wave and the $e^{i(\omega t - kz)}$ term has been suppressed.

Polarised light does not have to be linearly polarised. Consider, for example, a beam of light in which the electric vector goes around in a circle in a clockwise sense as time passes as seen by an observer looking into the beam.

Figure 4.2 (a) Generation of linearly polarised light from two orthogonal polarisations. (b) Generation of linearly polarised light from two orthogonal polarisations, by inducing a phase shift of $-\pi/2$ in the x -component of the polarisation.

This means the size of the electric field vector, at all times, is equal to the amplitude E_o and only the orientation changes. The electric field vector can be obtained at all times, with a x sine wave component, which is phase shifted one quarter of a cycle ($\pi/2$) behind a y sine wave component (see Figure 4.2 (b)). When the x component is E_o the y component is zero and vice-versa. The Jones vector representing this polarisation will be given by

$$E = \begin{bmatrix} E_o \\ iE_o \end{bmatrix} e^{i\omega t} = \begin{bmatrix} E_o \cos \omega t + iE_o \sin \omega t \\ -E_o \sin \omega t + iE_o \cos \omega t \end{bmatrix} \quad [4.3]$$

E_o is assumed to be real. Consider the real part of each component so that $E_x = E_o \cos \omega t$ and $E_y = -E_o \sin \omega t$. At $t=0$ the x component is given by E_o and the y component is zero. As time progresses the x component of the electric vector decreases while the y component of the electric field becomes negative. Thus, the electric field vector for this light has constant amplitude and rotates in a clockwise sense as seen by an observer looking into the light beam. If the x and y components are plotted against each other the tip of the electric field vector precesses around a circle over the course of time. This is circularly polarised light and, by convention, it is called right-handed circularly

polarised. Left-handed circularly polarised light may be similarly achieved by having the x component phase shifted one quarter of a cycle ($\pi/2$) ahead of the y component.

The most general polarisation state of completely polarised light is elliptically polarised light. In this case, the electric vector will trace out an ellipse whose major axis may make an angle with the x -axis. The Jones vector for this general case will be

$$E = \begin{bmatrix} E_x \\ E_y \end{bmatrix} = \begin{bmatrix} E_{x,r} + iE_{x,i} \\ E_{y,r} + iE_{y,i} \end{bmatrix} \quad [4.4]$$

where E_x and E_y are complex, represented by the real and imaginary parts of the electric fields $E_{x,r}$, $E_{y,r}$, $E_{x,i}$, and $E_{y,i}$ where these quantities are real numbers. It should be noted that there is still an implied $e^{i\omega t}$ time dependence. The actual electric field vector of the light at any instant of time may be determined by taking the real parts of the complex fields. Thus the x component of the electric field is $\text{Re}[E_x e^{i\omega t}]$ and the y component is $\text{Re}[E_y e^{i\omega t}]$. If the x and y components are plotted against each other the tip of the electric field vector precesses around an ellipse over the course of time.

The complex components of the field can also be written as a Jones vector given by

$$E = \begin{bmatrix} E_{x,r} + iE_{x,i} \\ E_{y,r} + iE_{y,i} \end{bmatrix} = \begin{bmatrix} A_x e^{i\phi_x} \\ A_y e^{i\phi_y} \end{bmatrix} \quad [4.5]$$

where $\phi_x = \text{Tan} \frac{E_{x,i}}{E_{x,r}}$, $\phi_y = \text{Tan} \frac{E_{y,i}}{E_{y,r}}$, $A_x = \sqrt{E_{x,r}^2 + E_{x,i}^2}$ and $A_y = \sqrt{E_{y,r}^2 + E_{y,i}^2}$.

The quantity $\delta = \phi_x - \phi_y$ is the phase shift introduced to the x component to induce the elliptical polarisation that was referred to when considering circular polarisation. For circular polarisation this must be exactly $\pm\pi/2$, while in the case of elliptically polarised light it may take any value from $-\pi$ to π .

Consider a Jones vector representing polarised light that is given by:-

$$E = \begin{bmatrix} E_x \\ E_y \end{bmatrix} \quad [4.6]$$

then the Jones vector for the orthogonal polarisation is given by:-

$$E_{\perp} = \begin{bmatrix} -E_y^* \\ E_x^* \end{bmatrix} \quad [4.7]$$

where * represents the complex conjugate.

4.3.2 Jones Matrices – Representing Optical Elements

When light passes through a polarising optical element the polarisation state of the light will change. A 2×2 complex matrix called a Jones matrix, which can change one Jones vector to another, can therefore represent the optical element mathematically.

As a trivial example of a Jones matrix consider light that travels through a transparent medium. In this case, the polarisation state does not change at all, so the Jones matrix representing the medium is simply the identity matrix. Almost as trivial is light that passes through an optically absorbing plate. The polarisation state of the light will not change, but the amplitudes of the two orthogonal components of polarisation of the light will be reduced by the same amount. It is not difficult to see that in this case the Jones matrix is given by:-

$$\begin{bmatrix} a & 0 \\ 0 & a \end{bmatrix} \quad [4.8]$$

where $0 < a < 1$.

An ideal linear polariser with its transmission axis coincident with the x -axis will transmit all of the light polarised in the x direction and will block all of the

light polarised in the y direction. Therefore the Jones matrix representing this polariser is given by:-

$$\hat{P} = \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} \quad [4.9]$$

because

$$\begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} E_x \\ E_y \end{bmatrix} = \begin{bmatrix} E_x \\ 0 \end{bmatrix} \quad [4.10]$$

Consider an ideal linear polariser with its transmission axis inclined at an angle θ_p to the x -axis then the Jones vector for the transmitted light is given by:-

$$A_p \begin{bmatrix} \cos\theta_p \\ \sin\theta_p \end{bmatrix} \quad [4.11]$$

where A_p is the transmitted field amplitude, which is dependent in the incident polarisation state. The goal is now to develop a matrix, which produces this result and evaluates A_p .

Suppose the representation of polarised light before it reaches the polariser is transformed into a new coordinate system that makes an angle θ_p with the original coordinate system. In this new coordinate system, the polariser has its transmission axis along the new x -axis. This means that equation 4.10 can be used to describe the change in the polarisation of the light. The resultant polarisation can then be transformed back to the original coordinate system by rotating it through an angle $-\theta_p$. The matrix that represents rotation from one coordinate system to another by an angle ϕ is given by:-

$$\mathbb{R}(\phi) = \begin{bmatrix} \cos\phi & \sin\phi \\ -\sin\phi & \cos\phi \end{bmatrix} \quad [4.12]$$

Hence it can be seen that the Jones vector E_p of light passing through a polariser at an angle θ_p to the x -axis is calculated by:-

$$E_p = \mathbb{R}(-\theta_p) \hat{P} \mathbb{R}(\theta_p) E_i \quad [4.13]$$

More explicitly this appears as:-

$$E_p = \left\{ \begin{bmatrix} \cos\theta_p & -\sin\theta_p \\ \sin\theta_p & \cos\theta_p \end{bmatrix} \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \cos\theta_p & \sin\theta_p \\ -\sin\theta_p & \cos\theta_p \end{bmatrix} \right\} \begin{bmatrix} E_x \\ E_y \end{bmatrix} \quad [4.14]$$

The term in the braces represents the linear polariser with its transmission axis at an angle θ_p to the x -axis. When the algebra is performed the Jones matrix is found for a linear polariser with its transmission axis at an angle θ_p to the x -axis is

$$\hat{P}(\theta_p) = \begin{bmatrix} \cos^2\theta_p & \sin\theta_p \cos\theta_p \\ \sin\theta_p \cos\theta_p & \sin^2\theta_p \end{bmatrix} \quad [4.15]$$

If this matrix is applied to a Jones vector representing a polarisation with components E_x and E_y it can be found that:-

$$\begin{bmatrix} \cos^2\theta_p & \sin\theta_p \cos\theta_p \\ \sin\theta_p \cos\theta_p & \sin^2\theta_p \end{bmatrix} \begin{bmatrix} E_x \\ E_y \end{bmatrix} = (E_x \cos\theta_p + E_y \sin\theta_p) \begin{bmatrix} \cos\theta_p \\ \sin\theta_p \end{bmatrix} \quad [4.16]$$

This represents linearly polarised light with its direction of polarisation making an angle θ_p with the x -axis and with an amplitude $E_x \cos\theta_p + E_y \sin\theta_p$ which is the equal to A_p in equation 4.11.

For incident light which is unpolarised E_x and E_y will be rapidly varying in a random manner so that the average intensities of the two component polarisations will be equal and the amplitude of the transmitted light will not depend on θ_p . In addition, if the incident light is circularly polarised then the

intensity of the transmitted light also will not depend on θ_p , since if $E_x = \pm iE_y$ the amplitude of the transmitted light will be independent of θ_p .

The transformation property demonstrated here is a general property of Jones matrices. If $\hat{J}(0)$ represents the Jones matrix for an optical element at 0 degrees to the x -axis then the Jones matrix for an element rotated through an angle θ is given by:-

$$\hat{J}(\theta) = \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix} \hat{J}(0) \begin{bmatrix} \cos\theta & \sin\theta \\ -\sin\theta & \cos\theta \end{bmatrix} \quad [4.17]$$

4.3.3 Jones Matrix of the Sample

The remaining (and most important!) optical element in the ellipsometer is the sample. To calculate the polarisation of light as it travels through an ellipsometer, a matrix representing the polarisation change upon reflection from the sample needs to be defined. If reflection from the sample does not depolarise the light then a 2×2 complex matrix representing reflection can be defined. The matrix representing reflection can be introduced formally as:-

$$R = \begin{bmatrix} R_{11} & R_{12} \\ R_{21} & R_{22} \end{bmatrix} \quad [4.18]$$

where the R_j 's are, for now, just complex numbers that represent the reflection properties of the surface. Later the calculation of the elements of R for a number of specific cases will be shown. It should be noted that the reflection matrix is not really like the other Jones matrices that have been mentioned previously because it does not have the same transformation properties given by equation 4.17.

The reflection matrix can be used in the same way as a Jones matrix to calculate the change in polarisation of an incident electric field. If the optical properties of the sample are known then R can be calculated. R can then be used to calculate the field modulation of the light measured by the

ellipsometer (see Figure 4.1), and hence relate the ellipsometric parameters $Tan\psi$ and $Cos\Delta$ to the optical properties of the sample.

4.3.3.1 Coordinate systems

When light is reflected from a surface, its direction of propagation is changed. It is therefore necessary to define two different coordinate systems in which to represent the Jones vectors, one for the incident light and another for the reflected light. These two coordinate systems are shown schematically in Figure 4.3.

The direction that the light travels before reflection and the direction it travels after reflection define a plane perpendicular to the plane of the sample surface called the plane of incidence. This plane is a convenient reference plane for all three coordinate systems. The unit vector, u , represents the direction that the incident beam is travelling and the unit vector, u' , represents the direction in which the reflected beam is travelling. Both u and u' lie in the plane of incidence. The unit vectors s and s' are defined to be perpendicular to the plane of incidence and therefore parallel to the plane of the surface. The s is used referring to “senkrecht” which is German for perpendicular. Finally, p and p' are defined as unit vectors perpendicular to both u and s , and u' and s' , respectively. Both p and p' will lie in the plane of incidence. The sense of p

Figure 4.3 Schematic of the reflection of light from a surface, showing the coordinate systems for the laboratory, the incident light, and the reflected light.

and p' are chosen so that p - s - u and p' - s' - u' each form a right-hand coordinate system.

The subscript p is used to identify the component of an electric field vector that lies in the plane of incidence and the subscript s to identify the component of an electric vector perpendicular to this plane for both the incident and the reflected light.

The relation between the incident light and the reflected light in the Jones vector formulation is written as:-

$$\begin{bmatrix} E_{p,r} \\ E_{s,r} \end{bmatrix} = \begin{bmatrix} R_{11} & R_{12} \\ R_{21} & R_{22} \end{bmatrix} \begin{bmatrix} E_{p,i} \\ E_{s,i} \end{bmatrix} \quad [4.19]$$

where the subscripts i and r indicate incident and reflected light.

In general, the off-diagonal elements of the reflection matrix are zero for isotropic and optically well-behaved samples (*Azzam and Bashara*). The off diagonal elements generally define systems which convert p -polarised light to s -polarised light and vice-versa (*Schubert et al.*; *Pettersson et al.*). In general, this doesn't occur in polymeric samples. Consequently, the reflection matrices considered here only contain the two complex numbers representing the reflection coefficients for s and p polarised light. This results in a change in the polarisation state of light reflected from the sample, which can be described using the Jones formalism:-

$$\begin{bmatrix} E_{p,r} \\ E_{s,r} \end{bmatrix} = \begin{bmatrix} R_p & 0 \\ 0 & R_s \end{bmatrix} \begin{bmatrix} E_{p,i} \\ E_{s,i} \end{bmatrix} \quad [4.20]$$

where R_p is the reflection coefficient for light with its electric vector in the plane of incidence and R_s is the reflection coefficient for light with its electric field vector perpendicular to the plane of incidence.

The above matrix equation can be written as two separate equations,

$$E_{p,r} = R_p E_{p,i} \quad \text{and} \quad E_{s,r} = R_s E_{s,i} \quad [4.21]$$

Consider Figure 4.3 and suppose that at some instant of time the incoming light that is linearly polarised with a positive p component and a positive s component. For an observer looking into the beam the electric field vector for this light will point to the right and up. In the case of the trivial example of linearly polarised light incident at normal incidence on a reflecting surface, that doesn't change the polarisation of the light at all. In this case, the electric field vector will not change its orientation when the light is reflected from the surface. However, the observer DOES change his point of view. The electric field vector of the reflected light will still have a positive s component, but after reflection, the p component of the electric field vector will also be negative. The electric field vector has not changed; it is the point of view of the observer and the orientation of the coordinate axes that have changed. This is because the reflection changes handedness in the same way that the reflection of a right hand in a mirror looks like a left hand. Of course, the same can be said for a light beam coming in at an arbitrary angle. For a perfect reflection, with no change in phase, the s component remains positive and the same size while the p component has the same magnitude but becomes negative. Consequently, the reflection matrix for such a surface is given by

$$\begin{bmatrix} -1 & 0 \\ 0 & +1 \end{bmatrix} \quad [4.22]$$

and not by the identity matrix. That is to say, $R_s = 1$ and $R_p = -1$. This behaviour is responsible for a phase shift of π in the p component of a wave for a perfect reflection.

In Ellipsometry the reflection properties of a sample are represented by the quantity:-

$$\rho = \frac{R_p}{R_s} = \tan \psi e^{i\Delta} \quad [4.23]$$

where ψ and Δ are the traditional parameters measured by ellipsometry. $\tan \psi$ is the ratio of $|R_p/R_s|$ and Δ is the change in phase difference between s and p components of the wave that occurs on reflection. Together these quantities describe the change in polarisation that occurs during reflection.

4.3.3.2 The Fresnel Reflection Coefficients

The next step is to determine how polarised light reflects from an interface between two materials with different indices of refraction. There are two different cases to consider. In one case, the electric field vector is parallel to the plane of incidence. This is the p or transverse magnetic polarisation. In the other case, the electric field vector is perpendicular to the plane of incidence. This is the s or the transverse electric polarisation.

Figure 4.4 (a) shows the situation for the p polarisation. A light beam whose electric field has an amplitude $E_{p,i}$ is incident on an interface between two

Figure 4.4 Schematic diagram of reflection and refraction of s & p -polarised light, showing the directions of the electric and magnetic fields for the incident, reflected, and refracted light.

media labelled 1 and 2 and characterized by indices of refraction N_1 and N_2 , at an angle of incidence ϕ_1 . Part of this incident beam is reflected from the interface and part is transmitted into the second medium. Let $E_{p,r}$ denote the electric field for the part that is reflected and $E_{p,t}$ denote the electric field for the part that is transmitted. The amplitude reflection and the amplitude transmission coefficients are defined as $r_p = E_{p,r}/E_{p,i}$ and $t_p = E_{p,t}/E_{p,i}$ respectively. The boundary conditions of electromagnetic theory require that the components of the electric and magnetic fields parallel to the interface must be continuous at the interface. If both media are optically well behaved (i.e., isotropic, etc.) then u , E , and H are mutually perpendicular and in general $H = N u \times E$, where u is a unit vector in the direction that the light is travelling and N is the index of refraction experienced by the light. It can be seen from Figure 4.4 (a) that the tangential component of the electric field of the incident light is $E_{p,i} \cos \phi_1$, that of the reflected light is $-E_{p,r} \cos \phi_1$, and that of the transmitted light is $E_{p,t} \cos \phi_2$. Equating the components of E parallel to the interface yields:-

$$E_{p,i} \cos \phi_1 - E_{p,r} \cos \phi_1 = E_{p,t} \cos \phi_2 \quad [4.24]$$

Equating the components of H parallel to the interface gives:-

$$H_{p,i} + H_{p,r} = H_{p,t} \quad [4.25]$$

Since the size of H is given by N, E this equation becomes:-

$$N_1 E_{p,i} + N_1 E_{p,r} = N_2 E_{p,t} \quad [4.26]$$

Combining these two equations and using the definitions of the amplitude reflection and transmission coefficients, the Fresnel equations for r_p and t_p can be found as:-

$$r_p = \frac{N_2 \cos \phi_1 - N_1 \cos \phi_2}{N_2 \cos \phi_1 + N_1 \cos \phi_2} \quad [4.27]$$

and

$$t_p = \frac{2N_1 \cos \phi_1}{N_2 \cos \phi_1 + N_1 \cos \phi_2} \quad [4.28]$$

Snell's law:-

$$N_1 \sin \phi_1 = N_2 \sin \phi_2 \quad [4.29]$$

represents an additional relationship that allows ϕ_2 to be calculated if the values of N_1 and N_2 and the angle of incidence ϕ_1 are known.

Turning to the s -polarisation and referring to Figure 4.4 (b), a similar analysis reveals that for continuity of the components of the electric field parallel to the interface requires that:-

$$E_{s,i} + E_{s,r} = E_{s,t} \quad [4.30]$$

while for continuity of the parallel components of the magnetic field means that:-

$$-H_{s,i} \cos \phi_1 + H_{s,r} \cos \phi_1 = H_{s,t} \cos \phi_2 \quad [4.31]$$

Since the size of H is given by n, E in each material, this last equation becomes

$$-N_1 E_{s,i} \cos \phi_1 + N_1 E_{s,r} \cos \phi_1 = N_2 E_{s,t} \cos \phi_2 \quad [4.32]$$

Combining these two equations results in the Fresnel equations for r_s and t_s :-

$$r_s = \frac{N_1 \cos \phi_1 - N_2 \cos \phi_2}{N_1 \cos \phi_1 + N_2 \cos \phi_2} \quad [4.33]$$

and

$$t_s = \frac{2N_1 \cos \phi_1}{N_1 \cos \phi_1 + N_2 \cos \phi_2} \quad [4.34]$$

Note that when $\phi_1 = \phi_2 = 0$ the transmission coefficients for p - and s -polarised light are identical, but the reflection coefficient for p -polarised light is the negative of that for s -polarised light as expected from section 4.2.3.1.

The Fresnel reflection and transmission coefficients for p - and s -polarised light are shown in Figure 4.5 (a) as a function of the angle of incidence for a dielectric material of refractive index 1.7 (approximately the refractive index of conjugated polymers). Note the point where the p reflection coefficient passes through zero. At this angle of incidence, known as the Brewster angle, the p -polarised component is completely suppressed from the reflected ray, and the light is entirely s -polarised. For angles of incidence less than the Brewster angle the reflected ray has an induced phase change of π for the p -polarised component (see Figure 4.5 (b)). Above this angle, there is no phase change in the p -polarised component. For the s -polarised component, no phase shift is observed over all angles of incidence in the range of 0° to 90° .

Figure 4.5 (a) The Fresnel Reflection and Transmission coefficients, for a dielectric, as a function of angle of incidence. The point where the p -reflection coefficient passes through zero is known as the Brewster angle. (b) The nature of the phase change upon reflection Δ for dielectrics and for materials of increasing absorption.

To fully understand the interaction of light with the material that the light is reflecting from the complex index of refraction N , needs to be defined as:-

$$N = n - ik \quad [4.35]$$

where n is the real index of refraction and k is the extinction coefficient. For a given material, n represents the ratio of the vacuum velocity of light to the phase velocity of the light in the material. The extinction coefficient is a measure of how rapidly the intensity of the light decreases as it passes through the material. All of the previously derived equations are valid when the indices of refraction are complex. The refractive index of air is always real (ie. $k=0$) and so the angle of incidence is real, although, if the index of refraction of the material is complex the angle of refraction must also be complex.

For a material with complex refractive index, the change in phase of the p -polarised component on reflection occurs gradually with increasing angle of incidence (see Figure 4.5 (b)). For low values of k the behaviour of the phase of the p -polarised component approaches the abrupt behaviour of the dielectric.

4.3.3.3 Isotropic Bare Surface Index Calculation

For the special case of a bare semi-infinite isotropic medium the ellipsometric values provide enough information to determine the complex index of refraction of the material. A material may be considered to be a substrate if:-

- It is absorbing and light does not reach the lower surface, e.g. a metal or silicon wafer without an oxide layer.
- Light reflected from the lower surface is scattered or diverted so that the reflected light does not go back to the detector, e.g. A glass wafer where the rear surface is abraded.

The measurement of $\rho=R_p/R_s$ from such a surface provides the real and imaginary components reflection properties of the sample. Using the

definition of ρ (equation 4.23), equations 4.26, 4.31, and Snell's Law (equation 4.28) yields:-

$$N_2 = N_1 \tan \phi_1 \sqrt{1 - \frac{4\rho \sin^2 \phi_1}{(1 + \rho)^2}} \quad [4.36]$$

which allows the direct inversion of Δ and ψ to determine the real and imaginary value of N_2 from a single measurement provided N_1 and the angle of incidence are known and the surface is free from films such as native SiO_2 on silicon substrates.

4.3.3.4 Thin Film Reflection Coefficients

The total amplitude reflection and transmission coefficients of a single uniform thin film on a substrate can be calculated using various different mathematical derivations. Each of these methods has advantages and disadvantages, although they all produce identical solutions.

The easiest way to visualise the calculation of a thin film reflection coefficient is to assess the multiple reflections that can take place in a thin film and to add up all of the contributions with their appropriate phase factors in order to find the total reflected and transmitted amplitudes.

Figure 4.6 (a) Multiple reflections of light in a single thin film. The index of refraction of the incident medium is n_1 , that of the film is n_2 , and that of the substrate is n_3 . (b) Schematic of two films stacked on a surface, including the various rays that must be taken into account to solve the problem by multiple reflections.

Consider the situation shown in Figure 4.6 (a) where a wave of amplitude A is incident on a film-covered surface. If the medium from which the light is incident is labelled medium 1, the film itself medium 2, and the substrate medium 3, then the wave is initially incident on the 1-2 interface from medium 1.

If r_{12} is the amplitude reflection coefficient for the 1-2 interface then a portion of the wave having an amplitude $r_{12}A$ is reflected at this interface. The rest of the incident wave is transmitted into the film so that just inside this interface its amplitude is given by $t_{12}A$, where t_{12} is the amplitude transmission coefficient for the 1-2 interface. The transmitted wave continues downward, into the film, until it strikes the 2-3 interface. Consequently it is phase shifted by an amount $\delta = 2\pi n_2 D \cos(\phi_2/\lambda)$. Here D is the thickness of the film, n_2 is its index of refraction, ϕ_2 is the angle of refraction for the light in the film and λ is the vacuum wavelength of the light.

The wave is then partially reflected back upward from the 2-3 interface, the reflection coefficient here is r_{23} . The reflected wave receives another phase shift of δ on the way back to the 2-1 interface. Some of this light is transmitted into medium 1 and some is reflected back into the film. The transmission coefficient at this interface is t_{21} and the reflection coefficient is r_{21} because the light is incident from the film side of the interface.

The light ray can be traced back and forth through the film forever, resulting in a total reflected amplitude, which is given by the infinite series:-

$$A\{r_{12} + t_{12}e^{-i\delta}r_{23}e^{-i\delta}t_{21} + t_{12}e^{-i\delta}r_{23}e^{-i\delta}r_{21}e^{-i\delta}r_{23}e^{-i\delta}t_{21} + \dots\} \quad [4.37]$$

so that the total reflection coefficient will be given by:-

$$R_{Total} = r_{12} + t_{12}t_{21}r_{23}e^{-i2\delta}\{1 + r_{21}r_{23}e^{-i2\delta} + (r_{21}r_{23}e^{-i2\delta})^2 + \dots\} \quad [4.38]$$

This series must always converge because there is no possibility that an infinite amount of light will be reflected from the surface when the amplitude

of the incident light is finite. The following relations can be used to simplify equation 4.38:-

$$r_{12} = -r_{21} \text{ and } t_{12}t_{21} = 1 - r_{12}^2 \quad [4.39]$$

These are both easily proved from the Fresnel coefficients (see equations 4.27, 4.28, 4.33 and 4.34). Using the binomial expansion:-

$$\frac{1}{1-x} = 1 + x + x^2 + \dots \quad [4.40]$$

which is similar to the series in equation 4.38 with $x = r_{12}r_{23}e^{-i2\delta}$ and converges if $|x| < 1$.

From these relations the total amplitude reflection coefficient for the wave can be deduced to be:-

$$R_{Total} = \frac{r_{12} + r_{23}e^{-i2\delta}}{1 + r_{12}r_{23}e^{-i2\delta}} \quad [4.41]$$

Since this derivation makes no reference to the actual polarisation state of the light, equation 4.41 gives the total reflection coefficient for the film covered surface for *p*-polarised light when the *p* Fresnel reflection coefficients are used and for *s*-polarised light when the *s* Fresnel reflection coefficients are used.

Similarly the total transmission coefficient can be found to be:-

$$T_{Total} = \frac{t_{12}t_{23}e^{-i\delta}}{1 + r_{12}r_{23}e^{-i2\delta}} \quad [4.42]$$

where, again, the total transmission is obtained for the *p*-polarisation and *s*-polarisation using the appropriate Fresnel coefficients.

4.3.3.5 Multiple Film Reflection Coefficients

It is sometimes needed to describe the reflection coefficient where there are several distinct films stratified on the sample surface. To begin with, consider a system with two films; then there will be four different materials and three interfaces, as shown in Figure 4.6 (b). Although in principle it may be possible to calculate the reflection coefficient directly by considering the multiple reflections as in section 4.3.3.4, in practice this becomes too tedious, especially in the case when there are more than two films.

However, it is possible to use the result from multiple reflection formulation effectively to provide a straightforward way of calculating the reflection coefficient from a sample consisting of more than one film. Recall that if there is a single film on a surface then the total thin film reflection coefficient, R_{Total} , is given by:-

$$R_{Total} = \frac{r_{12} + r_{23}e^{-i2\delta_2}}{1 + r_{12}r_{23}e^{-i2\delta_2}} \quad [4.43]$$

For a two-film system the term r_{23} , which represents the interfacial coefficient at the 2-3 interface for the single film case, can be replaced in the multiple film case by the total reflection coefficient for everything beyond medium number 2. That is, r_{23} should be replaced by R_{23} , where R_{23} is given by:-

$$R_{23} = \frac{r_{23} + r_{34}e^{-i2\delta_3}}{1 + r_{23}r_{34}e^{-i2\delta_3}} \quad [4.44]$$

Here R_{23} denotes the total reflection coefficient for everything beyond medium 2 and r_{23} to denote the actual Fresnel reflection coefficient between medium 2 and medium 3.

If medium number 4 is not the substrate but there are even more films, then r_{34} is replaced by R_{34} in the above equation where R_{34} is given by:-

$$R_{Total} = \frac{r_{34} + r_{45}e^{-i2\delta_4}}{1 + r_{34}r_{45}e^{-i2\delta_4}} \quad [4.45]$$

and so on.

This type of calculation can be used for any stratified system of layers by essentially working from the layer nearest to the substrate up to the top layer. This is ideal for implementation in an iterative route in a numerical calculation for the reflection coefficients of a stack of layers on a substrate.

4.4 Through the Ellipsometer –Extracting useful Data

At this point, all the necessary mathematics has been developed for tracing the change in the polarisation through the ellipsometer. The modulation of the intensity signal can now be evaluated. From this the measured parameters are introduced. The optical constants can then be derived from the measurement of these parameters.

4.4.1 Intensity Modulation of Light in the Ellipsometer

Since the initial light from the light source is unpolarised the usual rotational transformation before the polariser is unnecessary as the amplitude of the Jones vector after polarisation will be the same. Therefore, this rotation can be omitted from the calculation of the Electric field reaching the detector. Referring to Figure 4.1 the field, E_d , reaching the detector, at any given wavelength, can be written as:-

$$E_d = \hat{A}(\theta_A) * \hat{S} * \mathbb{R}(-\Omega t) * \hat{P}(0) * L \quad [4.46]$$

where $\hat{A}(\theta_A)$ represents the analyser at an angle θ_A , $\hat{S}$ represents the sample, $\hat{P}(0)$ represents the polariser and L represents the light source. More explicitly this appears as:-

$$E_d = \begin{bmatrix} \cos^2 \theta_A & \cos \theta_A \sin \theta_A \\ \cos \theta_A \sin \theta_A & \sin^2 \theta_A \end{bmatrix} \begin{bmatrix} r_p & 0 \\ 0 & r_s \end{bmatrix} \begin{bmatrix} \cos \Omega t & -\sin \Omega t \\ \sin \Omega t & \cos \Omega t \end{bmatrix} \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} E_o \\ E_o \end{bmatrix} \quad [4.47]$$

which reduces to:-

$$E_d = |E_o| |r_s| \{ \rho \cos \theta_A \cos \Omega t + \sin \theta_A \sin \Omega t \} \begin{bmatrix} \cos \theta_A \\ \sin \theta_A \end{bmatrix} \quad [4.48]$$

I_d , the intensity measured by the detector, can be found from the identity, $|E_d^* E_d|$. Consequently I_d is given by:-

$$I_d = |E_o|^2 |r_s|^2 \{ \rho^* \cos \theta_A \cos \Omega t + \sin \theta_A \sin \Omega t \} \{ \rho \cos \theta_A \cos \Omega t + \sin \theta_A \sin \Omega t \} \quad [4.49]$$

This simplifies to give:-

$$I_d = I_o \{ \alpha \cos 2\Omega t + \beta \sin 2\Omega t + 1 \} \quad [4.50]$$

where:-

$$I_o = \frac{|E_o|^2 |r_s|^2}{2} \cos^2 \theta_A \{ \tan^2 \psi + \tan^2 \theta_A \} \quad [4.51]$$

$$\alpha = \frac{\tan^2 \psi - \tan^2 \theta_A}{\tan^2 \psi + \tan^2 \theta_A} \quad [4.52]$$

$$\beta = 2 \cos^2 \Delta \frac{\tan \psi \tan \theta_A}{\tan^2 \psi + \tan^2 \theta_A} \quad [4.53]$$

4.4.2 Measured Parameters in Ellipsometry - α and β

Early ellipsometry experiments used equation 4.50 to model the time dependant intensity signal directly using linear regression. While this is

Figure 4.7 Integrated signals actually measured in ellipsometric measurements. Signal is divided into four time "bins" of duration $1/8$ a polariser revolution.

mathematically correct it proved to be time consuming and computationally inefficient. A more effective method is to divide the intensity time dependence into four temporal bins, of duration $\frac{1}{8}$ the period of the polariser revolution (see Figure 4.7). The integrated signal intensity for each of these bins is recorded. These intensities are represented by S_1 , S_2 , S_3 and S_4 . It can easily be seen from equation 4.50 that the integrated intensities are given by:-

$$\begin{aligned}
 S_1 &= \int_0^{\pi/4} I_d dt = \frac{1}{2} \left\{ \alpha + \beta + \frac{\pi}{2} \right\} \\
 S_2 &= \int_{\pi/4}^{\pi/2} I_d dt = \frac{1}{2} \left\{ -\alpha + \beta + \frac{\pi}{2} \right\} \\
 S_3 &= \int_{\pi/2}^{3\pi/4} I_d dt = \frac{1}{2} \left\{ -\alpha - \beta + \frac{\pi}{2} \right\} \\
 S_4 &= \int_{3\pi/4}^{\pi} I_d dt = \frac{1}{2} \left\{ \alpha - \beta + \frac{\pi}{2} \right\}
 \end{aligned}
 \tag{4.55}$$

Solving these equations for I_o , α and β gives:-

$$\begin{aligned}
 I_o &= \frac{1}{4} \{ S_1 + S_2 + S_3 + S_4 \} \\
 \alpha &= \frac{1}{2I_o} \{ S_1 - S_2 - S_3 + S_4 \} \\
 \beta &= \frac{1}{2I_o} \{ S_1 + S_2 - S_3 - S_4 \}
 \end{aligned}
 \tag{4.56}$$

From this α and β may be determined directly from S_1 , S_2 , S_3 and S_4 . $\tan \psi$ and $\cos \Delta$ can then be obtained using:-

$$\begin{aligned}
 \tan \psi &= \sqrt{\frac{1+\alpha}{1-\alpha}} \tan \theta_A \\
 \cos \Delta &= \frac{\beta}{\sqrt{1-\alpha^2}}
 \end{aligned}
 \tag{4.57}$$

This allows extremely precise measurements of these two parameters to be made, since S_1 , S_2 , S_3 and S_4 may be obtained by averaging over many polariser revolutions. For spectroscopic ellipsometry the traditional ellipsometric parameters, $\tan \psi$ and $\cos \Delta$, are determined. This is because in spectroscopic ellipsometry only polarisers are being used to determine the change in

polarisation state upon reflection. While it is possible to evaluate ψ unambiguously from equation 4.57 this isn't possible with Δ since $\cos\Delta = \cos(-\Delta)$.

It is important that the intensity signal to noise ratio at the detector is maximised to ensure that the measurement of $\tan\psi$ and $\cos\Delta$ is optimised. More significantly it is the signal to noise ratio of the minimum integrated intensity bin, which must be maximised, this is S_3 in Figure 4.7. This can be achieved by maximising the intensity minimum. The signal minimum can be found from equation 4.50 to be:-

$$I_{d\min} = I_o(1 - \sqrt{\alpha^2 + \beta^2}) \quad [4.58]$$

To maximise this $\alpha^2 + \beta^2$ must be minimised. Differentiating this quantity with respect to A yields:-

$$\frac{\partial(\alpha^2 + \beta^2)}{\partial A} = (\tan^2 A - \tan^2 \psi)(4 - 2\cos^2 \Delta) \quad [4.59]$$

This is equal to zero for a minimum, and so:-

$$\tan A = \tan \psi \quad [4.60]$$

Therefore in order to maximise the signal to noise of α and β the analyser must be set equal to ψ . This can be achieved by first measuring the value of ψ at an arbitrary value of A and then re-measuring with the analyser set to the measured value of ψ . Such a procedure is known as *tracking*.

4.4.3 Extracting the Optical Constants

Although the calculation of multiple-film reflection coefficients is not difficult, the interpretation of the ellipsometric data from thin film samples is not trivial. For a multiple thin film system no matter what way the data is

represented (α and β or $\tan \psi$ and $\cos \Delta$) there is only enough information to determine two unknowns. With even a monolayer sample on a known substrate, there are three unknowns (n , k and film thickness) to be determined. In experimental situations there are likely to be yet more unknowns to be determined.

This may be overcome in spectroscopic ellipsometry by utilising the spectral data, (i.e. two ellipsometric measurements for each wavelength). If there were no dispersion in the sample it would be a relatively simple task to calculate the optical constants and film thickness from two spectral measurements of $\tan \psi$ and $\cos \Delta$. This would allow up to four unknowns to be determined. In general for N spectral measurements up to $2N$ unknowns could be evaluated in this way.

However, there is undoubtedly dispersion present in real materials. This can be overcome by using optical models of the dispersion in the sample, to represent the unknown refractive index of layers in the sample. Depending on whether or not there is absorption present in the sample a model can be described by as little as three parameters. Considering that a typical ellipsometric spectrum consists of around 100 spectral measurements, such a situation should present no problems in evaluating these parameters, as well as any remaining unknowns, such as film thickness.

It would be extremely cumbersome to set up and solve individual equations for solving these unknowns every time a sample was measured. Another problem with such a methodology is that the noise in the ellipsometric parameters is much increased when such inversion techniques are used (Tompkins and McGahan). A more flexible method is to evaluate the ellipsometric parameters using an arbitrary structural and dispersion model of the sample. The model can then supply values of n and k which can be translated into model values of $\tan \psi$ and $\cos \Delta$. Such a model can then be fit

to the experimental data with a non-linear regression algorithm using the unknowns as free parameters in the regression.

4.4.3.1 Isotropic Cauchy Model

From first principles, the index of refraction and the extinction coefficient (the real and imaginary parts of the complex index of refraction) are not independent quantities. The Kramers-Kronig relation correlates the two different parts of the complex refractive index (*Lipson et al.* pg. 399). If the value of the extinction coefficient is known over the entire spectral range, the index of refraction may be calculated. However, it is not experimentally possible to measure the absorption over this range. The best that can be achieved is to measure the absorption over a spectral window and then fit a model, which is consistent with this data. Various models have been developed to model both the index of refraction and the extinction coefficient. Here only the simplest models are required over the spectral range specified by the emission spectra of the conjugated polymers under study.

For conjugated polymers, the absorption stretches from the edge of the visible and UV to higher energies. At lower energies, the value of n decreases as the wavelength increases and the value of k is essentially zero. The values of the index of refraction as a function of wavelength for many polymers can then be described in this spectral region by the Cauchy function, which uses only three parameters. It is given by:-

$$n(\lambda) = A + \frac{B}{\lambda^2} + \frac{C}{\lambda^4} \quad [4.61]$$

and the parameters A , B and C are called the Cauchy parameters. It is these parameters, which are evaluated in the modelling process of the data analysis of the ellipsometric data. This equation is valid for transparent or nearly transparent (ie. $k \approx 0$) spectral windows below the absorption edge of most of the conjugated polymers studied in this work. Since the ASE maximum is significantly red-shifted from the band-edge in all of the materials (see section

3.4.1), the Cauchy relationship can be used to describe the optical constants in the spectral region of the emission.

When there is absorption present in the spectral window under study, the Cauchy relationship is insufficient to describe the index of refraction, and the value of the extinction coefficient is no longer negligible. The appearance of a non-negligible extinction coefficient, k , within the spectral region of interest constrains the real part of the refractive index, n , to obey the Kramers-Kronig relationship:-

$$n(\varepsilon) = 1 + \frac{2}{\pi} \int_0^{\infty} \frac{\varepsilon' k(\varepsilon')}{\varepsilon'^2 - \varepsilon} d\varepsilon' \quad [4.62]$$

where the value of n at a given photon energy, ε , is related to k over all photon energies. This means that any function used to describe the spectral response of the extinction coefficient, k , must be accompanied by a corresponding function for n , satisfying equation 4.62.

Due to the inhomogeneous broadening present in organics, absorption peaks are best modelled using a gaussian function. The Kramers-Kronig consistent functions for a gaussian absorption peak, and its corresponding refractive index function are given by:-

$$\begin{aligned} k(\lambda) &= A_0 \operatorname{Re} \left\{ e^{-z^2} \operatorname{erfc}(-z) \right\} \\ n(\lambda) &= A_0 \operatorname{Im} \left\{ e^{-z^2} \operatorname{erfc}(-z) \right\} \end{aligned} \quad [4.63]$$

where A_0 is a constant and z is given in terms of the width, σ , and the central wavelength, λ_0 , of the gaussian by $z = \frac{\lambda_0 - \lambda}{\sigma}$ in terms of the wavelength λ . These functions can be superimposed on top of a Cauchy function to model materials displaying infra-red or other sub-gap absorption peaks. Although the dispersion due to the UV $\pi-\pi^*$ absorption remains dominant, it needs to be modified by adding equations 4.63 to the Cauchy function to take account of the proximity of the sub-gap absorption.

Figure 4.8 Schematic showing the interaction of p-polarised light with the optical indicatrix of a spin-cast polymer film.

4.4.3.2 Uniaxial Model

Due to the nature of polymeric thin films, and their formation through the spin coating procedure, the polymer chains tend to be aligned within the plane of the film. Since the absorption processes in the polymer occur along the polymer backbone, there is an inherent anisotropic behaviour in the optical constants in this direction. For an electric field polarisation in the plane of the film the refractive index is larger than for an electric field polarisation perpendicular to the plane of the film. This produces a uniaxial anisotropy, and results in the optical indicatrix looking much like a squashed sphere in shape, i.e. there are two n_{ord} components and a smaller n_{ext} along the optical axis, perpendicular to the plane of the film (see Figure 4.8).

For the situation illustrated in Figure 4.8 the reflection coefficients from the upper interface between materials 1 and 2 are (Azzam and Bashara):-

$$r_p^{12} = \frac{N_{2ord}N_{2ext}\cos\phi_1 - N_1\sqrt{N_{2ext}^2 - N_1^2\sin^2\phi_1}}{N_{2ord}N_{2ext}\cos\phi_1 + N_1\sqrt{N_{2ext}^2 - N_1^2\sin^2\phi_1}} \quad [4.64]$$

$$r_s^{12} = \frac{N_1\cos\phi_1 - \sqrt{N_{2ord}^2 - N_1^2\sin^2\phi_1}}{N_1\cos\phi_1 + \sqrt{N_{2ord}^2 - N_1^2\sin^2\phi_1}} \quad [4.65]$$

The reflection coefficients for the lower interface between materials 2 and 3 are (Azzam and Bashara):-

$$r_p^{23} = \frac{-N_{2ord}N_{2ext}\cos\phi_3 - N_3\sqrt{N_{2ext}^2 - N_3^2\sin^2\phi_3}}{N_{2ord}N_{2ext}\cos\phi_3 + N_3\sqrt{N_{2ext}^2 - N_3^2\sin^2\phi_3}} \quad [4.66]$$

$$r_s^{23} = \frac{-N_3\cos\phi_3 + \sqrt{N_{2ord}^2 - N_3^2\sin^2\phi_3}}{N_3\cos\phi_3 + \sqrt{N_{2ord}^2 - N_3^2\sin^2\phi_3}} \quad [4.67]$$

This is related to the angle of incidence in the ambient by Snell's law:-

$$N_1\sin\phi_1 = N_3\sin\phi_3 \quad [4.68]$$

When these reflection coefficients have been evaluated, the total reflection coefficient for the sample can be evaluated in the same way as for isotropic films using equation 4.41. The phase shift, for the p -polarisation, associated with the light travelling through the film is given by (Azzam and Bashara):-

$$\delta_p = 2\pi \frac{D_2 N_{1ord}}{\lambda N_{1ext}} \sqrt{N_{1ext}^2 - N_0^2 \sin^2\phi_0} \quad [4.69]$$

while the phase shift for the s -polarisation is given by (Azzam and Bashara):-

$$\delta_s = 2\pi \frac{D_2}{\lambda} \sqrt{N_{1ord}^2 - N_0^2 \sin^2\phi_0} \quad [4.70]$$

Ellipsometry is not sensitive to uniaxial anisotropy in the optical constants for films of thickness $< 100\text{nm}$ (Azzam and Bashara). Below this film thickness, any uniaxial film can only be modelled with an isotropic model. The results of such a modelling procedure give the ordinary refractive index of the optical indicatrix. For this reason isotropic models were used for any polymeric films less than 100nm .

4.4.3.3 Models to Interpret Surface Roughness or Inhomogeneous Films

In section 3.3.1, the dynamics involved in spin casting polymer thin films were discussed. It has been seen that solvent turbulence effects during the spin casting procedure produce inhomogeneous films with a “fluffy” or rough surface on top of a more densely packed layer.

Such structure in the film can be modelled using a bi-layer model. The lower layer can be modelled using a regular Cauchy model to model the optical constants of the more densely packed region. The upper layer can be modelled using a Bruggeman Effective Medium Approximation (BEMA) of a mixture of the dielectric constants of void space and the lower level, which has already been modelled. The dielectric constant is defined as $\epsilon = N^2$. The upper layer could of course also be modelled using another Cauchy model. However using the effective medium approximation has the advantage of introducing only one free parameter into the regression. As a result, this approach is favoured here over the use of a further Cauchy model to describe the upper layer.

The dielectric constant, ϵ , from a BEMA of a mixture of two different dielectric constants ϵ_A and ϵ_B is given by (Yang):-

$$f_A \frac{\epsilon_A - \epsilon}{\epsilon_A + 2\epsilon} + (1 - f_A) \frac{\epsilon_B - \epsilon}{\epsilon_B + 2\epsilon} = 0 \quad [4.71]$$

where f_A is the fraction of material A in the mixture. Yang supplies an algorithm for solving for ϵ from equation 4.71.

4.4.3.4 Model for Interpreting Composite Films

In some cases, it is necessary to consider the film as a composite of two separate materials with distinct optical constants. The average dielectric function of such a composite system can be described using Maxwell-Garnett theory. This model describes an inhomogeneous two-component medium

composed of guest inclusions, of dielectric constant ϵ_{guest} , embedded in an otherwise homogeneous 'host' matrix, of dielectric constant ϵ_{host} . *Bohren and Huffman* define the generalised Maxwell-Garnett dielectric function for an guest-host system, where the guest inclusions are arbitrary spheroids, as:-

$$\epsilon_{\text{av}} = \frac{(1-\rho)\epsilon_{\text{host}} + \rho\mathcal{F}\epsilon_{\text{guest}}}{1-\rho + \rho\mathcal{F}} \quad [4.72]$$

where ϵ_{av} is the average dielectric constant, ρ is the volume fraction of the inclusions and $\mathcal{F}$ is the local field factor of the guest inclusions. *Bohren and Huffman* write the local field factor of the guest inclusions as:-

$$\mathcal{F} = \iint \mathcal{P}(L_1, L_2) \frac{\sum_{j=1}^3 \lambda_j}{3} dL_1 dL_2 \quad [4.73]$$

where $\mathcal{P}(L_1, L_2)$ is the shape probability distribution function of the inclusions, L_1 and L_2 are geometrical factors, called depolarisation factors, related to the effect of the geometry of the inclusions on the average dielectric constant. λ_j are the principal components of the tensor relating the average electric field components inside the spheroid guest inclusions to the field in the host. These tensor components are written as:-

$$\lambda_j = \frac{\epsilon_{\text{host}}}{\epsilon_{\text{host}} + L_j(\epsilon_{\text{guest}} - \epsilon_{\text{host}})} \quad [4.74]$$

4.5 Isotropic Measurements of Refractive Index of Polymeric Materials

A series of conjugated polymers were spin cast on silicon substrates, and baked under vacuum at 60°C. The charge transfer complex PBD was dissolved with PMMA in a ratio of 3:1 so that a spin cast film could be

formed. An Alq₃ film was also prepared by vacuum deposition directly onto the silicon substrates in the usual manner.

These samples were then measured at an angle of incidence of 65°, which is close to the Brewster angle ($\phi_B = \tan^{-1}[n]$, n for conjugated polymers ~ 1.7) of conjugated polymers, using a SOPRA ES4G spectroscopic ellipsometer. Measurement of samples close to the Brewster angle maximises the polarisation of the reflected light and hence the magnitude of the $\tan \psi$ peaks (see section 4.5.2), which improves the sensitivity of the fitting procedure to the determination of parameters. Each sample was then aligned using the alignment telescope to ensure the same sample position for each sample. The alignment telescope (see Figure 4.1) is pre-aligned using a SiO₂ on silicon calibration wafer. The alignment telescope projects a collimated beam onto the sample and collects the beam from its normal reflection. The sample is adjusted so that the orientation of the beam coincides with itself upon reflection. It is then ensured that the signal intensity is of sufficient magnitude to emerge from any background noise at 1380nm and 620nm. This is to confirm that the signal intensity is adequate for both the photomultiplier tube and the GaInAs photodiode, so that measurements can be carried out effectively. Any number of counts from 100,000/sec to 1,000,000/sec on the detector was generally accepted. 100 spectral measurements were then taken between 1.653 μ m and 0.496 μ m.

Due to the need for flexibility in optical modelling a regression package was developed specifically for the data analysis of these materials. The package uses a Levenberg-Marquardt nonlinear least squares fitting algorithm (*Press*) to perform the regression on the raw data. Various optical models are available and the package allows the easy integration of new models with minimum editing of source code. The program was written in C and run on a Linux platform, using gnuplot to display the regression results (see appendix).

Figure 4.9 Ellipsometric and Regression results from a bare silicon substrate.

4.5.1 Modelling of the Substrate

The results and modelling for a bare substrate are shown in Figure 4.9. The model applied here is for a monolayer of SiO₂ on silicon crystal. The SiO₂ layer thickness was used as a free parameter in the regression. The film thickness from the regression was found to be $\sim 2.0\text{nm}$, which is consistent with the expected SiO₂ layer thickness from exposure of the silicon to ambient oxygen.

From this point forward in any modelling of the results for organic thin films assumes that the substrate is a silicon crystal with a 2.0nm layer of SiO₂. The SiO₂ layer thickness was kept as a fixed parameter during any regressions or calculations from this point forward.

4.5.2 Modelling of Polymer Thin films

For regression to be truly meaningful, the size of the residuals from the fitting must not be significantly greater than 2-3 times the standard deviation of the data itself, and they must be symmetrically distributed about zero. This is another way of saying that the regression line should travel through the mean of a cloud of data points, associated with the experimental noise present in the measurement. This can be achieved quantitatively by minimising a

maximum likelihood estimator. The maximum likelihood estimator is used for this work is written as:-

$$\chi^2 = \frac{1}{2N-M-1} \sum_{i=1}^n \left\{ \left(\frac{Tan\psi_{Data}^i - Tan\psi_{Model}^i}{\sigma_{Tan\psi}} \right)^2 + \left(\frac{Cos\Delta_{Data}^i - Cos\Delta_{Model}^i}{\sigma_{Cos\Delta}} \right)^2 \right\} \quad [4.75]$$

where N is the number of pairs of data points in the measurement, M is the number of parameters used in the regression, $\sigma_{Tan\psi}$ and $\sigma_{Cos\Delta}$ are the standard deviations for $Tan\psi$ and $Cos\Delta$ respectively. The standard deviation for a measurement of the ellipsometric parameters have been determined in Figure 4.10. This is achieved by subtracting two separate measurements from each other, over the spectral region 0.7-1.653 μm , (i.e. away from the dominant peak at 0.581 μm). The result from this subtraction is plotted below the measured parameters as $\delta Tan\psi$ and $\delta Cos\Delta$. This data is indicative of the experimental noise present in the data. The standard deviation for $Tan\psi$ and $Cos\Delta$ is then calculated from the distribution of this data about

Figure 4.10 Two separate measurements of $Tan\psi$ and $Cos\Delta$ for Thianthrene PPV are used to determine the standard deviation of ellipsometric measurements. The subtraction of the two measurements, away from significant features, are plotted as $\delta Tan\psi$ and $\delta Cos\Delta$ and the standard deviation of this determined.

Figure 4.11 Residuals of the fitting to $Tan\psi$ and $Cos\Delta$. Note that the value for χ^2 is inordinately high. There is still functionality remaining to be modelled in the ellipsometric data.

zero. It is now possible using these values for the standard deviations to estimate χ^2 during the fitting procedure.

χ^2 is basically just a way of comparing the residuals from the fit to the standard deviation of the data. Essentially $\sqrt{\chi^2}$ represents how far, on average the fit deviates from the data, in units of the standard deviation. An ideal fit would give $\chi^2=1$. A fit deviating by on average 2-3 standard deviation is still quite acceptable, which corresponds to a χ^2 of <10 .

Figure 4.11 shows the residuals from the fit of a simple Cauchy model to the experimental data for the Thianthrene PPV sample. As can be seen from the value of $\chi^2=174$ the fit is actually quite poor and the residuals are not normally distributed about zero, as would be the case for a good fit. This is symptomatic of the data for all the samples. While an initial observation of the fitting to the data is that the quality of the fitting appears to be excellent, the χ^2 statistic or an observation of the residuals is a more accurate measure of the quality of the fitting procedure.

In an attempt to improve the quality of the fitting procedure, three different models were proposed for polymeric films on silicon substrates. They are as follows:-

- Model I :- Regular isotropic Cauchy model for the polymer.
- Model II :- Regular isotropic Cauchy model for the polymer, incorporating a roughness layer, which is a BEMA with a mixture of one half void space and one half polymer.
- Model III :- Regular isotropic Cauchy model for the polymer, incorporating a roughness layer, which is a BEMA with a mixture of void space and polymer, with the mixing set as a free parameter in the regression.

The results from these fitting procedures are shown for all the measured materials in Figures 4.12-4.18. One of the most notable results from applying these models to the polymers is that $\chi^2 \approx 3200$ (about an order of magnitude larger than for the other thin films) for the PBD in PMMA film (see Figure 4.17). This is because a peak occurs in the $Tan\psi$ data at the position

Figure 4.12 Ellipsometric Data and results from regression of the proposed models for Alq3.

Figure 4.13 Ellipsometric Data and results from regression of the proposed models for DPOP-PPV.

where the detector changes. At this point the tracking temporarily breaks down, i.e. $Tan\psi$ is no longer equal to $TanA$, and the experimental noise increases so that the value for χ^2 is over estimated by the fitting procedure.

Strong peaks occur in the $Tan\psi$ data because the measurement was performed close to the Brewster angle of the polymer. Consequently, the reflection coefficient for the p -polarised light approaches zero, and most of

Figure 4.14 Ellipsometric Data and results from regression of the proposed models for HT94.

Figure 4.15 Ellipsometric Data and results from regression of the proposed models for MEH-DOO-PPV.

the wave from this polarisation is transmitted into the film. The reflection and transmission coefficients for the *s*-polarised light are approximately equal, with similar amounts of this component being reflected and transmitted into the film.

At the appearance of a peak in $Tan \psi$, destructive interference occurs between the light, which is reflected from the top interface, and the light, which is

Figure 4.16 Ellipsometric Data and results from regression of the proposed models for PFO.

Figure 4.17 Ellipsometric Data and results from regression of the proposed models for PBD doped into PMMA in a ratio of 3:1.

transmitted into the film and has been reflected upwards. Since the *s*-polarised light is split into two approximately equal amplitudes, the destructive interference acts to produce a small total reflected *s*-component. Most of the *p*-polarised light was transmitted into the film, and so the destructive interference produces a larger *p*-component in the reflected wave. This creates a maximum in $Tan\psi = \frac{|R_p|}{|R_s|}$. $Cos\Delta \cong 1$ at such an

Figure 4.18 Ellipsometric Data and results from regression of the proposed models for Thianthrene PPV.

interference fringe indicating that there is zero phase shift in the reflected light. From these observations it can be concluded from the raw data that in the spectral region of the peaks in $Tan\psi$ and $Cos\Delta$:-

- The angle of incidence is greater than the Brewster angle of the polymer. (no phase shift).
- The film refractive index is between the refractive index of air and the substrate. (no phase shift)
- There is no absorption present. ($Cos\Delta \cong 1$)

Due to the fact that most of the samples, with the exception of Alq₃ and the PBD doped PMMA, are of similar thickness and that there isn't a large contrast in the refractive index of these materials, the peaks in $Tan\psi$ and $Cos\Delta$ occur in similar positions. The information on the dispersion present in the samples is contained in the height and width of the peaks in $Tan\psi$ and $Cos\Delta$. This information is extracted, along with film thickness and structure, from the modelling parameters. The presence of well-defined peaks in the ellipsometric data is very important for the regression to find a clear global minimum for a given data set.

The χ^2 statistic remains inordinately high for all of the models proposed for the samples. In order to accept one of the models, either incorporating surface roughness or film inhomogeneity, the value for χ^2 should indicate that the fit improves by at least 2-3 standard deviations. In none of the data sets is there a significant increase in the quality of the fitting of the model to the data with the addition of either of the surface roughness structures. The conclusion from this must be that the simple Cauchy model fits to the data as well as either of the other two models. There is no experimental data to support the introduction of these more complicated models and from this point forward, they will be discarded in favour of the simple Cauchy model.

The general practice in the literature on ellipsometry is to accept the results of a curve fitting procedure provided it “looks good”. It is extremely rare that the χ^2 value or a similar statistic is quoted to quantify the validity of the model (Miller *et al.*). Without doubt, the curve fitting procedure employed here satisfies this criterion of “looking good”. This can be a somewhat dangerous strategy in a procedure, which relies so heavily on the modelling process for the extraction of useful information from the data. Nevertheless, it is not possible to discard the analysis of the simple Cauchy model, which generates the major trends in the data so accurately, and returns realistic parameter values. In this work, the presence of significant structure in the residuals points to some other factor influencing the shape of the data. This factor is somewhat loosely attributed to experimental artefacts, due to misalignments within the ellipsometry set-up. Such misalignments could be attributed to the light beam entering the collection optics at a slight skew angle. While in principle these artefacts could be added to a more complicated model incorporating misalignments in the ellipsometer, such a procedure would be quite intensive, with little reward in terms of useful information.

Table 4-1 Summarised Results for Simple Cauchy Model fitting to ellipsometry data. Also included is Profilometry Data for sample Film thickness. The standard deviation for each entry is shown after the $\pm$ symbol.

Material	Cauchy Parameters			Film Thickness Ellipsometry (nm)	Film Thickness Profilometry (nm)
	n_0	n_1	n_2		
Alq ₃	1.6594 $\pm$ 0.0004	0.0187 $\pm$ 0.0005	0.0018 $\pm$ 0.0002	288 $\pm$ 0.11	285 $\pm$ 20
DPOP-PPV	1.6377 $\pm$ 0.0011	0.0135 $\pm$ 0.0006	0.0032 $\pm$ 0.0001	85 $\pm$ 0.02	93 $\pm$ 5
HT94	1.6285 $\pm$ 0.0017	0.0187 $\pm$ 0.0010	0.0017 $\pm$ 0.0003	102 $\pm$ 0.03	104 $\pm$ 8
MEH-DOO-PPV	1.5613 $\pm$ 0.0025	0.0166 $\pm$ 0.0024	0.0266 $\pm$ 0.0007	117 $\pm$ 0.04	94 $\pm$ 7
PFO	1.5498 $\pm$ 0.0013	0.0263 $\pm$ 0.0007	0.0067 $\pm$ 0.0001	90 $\pm$ 0.02	96 $\pm$ 4
PBD-PMMA (3:1)	1.5943 $\pm$ 0.0006	0.0000 $\pm$ 0.0007	0.0004 $\pm$ 0.0002	164 $\pm$ 0.03	161 $\pm$ 13
Thiantrene PPV	1.6458 $\pm$ 0.0026	0.0161 $\pm$ 0.0016	0.0061 $\pm$ 0.0003	95 $\pm$ 0.04	102 $\pm$ 6

At this point, the remaining conclusion to be drawn is to accept the simple Cauchy model, with the qualification that there remain unmodelled experimental artefacts. To confirm the results from the ellipsometry procedure the samples were measured using stylus profilometry to determine the sample thickness. The results are summarised in Table 4-1 along with the parameters from a simple Cauchy analysis. All of the film thickness values predicted by the simple Cauchy model agree with the measured thickness from the profilometry measurements, within experimental error.

4.5.3 Inversion of the HT73 Polymer Data

The modelling of the HT73 sample presented some problems for the numerical modelling procedure described above. Within this data set there are no well-defined peaks in the ellipsometric data (see Figure 4.19). This means that the global minimum is less well defined, and so the fitting procedure produces optical constant values, which are divergent. A solution to this problem is to use an inversion technique on the raw data to extract the values of the optical constants directly. This involves estimating the film thickness through trial and error so that there is enough information to solve for values

Figure 4.19 Ellipsometric Spectra for HT73. It was not possible to obtain a unique solution with the standard modelling procedure. Inversion with a film thickness of 66nm produces the optical constant spectra shown here. A curve smoothing procedure was used to remove the noise from the data. Note the appearance of an absorption band in the IR part of the extinction coefficient.

of the optical constants, which are realistic. A value of 66nm for the film thickness is the only thickness value, which results in the optical constant spectrum producing results similar to the other conjugated polymers studied here. The results of the inversion of the ellipsometric values for HT73 are shown in Figure 4.19.

The results from the inversion explain the difficulties in fitting this data with a Cauchy model. The optical constants (refractive index, n , and extinction coefficient, k) are evaluated from above the band-edge out into the infrared. In the extinction coefficient spectrum, a significant absorption appears in the infrared part of the spectrum. This results in a region of anomalous dispersion in the refractive index. It is not possible for a simple Cauchy model to take account of this behaviour since it assumes that $k=0$ throughout the spectral range of the model.

Absorption measurements of this polymer do not reveal any absorption signal in the infra-red above that of the interference fringes. Hence the appearance of this band is not due to the normal linear absorption associated with the $\pi-\pi^*$ band transition. This may therefore be attributed to an excited state absorption because the polymer is being illuminated by light over a large spectral range, extending into the absorption band of the polymer and is thus more likely to excite long-lived excited state species (see section 5.2.1). The most likely candidate for this absorption is the polaron. In chapter 5, the appearance of these species in the absorption of conjugated polymers will be assessed.

4.5.4 Discussion of Isotropic Fitting Results

Since the spectral range of materials studied here spans the visible spectrum the refractive index of all of the materials cannot be compared directly. However, if the refractive index at a certain reference energy, defined to be at a specific energy below the bandgap, is known, then it is possible to use the refractive index at this reference energy to qualitatively observe any differences between the materials. Here the reference energy is defined to be

$\epsilon_R = \epsilon_g - 0.25\text{eV}$, where ϵ_g is the bandgap of the material. The reference energy is chosen to be 0.25eV below the bandgap, since the ASE maximum approximately occurs here for most polymers. Table 4-2 shows the bandgap, reference energy and the refractive index at the reference energy for some of the measured materials. There is a marked lack of contrast in the refractive index of the studied conjugated polymers. Nevertheless, it is noticeable that DPOP-PPV and HT94 have the lowest refractive index. In the case of DPOP-PPV, this can be attributed to the fact that it is a particularly disordered polymer, which results in a large free volume and so a lower dielectric constant. HT94 also has a large free volume, although this has less to do with disorder in the morphology of the polymer backbone and more to do with the long side chains acting to spread out the polymer chains, and thus lowering the dielectric constant. Also noticeable is the fact that Thianthrene PPV, which is well ordered, has a higher refractive index indicating a lower free volume.

It should be noted that a material with a high value for the refractive index does not necessarily have a low free volume. The presence of electron rich

Table 4-2 Table Showing the Bandgap Energy (Estimated from Absorption Spectra), the reference energy and the refractive index at the reference energy for the studied polymers polymers. Alq₃ has also been included for comparison.

Material	E_g	E_c	$n(E_c)$
Thiantrene PPV	2.61	2.36	1.785 ± 0.014
DPOP PPV	2.66	2.41	1.735 ± 0.006
MEH-DOO PPV	2.18	1.93	1.759 ± 0.012
HT73	2.10	1.85	$1.748 \pm \text{—}$
HT94	2.41	2.16	1.732 ± 0.008
PFO	2.88	2.63	1.761 ± 0.044
Alq ₃	2.75	2.50	1.765 ± 0.005

impurities and even molecular oxygen, within the polymer matrix may also act to raise the refractive index (*Osaki and Ishida*).

The lack of contrast in the refractive index between the polymers studied here does present problems in using these materials to increase optical confinement using a waveguide, made from these materials. However, in principle, a refractive index contrast Δn of up to 0.13 can be achieved by using wide bandgap materials such as PFO in the cladding layers, while using narrow bandgap materials such as MEH-DOO PPV or HT73 as the guiding layer of the waveguide. This is because the refractive index of the wider bandgap materials has relaxed significantly towards their DC level at the emission of the narrow bandgap materials, whose refractive index remains high because of the proximity of absorption levels to their emission.

In conclusion, the fitting of isotropic models to the ellipsometry data of thin films of conjugated polymers yields the following:-

- Poor fitting to the experimental data, although more complicated models do not improve the fitting to the data. The poor fitting is attributed to small misalignments in the experimental set-up.
- Film thickness measurements agree with profilometry measurements of the same samples, supporting the acceptance of the isotropic model for these films.
- Relatively poor contrast in the refractive index of the series of conjugated polymers studied here, although waveguides may be formed by the use of cladding layers made from wide bandgap materials, while using guiding layers made from low bandgap materials.

4.6 Uniaxial Measurements of Refractive Index of PmPV

As was discussed in section 4.3.3.2 ellipsometry becomes sensitive to the uniaxial nature of spin cast polymeric films when the film thickness is greater than $\sim 100\text{nm}$. In the case of the PmPV films studied here, it was found that isotropic models did not fit as well to the data as for other conjugated polymer films. Consequently, a uniaxial model was proposed for this polymer.

Figure 4.20 shows the ellipsometric data along with the fitting of a uniaxial model to the data. Below these are the resulting optical constant spectra for when the model has achieved it's best fit. As can be seen from the χ^2 statistic the quality of the fit is approximately the same as for the previous isotropic fitting models were for the thinner conjugated polymer films. The film thickness is 134nm and so this sample is just at the edge of detection for uniaxial behaviour, which is why a uniaxial model needs to be used in this case.

It is important to note that the model predicts that the ordinary refractive index is higher than the extraordinary refractive index, supporting the concept

Figure 4.20 Ellipsometric Data and results from regression of a uniaxial model without absorption for PmPV. The ordinary (n_{ord}) and extraordinary (n_{ext}) are shown in red. The uncertainty in the refractive index is omitted here for the sake of clarity, although it may be calculated from the uncertainty in the Cauchy coefficients.

of the polymer chains preferentially lying in the plane of the film. The ordinary refractive index is not greatly different from the values measured from the isotropic model for the other conjugated polymers. This highlights the fact that the refractive index modelled by the isotropic model is the ordinary refractive index, and not some combination of the ordinary and extraordinary refractive index.

4.7 Optical Constants of PmPV-Carbon Nanotube Composite thin films

Due to the limited number of suitable, low refractive index, charge transporting cladding materials, further candidates for such a role in a heterostructure waveguides need to be investigated. The PmPV carbon-nanotube composite discovered in Trinity College Dublin by *Curran et al.* displays excellent conduction properties (*Coleman et al.*) and has even been found to behave as an electron transport material in organic LED's (*Fournet et al.*). Consequently, such composite materials may well find a use as the charge transport/cladding layers in the heterostructure devices that are being proposed in this thesis.

Polymer nanotube composite solutions were made up at mass fractions (defined as $m_F = \frac{m_{NTSoot}}{m_{NTSoot} + m_{Polymer}}$ where m_{NTSoot} and $m_{Polymer}$ are the masses of the nanotube soot and the polymer respectively) of un-purified nanotube powder to polymer of 9%, 11%, 14%, 20%, 25%, 33%, 50% and 66%. The samples were made as follows:- A 66% sample was initially made by adding un-purified nanotube powder to a 30mg/ml solution of PmPV in *o*-Xylene in a ratio of two parts, by mass, of nanotube powder to one part polymer. This solution was initially intensely sonicated using an ultrasonic tip, followed by 2 hours sonication in an ultrasonic bath. This solution was then allowed to stand for 48 hours to allow in-soluble impurities (e.g. amorphous carbon and turbostratic graphite) in the nanotube powder to settle to the bottom of the solution. The solution was then decanted off from the settled solute resulting

Figure 4.21 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (9% mass fraction) composite.

in a pure solution of PmPV nanotube composite. The remainder of the solutions were then made up by diluting this solution with a stock 30mg/ml solution of PmPV in Xylene. These solutions were individually sonicated for 1 hour to disperse the nanotubes evenly throughout the solution. Thin films for ellipsometry were then spun on standard silicon substrates at 400rpm.

Figures 4.21-4.28 show the results of the regression of a uniaxial model

Figure 4.22 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (11% mass fraction) composite.

Figure 4.23 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (14% mass fraction) composite.

incorporating a Maxwell-Garnet effective medium approximation for needle-like inclusions on the ellipsometric data for composites of increasing mass fractions of un-purified nanotube powder to polymer from 9% to 66%.

In order to carry out the regression on the data, the local field factor, $\mathcal{F}$, in equation 4.72, must be evaluated at each wavelength of the $\text{Tan}\Psi$ and $\text{Cos}\Delta$

Figure 4.24 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (20% mass fraction) composite.

Figure 4.25 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (25% mass fraction) composite.

spectra. For needle-like inclusions, the local field factor is calculated from equation 4.73 and 4.74 to be:-

$$\mathcal{F} = \frac{5\epsilon_{host} + \epsilon_{guest}}{3(\epsilon_{host} + \epsilon_{guest})} \quad [4.76]$$

where ϵ_{host} and ϵ_{guest} are the dielectric constants of the polymer and the

Figure 4.26 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (33% mass fraction) composite.

Figure 4.27 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (50% mass fraction) composite.

nanotubes, respectively. The depolarisation factors were taken to be $L_1=0$ and $L_2=L_3=0.5$, which are consistent with a prolate spheroid inclusion (*Bohren and Huffman*).

The integral over the shape probability distribution, $\mathcal{P}(L_1, L_2)$, function in equation 4.72 was set to unity. This can be rationalised by considering that multi-walled nanotubes are typically tens of nanometers in diameter and

Figure 4.28 Ellipsometric Data and results from regression of a uniaxial model with absorption for PmPV nanotube (66% mass fraction) composite.

microns long, with aspect ratios generally in excess of 1000. During the composite preparation process, almost solely nanotubes are held while other non-cylindrical graphitic particles fall out of the polymer host (*Curran et al.*). As a result, the eccentricity, defined as $e = 1 - (|\text{minor axis}|)^2 / (|\text{major axis}|)^2$ of the inclusions is between 0.999 and 1, since the inclusions are almost exclusively nanotubes. Consequently, the shape of each nanotube inclusion can generally be considered as approximately the same, and so the integral over the shape probability distribution is equal to 1.

Referring to the data, the peaks in the $\tan\psi$ and $\cos\Delta$ spectrum decrease and become broader in intensity the higher the nanotube concentration. Less intense and broader ellipsometry peaks, are an indication of an increase in scattering or absorption within the films (*El Rhaleb et al.*). *Brennan* and *Ugarte et al.* have observed absorption in the near infrared and visible for multiwalled nanotubes in composite films and in aligned nanotube films respectively. As a result, it is necessary to include absorption in the optical constants of the nanotube inclusions. This is achieved by modelling the nanotube inclusions using a Kramers-Kronig consistent gaussian absorption function, super-imposed on a normal Cauchy function. The optical constants, of the guest inclusions, are also allowed to display a uniaxial anisotropy, with the extraordinary axis parallel to the normal of the polymer film.

A single regression was carried out on the 66% results, while holding the optical constants of the host medium constant at the values measured for a pure PmPV film (see section 4.6). The resulting optical constants for the nanotube inclusions are shown in Figure 4.29. The results of the regression place a broad absorption peak at $3.02\mu\text{m}$. Since this is well outside the spectral range of the measurement, little meaning can be attached to the position of this peak. Nanotube samples are known to contain a distribution of metallic, semi-metallic and semi-conducting nanotubes (*Ajayan et al.*). It is most likely that the increasing refractive index and extinction coefficient with increasing wavelength in the infra-red is due to Drude-like behaviour of the metallic nanotubes as opposed to edge of an absorption peak. The centring of a broad

Figure 4.29 Refractive Index and Extinction coefficient of the guest nanotube inclusions, as measured from the 66% mass fraction sample.

peak outside the spectral range of the measurement is merely the best way to model this behaviour and most likely has little physical meaning.

Using the optical constants of the nanotube inclusions and the polymer host, regression was carried out on each dataset in Figures 4.21-4.27, to obtain the optical constants of each film, with only the volume fraction of nanotubes and the film thickness as free parameters. The fits for this analysis are shown in the figures. The quality of the fitting procedure is comparable to the fitting for the isotropic polymer samples in section 4.5.2. It is noticeable that the total extinction coefficient for the composite films monotonically increases with increasing nanotube concentration. As a result, the refractive index begins to show anomalous dispersion in the near infra-red region at high nanotube concentrations. It can be seen that significant tuning of the refractive index can be achieved in the infra-red, at the expense of increased absorption, with increasing nanotube concentration. It should be noted that, for the 66% composite sample, the strength of the extinction coefficient ($k_{ord} = 0.12 @ 1.6\mu\text{m}$ corresponds to an absorption coefficient $\alpha = 2.5 \times 10^4 \text{ cm}^{-1}$) measured here will preclude this material from being used in waveguide applications, due to the heavy optical losses that this absorption will induce.

Figure 4.30 Measurement of volume fraction of nanotubes in spin cast polymer films against the mass fraction of nanotube soot in original solutions.

The anisotropy between the ordinary and extraordinary part of the refractive index also increases with increasing nanotube concentration. The increase in anisotropy can be attributed to the nanotubes having a greater physical length (0.1-10 μm) than the polymer, which ensures that they lie, even more preferentially than the polymer, within the plane of the film. The addition of such anisotropic elements to the polymer matrix acts to increase the observed anisotropy of the whole film.

It is instructive to plot the measured volume fraction of nanotube inclusions, ρ , from the regression of the datasets against the mass fraction of nanotube soot present in the original polymer solutions, before the films were spin cast (see Figure 4.30). As expected a linear relationship between these two parameters is observed. However, it should be noted that un-purified nanotube powder contains $\sim 30\%$ nanotubes (*Coleman et al.*). Therefore, the 50% mass fraction sample can actually contain no more than 23% pure nanotube by mass fraction, which corresponds to a maximum possible volume fraction of $\sim 15\%$ (assuming the density of the polymer is 1300kg/m³ and the density of the nanotube inclusions is the same as graphite ie.

2130kg/m³). The ellipsometry measurement of the volume fraction of nanotube inclusions at this concentration is almost twice this value.

The discrepancy between the measured value for the volume fraction of nanotube inclusions and the expected value deserves further comment. One possible scenario, which could explain this, is as follows; during the flow regime of the spin coating process, nanotubes are preferentially held in the film due to their greater inertial mass when compared to that of the polymer. This is analogous to pebbles lying on a riverbed; smaller pebbles are more likely to be displaced by the flow of the river than larger rocks. Consequently, the spin casting process may actually change the nanotube concentration in the resulting films, thus explaining the higher than expected values observed for the volume fraction of nanotube inclusions.

In conclusion, it can be said that the fitting of the results for the polymer nanotube composite samples, using the Maxwell-Garnet model, is comparable to that of the simple isotropic Cauchy model fits to the conjugated polymer data. The refractive index and the observed anisotropy of the polymer can be tuned across the measured spectral range with the addition of nanotubes with a noticeable increase of the refractive index in the infra-red. Such an increase in the refractive index makes the composites, of high nanotube concentration, less suitable as cladding layers in a waveguide as it is unlikely that a guiding layer of high enough index of refraction could be found to make a low loss waveguide. The presence of high levels of absorption in the composites will increase the propagation loss within a waveguide. However, a cladding layer of a low nanotube concentration composite could present a useful candidate as an electron transport layer.

4.8 Conclusions

The values for the ordinary refractive index for all of the conjugated polymers studied here have been obtained. Although the modelling procedure did not

provide entirely satisfactory fitting results, the agreement of the modelled film thickness with profilometry results and the realistic values obtained for the refractive index implied that the samples were modelled correctly. The discrepancy between the modelling of the data with an isotropic Cauchy model is believed to be due to experimental artefacts, which cannot be included into the model. The PmPV films were thick enough to measure uniaxial anisotropy within the films and a measurement could be made of the ordinary and extraordinary refractive index of this polymer. The uniaxial model fit to the data for this polymer was of similar quality to the isotropic models applied to the other polymers. The modelling of the PmPV nanotube composite data showed that the addition of nanotubes tuned the refractive index of the composite material with a notable increase towards the infra-red. This was at the expense of introducing significant absorption to the composite material. Such results make the composite a less attractive material for waveguide applications.

It is unlikely that a guiding layer of high enough index of refraction could be found to make a low loss waveguide. The presence of high levels of absorption in the composites will increase the propagation loss within a waveguide. However, it is possible that a composite made from low nanotube concentration could present a useful candidate for an electron transporting cladding layer.

References

- Azzam, R. M. A. and Bashara, N. M. (1977). Ellipsometry and Polarised light, Oxford.
- Brennan, M. E. (2001). Multiphoton Processes in Designer Organic Systems. Physics. Dublin, Trinity College Dublin.
- Coleman, J. N., Curran, S., Dalton, A. B., Davey, A. P., McCarthy, B., Blau, W. and Barklie, R. C. (1998). "Percolation-dominated conductivity in a conjugated-polymer-carbon-nanotube composite." Physical Review B-Condensed Matter **58**(12): R7492-5.
- Coleman, J. N., O'Brien, D. F., Dalton, A. B., McCarthy, B., Lahr, B., Barklie, R. C. and Blau, W. J. (2000). "Electron paramagnetic resonance as a quantitative tool for the study of multiwalled carbon nanotubes." Journal of Chemical Physics **113**(21): 9788-93.
- Curran, S. A., Ajayan, P. M., Blau, W. J., Carroll, D. L., Coleman, J. N., Dalton, A. B., Davey, A. P., Drury, A., McCarthy, B., Maier, S. and Strevens, A. (1998). "A composite from poly(m-phenylenevinylene-co-2,5-dioctoxy-p-phenylenevinylene) and carbon nanotubes: a novel material for molecular optoelectronics." Advanced Materials **10**(14): 1091-3.
- Drude, P. (1889). Annalen der Physik und Chemie **36**: 532.
- El Rhaleb, H., Cella, N., Roger, J. P., Fournier, D., Boccara, A. C. and Zuber, A. (1996). "Beam size and collimation effects in spectroscopic ellipsometry of transparent films with optical thickness inhomogeneity." Thin Solid Films **288**(1-2): 125-31.
- Fournet, P., Coleman, J. N., Lahr, B., Drury, A., Blau, W. J., O'Brien, D. F. and Horhold, H. H. (2001). "Enhanced brightness in organic light-emitting diodes using a carbon nanotube composite as an electron-transport layer." Journal of Applied Physics **90**(2): 969-75.
- Lipson, S. G., Lipson, H. and Tannhauser, D. S. (1995). Optical Physics, Cambridge University Press.
- Miller, E. K., McGehee, M. D., Diaz-Garcia, M., Srikant, V. and Heeger, A. J. (1999). "Index of refraction and waveguiding in thin films of a conjugated polymer which exhibits stimulated emission." Elsevier. Synthetic Metals **102**(1-3): 1091-2.
- Ajayan, P. M., (1997). "Carbon Nanotubes." Handbook of Organic Conductive Molecules and Polymers Nanostructured Materials and Nanotechnology. edited by H. S. Nalwa, Academic Press, 329-360.

Osaki, S. and Ishida, Y. (1973). "Injection of metal ions into polymer film by an electric field." Journal of Polymer Science, Polymer Physics Edition **11**(4): 801-5.

Pettersson, L. A. A., Carlsson, F., Inganaes, O. and Arwin, H. (1998). "Spectroscopic ellipsometry studies of the optical properties of doped poly(3,4-ethylenedioxythiophene): an anisotropic metal." Elsevier. Thin Solid Films **313-314**(1-2): 356-61.

Press, W. H. (1992). Numerical Recipes in C : the art of scientific computing, Cambridge University Press.

Rothan, A. (1945). Reviews of Scientific Instrumentation **16**: 26.

Schubert, M., Rheinlander, B., Woollam, J. A., Johs, B. and Herzinger, C. M. (1996). "Extension of rotating-analyzer ellipsometry to generalized ellipsometry: determination of the dielectric function tensor from uniaxial TiO_2 ." Journal of the Optical Society of America A-Optics & Image Science **13**(4): 875-83.

Tompkins, H. G. and McGahan, W. A. (1999). Spectroscopic Ellipsometry and Reflectometry - A Users Guide, Wiley Interscience.

Ugarte, D., Bacsá, W. S., Doudin, B., Forro, L. and de Heer, W. A. (1996). "Graphitic Nanotubes and Aligned Nanotubes Films." Brazilian Journal of Physics **26**(1): 123-7.

Yang, P. (2000). "Efficient finite-difference time domain scheme for light scattering by dielectric particles: application to aerosols." Applied Optics **39**(21): 3727-3737.

Chapter 5

EXCITED STATE ABSORPTION IN CONJUGATED POLYMERS

5.1 Introduction to Excited State Absorption

A prerequisite for the viability of a material in an electrically pumped polymeric laser is the display of lasing characteristics under optical pumping conditions. While this criterion, of pumping materials with high intensity pulses of short duration, will be satisfied by materials of large stimulated emission cross-section and good wave-guiding properties, other factors need to be considered. Indeed many materials, which in solution and dilute solid-state blends, display optically pumped lasing, will not do so under neat solid-state conditions and/or with pump pulses of longer duration.

In this chapter, features of the excited states of polymers will be examined. A case study of an initially promising material DPOP PPV is carried out in order to highlight the difficulties in producing suitable materials for polymeric lasing. The excited state absorption due to polarons for a variety of materials is then determined, and a strategy for improving future materials is discussed.

5.2 Polaron pairs in Conjugated Polymers

When an isolated small molecule is optically pumped, the only ways that the resulting singlet exciton can be quenched is by further absorption to higher singlet levels (e.g. S_1 - S_n) or by inter-system crossing (ISC) to a non-radiative triplet level. The absorption and emission transition rates of higher lying singlet levels generally take place on very fast timescales when compared to the lower S_0 - S_1 transitions. As a result, these transitions don't affect the population of the S_1 level significantly and significant population inversion can be readily obtained. Inter-system crossing prevents many organic dyes being used as continuous wave laser emitters due to the high inter-system crossing rates of organic molecules ($k_{ISC} \approx 10^5$ - 10^7 s⁻¹). This results in a build up of the triplet state population and subsequent quenching of singlet emission by T_1 - T_n absorption. Such problems can be overcome either by pumping the molecule with pulses of short duration (≤ 10 ns), which prevents inter-system

crossing to the triplet state, or by using molecules where the lack of spin orbit coupling k_{ISC} means is very small. Unfortunately, when the excited state dynamics of polymers are considered the situation is not so simple.

5.2.1 Formation of Inter-chain Polaron pairs

When a photon of energy greater than the absorption edge is incident on a chromophore of a conjugated polymer chain an electron and hole with opposite spins are excited in the LUMO and HOMO, respectively. In a material where two chromophores on two separate polymer chains are close enough to each other the possibility exists for the electron to transfer between the polymer chains and transfer the excitation to the second chromophore. Such a process is known as Förster transfer and will be discussed in more detail in section 5.2.3. The situation now exists whereby the excited electron and hole are separated onto adjacent chains, with their characteristic chain deformations constituting essentially a negative polaron P^- and a positive polaron P^+ bound by Coulomb attraction. Such a state consisting of a pair of separated bound polarons is termed an inter-chain polaron pair. This state can also be termed an excimer, if the two chromophores are equivalent, or an exciplex if the two chromophores are different.

In the presence of sufficient thermal energy kT the charges within the polaron pair can overcome the Coulomb attraction and move further away onto different polymer chains. It is by this mechanism that polaron states are formed by photo-excitation.

There is considerable experimental evidence indicating that excitons and other excited states are formed in PPV's by photo-excitation. The majority of these other species are bound inter-chain polaron pairs. Excitation spectra, corrected for absorbance, show that the quantum yield for singlet excitons is higher at low excitation energies than for higher energies (*Rothberg*). No change in decay lifetime was noted indicating that the emission only came from singlet excitons. Since the spectra are corrected for absorbance, this

behaviour indicates the presence of other excited states. The appearance of long-lived absorption bands at 0.5eV and 1.5eV after <1ps of excitation in PA experiments (*Hsu et al.*) on PPVs shows that there are excited states apart from the singlet exciton. Various species, such as polarons, bipolarons and triplet excitons as well as inter-chain polaron pairs, could have been responsible for these phenomena. The triplet exciton could not produce the two bands, at 0.5eV and 1.5eV, observed in the PA spectra. It is unlikely that two polarons could find each other and bind to form bipolarons in the short timescale observed in the PA experiments (<1ps). It is possible that polarons could have been responsible for the PA results. Both polarons and polaron pairs generate two absorption peaks, which could have occurred at 0.5 and 1.5eV. However only bound geminate polaron pairs could have produced the low carrier generation observed in the ps photoconductivity experiments of *Bradley et al.*. The low quantum yield for the generation of carriers in this experiment shows that most of the photons absorbed create bound geminate pairs. Consequently, it is generally accepted that the majority of excited states that are formed by photo-excitation in PPVs are bound polaron pairs.

5.2.2 Recombination of Inter-chain Polaron pairs

A polaron pair consists of two charges on separate chains, about 0.3-0.4nm apart. This means that the wavefunction overlap between the electron and the hole is very small. Accordingly, the radiative recombination rate of such polaron pairs is very small, despite being allowed by selection rules. As a result, the vast majority of polaron pairs decay non-radiatively, with the emission of phonons. The formation of polaron pairs is the primary cause of non-radiative relaxation in conjugated polymers, which, in general, results in the quantum yield being lower in conjugated polymers than in isolated small molecules where such excited states do not occur.

Radiative decay of inter-chain polaron pairs has been noted in cyano-PPV, CN-PPV by *Samuel et al.*. The photoluminescence was revealed as a second

band at a lower energy than the singlet exciton photoluminescence. This raises the question; why do inter-chain polaron pairs in CN-PPV decay radiatively and non-radiatively in other polymers? *Conwell et al.* performed Monte Carlo simulations on the packing of CN-PPV and MEH-PPV and found an inter-chain distance of 0.34nm for CN-PPV and an inter-chain distance of 0.41nm for MEH-PPV. It is believed that the shorter inter-chain distance facilitates better wavefunction overlap between the electron and the hole and results in a larger radiative recombination rate in CN-PPV than in other PPVs. Consequently emission is observed in CN-PPV, and other close packed polymers, but not in polymers of larger inter-chain distances.

The formation of an inter-chain polaron pair is also the mechanism by which polaron states relax. Free carriers of opposite charge in polymers are attracted to each other and form polaron pairs. These states then decay non-radiatively as before. Consequently, the formation of polarons and polaron pairs are the main non-radiative decay routes in conjugated polymers.

5.2.3 Energy Transfer

The term *energy transfer* is used to describe the process whereby an excited state can be transferred from one donor molecule to one acceptor molecule. It is not to be confused with *energy migration*, which refers to the process whereby an exciton moves through a material, usually by a series of energy transfers.

The primary mode of energy transfer that occurs in organic molecules is known as resonant or Förster transfer. This process depends upon an overlap between the absorption spectrum of the acceptor species and the emission spectrum of the donor species. The energy transfer is then mediated by a coherent dipole-dipole interaction between the donor and acceptor. The process is usually irreversible in organics because, when the energy has passed onto the acceptor species, relaxation through the vibrational levels (see section 2.4.2), present in the excited state, breaks the coherent dipole-dipole

interaction. The Förster energy transfer rate $K_{D \rightarrow A}$ for a donor and an acceptor separated by a distance R is given by *Pope and Swenberg*:-

$$K_{D \rightarrow A} = \frac{3f}{64\pi^5 \tau_{nat}^d R^6} \int_0^\infty \frac{E_F^d(\lambda) \sigma_{abs}^a(\lambda) \lambda^4}{n^4(\lambda)} d\lambda \quad [5.1]$$

where $E_F^d(\lambda)$ is the fluorescence quantum distribution spectrum (see equation 2.18) for the donor, σ_{abs}^a is the acceptor absorption spectrum, $n(\lambda)$ is the refractive index of the environment, f is an orientation factor, equal to $2/3$ for randomly orientated species, and τ_{nat}^d is the natural lifetime of the donor species. The natural lifetime is the time that the donor species spends within the vicinity of the acceptor species before being removed by radiative recombination, non-radiative decay or diffusion to other sites. The integration over all λ gives the overlap of the donor absorption spectrum and the acceptor emission spectrum. Equation 5.1 can be written as:-

$$K_{D \rightarrow A} = \frac{1}{\tau_D} \left(\frac{R_o}{R} \right)^6 \quad [5.2]$$

with

$$R_o = \left[\frac{3f}{64\pi^5} \int_0^\infty \frac{E_F^d(\lambda) \sigma_{abs}^a(\lambda) \lambda^4}{n^4(\lambda)} d\lambda \right]^{1/6} \quad [5.3]$$

where R_o is known as the Förster transfer radius. R_o is the distance at which the Förster transfer process to an acceptor species competes equally with the radiative recombination of the donor species. For acceptors within the Förster transfer radius of a donor the transfer rate is increased substantially above the radiative recombination rate. Consequently, no emission is observed from the donor and the excited state is transferred to the acceptor.

Förster transfer is a very important process within conjugated polymers and other organic materials. The presence of excited states such as polarons or

inter-chain polaron pairs cause absorption that overlaps the emission of singlet excitons. This causes the singlet exciton luminescence to be quenched in the presence of such excited state species. The formation of such species thus creates alternative non-radiative pathways for electrically and photo-excited species within polymers. Consequently, a good laser material should avoid the formation of polarons or inter-chain polaron pairs with an absorption overlapping the singlet exciton emission.

5.3 Polaron Absorption in DPOP-PPV - A case study

In recent years, there has been a rapid development in the physics of organic electroluminescent devices (*Friend et al.*). Enhanced understanding of material properties, such as carrier mobilities (see chapter 6) and PL yield is significant for realising an electrically pumped polymeric laser. Optically pumped organic lasing has been observed in numerous polymeric (*Hide et al.*) based devices and in many different structures, including distributed feedback systems (*Kallinger et al.*) and whispering gallery cavities (*Frolov et al.*). Investigations into electrically pumped lasing have been less successful. Large carrier densities have been observed but no spectral narrowing has been noted (*Harrison et al.*). Two explanations are put forward for this: non-balanced charge transport and excited-state absorption, which inhibits optical gain. In order to better understand the problems associated with electrical pumping of conjugated polymers a detailed analysis of the emission properties of a highly luminescent polymer, DPOP-PPV, is presented here. Of particular importance are the results on the quenching of stimulated emission by excited-state absorption. It will be shown here and in section 5.4, that excited-state absorption due to photo-induced and electrically induced species are of critical importance if conjugated polymers are to be used in electrically pumped lasers. This highlights the necessity to carefully consider the excited-state absorption during the design process of polymers for high luminescence efficiency optical applications.

5.3.1 Photo-physics of DPOP-PPV in Solution and Solid state

DPOP-PPV uses a common strategy in the design of conjugated polymers. Bulky side-groups are incorporated onto the polymer backbone at the vinylene bond, to induce disorder in the conformation of the polymer chain (see section 3.2.2), and to separate the polymer chains. This should prevent inter-chain species formation and exciton diffusion to quenching sites. Such a polymer should have a broad emission spectrum and a high PL quantum yield. The photo-physics of DPOP-PPV in solution and solid state will now be examined in detail.

5.3.1.1 Experimental Measurements of Photo-luminescence of DPOP-PPV

PL spectra of 0.25mg/ml solutions of DPOP-PPV in various solvents were measured using a Perkin Elmer LS50B luminance spectrometer. Solid-state spectra were taken of a thin film prepared by spin-coating from a 75mg/ml solution in toluene at 700rpm, giving a film thickness of 690nm. For PL the samples were excited at 440nm, the excitation maximum.

The quantum yield of DPOP-PPV in:- a dioxane solution, a 1% doping of a polystyrene (PS) matrix and a neat film were measured using an integrating sphere connected to a CCD grating spectrometer by an optical fibre, with an excitation wavelength of 354nm from a Helium Cadmium laser at $0.1\text{mW}/\text{cm}^2$. The use of the CCD spectrometer enables the PL signal and the exciting laser signal to be distinguished without the use of filters (*De Mello et al.*). The external PL quantum yield, defined as the ratio of the number of photons emitted to the number of photons absorbed, is calculated from the ratio of the integrated PL signal, with the sample in place, to the increase in the integrated laser intensity when the sample is removed.

The PL spectra for DPOP-PPV in various solvents and the solid-state are shown in Figure 5.1(a). The emission from solid-state and solution are broad

Figure 5.1 (a) The photoluminescence of DPOP-PPV in various solvents. (b) Plot of integrated PL intensity against solvent viscosity for DPOP-PPV. The quantum yield for emission increases with solvent viscosity.

bands with no apparent structure. The PL spectrum maximum in both solution and the solid-state is at 2.38eV, with no other strong vibrational features notable. Both the peak emission wavelength and the full width at half maximum were found to be largely independent of the solvent used. A large Stokes shift of $\sim 150\text{nm}$ is observed in both solution and the solid-state. The peak PL intensity, and hence the PL yield, was found to be highly solvent dependent. Significant decreases in emission were noted with toluene, tetrahydro-furan and chloroform when compared to dioxane.

The PL quantum yield for a dioxane solution of DPOP-PPV was measured to be $\sim 6\%$. In the solid-state a quantum yield of 52% is measured for a neat film, while the PL yield drops to 22% for the DPOP-PPV doped PS matrix.

5.3.1.2 Discussion of Photoluminescence of DPOP-PPV

Solvent choice can have strong influences on the PL of organic materials through dipole interactions, rotational effects, conformational changes (*Jones et al.*) and vibrational interactions (*Dhote et al.*). In this case, the unusual PL yield relationship in solution and the solid-state can be addressed by considering the large side groups attached to DPOP-PPV. There is a steric

hindrance between the two substituted phenoxyphenyl side groups and the phenyl ring on the polymer backbone resulting in a non-planar, conformation of the polymer. The broad structureless emission indicates a high degree of disorder and exciton confinement to short chain segments in DPOP-PPV. X-Ray diffraction experiments *Resel et al.* have shown that in the solid-state the polymer packs in a highly amorphous manner, producing severe torsional hindrances along the polymer backbone. The polymer packs by π -stacking of the phenoxyphenyl sidegroups, which rigidly support the polymer backbone in it's natural, disordered conformation. This results in large energy barriers to exciton hopping along the chain, which prevents exciton diffusion to quenching sites, and raises the PL yield. Similar improvements in the quantum yield have been observed in meta-substituted co-polymers of PPV where the conjugation along the polymer backbone has been broken (*Lipson et al.*). Further evidence for this interpretation arises from the luminescence emission maxima in both solution and thin film occurring at the same wavelength, which is indicative of an equivalent polymer chain orientation in both solution and solid-state. This is further supported by the strong relationship between PL yields and solvent choice. In solution, the polymer chains have greater spatial freedom to explore more planar conformations. This reduces the energy barriers for exciton diffusion along the polymer backbone, increasing the number of non-radiative routes available and decreasing the PL yield. The conformational freedom that the polymer has in solution is dependent on the viscosity of the solvent environment. It was found that the photoluminescence intensity is inversely proportional to the solvent viscosity (*Lide*) from Figure 5.1(b). The quantum yield of the matrix isolated DPOP-PPV in polystyrene, at 22%, indicates that the side chains have less freedom in the solid-state than in solution. The decrease in PL yield from neat solid-state to polystyrene is related to the fact that the side chains are not subject to close packing in the polystyrene matrix that they suffer in a pure DPOP-PPV environment.

5.3.2 ASE measurements on DPOP-PPV

In the solid state DPOP-PPV appears to be an excellent candidate for a laser material due to its broad emission spectrum and high quantum yield. A further criterion for a laser material is that it demonstrates Amplified Spontaneous Emission (ASE) in the solid state. In consideration of this, solid-state waveguides of DPOP-PPV were prepared and characterised so that ASE measurements could be carried out on this promising material.

5.3.2.1 Waveguide Characterisation and ASE Experiment

For a material to be a useful laser medium, it must have low scattering losses so that the propagation loss can be ignored with respect to the gain exhibited by the material. A film of DPOP-PPV on fused silica can act as an asymmetric waveguide, by using the fused silica and the ambient air as cladding. The polymer layer was produced by spin coating from a 75mg/ml solution in *o*-Xylene onto the substrate.

The propagation loss of such a waveguide was determined by first exciting a resonant mode using a prism film coupler (*Ulrich*). In the prism film coupler, the sample to be measured is brought into contact with the base of a prism by applying pressure to the base of the substrate with a screw clamp, creating a small air gap between the film and the prism. A collimated laser beam (HeNe

Figure 5.2 Experimental set up for determining (a) Waveguide Loss from a film on Fused Silica and (b) ASE detection from a similar waveguide on a thermally oxidised silicon wafer.

$\lambda=632.8\text{nm}$) strikes the base of the prism and is normally totally reflected at the prism base. At certain discrete values of the incident angle, the propagation constant of the incident light matches that of a waveguide mode and photons tunnel across the air gap into the film. The photons enter into a guided optical propagation mode, and a guided streak is observed propagating down the waveguide (see Figure 5.2(a)). The propagation loss of this mode can then be determined, using the method of *Okamura et al.*, by recording the scattered light along the track of such a resonant mode using a Nikon digital camera (see Figure 5.2(a)). A calibration of the length of the waveguide is then performed by imaging a ruler from the same aspect as the waveguide with the camera. The scattered intensity, I , can then be fit to the formula $I=I_0e^{-\alpha x}$ where I_0 is a constant, α is the scattering coefficient and x is the propagation length. The value for the loss can then be determined from the value of α .

ASE measurements are carried out on similar waveguides of DPOP-PPV on substrates of silicon wafers with a thermally grown layer of SiO_2 . The sample was pumped transversely (see Figure 5.2(b)) using a frequency tripled beam from a Nd:YAG laser, with $0.9\mu\text{J}$ pulses of 35ps duration at 355nm. A cylindrical lens is used to produce a thin pumped stripe 30mm long by 0.1mm wide. The pump length can then be adjusted by means of a shutter mounted on a translation stage. The waveguided output fluorescence was detected using a Peltier cooled CCD spectrometer (*Kretsch et al.*). The thin film substrate sample was cleaved along the $\langle 100 \rangle$ direction of the silicon to facilitate the output coupling of light from the waveguide.

5.3.2.2 Absence of ASE in DPOP-PPV

The scattered intensity versus the propagation length for the TE_0 mode of the waveguide is shown in Figure 5.3(a). The scattered intensity fits very well to the single parameter exponential decay outline in the previous section. The

Figure 5.3 (a) Determination of waveguide loss in a DPOP-PPV waveguide on fused silica. (b) Example of edge emission from a DPOP-PPV waveguide pumped at $8.5 \times 10^5 \text{ W/cm}^2$ in the ASE experiment. No spectral narrowing is observed.

waveguide loss, for the of the DPOP-PPV film, was found to be 5.7dB/cm (see Figure 5.3(a)). The emission spectrum from the DPOP-PPV waveguide on the silicon substrate is shown in Figure 5.3(b). No spectral narrowing was observed from the edge emission with increased pump intensity (maximum pump intensity was $8.5 \times 10^5 \text{ W/cm}^2$) or pump length dependence. The emission is merely due to fluorescence from the sample modified by waveguiding. There is no evidence of stimulated emission from the DPOP-PPV waveguide.

The absence of ASE within this material cannot be explained by scattering loss within the material. The waveguide loss of $5.4 \pm 0.1 \text{ dB/cm}$ indicates a low degree of polymer crystallinity and compares well with other highly emissive materials exhibiting ASE e.g. *m*LPPP which has a waveguide loss of $\sim 54 \text{ dB/cm}$ (*Sturm et al.*). Therefore, it is necessary to consider the excited states present in DPOP-PPV at high excitation intensities.

5.3.3 Excited State Absorption in DPOP-PPV

In order to explain the absence of ASE within a material of large PL yield and low scattering losses, the excited-state absorption of DPOP-PPV was

investigated. Photo-Induced Absorption (PA) spectroscopy was carried out, to investigate the absorption present in DPOP-PPV under high excitation intensities. These measurements were performed in the University of Sheffield under the supervision of Dr. Paul Lane.

5.3.3.1 Photo-Induced Absorption Experiment

PA spectroscopy can probe various excited-state absorptions (e.g. triplets and polarons) formed by photo-excitation. In this technique (see Figure 5.4) a 457.9 nm argon-ion laser line is used as the pump beam to excite the sample while a monochromated tungsten broad spectrum (0.5-5 μ m) light source is used as the probe. Both the pump and the probe were dispersed across the sample; the probe was assumed to have a uniform intensity and the pump a Gaussian distribution. An acousto-optical modulator was used to modulate the pump beam, while a photo-detector and a lock-in amplifier monitored the changes in the transmission of the probe beam.

The reason for using a phase sensitive (lock-in) detection technique is that the change ΔT in the sample transmission T is very small ($\Delta T / T < 10^{-4}$). The pump light is modulated at a reference frequency; therefore, ΔT is modulated at this frequency too. The modulated ΔT can then be detected by the lock-in amplifier referenced at the same frequency. The lock-in amplifier measures

Figure 5.4 Experimental Set-up for Photo-Induced Absorption Experiment.

the in-phase and quadrature signals with the laser modulation. By simultaneously measuring ΔT and T and scanning the wavelength of the probe light, the spectrum of the $\Delta T/T$ signal is obtained.

5.3.3.2 Temporal Response of PA Experiment

It is also possible to determine the lifetime of the excited species by measuring $\Delta T/T$ as a function of the modulation frequency. Provided the species lifetime can be considered mono-molecular, the frequency response of $\Delta T/T$ is relatively straight forward (*Lane et al.*, 1997).

Consider the intensity of the transmitted probe light through the sample:-

$$I(d) = \{1 - R\} I(0) e^{-\alpha d} \quad [5.4]$$

where $I(0)$ is the intensity of the probe light incident on the film, α is the absorption coefficient, d is the film thickness, R is the reflectivity, and the reflections from the backside are neglected. The absorption coefficient is equal to the number density of excitations times the absorption cross-section ($\alpha = N\sigma$). The pump beam induces changes in both α and R , resulting in a change in the transmitted intensity of:-

$$\Delta I(d) = \{1 - R\} I(d) [e^{-\Delta \alpha d} - 1] - \Delta R \cdot I(0) e^{-(\alpha + \Delta \alpha) d} \quad [5.5]$$

After dividing equation 5.5 by $I(d)$ (equation 5.4) and assuming that $\Delta \alpha d \ll 1$, the relative transmission is given by:-

$$\frac{\Delta T}{T} = \frac{\Delta I(d)}{I(d)} = -\Delta \alpha d - \frac{\Delta R}{1 - R} \quad [5.6]$$

In conjugated polymer samples R is less than 0.1 and $\Delta R/R \ll 10^{-6}$. Because $\Delta T/T$ is typically in the range 10^{-3} - 10^{-5} , the second term in equation 5.3 can be neglected. Note, this relation only holds in the small signal limit ($\Delta \alpha d \ll 1$)

for thin films, where the pump light is absorbed uniformly, creating an equal distribution in $\Delta\alpha$ across the film.

For lock-in amplification, the pump is modulated at a reference frequency ω (Figure 5.4), which means that ΔT is not constant in time. Rather its magnitude (and its phase) depends on the modulation frequency. In order to find the frequency dependent $\Delta T(\omega)$, the recombination dynamics are assumed to be mono-molecular with a single lifetime τ . Then the change in the number density of excitations N at time t can be written as:-

$$\frac{dN(t)}{dt} = G(t) - \frac{N(t)}{\tau} \quad [5.7]$$

where $G(t)$ is the generation rate and $N(t)/\tau$ describes the mono-molecular decay rate. The generation rate $G(t) = \gamma P(t)/\hbar\omega$, where $P(t)$ is the pump power, $\hbar\omega$ is the energy of a single pump photon and γ is the quantum efficiency of the photo-excitation. Now taking into account only the fundamental Fourier component, neglecting the higher orders:-

$$G(t) = G(\omega)e^{i\omega t} \quad [5.8]$$

And assuming $N(t)$ has the same form and substituting into equation 5.4, the frequency response of the number density of excitations is:-

$$N(\omega) = \frac{G(\omega)\tau}{1 + (\omega\tau)^2} - i \frac{G(\omega)\omega\tau^2}{1 + (\omega\tau)^2} \quad [5.9]$$

Relating $N(\omega)$ to the absorption cross-section σ ($\Delta\alpha = N\sigma$):-

$$\frac{\Delta T}{T} = \left\{ \frac{1}{1 + (\omega\tau)^2} - i \frac{\omega\tau}{1 + (\omega\tau)^2} \right\} A \cdot \tau \quad [5.10]$$

with $A = G(\omega) \cdot \sigma \cdot d$. The first term of equation 5.10 is the in-phase signal, which has the same phase as the pump, and the second term is a quadrature or out of phase signal, that is 90° phase relative to that of the pump.

5.3.4 Results of Photo-induced Absorption Experiment

Photo-induced absorption measurements were carried out on drop cast films of DPOP-PPV samples on fused silica substrates. All measurements were performed under vacuum ($\sim 2.7 \times 10^{-3}$ Torr; to prevent photo-degradation of the sample by oxygen) at 80K (to remove vibrational broadening effects e.g. phenyl ring oscillations (see section 2.10.1)).

5.3.4.1 Polaron Pair Absorption Peaks in DPOP-PPV

The PA spectrum of the DPOP-PPV film is shown in Figure 5.5. The PA spectrum is represented as the measured change in transmission normalised to the transmission for the probe beam. A strongly defined absorption feature appears at 1.9 eV, in both the in-phase and quadrature signals of the PA spectrum. For comparison, an example absorption spectrum of DPOP-PPV solution after FeCl_3 doping is also shown in Figure 5.5. As will be seen in section 5.4.1 the effect of doping a polymer with FeCl_3 is to produce an absorption due to positive polarons. This absorption band at 1.85 eV is very close to the PA band at 1.9 eV. The absorption due to the PA measurement and the doping induced absorption measurement are essentially due to the same energy transition between sub-gap energy levels. The spectral width of the PA feature is narrower (0.48 eV) than the doping induced absorption

Figure 5.5 In-Phase and Quadrature Photo-induced Absorption Signals. A Doping Induced Absorption signal has been included for comparison.

feature (0.9eV). It is proposed that this is due to the difference in temperature between the two measurements.

5.3.4.2 Lifetime measurements of polarons in DPOP-PPV

Figure 5.6 shows the dependence of the PA signal at 1.9eV with the pump beam modulation frequency. The frequency response of the in-phase and quadrature signals at 1.9eV was modelled using equation 5.10. The in-phase and quadrature signals were simultaneously fitted to the real and imaginary part of equation 5.10 respectively. A nonlinear regression algorithm was used to perform the regression with A and τ as free parameters. The quality of the model fit to the data, with a value of $\chi^2=4.378$, is highly suggestive of a mono-molecular decay rate for the PA signal. The lifetime obtained from the modelling of the frequency response of the PA signal is 0.5873 ± 0.0002 ms. The long lifetime indicates an energetically stable state that out lives the fluorescence (~ 1.44 ns) (*Penzkofer*) of the material. This indicates that the excited state will strongly quench the singlet fluorescence and hence quench stimulated emission.

Figure 5.6 Frequency Response of the In-Phase and Quadrature PA signals with theoretical fits for lifetime determination using equation 5.10.

5.3.5 Discussion of experimental results on DPOP-PPV

The key to interpreting the results of the PA spectroscopic experiment is that the measured PA signal is the same as that of the doping induced absorption measurement. It is expected that the absorption due to an inter-chain polaron pair would be similar to that of a polaron since, the energy levels of a polaron, in an inter-chain polaron pair, are not significantly affected by the presence of its companion polaron on another polymer chain (*Rothberg*). This effectively rules out most of the possibilities that the exciton triplet state or the bipolaron could have produced the PA signal. The lifetime measurement indicates that the decay of the PA signal is mono-molecular, which rules out the possibility of the PA signal being due to polarons, as polaron decay is bi-molecular. Consequently, the measured PA state is attributed to geminate polaron pairs. Both absorption bands overlap the PL spectrum of DPOP-PPV. As was seen in section 5.2 the presence of polarons or polaron pairs is known to quench singlet excitons (*Shinar*) and hence strongly reduce stimulated emission processes.

The phenoxyphenyl side chains provide the high T_g and PL yield for DPOP-PPV. However, they also have adverse effects by causing the high polaron or polaron pair population. Studies on families of di-phenyl substituted polymers have shown that none are suitable for optically pumped lasing (*Horhold et al.*). This is most likely due to the π -stacking of the phenoxyphenyl groups facilitating inter-chain electron transfer. The interaction of the side-groups provides a bridge of conjugation between the separated polymer chains, which allows the development of inter-chain polaron pairs. These states are localised over short chain lengths, which is consistent with the blue shift of the polaron pair absorption feature when compared to other PPV derivatives of similar emission wavelength (*Lane et al.*, 1997). It is this polaron pair absorption feature, which is preventing lasing from materials of this type by inhibiting emission from singlet excitons.

5.3.6 Summary of the Case Study on DPOP-PPV

This work provides an interesting study of how the chemical structure of DPOP-PPV strongly affects its optical properties in an unusual manner that was not foreseen. Initial results indicated excellent luminescent properties through exciton confinement along the polymer backbone. PA and doping induced absorption measurements have shown that the same structural feature that enhances luminescence destroys the simulated emission properties. The broad polaron pair absorption band centred on 1.9eV suggests DPOP-PPV is limited optically as a candidate for further electroluminescence studies only. To conclude, this work clearly demonstrates that in the design of highly luminescent polymers the alteration of excited-state absorption is valuable to complete the information of the ground state absorption and luminescence properties.

5.4 Polaron Absorption in other Conjugated Polymers

PA measurements were used to give quantitative measurements of the absorption intensity and lifetime of photo-excited states within DPOP-PPV. These measurements were performed during a short research expedition to the University of Sheffield. However to maintain the research strategy outlined in chapter 1, where a large body of materials is to be studied, further measurements need to be carried out on all of the materials in this thesis. As was mentioned in the previous section, the absorption of polymers doped with FeCl_3 is due to pure polarons on the polymer. It was possible to employ this method on a range of materials in TCD. Hence, further investigations into the excited state absorption are confined to doping measurements.

5.4.1 Absorption due to doping of Polymers with FeCl_3

FeCl_3 is an oxidising agent. As such, it is energetically favourable for FeCl_3 to be an electron acceptor. The backbone of conjugated polymers is rich in

electrons and so provides an ideal target for such electron acceptors. When a FeCl_3 molecule encounters a polymer chain, an electron is removed from the backbone. This results in a positive charge, or hole, residing on the polymer backbone, stabilised by a FeCl_4^- anion (*Przyluski et al.*). The hole, while electrostatically attracted to the counterion, behaves as a positive polaron. As a result, an absorption band associated with positive polarons appears in the absorption spectrum of such a doped polymer.

However, this method is not without its drawbacks. Not least of these is that the method is confined to polymer solutions. Films formed from doped solutions are of poor quality and variable thickness. Furthermore, the absorbance across a thin film due to polarons is five orders of magnitude less than for a 1 cm cuvette, and so is undetectable unless the modulation technique of the PA experiment is used.

Another major drawback is that the FeCl_4^- counter-ions proximity to the polymer chains disrupts the polymer lattice and so introduces trap states to the absorption of the polymer. These states are identifiable by the appearance of a long tail stretching towards the infrared in the low doping concentrations

Figure 5.7 Schematic showing the transitions present in a doped polymer with counter-ions in close proximity to the polymer chains.

of some of the polymers (see Figures 5.8 – 5.9). The trap states form above and below the HOMO and LUMO band-edges respectively, with an exponential distribution, as shown in Figure 5.7. At higher doping concentrations, the band gap fills up with these trap states and the material behaves like a metal (*Moliton*).

Nevertheless, it is possible to gain useful qualitative information from the absorption spectra of successively doped polymers with increasing concentration of FeCl_3 . By fitting the polaron absorptions with Gaussian lineshapes on top of an appropriately placed Gaussian absorption above the band-edge it is possible to determine the polaron energy, width and absorption intensity. The purpose of the Gaussian lineshapes above the bandedge is to remove the effect of the tail, due to the traps caused by the counterions, from the determination of the polaron parameters. The fitting procedure is performed over energies from below the bandedge to 1.1 eV in order to simplify the regression procedure.

In summary the doping induced absorption measurement has some limitations:-

- Measurements confined to solution.
- Trap states due to counterions superimposes on top of the polaron absorption.

However these limitations are outweighed by the:-

- Simplicity of measurements.
- Measurement of true polaron species, as opposed to the geminate polaron pairs of PA.

Figure 5.8 (a) Doping Induced Absorption spectra for DPOP-PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.

5.4.2 Doping Induced Absorption Measurements

Polymer solutions of 0.25mg/ml in Xylene were successively doped with droplets of FeCl_3 (0.025M in DCM) solution in a cuvette within a Shimadzu spectrophotometer. An absorption spectrum was taken after the addition of each FeCl_3 droplet. The volume of a FeCl_3 solution droplet was estimated to

Figure 5.9 (a) Doping Induced Absorption spectra for HT73 upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.

Figure 5.10 (a) Doping Induced Absorption spectra for MEH-DOO PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.

be $0.0126 \pm 0.0003\text{mls}$ by counting the number of FeCl_3 solution droplets necessary to make up a volume of 1ml in a measuring cylinder. This was repeated 10 times in order to estimate the variance in the volume of a droplet. Using this it is then possible to determine the concentration of FeCl_3 in the polymer solution for a given number of added droplets.

Figure 5.11 (a) Doping Induced Absorption spectra for Thianthrene PPV upon successive addition of FeCl_3 . (b) The polaron intensity monotonically increases linearly with the addition of FeCl_3 with no indication of combination of polarons to form bipolarons.

Figure 5.12 (a) Doping Induced Absorption spectra for HT94 upon successive addition of FeCl₃. (b) The polaron intensity increases in a step-like manner with the addition of FeCl₃. This indicates the FeCl₃ molecules are breaking down polymer aggregates before doping the polymer chains.

Figures 5.8 – 5.15 show the doping induced absorption spectra for the materials under review in this thesis. In all of these figures, the spectra of the materials at different doping concentrations are shown in part (a) of the figures. Part (b) of the figures shows the integrated intensity of the polaron peak against the concentration of FeCl₃ in the polymer solution. Also shown in the figures are the regression results from the fitting of a gaussian lineshape to the polaron part of the spectrum.

For the following materials; DPOP-PPV, HT73 and MEH-DOO-PPV (see Figures 5.8-5.10), the polaron absorption is characterised by an intense, broad featureless band of width 0.37eV, 0.25eV and 0.25eV respectively. The FeCl₃ concentration dependence of the polaron peak is linear and monotonically increasing.

For the Thianthrene PPV (see Figure 5.11) the polaron absorption is approximately two orders of magnitude less than for the first three materials. The polaron absorption is considerably narrowed, 0.09eV, and only emerges out of the background absorption of the trap distribution above

Figure 5.13 (a) Doping Induced Absorption spectra for PFO upon successive addition of FeCl₃. (b) The polaron intensity monotonically increases with a power law dependance with the addition of FeCl₃ with no indication of combination of polarons to form bipolarons.

doping concentrations of 5×10^{-4} M. The polaron intensity then increases linearly from this point with no sign of an onset of decrease.

For the materials; HT94 and PFO (see Figures 5.12-5.13), the polaron absorption is also narrow and of low intensity. However, the concentration dependence of the absorption intensity is non-linear. In the case of HT94 the absorption only emerges at 6×10^{-4} M, and is characterised by a sharp step like function followed by a very slight increase. For the PFO data, three peaks were required to fit to the polaron peak. However, a similar step function is noticeable before the concentration dependence begins to obey a fourth order power law.

Figure 5.14 (a) Doping Induced Absorption spectra for PmPV upon successive addition of FeCl₃. (b) The polaron intensity monotonically increases with a power law dependence with the addition of FeCl₃ with no indication of combination of polarons to form bipolarons.

Similar behaviour is noticeable for the PmPV polymer (see Figure 5.14) although here the polaron peak is a broad, intense band. The polaron absorption intensity increases with a fourth order power dependence immediately upon doping. In the case of the PmPV nanotube composite (see

Figure 5.15 (a) Doping Induced Absorption spectra for a 12.5% PmPV nanotube composite upon successive addition of FeCl₃. (b) The polaron intensity monotonically increases linearly with the addition of FeCl₃ with no indication of combination of polarons to form bipolarons.

Figure 5.15), the polaron peak increases linearly with doping concentration, with comparable linewidth to the PmPV polarons, although the absorption intensity is decreased.

5.4.3 Discussion of doping results

The doping results for all of the materials under study here show no evidence of the polaron intensity decreasing with increasing doping concentration. No other state, red shifted from the polaron peak, appears in the absorption spectra. In addition, the absorption intensity never decreases with increasing FeCl_3 concentration. The first conclusion that can be drawn from these results is that there is no bipolaron formation over the doping concentrations investigated here.

In order to understand the varied results of the concentration dependence of these materials it is necessary to consider the polymer conformation of the materials under study. The conformation and morphology play a very important role in determining how a charge, doped onto the chain, behaves within the material. In fact, the charge behaves as any excited state would and much of the terminology introduced in chapter 2 becomes relevant in the description of polarons.

In section 2.6.2, it was seen that the lattice deformation of the polymer would decrease if the excited state were delocalised over many repeat units of the polymer. This led to a narrowing of the absorption with the appearance of vibronic structure. Conversely, a more confined excited state leads to greater lattice relaxation and a broader gaussian shaped structure in the absorption lineshape. Within the materials studied here, both of these circumstances are present.

In the case of DPOP-PPV, geometry optimisation has predicted that considerable torsional hindrances are set up along the polymer backbone due to the steric hindrance of the side groups (see section 3.2.1). Such a situation acts to decrease the conjugation length and confine the excited state to a small

segment of the polymer chain. This leads to a greater lattice deformation and a broad structureless absorption band in the polaronic absorption. These materials are less likely to form polymer aggregates, due to their highly disordered conformation, and will be less liable to form microcrystallites and fibrules. Consequently, they are more susceptible to an attack from a dopant molecule at an interstitial site, and are readily doped in solution. This explains the ease with which this material was doped, and the linear relationship between the dopant concentration and the polaronic absorption intensity.

The geometry optimisation for MEH-DOO-PPV indicates a planar well-ordered polymer backbone. The side-groups in this material are highly disordered, and have been placed on the backbone to prevent inter-chain species formation, by spacing out the polymer chains. As a result, the polymer behaves similarly to DPOP-PPV in that it is easily doped with a linear concentration dependence. There are all the signatures of strong lattice deformation by the polaron, with a broad red-shifted featureless band. In this case, it is most likely due to self-trapping of the polaron where the lattice merely relaxes to accommodate the polaron, and thus tending to trap the polaron. If the polymer is free in solution, without the formation of aggregates to force the structure to remain planar, then the polaron remains confined to a small segment of the polymer chain. Consequently, the broad featureless absorption of the polaron is observed

HT73 is a co-polymer consisting of a 95% 2-methoxy-5-octyloxy-1,4-xylylidene component and a 5% diphenyl-1,4-xylylidene component. The conformation of the 2-methoxy-5-octyloxy-1,4-xylylidene component is of a planar rod-like structure while the conformation of the diphenyl-1,4-xylylidene component introduces a torsional effect to the polymer backbone, similar to that of DPOP-PPV. This means that the conjugation length of the 2-methoxy-5-octyloxy-1,4-xylylidene component is much longer than that of the diphenyl-1,4-xylylidene component. The morphology of this material is likely to be made up of ordered crystalline regions where the polymer chain is

made up of the 2-methoxy-5-octyloxy-1,4-xylylidene component and disordered regions where the backbone consists of the diphenyl-1,4-xylylidene component. This results in the bandgap of the diphenyl-1,4-xylylidene component being considerably larger than that of the 2-methoxy-5-octyloxy-1,4-xylylidene component.. Consequently, excitons from the diphenyl-1,4-xylylidene component diffuse along the polymer backbone to the 2-methoxy-5-octyloxy-1,4-xylylidene component, giving rise to the red emission with pronounced vibronic structure. However, the broad featureless band in the polaronic absorption, suggests a highly localised state with strong lattice relaxation. This suggests that the polaron is localised on the diphenyl-1,4-xylylidene component of the polymer backbone. There are two possible reasons for this. 1. The polaron is stabilised by the twisted structure of the diphenyl substituted vinylene bond as in the case of DPOP-PPV or more likely 2. The polymer is predominantly doped at the diphenyl-1,4-xylylidene unit and the polaron is Coulomb trapped due to the presence of the FeCl_4^- counter-ion. The diphenyl-1,4-xylylidene component is easier to dope because it inhibits the formation of aggregates and fibrules and gives rise to a linear relationship between the dopant concentration and the polaron absorption intensity. It is not possible to tell whether or not the polaron is stabilised by the diphenyl-1,4-xylylidene unit or by the presence of counterions by using the doping measurement. Optically excited PA measurements need to be carried out to see if the polaron remains localised without the presence of counterions.

In the case of the Thianthrene PPV, a narrower less intense polaron peak is observed. The absorption due to the trap distribution is more prominent because the polaron peak is better defined, and absorption intensity is decreased. The conformation of the Thianthrene PPV is of a well-ordered herring-bone type structure. In addition, the crystallinity provided by the aggregates prevents strong chain deformation. This promotes a longer conjugation length and the formation of aggregates. The longer conjugation

length allows greater delocalisation of the polaron along the polymer chain and hence a reduction in the lattice deformation. This results in a narrower more defined lineshape in the polaron absorption. The presence of aggregates in the solution makes the material more difficult to dope due to the lack of interstitial sites for the FeCl_3 molecules to attack. The relationship between the dopant concentration and the polaron absorption intensity, suggests that the FeCl_3 acts to break up the aggregates to a certain degree so that it can attack further interstitial sites. If all of the aggregates are broken up, the linear relationship between dopant concentration and polaron absorption intensity resumes. However, some aggregate species must remain as the polaron peak remains very narrow, although there is a small increase in the polaron width as the FeCl_3 concentration increases.

In the case of HT94 and PFO, the polymer conformation is linear and planar with no torsional hindrances in the geometry-optimised structure. This promotes the formation of aggregates in solution. These aggregates are crystalline regions of the polymer and are highly ordered, favouring polaron delocalisation along the polymer backbone. In turn, the lattice distortion is decreased and the width of the polaron absorption is decreased. Indeed, in the PFO spectra two peaks were required to fit to the experimental data. This could be the appearance of a vibronic structure in the polaron absorption spectrum. The presence of aggregates in the solution makes the material more difficult to dope due to the lack of interstitial sites for the FeCl_3 molecules to attack. The relationship between the dopant concentration and the polaron absorption intensity, suggests that the FeCl_3 needs to break up the aggregates before they can be doped. This is indicated by the sudden appearance of the polaron peak above a threshold followed by a power law dependence in the concentration dependence. The physical reasons behind this are unclear. For the purposes of this work it will be assumed that the presence of a threshold followed by a power law relation in the concentration dependence, indicates the breaking down of polymer aggregates within the solution. The HT94 is

the most difficult material to dope and only really displays a threshold at which the polaron appears, but may display the power law dependence at higher doping concentrations. The polaron absorption is a well-resolved narrow peak, in direct contrast to the exciton emission, which is a broadband. This behaviour indicates that the introduction of ether groups into the polymer backbone acts to promote polaron delocalisation, while forcing the excitons to be localised between the ether groups on the backbone.

In the case of PmPV, a twisted backbone has deliberately been introduced to the polymer backbone due to the *meta*-linkage. Despite the disorder that this introduces to the polymer conformation, this material is known to form aggregates (*Henderson et al.*). It is believed that the *meta*-linkage acts to expose the backbone and so makes polymer chains interact both with other polymer chains as well as carbon nanotubes via a dipole effect (*in het Panhuis et al.*). The *meta*-linkage inhibits the delocalisation of states along the polymer chain and so this leads to a broadened polaron absorption compared to the other materials with aggregate formation. As a result, there is a broad polaron absorption that displays a nonlinear relationship with increasing doping concentration. The polaron absorption spectrum displays two peaks for the PmPV; one at 2.28eV and another at 1.92eV. Such a large energy difference between these two peaks is unlikely to be caused by vibronic structure. It has been proposed that the reason for this is that there are two polaronic absorptions in the absorption spectra (*Lane et al.*, 2000); one due to the ω_1 (1.92eV peak) transition and another due to the forbidden ω_3 (2.28eV peak) transition. The ω_3 transition becomes allowed upon the breaking of C_{2h} symmetry, which is the case for a *meta*-linked polymer.

The PmPV nanotube composite sample displays the same absorption peaks as the ordinary PmPV sample, although there is now a linear behaviour in the concentration dependence with increasing FeCl_3 concentration. The reason for this is that the introduction of nanotubes is known to reduce the

aggregation within the PmPV (Coleman *et al.*). Consequently, the FeCl₃ is doping a material without aggregates and so a linear concentration dependence is observed. A polymer chain in the composite, while not aggregated, is still interacting with the nanotubes and so is less easy to dope than a free polymer chain. This explains why the polaronic absorption is less intense for the composite than for the polymer at a doping concentration of 5.625×10⁻⁴M.

It is useful to quantify the lattice distortion of the polymers when considering the energy of polaron states in conjugated polymers. A simple way of doing this is to consider a quantity, γ , the lattice distortion parameter, which can be defined as:-

$$\gamma = \frac{E_g - E_{Pol}}{E_g} \quad [5.11]$$

where E_g is the bandgap of the material and E_{Pol} is the energy of the polaron transition. Values of γ near zero means that there is very little lattice distortion present in the material and the polaron is simply a charge residing in the HOMO or LUMO. A finite value of $\gamma < 1$ indicates lattice distortion and the presence of a polaron with sub-gap levels. γ can be used to quantify the amount of lattice distortion present in the material

Table 5-1 Table showing the Bandgap, E_g , and Polaron Energy, E_{Pol} , of the materials under study. Also shown is the distortion parameter, γ , which is a measure of the distortion of each polymer when a polaron is present on a chain segment.

Material	E_g (eV)	E_{Pol} (eV)	γ
DPOP-PPV	2.66 ± 0.02	1.750 ± 0.003	0.342 ± 0.016
MEH-DOO-PPV	2.18 ± 0.02	1.570 ± 0.012	0.280 ± 0.024
HT73	2.10 ± 0.02	1.550 ± 0.011	0.262 ± 0.024
PmPV:NT 8:1	2.72 ± 0.02	2.270 ± 0.003	0.165 ± 0.016
PmPV	2.72 ± 0.02	2.280 ± 0.011	0.182 ± 0.019
PFO	2.88 ± 0.02	2.450 ± 0.006	0.149 ± 0.016
Thiantrene-PPV	2.61 ± 0.02	2.230 ± 0.005	0.146 ± 0.017
HT04	2.41 ± 0.02	2.210 ± 0.000	0.083 ± 0.017

Table 5-1 shows the values for the bandgap, polaron energy and distortion parameter, calculated from equation 5.11, for all of the materials measured by the doping induced absorption method. Note that the three materials that displayed a linear doping concentration dependence have the highest lattice distortion parameters. The remaining materials that tended to form aggregates, which caused a non-linear doping concentration dependence, have significantly lower values for the lattice distortion parameter. Indeed there is a decrease of at least 0.1 in the lattice distortion parameter for aggregated materials compared to the materials, which didn't display signatures of aggregation.

The case study of DPOP-PPV has highlighted the problem of polarons and polaron pairs destroying stimulated emission in highly luminescent polymers. The mechanism for this is Förster energy transfer from singlet excitons to these species. Given the polymer emission spectra and PL quantum yield, combined with the polaron absorption coefficients at a given concentration of FeCl_3 , it is possible to make an estimate of the Förster transfer radius for polarons in the materials under study here. Of course, this assumes that each FeCl_3 molecule added to the solutions of the polymers forms a polaron. Despite the possibility that this may not be entirely true, the results of such an analysis do provide some idea of how the problems of excited state absorption may be eliminated.

Figure 5.16 shows two examples of the determination of the overlap integral in equation 5.3. The DPOP-PPV example shows where there is a large γ -value and the polaron absorption is to the red of the PL. The HT94 example shows where there is a small γ -value and the polaron absorption is to the blue of the PL. It is also noticeable that the absorption cross-section is two orders of magnitude less for the HT94 sample than for the DPOP-PPV sample. This could easily be due to overestimating the number of incidences of doping within the HT94 sample. It would be imprudent to make any comparisons

Figure 5.16 (a) Overlap of Polaron absorption with the PL for DPOP-PPV.
(b) Overlap of Polaron Absorption with PL for HT94.

between these two materials based on the magnitude of the polaron absorption cross-section, since they may be effectively doped to a different extent.

Table 5-2 shows the estimated Förster transfer radius for each of the materials studied here. A threshold number density equal to $\frac{3}{4\pi r^3}$ where r is the Förster transfer radius is also shown. If the number density of polarons within the material is greater than the threshold polaron density, any excitonic states that are produced will be quenched. From table 5-2 it can be seen that this threshold number density is between 10^{17} - 10^{18} cm^{-3} . Note, in chapter 3 the stimulated emission cross-section for conjugated polymers was found to be in the region of 10^{-16} cm^2 . This means that, neglecting scattering losses, $>10^{16}$ excitons/ cm^3 need to be created in order to create gain in a polymeric device. Considering electro-luminescent devices have efficiencies of the order of 1%, approximately 2×10^{18} carriers would need to be injected into a device in order to create such a number density of electrons. If optical losses were considered it is possible that the necessary number of carriers needed to create gain would be a further order of magnitude higher. In this circumstance, the

Table 5-2 Table of the Fluorescence quantum efficiency (see section 3.4), The estimated Förster Radius and the Threshold Number density for polarons in materials studied here.

Material	Φ_f	Förster Radius (nm)	Threshold Number Density ($\times 10^{16} \text{cm}^{-3}$)
DPOP-PPV	0.68	6.7	0.81
HT73	0.25	4.2	3.27
HT94	0.36	1.9	36.83
MEH-DQ-PPV	0.19	5.8	1.24
PFO	0.46	4.1	3.59
PmPV	0.12	6.0	0.47
PmPV NT 8:1	0.12	7.1	0.66
Thianthrene PPV	0.59	3.1	8.08

carrier density exceeds the threshold polaron density by at least an order of magnitude.

In order to remedy this situation it is necessary to decrease the Förster Transfer radius for excitons to polarons by decreasing the integral overlap between the polaron absorption band and the exciton emission band. There are two possible ways of achieving this:-

- Decreasing the intensity of the polaron absorption band
- Shifting the polaron absorption band away from the emission band

As has been seen little faith can be placed in the intensity of the measured polaron absorption band and so no real trends can be observed by this method. Careful PA measurements on all of the materials would be required, in order to gain accurate values for the intensity of the transitions. There may then be some observable trend in the materials that would point to a way decreasing the integral overlap between the polarons and the excitons.

Shifting the polaron absorption band away from the emission band of a material is more likely to give favourable results. As has been seen in this work, materials that tend to aggregate together seem to produce a more blue shifted polaron peak while disordered materials tend to produce a more red-

shifted polaron peak. In addition, the introduction of ether groups into the polymer backbone acts to increase the delocalisation of polarons resulting in blue shifted narrower polaron absorption peaks. As will be seen in the next chapter, increased disorder within materials has a detrimental effect on the carrier mobility of the polymers. The low mobility of carriers in these materials is one of the contributory factors in the low electro-luminescent efficiency of polymeric LED devices. It would be favourable to increase the carrier mobility while also decreasing the integral overlap between the polaron absorption and the exciton emission. Increasing the order within the materials is the most likely way of achieving this dual goal. Within more crystalline polymers the long-range order is increased which, allows greater carrier mobility (due to lack of trapping sites) and greater delocalisation of polaron species (decreasing the change in bond order, and blue shifting the polaron energy).

5.4.4 Summary of the Doping Induced Absorption Measurements

To summarise the doping induced absorption measurements, it may be said that:-

- Disordered Polymers, while having a larger PL Yield, have a more red-shifted polaron absorption peak, which overlaps the exciton emission.
- Polymers displaying aggregation (and hence a greater degree of crystallinity), have a more blue shifted polaron peak, which also overlaps the emission.
- In all of the materials studied here, the integral overlap of the polaron absorption and the exciton emission will have a deleterious effect on the stimulated emission properties under electrically pumped conditions.
- The most effective way of reducing this integral overlap is to use polymers displaying greater crystallinity.

5.5 Conclusions

For PL applications, the strategy of creating polymers with greater disorder and large side-groups, to prevent inter-chain species formation, is a justifiable one. However, as the case study with DPOP-PPV has shown, care needs to be taken with the choice of side-groups, as a diphenyl-substituted polymer tends to promote inter-chain species formation. While such disordered materials do provide useful materials for optically pumped lasing, materials for an electrically pumped device will need to satisfy further criteria than just, a high PL yield and low inter-chain species formation. The doping induced absorption measurements suggest that more crystalline materials would prove to be more suitable for electrically pumped devices.

A complete PA spectroscopy study needs to be carried out on these materials to obtain more accurate polaron absorption cross-sections, so that the Förster radius of aggregated and disordered polymers can be compared. Also a further PA study on materials of different degrees of order needs to be performed, so that the necessary degree of polymer crystallinity, to remove the problems of associated with polarons, can be ascertained.

References

- Bradley, D. D. C., Shen, Y. Q., Bleier, H. and Roth, S. (1988). "Transient photoconductivity in highly oriented poly(p-phenylenevinylene)." Journal of Physics C: Solid State Physics **21**(15): L515-22.
- Coleman, J. N., Dalton, A. B., Curran, S., Davey, A. P., McCarthy, B., Drury, A., Byrne, H. J., Roth, S. and Blau, W. (1998). Optical and electrical properties of a polymer-nanotube composite. Proceedings of the Third International Conference on Excitonic Processes in Condensed Matter. EXCON'98. Electrochemical Society Inc., Pennington, NJ, USA.
- Conwell, E. M., Perlstein, J. and Shaik, S. (1996). "Interchain photoluminescence in poly(phenylene vinylene) derivatives." Physical Review B-Condensed Matter **54**(4): R2308-10.
- De Mello, J. C., Wittmann, H. F. and Friend, R. H. (1997). "An improved experimental determination of external photoluminescence quantum efficiency." Advanced Materials **9**(3): 230-2.
- Dhote, J., Kretsch, K. P., Davey, A. P., Blau, W. and Byrne, H. J. (1999). "Luminescent quantum yields and vibrational spectroscopy." Synthetic Metals **102**(1-3): 1529-30.
- Friend, R. H., Gymer, R. W., Holmes, A. B., Burroughes, J. H., Marks, R. N., Taliani, C., Bradley, D. D. C., Dos Santos, D. A., Bredas, J. L., Logdlund, M. and Salaneck, W. R. (1999). "Electroluminescence in conjugated polymers." Nature **397**(6715): 121-8.
- Frolov, S. V., Shkunov, M., Vardeny, Z. V. and Yoshino, K. (1997). "Ring microlasers from conducting polymers." Physical Review B-Condensed Matter **56**(8): R4363-6.
- Harrison, N. T., Tessler, N., Moss, C. J., Pichler, K. and Friend, R. H. (1998). "Peak current density and brightness from poly(p-phenylenevinylene) based light-emitting diodes." Optical Materials **9**(1-4): 178-82.
- Henderson, K., Dalton, A. B., Chambers, G., Drury, A., Maier, S., Ryder, A. G., Blau, W. and Byrne, H. J. (2001). "Solvent effects on the luminescent properties of conjugated molecules." Synthetic Metals **119**(1-3): 555-6.
- Hide, F., Schwartz, B. J., Diaz-Garcia, M. A. and Heeger, A. J. (1997). "Conjugated polymers as solid-state laser materials." Synthetic Metals **91**(1-3): 35-40.

Hörhold, H. H. and Helbig, M. (1987). "Poly(Phenylenevinylene)s - Synthesis and Redoxchemistry of Electroactive Polymers." Makromol. Chem. Macromol. Symp. **12**: 229-258.

Hsu, J. W. P., Yan, M., Jedju, T. M., Rothberg, L. J. and Hsieh, B. R. (1994). "Assignment of the picosecond photoinduced absorption in phenylene vinylene polymers." Physical Review B-Condensed Matter **49**(1): 712-15.

in het Panhuis, M., Munn, R. W. and Blau, W. J. (2001). "Optimal polymer characteristics for nanotube solubility." Synthetic Metals **121**(1-3): 1187-8.

Jones, G., II, Jackson, W. R., Chol-yoo, C. and Bergmark, W. R. (1985). "Solvent effects on emission yield and lifetime for coumarin laser dyes. Requirements for a rotary decay mechanism." Journal of Physical Chemistry **89**(2): 294-300.

Kallinger, C., Hilmer, M., Haugeneder, A., Perner, M., Spirk, W., Lemmer, U., Feldmann, J., Scherf, U., Mullen, K., Gombert, A. and Wittwer, V. (1998). "A flexible conjugated polymer laser." Advanced Materials **10**(12): 920-3.

Kretsch, K. P., Belton, C., Lipson, S., Blau, W. J., Henari, F. Z., Rost, H., Pfeiffer, S., Teuschel, A., Hillman, H. and Horhold, H. H. (1999). "Amplified spontaneous emission and optical gain spectra from stilbenoid and phenylene vinylene derivative model compounds." Journal of Applied Physics **86**(11): 6155-9.

Lane, P. A., Cadby, A. J., Mellor, H., Martin, S. J., Lidzey, D. G., Bradley, D. D. C., Lipson, S. M., O'Brien, D. F. and Blau, W. J. (2000). "Photophysics of a poly(phenylenevinylene) with alternating meta-phenylene and para-phenylene rings." Physical Review B-Condensed Matter **62**(23): 15718-23.

Lane, P. A., Wei, X. and Vardeny, Z. V. (1997). "Spin and spectral signatures of polaron pairs in pi -conjugated polymers." Physical Review B-Condensed Matter **56**(8): 4626-37.

Lide, D. R., Ed. (1994). CRC handbook of Chemistry and Physics.

Lipson, S. M., O'Brien, D. F., Byrne, H. J., Davey, A. P. and Blau, W. J. (2000). "Improvement of luminescence efficiency and photostability in polymer thin films." Thin Solid Films **370**(1-2): 262-7.

Moliton, A. (1998). Ion Implantation Doping of Electroactive Polymers and Device Fabrication. Handbook of Conducting Polymers. T. A. Skotheim, R. L. Elsenbaumer and J. R. Reynolds: 589-638.

Okamura, Y., Yoshinaka, S. and Yamamoto, S. (1983). "Measuring mode propagation losses of integrated optical waveguides: a simple method." Applied Optics **22**(23): 3892-4.

Penzkofer, A. (2000). 2nd annual LUPO report.

Pope, M. E. and Swenberg, C. E. (1982). Electronic Processes in Organic Crystals, Oxford University Press.

Przyluski, J., Zagorska, M., Conder, K. and Pron, A. (1982). Polymer **23**: 1872.

Resel, R., Tertinek, B., Tasch, S., Davey, A., Blau, W., Horhold, H. H., Rost, H. and Leising, G. (1999). "Conformation studies on layers of soluble poly(para-)phenylenevinylenes." Synthetic Metals **101**(1-3): 96-7.

Rothberg, L. J. (1997). Primary Photoexcitations in Conjugated Polymers: Molecular Exciton versus Semiconductor Band Model. N. S. Sariciftci, World Scientific Publishing: 129-38.

Samuel, I. D. W., Rumbles, G. and Collison, C. J. (1995). "Efficient interchain photoluminescence in a high-electron-affinity conjugated polymer." Physical Review B-Condensed Matter **52**(16): R11573-6.

Shinar, J. (1997). Optically Detected Magnetic Resonance (ODMR) Studies of π -Conjugated Polymer Films Solutions, Blends and Devices. Handbook of Organic Conductive Molecules and Polymers. H. S. Nalwa, Marcel Dekker. **3**: 319-366.

Sturm, J., Tasch, S., Niko, A., Leising, G., Toussaere, E., Zyss, J., Kowalczyk, T. C., Singer, K. D., Scherf, U. and Huber, J. (1997). "Optical anisotropy in thin films of a blue electroluminescent conjugated polymer." Thin Solid Films **298**(1-2): 138-42.

Ulrich, R. (1970). "Theory of the prism-film coupler by plane-wave analysis." Journal of the Optical Society of America **60**(10): 1337-50.

Chapter 6

DEVELOPMENT OF ORGANIC DOUBLE HETERO-STRUCTURE WAVEGUIDING DEVICES

6.2 Overview of Electroluminescence in Conjugated Polymers

The process of electro-luminescence in conjugated polymers is given as follows:
1. Charge injection 2. Charge transport 3. Recombination
4. Radiative recombination with the emission of photons. In this
section, each of these processes will be reviewed in detail, with specific
reference to conjugated polymers.

6.2.1 Charge Injection

The Charge Injection process can determine the electrical properties of a
polymeric device. The characteristics depend on the nature of the material of
the bulk, where the physical processes, which govern the behaviour of charge
carriers at a metal/polymer interface, will be considered.

6.1 Introduction

In order to create a double heterostructure device, the electrical properties of conjugated polymers need to be considered. In this chapter the physical properties, that affect the electrical behaviour of disordered materials will be considered. Following on from this, models for the behaviour of unipolar conduction in planar devices will be developed. Using these models, in conjunction with single carrier transport measurements, electrical properties of the materials studied in this thesis, such as mobility and free carrier densities, are then obtained. From this point, it is then reasonable to consider the behaviour of these materials in bipolar devices, where light emission occurs.

Using the measurements of chapter 4 simulations of the waveguiding behaviour within double hetero-structure devices are carried out. The emission behaviour of an electrically pumped waveguiding device is then observed and the prospects of fabricating an electrically pumped polymeric laser are considered.

6.2 Overview of Electroluminescence in Conjugated Polymers

The process of electro-luminescence in conjugated polymers is governed by four distinct processes:- 1. Charge injection 2. Charge Transport 3. Electron-hole capture and 4. Recombination with the emission of photons. In this section, each of these processes will be reviewed in detail, with specific reference to conjugated polymers.

6.2.1 Charge Injection

The Charge injection process can dominate the electrical properties of a polymeric device if the characteristic impedance of the contact exceeds that of the bulk. Here the physical processes, which govern the behaviour of charge carriers at a metal-polymer interface, will be considered.

6.2.1.1 Electrical Contacts and Formation of Schottky Barrier

When a metal is brought into intimate contact with a semi-conducting polymer charge transfer from the metal to the semiconductor usually occurs so that electrons can occupy their lowest possible energy state. The Fermi level, ε_F , of a material in isolation is a reference energy level, of the Fermi-Dirac distribution, for which the probability of occupation is equal to $1/2$. The probability for a state of energy $\varepsilon \gg kT$ below ε_F is 1 while the probability for a state $\varepsilon \gg kT$ above ε_F is zero. This means that the Fermi level is effectively the energy of the most energetic electrons within a material. Consequently, charge transfer takes place until the Fermi level in both materials is equal, at the interface of the metal and the semi-conductor.

Due to the charge-transfer that takes place between the metal and the semiconductor, a potential difference is created across the interface between the materials. It is possible to quantify this in terms of the work functions of the materials. The work function of a metal, ϕ_M , is the potential barrier between the Fermi level and the lowest electronic energy level in a vacuum. The work function of a semi-conducting polymer is defined as:-

$$\phi_S = \chi_S + (\varepsilon_{LUMO} - \varepsilon_F) \quad [6.1]$$

where χ_S is the electron affinity, which is the potential required to ionise the lowest excited state of the polymer, ε_{LUMO} is the lowest energy of the LUMO band and ε_F is the Fermi level for the polymer (see Figure 6.1). The Fermi level (and hence the work function) of a polymer is dependent on the dopant and impurity concentration. Due to the synthesis methods employed, conjugated polymers are lightly *p*-doped, and so the Fermi level tends to reside closer to the HOMO than the LUMO for most polymers.

The energy barrier due to the metal being in contact with the polymer can then be defined as the difference between the metallic and polymer work

Figure 6.1 (a) Schematic of the band diagram for a neutral contact (b) Schematic for the band diagram of an Ohmic contact (c) Schematic for an electron blocking contact.

functions $(\phi_M - \phi_s)$. The contact potential, V_c , is then equal to this quantity divided by the electronic charge e :-

$$V_c = \frac{1}{e} \{ \phi_M - \chi_s - (\epsilon_{LUMO} - \epsilon_F) \} \quad [6.2]$$

For an electron leaving the conduction band and entering the metal it must have an energy equal to eV_c , while for an electron to be injected into the semiconductor it must be able to surmount the potential barrier $(\phi_M - \chi_s)$. The barrier to injection can thus be varied by applying an electric field across the interface. The field alters both the height and the width of the contact. Such potential barriers are known as *Schottky barriers* and the effect of decreasing the barrier height and width is known as the *Schottky Effect*.

Depending on the respective Fermi levels are for the metal and the polymer, various different types of contact can be created. The contacts most relevant to this work are blocking contacts, neutral contacts and Ohmic contacts.

6.2.1.1.1 *Neutral Contacts*

A neutral contact is one for which $\phi_M = \phi_S$. Under this condition, no net charge flows across the metal-semiconductor interface (see Figure 6.1(a)). Consequently, there is no build-up of space charge and no band bending occurs. It is possible for a neutral contact to be set up when $\phi_M \neq \phi_S$ where the ambient temperatures are low, or when charge trapping levels are significantly above or below ϵ_F . Under these conditions, the population density is too low to cause significant band bending, and no contact potential is set up.

6.2.1.1.2 *Ohmic Contacts*

An Ohmic contact is set up, for electrons, when $\phi_M > \phi_S$ and the Fermi level of the metal is approximately equal to ϵ_{LUMO} (see Figure 6.1(b)). Under these conditions, electrons need only overcome the contact potential to be injected into the semi-conducting polymer. This means that the contact resistance is negligible when compared to the bulk of the polymer. The free carrier density of the metal is considerably greater than in the bulk of the semi-conductor and the contact acts as reservoir of carriers. Consequently, the current-voltage characteristics of such interfaces become limited by the bulk electrical properties of the polymer, rather than the characteristics of the interface. Although an Ohmic contact does not play a significant role in the conduction process of devices, the current-voltage characteristics are still non-linear. This is because, when Ohmic contacts are used, the current flow in organic materials becomes *bulk limited*. Measurements can then be performed, using Ohmic contacts, to obtain information about the properties of the polymers rather than the metal polymer interface. The physics behind the bulk limited conduction process will be dealt with in section 6.2.2. Note that an Ohmic

contact can be set up for holes, when $\phi_M < \phi_S$ and the Fermi level of the metal is approximately equal to ε_{HOMO} .

6.2.1.1.3 Blocking Contact

The Schottky barrier shown in Figure 6.1(c) is an example of a blocking contact for electrons. This occurs when $\phi_M > \phi_S$ and the Fermi level of the metal is not equivalent to ε_{LUMO} . When the interface is placed under forward-bias electrons can easily pass over the contact potential barrier, and flow from the semiconductor to the metal. However, under reverse-bias, the current is limited by the number of electrons that can surmount the larger $(\phi_M - \chi_S)$ potential barrier. This type of conduction is known as being *electrode limited*. The mechanisms by which charge carriers overcome potential barriers is discussed in section 6.2.1.2. A blocking contact for holes is similarly created when $\phi_M < \phi_S$ and the Fermi level of the metal is not equivalent to ε_{HOMO} .

For efficient devices to be created it is desirable that Ohmic contacts be used for charge injection. This requires that the work function of the hole injecting

Table 6-1 Table showing the Work function, ϕ_M , for a variety of different metals. Values taken from (Lide). All values determined from photoelectric effect or from Contact Potential difference if *

Metal	Symbol	ϕ_M/eV
Cesium	Cs	2.14
Potassium	K	2.3
Sodium	Na	2.75
Calcium	Ca	2.87
Scandium	Sc	3.5
Gallium	Ga	4.2
Lead	Pb	4.25
Silver	Ag	4.26
Aluminium	Al	4.28
Chromium	Cr	4.5
Tungsten*	W	4.55
Molybdenum	Mo	4.6
Indium Tin Oxide	ITO	4.8
Zinc*	Zn	4.9
Gold	Au	5.1
Platinum	Pt	5.65
Selenium	Se	5.9

contact should match ϵ_{HOMO} and the work function of the electron injecting contact should match ϵ_{LUMO} . These parameters are given by the electron affinity and the ionisation potential respectively of the polymer. Typical values of the electron affinity and ionisation potential for PPVs are 2.6eV and 5.1eV respectively (*Campbell et al.*). The work function of various metals is given in Table 6-1. Provided the injecting electrode work function is within 0.5eV of the relevant band the contact will be Ohmic (*Baessler et al.*). ITO is a useful hole injecting contact since it forms an Ohmic contact to PPV and is transparent, so that emission can be observed transversely from the polymer film. Ideally, Calcium electrodes would be used for electron injection. However, it is not experimentally possible to fabricate alkali metal contacts, without the use of a nitrogen glove box, with fabrication and test facilities. Such facilities are not currently available in Trinity College and so more stable aluminium electrodes are used for electron injection.

6.2.1.2 Electrode Limited Current Flow

The formation of potential barriers at the contact-polymer interface has been described previously. Up until now, little has been said about the mechanisms by which charge can be injected from contacts with significant Schottky barriers. There are two possible ways for the charge to surmount the barrier. The electrons can be excited thermally by the process of Thermionic Emission, or they can quantum mechanically tunnel through the barrier, if the barrier is low and narrow enough. Tunnelling through the barrier leaves the electron in the same energy state that it was in on the metal side of the contact. These two mechanisms have been studied in detail by Schottky (*Sze*) and by *Fowler and Nordheim*.

6.2.1.2.1 Thermionic Emission

The kinetic energy of charge carriers in a solid is increased with increasing temperature. Hence, the likelihood of a charge carrier surmounting a given potential barrier also increases with temperature. Thermionic emission can

hence give rise to a thermally induced current flow from the metal to the polymer. The current flow induced by thermionic emission is given by the Richardson equation (*Venebles*):-

$$J = A^* T^2 e^{\left(\frac{e\phi}{kT}\right)} \quad [6.3]$$

where A^* is the material dependent effective Richardson constant, ϕ is the metal-polymer barrier height at a given applied voltage and T is the absolute temperature. At zero applied bias there is a dynamic equilibrium between current flowing from metal to semiconductor and vice versa and no net current is observed.

The application of an electric field across the metal-polymer interface decreases the barrier for injection and the carrier density in the polymer can be increased. The barrier height has a field dependence of $\sqrt{E}$, for neutral contacts and $\sqrt[4]{E}$, for blocking contacts. The electric field can then sweep the carriers away from the interface. (*Mott et al.* (1940) and *Sze*) have shown that in semiconductors of low mobility, such as polymers, the back flow of charge carriers is important in the description of the current flow across the interface. *Rikken et al.* argued that equation 6.3 should be modified for organic devices by the addition of an empirical factor n such that kT becomes nkT . Note that equation 6.3 only applies to organic devices when the counter electrode is an Ohmic contact.

6.2.1.2.2 Fowler Nordheim Tunnelling

Even at very low temperatures, it is possible for carriers to surmount a potential barrier at an electrode polymer interface. *Fowler and Nordheim* have shown that when an electric field acts, to reduce the potential barrier, there is a significant probability that quantum mechanical tunnelling of the charge carriers to the other side of the barrier occurs. This increases the charge density on the polymer side of the barrier and these extra carriers are

swept away by the applied field. Such a process gives rise to a current density given by:-

$$J = \frac{A^* T^2}{\phi} \left(\frac{eE}{kT\kappa} \right)^2 e^{-\left(\frac{2\kappa\phi^3}{3eE} \right)} \quad [6.4]$$

where e is the electronic charge, E is the applied electric field and κ describes the barrier. If the barrier is triangular in shape κ is given by:-

$$\kappa = \frac{4\pi\sqrt{2m^*}}{h} \quad [6.5]$$

where m^* is the effective mass of the charge carriers and h is Planck's constant. Fowler-Nordheim tunnelling can be distinguished from other forms of charge injection by rewriting equation 6.4 in the form:-

$$\ln\left(\frac{J}{E^2}\right) = -m\left(\frac{1}{E}\right) + c \quad [6.6]$$

A plot of $\ln\left(\frac{J}{E^2}\right)$ against $\frac{1}{E}$ gives a straight line with a negative slope. The height of the potential barrier can then be obtained from the slope of the line, m , using equations 6.6, 6.5 and 6.4.

Current-Voltage characteristics for organic devices have been modelled very successfully using equation 6.6, for interface barrier heights, which are large compared to kT (*Parker*). However, values for the current predicted from actual device parameters using the Fowler-Nordheim equation exceed the experimentally measured currents by several orders of magnitude. *Davids et al.* rationalise this by considering a current due to the carriers tunnelling back into the electrode after they have been injected into the polymer. This results in a considerably lower observed current than that predicted by equation 6.4. This effect is similar to the reverse current in thermionic emission electrodes and is again a consequence of the low carrier mobilities of organic materials.

6.2.2 Charge Transport

The second, and most important, aspect of electro-luminescence is the transport of charge carriers through the bulk of the polymer. The bulk properties of the polymer will dominate the electro-luminescence, if the characteristic impedance of the bulk exceeds the impedance of the electrode interface. Here the physics of a charge within a disordered environment, in the presence of traps, will be considered before developing a model to describe the current flow of charge in unipolar and bipolar devices.

6.2.2.1 Physical Models for Electronic Conductivity in Organic Materials

The behaviour of charge within a disordered, amorphous environment is dependent on the presence of traps within the bandgap. This means that there are at least two possible charge transport mechanisms possible in these materials:- coherent band transport, through extended delocalised states in either the HOMO or the LUMO, **or** hopping from trapping site to trapping site. Whether transport takes place coherently according to the band model or by the hopping model depends upon the relative strengths of electron-phonon coupling with intra-molecular (nuclear) vibrations and inter-molecular (lattice) vibrations. This can be quantified by comparing the charge relaxation time, τ_c , to the intra-molecular vibrational period, τ_n , and the inter-molecular vibrational period, τ_p .

If $\tau_c < \tau_n < \tau_p$, the charge moves rapidly, through the lattice and the motion of the nuclei can be regarded as being stationary, then the motion of the charge is governed by a band-like model. Here the charge motion is a wavelike over many lattice sites before a scattering event occurs.

If $\tau_n < \tau_c < \tau_p$, the nuclei vibrate when the charge is on a given lattice site and a lattice distortion ensues, which results in relaxation of states out of the and LUMO towards the centre of the band gap, with the formation of a polaron (see chapter 5). The charge is then self-localised or self trapped. The

conductivity of the polymer could then be expected to be dependent on a hopping mechanism, from polaron site to polaron site as well as between trapping sites due to lattice imperfections.

Hopping is the predominant mechanism behind the conductivity in polymers and organics generally (*Roth*) although at high temperatures, band transport may dominate and at low temperatures, quantum effects may appear. This will now be considered in some detail along with two other possible models for the conductivity of polymers; Fluctuation Induced Tunnelling and the Poole Frenkel Effect.

6.2.2.1.1 Variable Range Hopping

As has just been seen, these materials tend to have many electronic states in the forbidden bandgap due to both structural disorder and the strong electron phonon coupling associated with molecular materials. This suggests that transport will be dominated by hopping from state to state. This sort of transport mechanism was first investigated by Mott in 1969 (*Sharma*).

The hopping process, or more accurately, phonon assisted quantum mechanical tunnelling, is outlined in Figure 6.2. An electron in a given gap

Figure 6.2 Trap States in a semi-conducting polymer. This is the origin of hopping transport in conjugated polymers. Electrons "hop" between trap states of various distances or energies. Note transition A is of a higher energy change and shorter hopping distance whereas transition B is of lower energy change and longer distance.

state is surrounded by other localised states at various distances and energies. The hopping rate to any of these states is proportional to the probability of finding the electron in that state. As can be seen from Figure 6.2, for an electron to move from one trap state to another requires two parallel processes to take place; a change in the electron's position and a change in its energy.

The probability of finding the electron at a displacement r from its initial trap position can be found from the exponential decay of the electronic wavefunction:-

$$\psi(r) = A_0 e^{-\frac{r}{r_0}} \quad [6.7]$$

where A_0 is a constant and r_0 is known as the localisation length.

For the electron to make an energy transition to a different energy, it will require a phonon of energy ε , where ε is the energy difference between its initial and final state. For a contribution to conduction processes the electron has to be lifted in energy to a higher state so ε is always positive. The number of available phonons, N_{ph} , of energy ε at a given temperature is proportional to the Boltzmann factor:-

$$N_{ph}(\varepsilon) \propto e^{-\frac{\varepsilon}{kT}} \quad [6.8]$$

where k is the Boltzmann constant and T is the temperature.

Referring to Figure 6.2, the probability of an electron being found in a state of displacement r , is given by the square of the wavefunction equation 6.7 and the probability of an electron increasing in energy ε , is proportional to the Boltzmann factor in equation 6.8. Consequently, the probability for an

electron to make transition A in Figure 6.2 is proportional to the product of these two factors:-

$$p(r, \varepsilon) \propto e^{-\left(\frac{2r}{r_0} + \frac{\varepsilon}{kT}\right)} \quad [6.9]$$

Consider the situation in Figure 6.2, at a given temperature, where the probability for transition A to occur, p_A , is greater than the probability for transition B, p_B . Now if the temperature is lowered, while the probability of both transitions decreases, p_A decreases much faster than p_B , because transition A requires greater phonon energy than transition B. Consequently, at lower temperatures transitions of lesser energy increase and greater hopping distances are favoured. Conversely, at higher temperatures transitions of greater energy increase and lesser hopping distances are preferred.

Now consider an electron-hopping event, such as transition A in Figure 6.2, occurring within a disordered organic solid. An electron hops from an initial state to a final state where there is a displacement, r , and an energy difference, $\varepsilon(r)$, between the initial and final states. For this process to take place, there must be on average at least one state of energy between zero and $\varepsilon(r)$ within a volume V_{Sphere} equivalent to a sphere of radius r centered on the initial state. Given a density of states $n(\varepsilon_p)$, this condition is met if $n(\varepsilon_p) \cdot \varepsilon(r) \cdot V_{Sphere} = 1$. This means that the energy difference between the initial and final states can be written as:-

$$\varepsilon(r) = \frac{3}{4\pi r^3 n(\varepsilon_F)} \quad [6.10]$$

Substitution of this expression into equation 6.9 yields an exponent of the form $-(ar + \frac{b}{r^3})$. In order to calculate the maximum probability, $p(\varepsilon, r)$, this

term needs to be minimised, which gives the most probable hopping distance as:-

$$\langle r \rangle = \left[\frac{8\pi}{9r_o} kTn(\epsilon_F) \right]^{\frac{1}{4}} \quad [6.11]$$

The conductivity of the material is then controlled by this hopping distance. Assuming the conductivity is then proportional to the hopping probability and substituting equation 6.11 and 6.10 into equation 6.9 the conductivity is deduced to be:-

$$\sigma = \sigma_o e^{-\left(\frac{T_o}{T}\right)^{\frac{1}{4}}} \quad [6.12]$$

where T_o is given by:-

$$T_o = \frac{f}{kn(\epsilon_F)r_o^3} \quad [6.13]$$

f is a scale factor due to a combination of dimensionless factors, and is equal to 0.30907.

This theory allows the determination of variable range hopping characteristics from plots of $\ln \sigma$ against $(1/T)^{\frac{1}{4}}$. The power $1/4$ is representative of an effective dimensionality characteristic of the phenomenon (three spatial dimensions and one energy dimension). In d spatial dimensions $1/4$ is raised to the power $1/(d+1)$. *Sanjai et al.* have studied Variable Range Hopping (VRH) in polyaniline doped with methane sulphonic acid. They observed 3-d VRH with a localisation length $r_o = 0.71 \text{ \AA}$ and found the most probable hopping distance to be $5.5 \text{ \AA}$ at 100K.

In a later work, *Mott et al.* (1969) expressed the field dependence of the conductivity to be:-

$$\sigma = \sigma_o e^{(-e\langle r \rangle E)} \quad [6.14]$$

where E is the applied electric field.

electron to make transition A in Figure 6.2 is proportional to the product of these two factors:-

$$p(r, \varepsilon) \propto e^{-\left(\frac{2r}{r_0} + \frac{\varepsilon}{kT}\right)} \quad [6.9]$$

Consider the situation in Figure 6.2, at a given temperature, where the probability for transition A to occur, p_A , is greater than the probability for transition B, p_B . Now if the temperature is lowered, while the probability of both transitions decreases, p_A decreases much faster than p_B , because transition A requires greater phonon energy than transition B. Consequently, at lower temperatures transitions of lesser energy increase and greater hopping distances are favoured. Conversely, at higher temperatures transitions of greater energy increase and lesser hopping distances are preferred.

Now consider an electron-hopping event, such as transition A in Figure 6.2, occurring within a disordered organic solid. An electron hops from an initial state to a final state where there is a displacement, r , and an energy difference, $\varepsilon(r)$, between the initial and final states. For this process to take place, there must be on average at least one state of energy between zero and $\varepsilon(r)$ within a volume V_{Sphere} , equivalent to a sphere of radius r centered on the initial state. Given a density of states $n(\varepsilon_p)$, this condition is met if $n(\varepsilon_p) \cdot \varepsilon(r) \cdot V_{Sphere} = 1$. This means that the energy difference between the initial and final states can be written as:-

$$\varepsilon(r) = \frac{3}{4\pi r^3 n(\varepsilon_F)} \quad [6.10]$$

Substitution of this expression into equation 6.9 yields an exponent of the form $-(ar + \frac{b}{r^3})$. In order to calculate the maximum probability, $p(\varepsilon, r)$, this

The nature of variable range hopping gives rise to the dispersive nature of the conduction in disordered organic materials. The stepwise motion between localised states, where the transport takes place by tunnelling from site to site, within a manifold of localised states gives rise to a broad distribution of the charge transit time, over a given thickness of the material. This means that the conventional notion of a well-defined drift mobility loses its validity under these circumstances. Transient photoconductivity or time of flight experiments on disordered materials are unable to measure a drift mobility in the usual way. Instead, a material is characterised by two decay constants in the current; one before charge reaches the detecting electrode and one after charge has reached the detecting electrode (*Zallen*). Mobilities measured by DC measurements are essentially an effective mobility for the material dependent on the trap density of the material.

6.2.2.1.2 *Fluctuation Induced Tunnelling*

Most conjugated polymers consist of domains of micro-crystallites separated by amorphous regions. The micro-crystallites have an enhanced conductivity, and so the amorphous regions behave as an insulating barrier between them. If these crystalline regions are close enough and the insulating barrier sufficiently thin, carriers can tunnel from region to region. *Sheng* noticed this effect for various disordered systems including doped polyacetylene. The field dependence of the conductivity can be expressed as (*Abeles et al.*):-

$$\sigma = \sigma_0 e^{\left(\frac{E_0}{E}\right)} \quad [6.15]$$

for the high field, non-linear regime, where E is the field and E_0 is related to the average capacitance between two adjacent microcrystalline regions.

6.2.2.1.3 *The Poole-Frenkel Effect*

The Poole-Frenkel effect is sometimes called the “internal Schottky effect” since the mechanism of this effect is associated with the field enhanced thermal excitation of trapped carriers, which is similar to the Schottky effect

Figure 6.3 The Poole-Frenkel Effect for a Coulomb Trap in a semiconductor. Under the application of an electric field the potential barrier for freeing a trapped electron decreases, allowing it to escape by thermal excitation, or tunnelling, for high applied fields.

in thermionic emission (see section 6.2.1.2.1). The effect for a one-dimensional model is outlined in Figure 6.3 where an applied electric field lowers the Coulomb potential for a trapped electron to escape. When the electron escapes it moves in the combined field of the Coulomb trap and the applied external field. The Poole-Frenkel effect is only effective for traps, which are neutral when filled and positively charged when empty. Traps that are neutral when empty and charged when filled, will not manifest the Poole-Frenkel effect because of the lack of Coulombic interaction.

Jonscher and *Ieda* have shown that a three dimensional treatment gives the temperature dependent conductivity due to this process is:-

$$\sigma = \sigma_o e^{\left(\frac{\beta_{PF} E^2}{2kT} \right)} \quad [6.16]$$

where σ_o is the low field conductivity, E is the electric field strength and T is the absolute temperature. β_{PF} is the Poole-Frenkel constant, which

determines the effect of an applied field on a single charge in a Coulomb potential:-

$$\beta_{PF} = \left(\frac{e^3}{\pi\epsilon} \right)^{\frac{1}{2}} \quad [6.17]$$

where ϵ is the permittivity.

While the Poole-Frenkel effect is common in amorphous semiconductors it is rarely manifested in conjugated polymers. This is because the vast majority of traps in conjugated polymers are due to morphological effects as opposed to the presence of ions, which can give up electrons.

6.2.2.2 Current Flow in Organic Devices

At this point, models for the current flow in organic devices will be developed, in order to describe the current-voltage behaviour of devices made from conjugated polymers. It will first be highlighted, why these devices do not follow Ohms Law exclusively, before introducing the SCLC model, which is generally used to describe the current-voltage behaviour of organic devices.

6.2.2.2.1 Limitations on Current Flow in Organic Materials

As previously discussed, the bulk properties of an organic material will dominate its electrical properties in the presence of a small barrier to charge injection. At low voltages, intrinsic carriers will begin to drift with the field with an average velocity, which is proportional to the applied field, E . This results in a current density, J , given by Ohm's law:-

$$J = \sigma E \quad [6.18]$$

where σ is the conductivity. The following relation links the conductivity of a material to its carrier drift mobility, μ , and carrier density, n :-

$$\sigma = ne\mu \quad [6.19]$$

where e is the electronic charge charge.

The disorder present in organic materials means that they tend to have extremely low intrinsic carrier mobilities and carrier densities (see section 6.2.2.1) and therefore cannot compensate for injected charge. This is manifested by a long dielectric relaxation time τ_d which is defined as being the time taken for a material to redistribute excess charge in order to restore itself to charge neutrality after the injection of a small charge excess. This is obtained by the expression:-

$$\tau_d = \frac{\epsilon}{ne\mu} \quad [6.20]$$

At low applied fields Ohm's law can be used to describe the current-voltage relationship for organic materials. On the other hand, if the applied field is increased the carrier transit time τ_t decreases because the average carrier velocity increases with field. When $\tau_t \cong \tau_d$ the material is no longer able to redistribute charge in the time of a carrier's journey through the material. At this point the following relation is true:-

$$\frac{\epsilon}{ne\mu} \cong \frac{d^2}{\mu V} \quad [6.21]$$

where d is the material thickness and V is the applied voltage. At higher applied fields, the number of carriers in the material is increased above the normal carrier density n . This results in a build up of space charge in the material, which influences the current flow, and Ohm's law is no longer valid.

6.2.2.2.2 *Unipolar Space Charge Limited Conduction*

Before considering the general case of bipolar charge transport, it is important to develop a simpler model describing unipolar charge transport. The models developed here will be of great use for extracting physical parameters, such as mobility and free carrier density from the unipolar current-voltage characteristics of Platinum:ITO and Aluminium:Aluminium devices.

6.2.2.2.1 Trap Free Solids (Ideal case)

In order to describe the current flow, for single carrier injection, in a region of space charge it is necessary to calculate the electric field inside the sample. This calculation has been applied specifically for electrons. The very same calculation is equally valid for holes, although the electron density, n , should be replaced with the hole density, p , to keep the nomenclature clear. In the presence of space charge the electric field follows Poisson's equation:-

$$\frac{dE(x)}{dx} = \frac{\rho}{\epsilon} = \frac{e[n(x) + n_t(x)]}{\epsilon} \quad [6.22]$$

where ρ is the charge density, $n(x)$ is the thermally generated free electron density and $n_t(x)$ is the trapped electron density. The current density is given by:-

$$J = e\mu n(x)E(x) \quad [6.23]$$

In the absence of traps and equation 6.22 becomes:-

$$2E(x)\frac{dE(x)}{dx} = \frac{2J}{e\mu} \quad [6.24]$$

This can be solved using the boundary condition for the applied voltage $V = \int_0^d E(x)dx$ to give the current density:-

$$J = \frac{9}{8}e\mu \frac{V^2}{d^3} \quad [6.25]$$

This equation is the solid-state analogue of Childs law for Space Charge Limited Conduction (SCLC) in a vacuum. It must be remembered that for low applied voltages Ohm's Law still applies. The onset at which SCLC takes

over from the linear Ohmic response occurs when the SCLC current is equal to the Ohmic current. This voltage is given by:-

$$V_{\Omega} = \frac{8 ned^2}{9 \epsilon} \quad [6.26]$$

For all voltages above this voltage, SCLC will apply. Rearranging equation 6.26 shows that:-

$$\frac{d^2}{\mu V_{\Omega}} = \frac{9 \epsilon}{8 ne\mu} \quad [6.27]$$

or more explicitly that $\tau_t = \tau_d / 8$. This shows that SCLC becomes the dominant mode of charge transport even before the carrier transit time exceeds the dielectric relaxation time. Equations 6.25 and 6.26 can be used to obtain the carrier mobility and the thermally generated carrier population in the absence of traps from the current-voltage behaviour of devices made using Ohmic/near Ohmic contacts.

6.2.2.2.2.2 Traps Confined to Discrete Levels

In the presence of discrete trap levels equation 6.22 can be solved with $n_t(x) \neq 0$. The solution is written as:-

$$J = \frac{9}{8} \epsilon \mu \theta \frac{V^2}{d^3} \quad [6.28]$$

where θ is a scaling term incorporating the number of traps present in the material:-

$$\theta = \frac{n}{n + n_t} \quad [6.29]$$

where n_t is the density of electron traps in the material. If there are no traps present in the material $\theta=1$ and the expression for J reads the same as for the

trap free case. In the presence of traps $\theta < 1$ and so the current density is much reduced, compared to the trap free case. The onset of SCLC is then given by:-

$$V_{\Omega} = \frac{8 \text{ end}^2}{9 \theta \epsilon} \quad [6.30]$$

The presence of traps thus acts to raise the voltage at which V_{Ω} occurs. This is because the presence of traps causes the injected charge to become trapped and so it cannot contribute to the conduction process. The presence of these traps results in the material having a decreased mobility. Thus, the mobility is actually an effective mobility $\mu_{\text{eff}} = \theta \mu$ where μ is the trap free mobility.

As the voltage is increased, more carriers are injected into the material and the traps become filled. This is represented by an increase in the Fermi level as more charge is injected into the material. At some point, all of the traps will be filled and injected charge can contribute to the conduction process. Consequently, the current density increases sharply and the material behaves as if there are no traps. This is termed the Trap Free Limit and the voltage where this happens is labelled V_{TFL} . This represents the point at which the Fermi level passes through ϵ_t , the energy of the traps, and so they become filled.

Traps fall into two different categories; 1. *Shallow Traps* and 2. *Deep Traps*.

Shallow Traps are defined as having a characteristic energy $\epsilon_t < \epsilon_{F_0}$ for holes (or $\epsilon_t > \epsilon_{F_0}$ for electrons) where ϵ_t is the trap energy and ϵ_{F_0} is the Fermi level under zero applied field. In this case, SCLC occurs before the traps are filled and $V_{\Omega} < V_{\text{TFL}}$. This is characterised by the appearance of a space charge limited conduction region at lower voltage before the sharper increase to trap free conduction.

Deep Traps are defined as having a characteristic energy $\epsilon_t > \epsilon_{F_0}$ for holes (or $\epsilon_t < \epsilon_{F_0}$ for electrons). In this case, SCLC occurs only after the traps are filled

and $V_o = V_{TFL}$. This is characterised by a sharp transition to trap free SCLC after Ohmic conduction.

6.2.2.2.3 Trap Distributions

Due to the disorder present within conjugated polymers, traps are unlikely to be present in single, discrete levels. Consequently, the theory needs to be extended to include the more likely occurrence of a trap distribution. The two trap distributions, $D_T(\epsilon)$, most likely to occur in conjugated polymers are the exponential distribution and the Gaussian distribution. The exponential distribution function is given by:-

$$D_T(\epsilon) = \frac{D_{T_o}}{kT_c} e^{-\left(\frac{\epsilon_{LUMO}-\epsilon}{kT_c}\right)} \quad [6.31]$$

where D_{T_o} is the density of traps and T_c is the characteristic trap energy given by $T_c = \frac{\epsilon_i}{k}$ where ϵ_i is the characteristic trap energy. The Gaussian distribution function is given by:-

$$D_T(\epsilon) = \frac{D_{T_o}}{\sqrt{2\pi}\sigma_i} e^{-\frac{1}{2}\left(\frac{\epsilon-\epsilon_i}{\sigma_i}\right)^2} \quad [6.32]$$

where D_{T_o} is the density of traps, ϵ_i is the trapping level and σ_i is the standard deviation of the Gaussian function.

Using these distribution functions, it is possible to solve equation 1.22 for the current density:-

$$J = n(\epsilon_{HOMO}) \mu e^{1-l} \left(\frac{l}{l+1} \frac{\epsilon}{D_i} \right)^l \left(\frac{2l+1}{l+1} \right)^{l+1} \frac{V^{l+1}}{d^{2l+1}} \quad [6.33]$$

where $l = \frac{T_c}{T}$ for the exponential distribution and $l = \sqrt{1 + \frac{2\pi\sigma_i^2}{16k^2T^2}}$ for the Gaussian distribution, $n(\epsilon_{HOMO})$ is the density of HOMO states and T is the absolute

temperature. The threshold voltage for SCLC in the presence of deep traps is given by:-

$$V_{\Omega} = \frac{ed^2 D_t}{\epsilon} \left(\frac{p}{n(\epsilon_{HOMO})} \right)^{\frac{1}{l}} \left(\frac{l+1}{l} \right) \left(\frac{l+1}{2l+1} \right)^{\frac{l+1}{l}} \quad [6.34]$$

and the trap free limit voltage is given by:-

$$V_{TFL} = \frac{ed^2}{\epsilon} \left\{ \frac{9}{8} \frac{D_t}{n(\epsilon_{HOMO})} \left(\frac{l+1}{l} \right)^l \left(\frac{l+1}{2l+1} \right)^{l+1} \right\}^{\frac{1}{l-1}} \quad [6.35]$$

The SCLC current-voltage characteristics follow a power law $J=KV^{m+1}$ where l is related to the depth of the traps. Provided the current-voltage (IV) characteristics follow this bulk-limited process, and data is obtained that includes V_{Ω} and V_{TFL} , the material properties such as mobility, intrinsic carrier density, trap density and densities of states may be determined.

It should be noted that equations 1.33-1.35 do **not** describe the current density for a shallow distribution of traps. For a shallow Gaussian distribution of traps equation 1.28 governs the current density and hence V_{Ω} is given by equation 1.30. However, the exponential distribution, by its nature, has deep lying traps so these equations always govern an exponential distribution. In this case, the current density is given by equation 6.28.

6.2.2.2.3 Bipolar Space Charge Limited Conduction

The current-voltage behaviour of bipolar devices can be thought of simply as unipolar SCLC by two simultaneous, parallel pathways. However, this scenario neglects the recombination of charge carriers. *Lampert et al.* have shown that the current voltage behaviour, incorporating recombination in the plasma limit, is of the form:-

$$J = \left(\frac{9\pi}{8} \right)^{\frac{1}{2}} \epsilon \left(\frac{2e\mu_p\mu_n(\mu_p + \mu_n)}{\epsilon B} \right)^{\frac{1}{2}} \frac{V^2}{d^3} \quad [6.36]$$

where μ_p is the hole mobility, μ_n is the electron mobility and B is the bimolecular recombination coefficient. The key point to note here is that

upon increasing B , the recombination increases and the measured current decreases. It should be pointed out that this is a highly idealised system and that in the presence of traps the form of the current density can be significantly modified. However, extraction of meaningful data then becomes extremely difficult due to the increased number of unknowns. Consequently, it is better to extract physical parameters from unipolar devices before considering the more complicated bipolar case.

6.2.3 Exciton Formation

The process of electron-hole capture in electro-luminescent devices is not well studied. Nevertheless, there are some simple models, which can be applied to gain some insight into physical processes at work in the operation of efficient OLED devices.

6.2.3.1 Langevin electron-hole capture

To observe efficient electron-hole capture in these very thin structures ($\sim 100\text{nm}$) it is necessary for one or other of the carriers to be of very low mobility. In this scenario, the local charge density is sufficiently high to ensure that a counter charge passes within a collision capture radius of at least one charge. There is strong experimental evidence to show that the formation of electron-hole pairs follows a Langevin process (*Blom et al.* (1997) and *Scott et al.*).

The capture of a free electron by a free hole to form an exciton is a bimolecular process. The rate of decrease in current density due to efficient electron-hole capture process can be written as:-

$$\frac{dN_{ex}}{dt} = Bpn \quad [6.37]$$

where N_{ex} is the number of excitons formed, B is the bimolecular capture constant and n and p are respectively the electron and hole carrier concentrations at the recombination zone.

The Langevin capture process assumes that the electron and the hole encounter each other at random. The electron falls into the Coulomb potential of the hole. The electron (or hole) can escape by two mechanisms; 1. It is thermally activated to escape the Coulomb potential or 2. It already has sufficient kinetic energy to escape. Provided the electron is moving slowly enough it will be captured by the hole if it is close enough so that the Coulomb energy is greater than the thermal energy. This results in an electron capture radius (*Langevin*):-

$$R_c = \frac{e^2}{4\pi\epsilon kT} \quad [6.38]$$

If the electron comes within R_c of the hole **and** has a mean free path considerably less than R_c it will lose much of its kinetic energy within this radius and so will be unable to escape the coulomb potential of the hole. The mean free path of charge carriers in polymers amounts to the distance between conjugated sites, which is of the order 10Å. A typical value for R_c is 185 Å at $T=300K$ ($\epsilon_r=3$). As a result, the rate-limiting step in the capture process is the diffusion of the electron and hole towards each other. This means the bimolecular capture constant is given by (*Blom et al.* (1997)):-

$$B = \frac{e}{\epsilon} (\mu_n + \mu_p) \quad [6.39]$$

The formation of excitons is thus linked to the carrier mobility. It can be seen that for an electrically pumped laser material the electron and hole mobility is of critical importance for the creation of sufficient excitons to exceed the threshold for gain. The increase of electron and hole mobility, while retaining the situation where one carrier is more mobile than the other is undoubtedly a key strategy for increasing the exciton creation efficiency.

6.2.3.2 Singlet-Triplet Ratio

During photoluminescence, it has been seen that the formation of triplet excitons is unlikely, due to the lack of spin-orbit coupling in conjugated

polymers. However, for electro-luminescent applications, the random nature of the electron-hole capture process means that this situation no longer holds true.

It can be seen that if the spin states for the triplet exciton, χ_{S,M_S} , are written down as (*Atkins*):-

$$\begin{aligned}\chi_{1,+1} &= \chi_{\uparrow}^{(1)} \chi_{\uparrow}^{(2)} \\ \chi_{1,0} &= \frac{1}{\sqrt{2}} \{ \chi_{\uparrow}^{(1)} \chi_{\downarrow}^{(2)} + \chi_{\downarrow}^{(1)} \chi_{\uparrow}^{(2)} \} \\ \chi_{1,-1} &= \chi_{\downarrow}^{(1)} \chi_{\downarrow}^{(2)}\end{aligned} \quad [6.40]$$

and the spin state for the singlet exciton is written as:-

$$\chi_{1,0} = \frac{1}{\sqrt{2}} \{ \chi_{\uparrow}^{(1)} \chi_{\downarrow}^{(2)} - \chi_{\downarrow}^{(1)} \chi_{\uparrow}^{(2)} \} \quad [6.41]$$

that there are three possible states for the triplet exciton and only one possible state for the singlet exciton. This means, assuming a random spin orientation in the charges involved in the capture process, that the ratio of singlets created to triplets created should be 1:3. Consequently, the efficiency of electroluminescent devices should be limited to 25% of the solid-state quantum efficiency. Recently, there has been some experimental evidence that contradict this view, although the behaviour is not well understood from a theoretical point of view. The results of these experiments will be presented in the literature review of recent results in section 6.3.

6.2.4 Exciton Recombination in Organic Devices

After the formation of a singlet exciton, by charge capture, it is impossible to distinguish such a singlet exciton from that formed by photo-excitation. Consequently, the fluorescence quantum yield is one of the most important parameters in the electro-luminescence process.

6.2.4.1 Electro-luminescence Efficiency

Tsutsui et al. have developed a simple expression for the electro-luminescence quantum efficiency, $\eta\phi$:-

$$\eta\phi = \gamma\eta_r\phi_F \quad [6.42]$$

where γ is a double injection factor, η_r quantifies the efficiency of the formation of a singlet exciton from an injected carrier pair and ϕ_F is the fluorescence quantum efficiency. The injection factor, γ , is dependent on the processes of carrier injection outlined in section 6.2.1, and is maximised (i.e. $\gamma=1$) when balanced charge injection is achieved. The parameter η_r represents a number of processes; such as carrier transport (i.e. carrier mobility and free carrier density) as well as the trapping and de-trapping of carriers and the electron-hole charge capture process. The presence of the fluorescence quantum efficiency, ϕ_F , in equation 6.4.2 means that highly fluorescent materials are preferred for the production of efficient electro-luminescent devices.

All three parameters in equation 6.42 can be strongly influenced by the extreme conditions present in an operating EL device. It has been shown that thickness optimised double hetero-structure devices are the best way to maximise the parameters γ and η_r (*Adachi et al.*). It is usually the ϕ_F parameter that is the dominant factor in determining the electro-luminescence efficiency.

6.2.4.2 Quenching of Luminescence in Organic Devices

The ϕ_F parameter is not necessarily the same value as that measured in a solid state film, as numerous factors present in an operating device can open up further non-radiative pathways for the singlet exciton. *Kersting et al.* have studied the effect of field-induced luminescence quenching using time-resolved PL measurements. They find that the formation of singlet

excitons is not affected by increasing field, whereas their radiative decay strongly depends on the external field. Several mechanisms have been suggested for the quenching of singlet excitons in the high electric fields present in a device:-

- Increased polaron population at high fields act as effective quenching sites for singlet excitons (*Graupner et al.*). Quenching of excitons by polarons has also been seen in chapter 5. It may be limited by having balanced transport properties so that similar populations of electrons and holes in the recombination zone.
- Electric Power dissipation within the device, results in an increase in temperature in the device, which increases collisional quenching mechanisms, or increases the non-radiative decay rate of the singlet exciton. This could be reduced by improved thermal management in the design of devices.
- The position of the recombination zone changes with increasing field and moves towards the electrodes, or quenching sites (*Lozykowski et al.*). This could be avoided by the use of materials with decreased field dependence in the mobility.
- The electric field could influence the exciton-exciton annihilation processes (*Kepler*).
- Quenching is also caused by field-induced annihilation of the exciton.

It is quite likely that field induced annihilation dominates the quenching process at increased fields, where the applied electric field is of similar magnitude to the Coulomb field of the electron-hole pair. Onsager and Poole-Frenkel models have been used to describe this separation of charge carriers and the subsequent quenching of the electro-luminescence efficiency (*Kalinowski et al.*).

6.3 Review of Recent Results from the Literature

In this section, some of the recent data, relevant to electrically pumped polymeric lasing will be reviewed. The two most likely ways of increasing electro-luminescence efficiency and hence obtaining threshold conditions is to increase transport properties, such as mobility and to increase electron-hole capture processes. Recently a groundbreaking paper by *Schön et al.* has demonstrated organic solid-state injection lasers using single crystals of tetracene. This paper highlights how the importance of carrier mobility in creating the conditions necessary for electrically pumped lasing. As was mentioned in section 6.2.3 the electron-hole capture process has not been well studied. For this reason, the paper by *Wilson et al.* on spin dependence of exciton formation in conjugated materials is of some importance to the understanding of the electro-luminescent process. These two important papers will now be reviewed in detail.

6.3.1 Electrically Pumped Lasing in Single Crystal Devices

Schön et al. were the first to demonstrate an organic solid-state injection laser. In order to achieve this they have used a novel field effect transistor device structure made from a single crystal of tetracene. This work was carried out in Bell Labs where considerable progress has recently been made in the growth of low defect high quality organic single crystal growth (*Kloc et al.*).

Single crystals of tetracene have been shown to exhibit mobilities of $\sim 2 \text{ cm}^2 \text{V}^{-1} \text{s}^{-1}$ in tetracene at room temperature. Such mobilities are four orders of magnitude greater than the mobilities of materials used in conventional OLEDs.

Two field effect electrodes were used to ensure facile, balanced charge injection. The field effect electrodes were achieved by sandwiching the tetracene crystal between two field effect transistor structures. Aluminium and

Gold were used for the Source and Drain of each transistor, while an insulating layer of Al_2O_3 was sputtered onto the surface of the crystal before laying down an Aluminium doped ZnO gate. Positive gate voltages give rise to an electron gas at the tetracene- Al_2O_3 interface while a negative Gate voltage results in the formation of a hole gas. If a potential difference is applied between the two gate electrodes the electron and hole gasses will flow towards each other, meet and form excitons. The current density was varied by modulating the applied gate voltages to increase the carrier density in the device, while maintaining the potential difference between the gate electrodes at 5V.

The tetracene crystal and the Al_2O_3 layers formed a planar waveguide, although leakage of the optical field into the ZnO layers resulted in high propagation losses of $\sim 100\text{cm}^{-1}$. The ends of the tetracene crystal formed mirrors for a Fabry-Perot cavity. The mirror reflectivity was estimated to be 8%, although was probably considerably less due to scattering.

Using these devices, Schön observed ASE at 575.7nm followed by lasing at 5K and 300K. At 5K lasing with a threshold current density of the order of $500\text{A}/\text{cm}^2$ was observed. At 300K, the threshold current density was found to be $1600\text{A}/\text{cm}^2$ for pulsed excitation. Schön estimates that optimisation of the end mirrors and the waveguide structure of these devices could give rise to the threshold current density dropping by two orders of magnitude. Such improvements could make the operation of room temperature CW laser devices feasible.

In light of recent controversy surrounding the work of Schön et al., after the submission of this thesis, considerable doubt has been placed on the validity of these results. In spite of this, Schön still maintains that he observed all of the phenomena that he published in scientific journals. For further information, the reader is referred to the report by *Beasley* commissioned by Lucent Technologies after independent researchers were unable to verifiably replicate the results of Schön.

6.3.2 Singlet Triplet Ratio in Organic Devices

In the work of *Wilson et al.*, the spin-orbit coupling present in a Platinum containing polymer allows the observation of optically and electrically generated simultaneous singlet and triplet emission. Using this fact, Wilson was able to calculate the singlet generation fraction, χ_s , in electro-luminescent devices using this polymer as an emissive layer. He was also able to perform the same measurements for devices using the corresponding monomer and compared the singlet generation fraction to that of the polymer.

The polymer and monomer both display a fluorescence band at 2.2eV and a phosphorescence band at 1.5eV. The exchange energy of 0.7eV indicates an excited state, which is self-localised. The intersystem crossing rate has been measured to be close to unity for both the polymer and the monomer (*Wittmann et al.*). However, the singlet emission is still stronger than triplet emission due to the high non-radiative decay rate. The quantum yield for phosphorescence is found to be 0.1%.

Assuming the quantum yield for electrically and photo-generated excitons is the same, ie. $\phi_{EL} = \phi_{PL}$, Wilson derived the following relation:-

$$\frac{R_{PL}}{R_{EL}} = \frac{\chi_s \phi_{ISC}}{1 + \chi_s (\phi_{ISC} - 1)} \quad [6.43]$$

where R_{PL} , R_{EL} are the ratios of the observed phosphorescence to fluorescence for electrical and photo-excitation respectively. ϕ_{ISC} is the quantum yield for intersystem crossing. This allowed χ_s to be measured from the observation of the phosphorescence and fluorescence from electrically and photo-generated excitons. Wilson checks that $\phi_{EL} = \phi_{PL}$ by measuring the lifetimes of the triplet excitons in his devices. He finds that the monomer triplet exciton lifetime is $\sim 10\mu s$ and the polymer triplet exciton lifetime is $\sim 3\mu s$. Since any electrical quenching effects in a device will be different at different positions in the emissive layer Wilson also measured χ_s at various different device thicknesses.

No thickness dependence was observed so it seems that the assumption that $\phi_{EL} = \phi_{PL}$ is valid.

Wilson then found that the singlet generation fraction in EL devices is $22 \pm 1\%$ for the monomer and $57 \pm 4\%$ for the polymer. This is rationalised as follows. The value of χ_s for the monomer is close to the 25% expected for a random Langevin capture process. The Langevin capture radius is of the order 18nm (see section 6.2.3.1). This is considerably larger than the molecular dimension for a monomer unit, but comparable to the delocalisation length along a polymer chain. Therefore, for molecular materials, the electron-hole capture occurs at a range where only the Coulomb interaction is effective and there is no contribution from electron-hole wavefunction overlap. Consequently, the capture process proceeds as expected for a Langevin mechanism, resulting in excitons, which are independent of the spin states, of the captured charge pair. However, for polymers, when electrons and holes are present on the same chain within the capture radius the interaction also includes a contribution from the direct overlap of electron and hole wavefunctions. As was seen in section 2.8 the triplet exciton has been calculated to be more localised than the singlet exciton. The singlet exciton delocalisation is of the same order of magnitude as the Langevin capture radius, while the triplet exciton delocalisation is considerably less than this. Consequently, the formation of singlet excitons can compete with the random charge capture process. Thus the overall capture process becomes spin dependent in favour of the formation of singlet excitons. As a result, Polymers displaying greater singlet exciton delocalisation should have increased electro-luminescent efficiency.

These recent results bode well for the future of both OLEDs and polymeric lasing. The results from these two papers indicate some desirable properties that should be developed in future materials. Materials with high carrier mobility are essential for gaining laser action, while greater charge delocalisation can overcome the limitation of the EL quantum yield to be less

than 25% of the PL quantum yield. Both of these properties could be achieved by developing materials with increased long-range order.

6.4 Optical Modelling of Heterostructures

A commonly used modelling system for optical waveguides is the BPM_CAD (Beam Propagation Method by Computer Aided Design) package from the Optiwave Corporation. This package can be used to optimise waveguide structures at the design stage. Since the objective here is to create optimised organic heterostructure devices, this package can be used using the optical constants for the materials measured in chapter 4.

The 2D BPM package is best used to describe the behaviour of the optical field inside a planar waveguide. The BPM uses a Crank-Nicholson finite difference method to solve the Helmholtz equation in 2-dimensions in the presence of a Gaussian profile of initial values and the associated boundary conditions described by the geometry of the waveguide and the optical constants of specific waveguide layers.

The field calculation is based on a numerical solution of the Helmholtz equation (*Van Roey et al.* and *Yevick*) inside a given polymer thin film:-

$$\left\{ \frac{\partial^2}{\partial x^2} + \frac{\partial^2}{\partial z^2} + k_o^2 n^2(x) \right\} E_y(x, z) = 0 \quad [6.44]$$

where the film is in the x - z plane, the refractive index, $n(x)$, is a function of the x -ordinate and $E_y(x, z)$ is the electric field in the y -direction. Considering a solution of the form $E_y(x, z) = E_F(x, z)e^{-i\beta z}$, propagating in the z -direction, where $E_F(x, z)$ is a slowly varying function in z , equation 6.44 becomes:-

$$\left\{ \frac{\partial^2}{\partial x^2} + k_o^2 (n^2(x) - \beta^2) \right\} E_F(x, z) = 2ik_o\beta \frac{\partial}{\partial z} E_F(x, z) \quad [6.45]$$

The form of the amplitude of the waveguided light, $E_F(x, z)$, at any point in the x - z plane is governed by this equation.

Figure 6.4 Schematic showing how Beam Propagation Method calculates the field at different points E_j^m on the grid. Also shown are the boundary conditions that the Helmholtz equation must satisfy due to changes in the refractive index.

The solution can be obtained numerically over a grid of points in the x - z plane by writing equation 6.45 in the form:-

$$\frac{B}{2} \left\{ \frac{(E_{j+1}^{m+1} - 2E_j^{m+1} + E_{j-1}^{m+1}) + (E_{j+1}^m - 2E_j^m + E_{j-1}^m)}{(\Delta x)^2} \right\} + C \left\{ \frac{E_j^{m+1} + E_j^m}{2} \right\} = \frac{E_j^{m+1} - E_j^m}{\Delta z} \quad [6.46]$$

where E_j^m , Δx , Δz are as shown in Figure 6.4 and $B = \frac{1}{2ik_0\beta}$ and $C = \frac{k_0(n^2(x) - \beta^2)}{2i\beta}$. Equation 6.46 is the Crank-Nicholson equation (*Press*) for finite difference at $m+1/2$. Given the initial conditions across a row of the grid in Figure 6.4 it is possible to solve these equations for all E_j^{m+1} and hence solve for the field as it propagates down the waveguide. The advantage of using this procedure is that the calculated field is relatively insensitive to the choice of the parameters Δx , Δz (*Press*).

In order to gain some insight into the possibilities of an electrically pumped heterostructure device based on waveguiding a simulation was carried out on a symmetric waveguide sandwiched between two layers of a material with the

same optical constants as gold. The waveguide was modelled with cladding layers of $n=1.4537$, and with a guiding layer of $n=1.7142$ at a wavelength of 630nm in the Transverse Electric (TE) polarisation. These values of refractive index correspond those of polystyrene and DPOP-PPV respectively and represent an example of the greatest possible contrast between the refractive index of cladding and guiding layers currently available. As a result, the results of this simulation represent the best possible scenario with regards to limiting the propagation loss in a double hetero-structure waveguide device. The grid spacing for these calculations was $\Delta z=0.1\mu\text{m}$ and $\Delta x=0.01\mu\text{m}$. The simulation was performed at various different layer thicknesses of the cladding and guiding layers in order to obtain an absorption map (see Figure 6.5) for the different layer thicknesses. From this it is possible to know approximately what propagation losses are present for a given device configuration.

The absorption map is characterised by extremely high absorption coefficients of the order $\sim 1000\text{cm}^{-1}$ when the cladding and guiding layers are at $\sim 50\text{nm}$ thickness. This is an extremely lossy waveguide and is certainly not

Figure 6.5 Optical Loss map for Heterostructure waveguide on gold as a function of guiding layer and cladding layer thickness. Calculations performed on cladding layer of $n=1.4537$ and guiding layer of $n=1.7142$ at a wavelength of 630nm.

Figure 6.6 Lossy Waveguide; Cladding layers are 100nm thick and guiding layer is 150nm thick.

suitable for creating gain by waveguide propagation. A typical lossy waveguide is shown in Figure 6.6 where the waveguide is unable to confine the optical field away from the metal electrodes. The waveguide is centered symmetrically on the origin of the width axis. Large propagation losses ensue because of the penetration of the optical field into the metal, which possesses a large extinction coefficient. Further confinement could possibly be achieved by increasing the refractive index mismatch between the cladding and the guiding layer, although this would require unrealistic values for the refractive index of the guiding layer, which could not be expected to be found in polymers.

The propagation of the optical field in a low loss waveguide is shown in Figure 6.7. It can be clearly seen from the cross section in the inset that the optical field is well confined in the guiding layer of the waveguide. The optical field has decayed almost completely by the time it reaches the metal and so the propagation loss here is minimal. However, this comes at the price of having device thickness of the order of $\sim 1\mu\text{m}$.

Close inspection of the optical loss map (see Figure 6.5) reveals ripples in the optical loss at certain thicknesses of the guiding layer. These are particularly

Figure 6.7 Low Loss Waveguide; Cladding layers are $0.6\mu\text{m}$ thick and guiding layer is $0.5\mu\text{m}$ thick.

noticeable in the low loss regions of the simulation. These ripples are attributed to the presence of leaky waveguide modes. At certain guiding layer thicknesses the waveguide condition cannot be met by the light at a fixed wavelength; therefore, the light leaks out into the cladding and the metal, and so the waveguide loss increases. This can be clearly seen in the inset of Figure 6.8 where there are clear antinodes present in the cladding layer. The presence

Figure 6.8 Leaky Waveguide; Cladding layers are $0.6\mu\text{m}$ thick and guiding layer is $0.4\mu\text{m}$ thick.

of leaky modes contributes significantly to the propagation loss of the waveguide. Consequently, every effort should be made to avoid them in an optimised device, as they discard the advantage gained by having a thicker cladding layer.

From the absorption map it is possible to see that in order to fabricate a low loss waveguide, with propagation losses of the order of 10cm^{-1} , it is necessary to have cladding layers of at least $0.5\mu\text{m}$ and guiding layers of the order of $0.2\mu\text{m}$. This presents some problems for the operation of double heterostructure type devices. Consider a layer of thickness $0.5\mu\text{m}$. Typical mobilities for PPV type polymers are of the order of $\sim 10^{-7}\text{cm}^2\text{V}^{-1}\text{s}^{-1}$. In order to obtain light from a device, current densities of the order of $100\text{mA}/\text{cm}^2$ need to be induced. To achieve this current density within the layer, a voltage of $\sim 600\text{V}$ (estimated from equation 6.28) would need to be applied. This corresponds to a field of $\sim 10^7\text{V}/\text{cm}$. As can be seen from Tables 6-2 and 6-3 section 6.4, the catastrophic breakdown voltage for the unipolar devices has been found to be in the region of $\sim 10^6\text{V}/\text{cm}$. Consequently, it is not yet possible to obtain light from low loss waveguide heterostructures made from PPVs.

6.5 Electrical Measurements on Organic Materials

In this section, basic electrical measurements are performed, in order to obtain the electrical characteristics, such as mobility and free carrier density, of a series of conjugated polymers. Where possible, measurements on the trap distribution in these materials are also carried out.

6.5.1 Experimental Set up for Low Current Measurements

The experimental set-up for obtaining current-voltage as well as emission characteristics from organic devices is shown in Figure 6.9. The IV Characteristics of unipolar and bipolar devices can be recorded using a Keithley 2400 Sourcemeter and a Keithley 2001 Ammeter connected to a

personal computer and controlled using a visual basic data collection program. All devices measured were in a six-finger format as shown in Figure 6.10 for a bipolar device, where the anode is ITO and the cathode is Aluminium. A six-point switch, connected to the six-point probes, allows the external switching to any device finger. The device is maintained in a vacuum chamber (pressure $\sim 1 \times 10^{-1}$ mbar) to prevent degradation due to oxygen attack during measurements, unless otherwise stated. In the case of light emitting devices, the emission characteristics can be measured using a Topcon BM-8 luminance meter. Spectral measurements could be performed with an Oriel 77400 spectrograph, connected to an Andor B401-UV CCD, using an Oriel 77863 liquid light guide to couple the emission into the spectrometer.

6.5.2 Important Considerations for Low Current Measurements

When performing voltage-current measurements where the observed current is very small, experimental noise can be a significant problem. The most useful data region for parameter extraction is the Ohmic conduction region. This typically involves the measurement of currents of the order of nA. Low current measurements of this type are subject to a number of error sources

Figure 6.9 Schematic showing the Experimental Setup for Current-Voltage characterisation of Unipolar devices and Organic LED's (OLEDs). Luminescence and Spectral Measurements are also taken for OLEDs.

Figure 6.10 Schematic showing the structure of a six-fingered device. Also shown is the Transverse emission which is normally measured as well as the edge emission which is measured from Double Heterostructure Waveguide devices in section 6.5.

that can have a serious impact on the accuracy of a given measurement. Consequently, some effort was put into identifying and reducing these noise sources, so accurate measurements could be carried out. As a result, the following steps were taken to optimise the experimental setup.

- All cables and connections were cleaned using solvent to remove any grease and dirt present. This minimises any extra resistance due to connections and removes any extraneous currents due to dielectric absorption.
- All connections were kept as short as possible and were affixed to the experimental bench. This prevents the cables moving, and so prevented currents due to the cable moving in the earth's magnetic field as well as preventing piezo-electric and tribo-electric effects.
- Care was taken to ensure that the entire measurement circuit was enclosed within electromagnetic shielding, with a common earth. This removes effects from background electromagnetic radiation.
- Finally, all measurements were performed in an air-conditioned room so that the humidity was minimised.

6.5.3 Unipolar Current Voltage characteristics

In this section, the unipolar charge transport characteristics of conjugated polymers will be studied. In keeping with the research strategy, outlined in section 1.4, a wide range of materials will be investigated, in order to find optimal materials for transport in an electrically pumped laser.

6.5.3.1 Current Voltage Measurements for Electrons

Aluminium bottom contacts ($\sim 100\text{nm}$) were sputtered onto glass substrates at a rate of $\sim 0.1\text{\AA/s}$. A series of conjugated polymers were spin cast on top of these electrodes, and baked under vacuum at 60°C in the usual manner. The charge transfer complex PBD was dissolved with PMMA in a ratio of 3:1, in cyclohexanone, so that a spin cast film could be formed. An Alq_3 film was also prepared by vacuum deposition directly onto the aluminium electrodes in the usual manner. Top contacts of aluminium were then laid down at a rate of $\sim 0.15\text{\AA/s}$ for the first 20nm and at a rate of $\sim 5\text{\AA/s}$ until a total film thickness of $\sim 70\text{nm}$ was achieved.

The IV characteristics of these samples were then recorded using the experimental set-up described previously. The IV characteristics for each

Figure 6.11 Log-log current voltage characteristics for Alq_3 . Also included is the appropriate fitting to the data.

Figure 6.12 Log-log current-voltage characteristics for DPOP-PPV. Also included is the appropriate fitting to the data.

material are displayed in Figures 6.11-16 on log-log plots. The results of the fitting of the equation of a straight line have also been plotted for the linear regions of the log-log plots. The parameters of this fitting procedure are also given beneath each graph.

All of the materials tested demonstrated a linear Ohmic region at low voltages in the IV characteristic. At increased voltages DPOP-PPV, HT73, HT94 and

Figure 6.13 Log-log current voltage characteristics for HT73. Also included is the appropriate fitting to the data.

Figure 6.14 Log-log current voltage characteristics for HT94. Also included is the appropriate fitting to the data.

MEH-DOO PPV (Figures 6.12-15) displayed a quadratic region. At still higher voltages, DPOP-PPV, HT73 and MEH-DOO PPV all exhibit a region of increased slope of the order 7-11. All of the Thianthrene PPV (Figure 6.16) sample shows a well-defined linear Ohmic region and deviates from this at voltages above $\sim 5V$. However, it was not possible to gain a good fit of slope 2 or higher above this. The Alq₃ (Figure 6.11) sample exhibits an Ohmic

Figure 6.15 Log-log current voltage characteristics for MEH-DOO PPV. Also included is the appropriate fitting to the data.

Figure 6.16 Log-log current voltage characteristics for Thianthrene PPV. Also included is the appropriate fitting to the data.

region of slope 1 followed by a region of slope 5. The quality of the curve fitting procedures was excellent as can be seen from the values of R^2 , where the worst fit yields a value of $R^2=0.967$, while most of the fits yield a value of R^2 in the region of 0.98-0.99.

All of the devices were tested repeatedly, to ensure that the measured current was representative of an ideal device, and not due to filamental injection or other anomalous mechanisms. The data displayed here is typical for the measured devices. All devices were tested with increasing applied voltage until

Table 6-2 Characteristics of Aluminium:Aluminium Unipolar Devices, showing the device thickness, area and the Catastrophic Breakdown Field.

Material	Thickness (nm)	Area ($\times 10^{-6} \text{m}^2$)	Breakdown Field ($\times 10^6 \text{V/cm}$)
Thiantrene PPV	46 ± 14	4.32 ± 0.04	5.9 ± 1.9
PBD:PMMA 75%	108 ± 18	5.11 ± 0.05	2.8 ± 0.5
HT73	27 ± 6	4.76 ± 0.05	6.7 ± 1.7
HT94	50 ± 7	5.00 ± 0.05	5.2 ± 0.8
MEH-DOO-PPV	58 ± 6	4.78 ± 0.05	5.0 ± 0.6
DPOP PPV	62 ± 13	4.70 ± 0.05	4.4 ± 1.0
Alq ₃	205 ± 6	4.66 ± 0.05	2.2 ± 0.1

catastrophic breakdown occurred and the measured current suffered a dramatic decrease of 1-3 orders of magnitude. The film thickness of each device was then determined by stylus profilometry in the region of the electrodes. The device area was also obtained by measuring the dimensions of the top contact using a travelling microscope. The device thickness, area and the electric field at catastrophic breakdown, relevant to the IVs displayed in Figures 6.9-14, are summarised in Table 6-2.

6.5.3.2 Current Voltage Measurements for Holes

For hole only current measurements bottom contacts of ITO (~100nm) on glass substrates (UQG) were used. The bottom contact was etched, to form devices of similar dimensions to the Aluminium:Aluminium devices, using photolithography. A series of conjugated polymers were spin cast on top of these electrodes, and baked under vacuum at 60°C in the usual manner. A sample made from the commercial hole transport layer, PVK, was also spin cast from DCM for comparison. Top contacts of Platinum were then sputtered down at a rate of $<0.025\text{\AA/s}$ for the first 20nm and at a rate of $\sim 0.1\text{\AA/s}$ until a total film thickness of $\sim 70\text{nm}$ was achieved. The Platinum top contacts were laid down much more slowly than the aluminium contacts to prevent penetration and diffusion of Platinum into the polymer layer. This

Figure 6.17 Log-log current voltage characteristics for DPOP PPV. Also included is the appropriate fitting to the data.

Figure 6.18 Log-log current voltage characteristics for HT73. Also included is the appropriate fitting to the data.

can cause a decrease in the effective device thickness and can even short circuit the devices. All devices were immediately measured after Platinum deposition to prevent diffusion of the Platinum affecting the results significantly.

The IV characteristics of these samples were then recorded using the experimental set-up described previously. The IV characteristics for

Figure 6.19 Log-log current voltage characteristics for HT94. Also included is the appropriate fitting to the data.

Figure 6.20 Log-log current voltage characteristics for MEH-DOO PPV. Also included is the appropriate fitting to the data.

each material are displayed in Figures 6.17-22 on log-log plots, in the same manner as before.

All of the materials tested demonstrated a linear Ohmic region at low voltages in the IV characteristic. At increased voltages, HT73 and HT94 display a quadratic region. HT73 then exhibits a region of increased slope of ~ 4 , at still higher voltages. DPOP-PPV and MEH-DOO PPV both show a transition

Figure 6.21 Log-log current voltage characteristics for PVK. Also included is the appropriate fitting to the data.

Figure 6.22 Log-log current voltage characteristics for Thianthrene PPV. Also included is the appropriate fitting to the data.

from linear behaviour to an increase of slope ~ 4 -5 before showing some evidence of returning to a slope 2 characteristic. Both the Thianthrene PPV and the PVK sample exhibit a well-defined linear Ohmic region that deviates at higher voltages, without showing a well-defined slope 2, or higher, region. The quality of the curve fitting procedures was excellent as can be seen from the values of R^2 , where the worst fit yields a value of $R^2=0.979$, while most of the fits yield a value of R^2 in the region of 0.99.

As before, all of the devices were tested repeatedly, to ensure that the measured current was representative of an ideal device. The data displayed

Table 6-3 Characteristics of Platinum:ITO Unipolar Devices, showing the device thickness, area and the breakdown Voltage.

Material	Thickness (nm)	Area ($\times 10^{-6} \text{m}^2$)	Breakdown Field ($\times 10^6 \text{V/cm}$)
Thianthrene PPV	62 ± 11	4.20 ± 0.04	4.8 ± 1.3
HT73	39 ± 9	3.23 ± 0.04	3.3 ± 0.5
HT94	85 ± 8	4.36 ± 0.04	2.2 ± 0.5
MEH-DOO-PPV	70 ± 8	4.59 ± 0.05	4.7 ± 2.0
DPOP PPV	153 ± 11	4.49 ± 0.04	2.2 ± 0.7
PVK	336 ± 14	5.34 ± 0.05	1.1 ± 0.3

here is typical for the measured devices. All devices were tested with increasing applied voltage until dielectric breakdown occurred.

The film thickness and device area of each device was then determined by stylus profilometry, and measurement with a travelling microscope respectively. The device thickness, area and breakdown voltage, relevant to the IVs displayed in figures 6.17-22, are summarised in Table 6-3.

6.5.3.3 Discussion of Unipolar Current Voltage Measurements

As has been seen in section 6.2 there are numerous models for the IV characteristics of organic devices. In this section, all of the models from the injection limited models to the bulk limited SCLC models will be applied to the data, in order to find the most suitable model for the data.

A Fowler-Nordheim tunnelling model was applied to the IV data for all of the polymer devices, by plotting $\ln\left(\frac{J}{E^2}\right)$ against $\frac{1}{E}$. As an example the fitting of a straight line to the electron transport data for the DPOP-PPV Aluminium:Aluminium device was considered:- The line could only be fit in the high field region ($V > \sim 20\text{V}$) resulting in a negative slope of $m = -1.65 \times 10^{-6}$, which predicts a barrier height of $\sim 5 \times 10^{-25} \text{eV}$. It is unlikely that such a barrier could give rise to injection-limited behaviour of any sort, as thermal effects would easily be overcome such a barrier. Application of this model to the hole transport data for the DPOP-PPV Platinum:ITO device produced a similarly unlikely barrier height of $2 \times 10^{-25} \text{eV}$. Application of this model to the other polymer samples yielded comparable results to those obtained for the DPOP-PPV samples. Consequently, the Fowler-Nordheim tunnelling mechanism can be discarded for these devices.

Modelling the data using a thermionic emission mechanism (equation 6.3) was also attempted, by plotting $\ln J$ against $\sqrt{E}$ and $\sqrt[4]{E}$. In this case, significant curvature was found in the graphs and so it is unlikely that this model was applicable to the data.

Table 6-4 Electron and Hole Transport Characteristics for the materials studied in this thesis. The conductivity σ , free carrier density p_o/n_o and the effective mobility calculated from the Ohmic region, μ_{eff}^o , are summarised for all materials. The mobility from the SCLC (Slope 2) region, μ_{eff}^{SCLC} , is also shown, where possible.

Electron Transport Characteristics				
Material	σ ($\times 10^{-10}$ S cm $^{-1}$)	n_o ($\times 10^{18}$ cm $^{-3}$)	μ_{eff}^o ($\times 10^{-2}$ cm 2 V $^{-1}$ s $^{-1}$)	μ_{eff}^{SCLC} ($\times 10^{-2}$ cm 2 V $^{-1}$ s $^{-1}$)
Thiathrene PPV	19.00 $\pm$ 6.84	5.51 $\pm$ 3.90	21.50 $\pm$ 23.00	—
PBD:PMMA 75%	1.91 $\pm$ 0.41	1.96 $\pm$ 0.81	6.07 $\pm$ 3.83	4.11 $\pm$ 3.80
HT73	4.95 $\pm$ 1.51	10.50 $\pm$ 5.49	2.93 $\pm$ 2.42	1.56 $\pm$ 1.44
HT94	2.64 $\pm$ 0.68	6.06 $\pm$ 2.16	2.72 $\pm$ 1.57	1.60 $\pm$ 1.31
MEHDDO-PPV	0.67 $\pm$ 0.13	4.78 $\pm$ 1.16	1.14 $\pm$ 0.45	0.75 $\pm$ 0.60
DPOP PPV	0.59 $\pm$ 0.16	3.70 $\pm$ 1.70	1.00 $\pm$ 0.73	0.30 $\pm$ 0.38
Alq $_3$	0.18 $\pm$ 0.06	1.33 $\pm$ 0.13	0.87 $\pm$ 0.38	—

Hole Transport Characteristics				
Material	σ ($\times 10^{-9}$ S cm $^{-1}$)	p_o ($\times 10^{18}$ cm $^{-3}$)	μ_{eff}^o ($\times 10^{-7}$ cm 2 V $^{-1}$ s $^{-1}$)	μ_{eff}^{SCLC} ($\times 10^{-7}$ cm 2 V $^{-1}$ s $^{-1}$)
MEHDDO PPV	30.20 $\pm$ 4.79	5.23 $\pm$ 2.38	36.10 $\pm$ 22.20	78.60 $\pm$ 93.70
Thiathrene PPV	45.40 $\pm$ 13.20	42.40 $\pm$ 16.30	6.67 $\pm$ 4.50	—
HT73	6.27 $\pm$ 2.23	6.81 $\pm$ 4.45	5.86 $\pm$ 4.54	3.02 $\pm$ 3.95
HT94	3.23 $\pm$ 0.48	3.55 $\pm$ 0.75	5.68 $\pm$ 2.04	4.94 $\pm$ 3.84
DPOP PPV	0.18 $\pm$ 0.04	2.99 $\pm$ 1.13	0.37 $\pm$ 0.21	0.33 $\pm$ 0.71

The most likely mechanism describing the IV behaviour of the conjugated polymer devices measured here, is SCLC in the presence of a broad distribution of traps (*Campbell et al.*). The presence of well-defined linear regions separated by transition regions at specific applied voltages in the log-log IV characteristics is strongly indicative of SCLC behaviour.

The presence of Ohmic regions followed by a transition voltage, combined with the observation of V_α , allows the determination of the effective mobility, μ_{eff} , and free carrier concentration, n_o/p_o , of the polymers from equations 6.18 and 6.30. These parameters are listed for electrons and holes in Table 6-4. It is possible in the materials where there is a well-defined slope 2, SCLC region to calculate the mobility by a second method using equation 6.28. Both of these methods have been used to calculate μ_{eff}^o , the ohmic mobility in equation 6.18, and μ_{eff}^{SCLC} , the SCLC mobility in equation 6.28.

The close agreement between μ_{eff}^o and μ_{eff}^{SCLC} for all of the materials is an example of the self-consistency of the SCLC theory when compared to the injection limited models.

As has been mentioned in section 6.2.3.1 the mobility is of critical importance in obtaining light emission in OLEDs and hence obtaining population inversion in any proposed laser device. Consequently, the mobility is a very important parameter, for the classification of possible laser materials. As can be seen from Table 6-4 the mobility of all of the materials is in the region of $10^{-7} \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$ for holes and $10^{-8} \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$ for electrons. For conjugated polymers the measured hole mobility has been found to range from 10^{-11} - $10^{-7} \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$ (Conwell *et al.*), with electron mobility being orders of magnitude less (Bozano *et al.*), with some researchers reporting that the electron mobility is more than three orders of magnitude less than the hole mobility (Blom *et al.* (1996)). It is possible that the electron mobilities measured here are overestimated, as in the presence of an Al_2O_3 Aluminium electrodes can become hole injecting and so the measured current density is a superposition of electron and hole transport. This could also explain the disappointingly low mobility for Alq_3 , measured here to be $8.7 \times 10^{-9} \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$ as compared to the value of $5 \times 10^{-7} \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$ measured by Era *et al.*. In the case of the measurement here, the very low hole mobility of Alq_3 could have contributed to a low effective carrier mobility. It should be pointed out that the estimation of mobility from this measurements technique is only accurate to approximately an order of magnitude, as can be seen from the large estimates of error. This is primarily due to the large errors associated with measurement of film thickness.

The presence of trap limited SCLC followed by regions of higher slope, in some of the devices, demands further discussion. If the traps present were shallow traps, the IV characteristic would have an Ohmic region at low voltages, followed by a slope 2 SCLC region followed by a sharp increase to trap free SCLC conduction. If the traps present were deep traps the Ohmic region would be followed by either:-a sharp increase to trap free SCLC conduction if the traps were discrete or a region of high slope, indicating the

Table 6-5 Table showing, where possible, the characteristic trap energy, ϵ_T and the trap density, D_{T0} , for electrons and holes in the materials studied here.

Electron Trap Characteristics			Hole Trap Characteristics		
Material	ϵ_T (eV)	D_{T0} ($\times 10^{18}$ cm $^{-3}$)	Material	ϵ_T (eV)	D_{T0} ($\times 10^{18}$ cm $^{-3}$)
Thiantrene PPV	—	—	Thiantrene PPV	—	—
HT73	0.2626	9.678	HT73	0.0782	23.004
HT94	—	—	HT94	—	—
MEH-DOO-PPV	0.1669	6.609	MEH-DOO-PPV	0.0847	5.158
DPOP PPV	0.1591	5.032	DPOP PPV	0.1038	1.772
Alq $_3$	0.1038	291.1	PVK	—	—

filling of a Gaussian or an exponential distribution of traps, followed by a trap free SCLC region. This latter case can be observed in the behaviour of MEH-DOO-PPV and DPOP-PPV Platinum:ITO devices although the trap free limit cannot be observed over many orders of magnitude of current. For most of the materials, a region of slope 2 is observed, followed by a region of high slope. This may be possible if deep lying traps were present, which the Fermi level couldn't sample at lower applied voltages. For the devices, in which this behaviour occurs, it is then possible to determine the density of traps present, D_{T0} , and the characteristic trap energy, ϵ_i , provided the density of HOMO states, $n(\epsilon_{HOMO})$, is known. To do this a typical value of $n(\epsilon_{HOMO})=10^{20}$ cm $^{-3}$ (Mark *et al.*) is used in the calculation. The trap density and the characteristic trap energy are given in Table 6-5 for all of the materials where this calculation is possible.

6.6 Waveguiding Organic Double Heterostructure

At this point, all of the information is available, on the physical properties of a wide range of materials, so that the design of a waveguiding double heterostructure waveguiding device can be considered. The combined properties of the optical constants, the excited state absorption and the transport properties all play a significant role in the operation of such a device.

6.6.1 Fabrication

The refractive index data obtained in chapter 4, limits the possibilities considerably for the fabrication of a waveguide device, due to the lack of significant contrast in the refractive index of the materials measured, and the lack of guiding materials with a larger refractive index than Alq₃. However, there are two possible device configurations; ITO:PFO:HT73:Alq₃:Al and ITO:PEDOT:HT73:Alq₃:Al.

It was attempted to make the ITO:PFO:HT73:Alq₃:Al devices, but problems due to the lack of orthogonal solvents for the polymers resulted in mixing between the HT73 and the PFO layers, so this device could not be fabricated. It was possible to prepare the ITO:PEDOT:HT73:Alq₃:Al device. The ITO layer was patterned using photolithography, in the same manner as before. PEDOT was spin cast on top of the substrate, before spin casting a layer of HT73. A layer of Alq₃ was then evaporated onto the device in the usual manner, before evaporating an aluminium contact. The estimated layer thicknesses were as follows; ITO=100nm, PEDOT=50nm, HT73=100nm, Alq₃=50nm and Al=100nm.

6.6.2 Device Characteristics of Heterostructure

The current-voltage behaviour was measured, using the experimental set-up shown in Figure 6.9. The IV characteristic for the heterostructure is shown in Figure 6.23(a). Also shown in Figure 6.23 (b) is the transverse emission electro-luminescence, with the spectral response of the human eye. The luminance of the device was measured using the luminance meter, at an applied bias of 30V, to be 0.18Cd/m². The external quantum efficiency of the device, η_{ext} , is defined as the ratio of the number of photons emitted, from the device in the transverse direction, per unit volume per unit time to the number of charge carriers flowing within that same unit volume per unit time. This ratio is equal to the number of photons produced per unit area of the device per second to the number of charge carriers flowing

Figure 6.23 (a) The Current-Voltage characteristic for the ITO:PEDOT:HT173:Alq₃:Al device. (b) The transverse emission spectrum from the device, showing the overlap between the emission and the spectral response of the human eye. Also shown in the table are the values of the current density, luminance and device efficiency at 30 V.

within that same unit area. Consequently the external quantum efficiency is given by:-

$$\eta_{ext} = \frac{Le}{6.83Jhc \int_0^\infty \frac{E_F(\lambda) \cdot V_R(\lambda)}{\lambda} d\lambda} \quad [6.47]$$

where L is the measured luminance, J is the current density, $E_F(\lambda)$ is the fluorescence quantum distribution, normalised to 1 and $V_R(\lambda)$ is the Commission International de l'Eclairage (CIE) standard response of the human eye (see Figure 6.23).

Using equation 1.47, the external quantum efficiency was calculated to be 0.096 ± 0.007 %, from the values of luminance, current density and overlap integral between the electro-luminescence and the CIE curve measured at an applied bias of 30V.

6.6.3 Spectral emission from edge of device

PL spectra of the edge emission and transverse emission from the triple layer heterostructure were taken using an Oriel 77400 spectrograph connected to

Figure 6.24 Graph showing the Edge and Transverse Emission from the Heterostructure waveguide. Also shown is the quotient of the Edge PL Intensity divided by the Transverse PL Intensity. Peak occurs at 655nm. Simulation Predicts Peak at ~630nm.

an Andor B401-UV CCD camera (see Figure 6.9). The light was collected using an Oriel 77863 liquid light guide, which was placed as close as possible to the emission. These measurements were performed in air. The emission spectra are shown in Figure 6.24.

The intensity of the edge emission, from the triple layer device, was measured through a polariser, set at different azimuthal angle, was measured with a photodiode to determine the polarisation of the emitted light. The device degrades rapidly in air so short exposure times used. Despite this, the emission decayed significantly, over the course of 36 measurements. It was assumed that the intensity of the emission decayed according to $I_n = I_0 e^{-\alpha n}$ where I_n is the intensity of the n th measurement, I_0 is the intensity of the first measurement and α is a decay constant. A correction assuming this form of exponential degradation was applied to obtain a corrected data set. Both the measured and corrected data sets are shown in Figure 6.25. An elliptical polarisation in electric field was fitted to the corrected data to find $E_{\parallel}$ and $E_{\perp}$, the Electric field parallel and perpendicular to the plane of the polymer film. Using these values, the anisotropy of the emission, $A = \frac{E_{\parallel} - E_{\perp}}{E_{\parallel}}$ was found to be 0.16 ± 0.02 .

Figure 6.25 Graph showing the Intensity of emission versus azimuthal angle for the edge emitted light from the heterostructure device.

6.6.4 Discussion of the Heterostructure Characteristics

It is noticeable, that the currents obtained with the heterostructure device are ~ 3 orders of magnitude less than those obtained by unipolar measurements suggesting a large value of B in equation 6.36. This indicates well-balanced charge transport and injection, resulting in a reasonable device efficiency of $\sim 0.1\%$. The current state of the art efficiency is about an order of magnitude greater than this. However, it must be pointed out that these devices are un-optimised, so improvements in efficiency could be obtained.

The observation that there is an anisotropy ~ 0.2 in the polarisation of the light can be attributed to the polymer chains lying in the plane of the film. This is similar to the situation in section 4.6 where anisotropy in PmPV was detected by the ellipsometry measurements. In this case, the anisotropy is due to emissive species lying in the plane of the polymer film. The value measured here may well be considerably lower than the actual anisotropy in the emission as light reflected off the surface of the glass substrate may also be detected. Due to the reflection at various different angles, a randomisation of the polarisation takes place, decreasing the detected anisotropy. It is most likely that most of the waveguided light within the heterostructure device propagates in TE configurations.

There is no evidence of lasing or ASE in the results of this device. The small currents obtained, along with the relatively low values for the luminance, are several orders of magnitude too low to exceed laser threshold conditions, in the presence of the large optical losses, which are most likely present in a device of these dimensions (see section 6.4). However, this work is the first attempt to optimise a waveguiding OLED structure, using optical design simulations. To illustrate the power of the BPM_CAD modelling approach, a simulation using the estimated layer thickness for each electrode =100nm for the PEDOT=50nm and for the Alq₃=50nm and for the HT73 =100nm was carried out using the measured optical constants for each material over the wavelength range 600-700nm for the TE propagation. The field emerging from a 0.1mm propagation length divided by the initial field is plotted as function of wavelength in Figure 6.24. This clearly shows that there is a peak in the propagation of the electric field at 630nm (see Figure 6.24). This means that for this estimated device structure, there is a predicted decrease in the propagation loss of the device at 630 nm.

In order to compare the changes to the edge emission profile due to propagation within the waveguide the quantity, $Q(\lambda)$ is defined as:-

$$Q(\lambda) = \frac{PL_{Edge}(\lambda)}{PL_{Transverse}(\lambda)} \quad [6.48]$$

where PL_{Edge} is the Edge emission PL and $PL_{Transverse}$ is the Transverse emission PL. $Q(\lambda)$ is also plotted in Figure 6.24. It can be seen that $Q(\lambda)$ is approximately constant in wavelength, apart from a peak centred at 655nm. This means that there is a significant reduction in the waveguide loss in this region.

The prediction of a decrease in waveguide loss at 655nm by the simulation is quite close to the observed peak in $Q(\lambda)$ at 630nm. This suggests that the simulation, using the optical constants from chapter 4 and the estimated device dimensions, is an accurate representation of the propagation of light

within the double heterostructure waveguide. The most likely source of error in the prediction of the peak in $Q(\lambda)$ is the inevitable inaccuracy in determining the layer thickness from profilometry.

6.7 Conclusions

The electrical properties of a series of conjugated polymers have been measured using single layer unipolar device structures. Waveguide simulations have also been carried out in order to minimise optical propagation losses within double heterostructure waveguide devices. Low loss double heterostructure waveguide structures can be made with guiding layers of thickness $\sim 0.5\mu\text{m}$ and cladding layers of thickness $\geq 0.5\mu\text{m}$. However, the values obtained for the mobility prohibit light emission from such structures. Light emission can be obtained from high loss double heterostructure waveguide devices. The emission characteristics have been shown to follow quite closely the simulated behaviour of such structures, however the optical loss from these structures is still of the order of 1000cm^{-1} .

References

- Abeles, B., Ping, S., Coutts, M. D. and Arie, Y. (1975). "Structural and electrical properties of granular metal films." Advances in Physics **24**(3): 407-61.
- Adachi, C., Tsutsui, T. and Saito, S. (1990). "Confinement of charge carriers and molecular excitons within 5-nm-thick emitter layer in organic electroluminescent devices with a double heterostructure." Applied Physics Letters **57**(6): 531-3.
- Atkins, P. W. (1998). "Physical Chemistry."
- Baessler, H., Herrmann, G., Riehl, N. and Vaubel, G. (1969). "Space-charge-limited currents in tetracene single-crystals." Journal of Physics & Chemistry of Solids **30**(6): 1579-85.
- Beasley, M. (2002). "Report of the investigation committee on the possibility of scientific misconduct in the work of Hendrik Schön and coauthors." Available at http://www.lucent.com/news_events/researchreview.html.
- Blom, P. W. M., de Jong, M. J. M. and Breedijk, S. (1997). "Temperature dependent electron-hole recombination in polymer light-emitting diodes." Applied Physics Letters **71**(7): 930-2.
- Blom, P. W. M., de Jong, M. J. M. and Vleggaar, J. J. M. (1996). "Electron and hole transport in poly(p-phenylene vinylene) devices." Applied Physics Letters **68**(23): 3308-10.
- Bozano, L., Carter, S. A., Scott, J. C., Malliaras, G. G. and Brock, P. J. (1999). "Temperature- and field-dependent electron and hole mobilities in polymer light-emitting diodes." Applied Physics Letters **74**(8): 1132-4.
- Campbell, A. J., Bradley, D. D. C. and Lidzey, D. G. (1997). "Space-charge limited conduction with traps in poly(phenylene vinylene) light emitting diodes." Journal of Applied Physics **82**(12): 6326-42.
- Conwell, E. M. and Gartstein, Y. N. (1995). "Factors determining polaron mobility in light emitting diodes." SPIE-Int. Soc. Opt. Eng. Proceedings of Spie - the International Society for Optical Engineering **2528**: 23-31.
- Davids, P. S., Kogan, S. M., Parker, I. D. and Smith, D. L. (1996). "Charge injection in organic light-emitting diodes: tunneling into low mobility materials." Applied Physics Letters **69**(15): 2270-2.
- Era, M., Ikeda, Y., Tokuhisa, H. and Tsutsui, T. (1999). "Electric conduction of electroluminescent metal chelate thin films." Molecular Crystals & Liquid Crystals **327**: 171-4.

Fowler, R. H. and Nordheim, L. (1928). "Electron Emission in Intense Electric Fields." Proceedings of the Royal Society of London, Series A. **119**: 173.

Graupner, W., Partee, J., Shinar, J., Leising, G. and Scherf, U. (1996). "Dynamics of long-lived polarons in poly(para-phenylene)-type ladder polymers." Physical Review Letters **77**(10): 2033-6.

Ieda, M. (1971). "Dielectric breakdown of polymer materials." Solid State Physics **6**(10): 3-10.

Jonscher, A. K. (1967). Thin Solid Films **1**: 213.

Kalinowski, J., Stampor, W. and Di Marco, P. (1996). "Electromodulation of luminescence in organic photoconductors." Journal of the Electrochemical Society **143**(1): 315-25.

Kepler, R. G. (1993). "Exciton-exciton annihilation and exciton kinetics in poly(di-n-hexylsilane)." Physical Review B-Condensed Matter **47**(15): 9253-62.

Kersting, R., Lemmer, U., Deussen, M., Bakker, H. J., Mahrt, R. F., Kurz, H., Arkhipov, V. I., Bassler, H. and Gobel, E. O. (1994). "Ultrafast field-induced dissociation of excitons in conjugated polymers." Physical Review Letters **73**(10): 1440-3.

Kloc, C., Simpkins, P. G., Siegrist, T. and Laudise, R. A. (1997). "Physical vapor growth of centimeter-sized crystals of alpha -hexathiophene." Journal of Crystal Growth **182**(3-4): 416-27.

Lampert, M. A. and Mark, P. (1970). Current injection in solid, Academic Press.

Langevin, P. (1903). Annales de Chimie et de Physique **28**: 289.

Lide, D. R., Ed. (1994). CRC handbook of Chemistry and Physics.

Mark, P. and Helfrich, W. (1962). Journal of Applied Physics **33**: 205.

Mott, N. F. and Davis, E. A. (1969). Electronic Processes in Nanocrystalline Materials. Oxford, Clarendon Press.

Mott, N. F. and Gurney, R. W. (1940). Electronic Processes in Ionic Crystals. New York, Dover Publications.

Parker, I. D. (1994). "Carrier tunneling and device characteristics in polymer light-emitting diodes." Journal of Applied Physics **75**(3): 1656-66.

Press, W. H. (1992). Numerical Recipes in C : the art of scientific computing, Cambridge University Press.

Rikken, G., Braun, D., Staring, E. G. J. and Demandt, R. (1994). "Schottky effect at a metal-polymer interface." Applied Physics Letters **65**(2): 219-21.

Roth, S. (1991). Hopping Transport in Solids. M. Pollak and B. Shklovskii.

Sanjai, B., Raghunathan, A., Natarajan, T. S., Rangarajan, G., Thomas, S., Prabhakaran, P. V. and Venkatachalam, S. (1997). "Charge transport and magnetic properties in polyaniline doped with methane sulphonic acid and polyaniline-polyurethane blend." Physical Review B-Condensed Matter **55**(16): 10734-44.

Schön, J. H., Kloc, C., Dodabalapur, A. and Batlogg, B. (2000). "An organic solid state injection laser." Science **289**(5479): 599-601.

Scott, J. C., Karg, S. and Carter, S. A. (1997). "Bipolar charge and current distributions in organic light-emitting diodes." Journal of Applied Physics **82**(3): 1454-60.

Sharma, B. L., Ed. (1984). Metal-Semiconductor Schottky Barrier Functions and Their Applications. New York, Plenum Press.

Sheng, P. (1980). "Fluctuation-induced tunneling conduction in disordered materials." Physical Review B **21**(6): 2180-2195.

Sze, S. M. (1981). Physics of semiconductor devices, Wiley.

Tsutsui, T. and Saito, S. (1993). Intrinsically Conducting Polymers : An Emerging Technology. NATO ASI Series E : Applied Sciences. M. Aldissi. **246**.

Van Roey, J., van der Donk, J. and Lagasse, P. E. (1981). "Beam-propagation method: analysis and assessment." Journal of the Optical Society of America **71**(7): 803-10.

Venebles, J. A. (2000). Introduction to surface and thin film processes, Cambridge University Press.

Wilson, J. S., Dhoot, A. S., Seeley, A., Khan, M. S., Kohler, A. and Friend, R. H. (2001). "Spin-dependent exciton formation in pi-conjugated compounds." Nature **413**(6858): 828-31.

Wittmann, H. F., Friend, R. H., Khan, M. S. and Lewis, J. (1994). "Optical spectroscopy of platinum and palladium containing poly-ynes." Journal of Chemical Physics **101**(4): 2693-8.

Yevick, D. (1994). "A guide to electric field propagation techniques for guided-wave optics." Optical & Quantum Electronics **26**(3): S185-97.

Zallen, R. (1983). The physics of amorphous solids. New York, Wiley.

Chapter 7

DISCUSSION OF PROSPECTS FOR POLYMERIC LASING

7.1 Review of Research carried out in this Thesis

The basic aim of this thesis has been to design and construct an organic waveguiding double hetero-structure device. A considerable catalogue of information, about the properties of the organic materials, was required to do this. Namely, information on the refractive index, excited state absorption and charge transport properties was built up in the course of the thesis so that the device design and fabrication procedure could be carried out. The highlights of these measurements will now be summarised in brief before the problems, and their possible solutions, of creating a polymeric laser are considered.

7.1.1 Refractive Index Measurement

The ordinary refractive index has been measured for all of the conjugated polymers studied in this thesis. The values obtained for the χ^2 statistic from the fitting of the simple Cauchy models to the data was not low enough to consider the models statistically valid. Despite this, the modelled film thickness agreed very well with the profilometry results and the realistic values obtained for the refractive index were obtained. This implies that the samples could be modelled accurately using a homogeneous isotropic Cauchy model. The discrepancy between the modelling of the data with an isotropic Cauchy model is believed to be due to experimental artefacts, which cannot be conveniently incorporated into the model. Only the PmPV films were thick enough to resolve uniaxial anisotropy within the films. The ordinary and extraordinary refractive indices were measured for this polymer. The uniaxial model fit to the data for this polymer had similar values of the χ^2 statistic to the isotropic models applied to the other polymers.

The modelling of the PmPV nanotube composite data produced somewhat ambiguous results. It was observed that the addition of nanotubes increased both the refractive index and absorption of the composite films. These results make the composite less attractive as a material for waveguiding applications, although further measurements need to be taken with lower nanotube

concentrations. It is unlikely that a guiding layer, made from composite, of high enough refractive index and low enough absorption could be prepared to make a low loss waveguide. The presence of high levels of absorption in the composites increases the propagation loss within a waveguide. However, a composite made from low nanotube concentration could be a useful candidate for an electron transporting cladding layer.

7.1.2 Excited State Absorption of Polymers

The measurement of the excited state absorption of the series of conjugated polymers highlights a fundamental problem in creating an electrically pumped CW polymer laser. The strategy of creating polymers with greater disorder and large side-groups, to prevent inter-chain species formation is a very effective way of increasing the PL quantum yield. However, care needs to be taken with the choice of side-groups, as diphenyl-substituted polymers tend to promote inter-chain species formation as was seen with the DPOP-PPV case study. Disordered materials are generally excellent candidates for optically pumped lasing. However, materials for an electrically pumped device will need to satisfy further criteria than just, a high PL yield and low inter-chain species formation. The doping induced absorption measurements suggest that more rigid, crystalline materials would prove to be more suitable for electrically pumped devices. For such a strategy to be successful steps would need to be taken to prevent inter-chain species decreasing the stimulated emission cross-section. This could be achieved if the materials were packed close enough to each other, so that the probability of interchain recombination is similar to that of intra-chain recombination.

While the doping induced absorption measurements of this thesis have provided a useful qualitative study of the materials, further measurements need to be performed. A complete PA spectroscopy study should be carried out on these materials to obtain more accurate polaron absorption cross-sections, so that the Förster radius of aggregated and disordered polymers can be compared. In addition, a further PA study on materials of different degrees

of order should be carried out, to ascertain the degree of polymer crystallinity needed to remove the strong lattice relaxation associated with polarons.

7.1.3 Waveguide design and Hetero-structure Emission

The electrical properties of the conjugated polymers under study in this thesis have been measured using single layer unipolar device structures. Waveguide simulations were carried out in order to minimise the optical propagation losses within double hetero-structure waveguide devices. The simulations show that low loss double hetero-structure waveguide structures can be made with guiding layers of thickness $\sim 0.5\mu\text{m}$ and cladding layers of thickness $\geq 0.5\mu\text{m}$. However, for a polymer layer of thickness $\sim 0.5\mu\text{m}$, the values obtained for the carrier mobility prohibit the current densities necessary to obtain light emission. Nevertheless, light emission can be obtained from layers of thickness of the order 100nm. Only high loss double hetero-structure waveguide devices can be fabricated from layers of this thickness. A high loss double hetero-structure waveguide device was fabricated from PEDOT, HT73 and Alq_3 . The emission characteristics of this device have been shown to follow quite closely to the simulated behaviour of such a device, however the optical loss from these structures is still of the order of 1000cm^{-1} . This prevents the possibility of observing stimulated emission from these devices. Materials of greater mobility are needed to allow this approach to be successful.

7.2 Problems to be overcome

This work has highlighted three significant problems with conjugated polymers, which must be overcome if an electrically pumped waveguiding double hetero-structure type laser is to be developed. The first of these is the practical issue of solvent orthogonality, which considerably influenced the range of possible materials that could be used in devices. The second is the issue of absorption due to polarons. Finally, the issue of low carrier mobility in polymers was a major hindrance in developing a low loss waveguide structure.

7.2.1 Solvent Orthogonality

Throughout this work, the difficulty of solvent orthogonality has been a great hindrance to investigating device structures with various materials. For polymeric materials, the only film formation technique used was that of spin casting from solution. This places many restrictions on what materials may be used in multilayered devices. Most of the materials studied here have similar solvency characteristics, as they were all synthesised in similar solvents.

This raises the issue of producing similar materials with orthogonal solvency with the same or better opto-electronic properties. A standard system whereby specific solvency could be assigned to materials of a specific charge transport type would be very valuable for making multi-layered devices. However, this is not a practical change as the physical properties of these polymers are very sensitive to the solvent environment in which they are synthesised. For such a system to be adopted decreases in polymer purity, quantum efficiency and trap densities would have to be accepted.

From this situation, it can easily be seen that different deposition techniques that decouple the effect of material solvency from the device configurations need to be explored. This would facilitate a richer array of possible device configurations to be fabricated and characterised.

7.2.2 Polaron Absorption

Sub-bandgap absorption and exciton annihilation due to polarons formed from free charge carriers in the polymer remains the greatest obstacle to electrically pumped polymeric lasing. Until this problem has been rectified, the effective stimulated emission cross-section will be less than zero resulting in net absorption, no matter what device configuration is chosen.

The reason why polaron absorption is a problem is because when a charge is placed on the polymer chain a local lattice deformation occurs, resulting in an absorption red-shifted from the bandedge. Consequently, the polaron

absorption is in a similar spectral region as the fluorescent emission and the emission from the excitons is quenched by energy transfer processes.

Clearly, this must be addressed by either changing device architecture, to separate polarons and excitons, or by a fundamental change of the emissive material to shift the polaron absorption away from the spectral region of the gain.

7.2.3 Low Carrier Mobility

The low intrinsic carrier mobility of both electrons and holes in conjugated polymers was a major hindrance in this work for the development of low loss waveguide devices. The carrier mobilities ($\leq 10^{-7} \text{cm}^2 \text{V}^{-1} \text{s}^{-1}$) have been shown to be orders of magnitude too low to obtain lasing using this type of method. Ideally, the carrier mobility should be in the region of 10^{-2} - $10^2 \text{cm}^2 \text{V}^{-1} \text{s}^{-1}$ for the approach of making waveguiding double hetero-structures to be successful. There are essentially three reasons why the carrier mobility is so low in conjugated polymers:- 1. Distribution of conjugation lengths 2. Trapping on chemical impurities and 3. Self-trapping of charges on polymer chains.

When a charge is added to a polymer chain, it tends to seek out a region of longer conjugation length where the energy of the charge is reduced. This results in the trapping of the charge on chain segments of long conjugation length. The carrier mobility is then influenced by the charge hopping from site to site. This gives rise to carrier mobility, which is very low in comparison to the carrier mobility of ordered crystals where such trapping sites are much less likely to occur.

Trapping sites due to impurities and imperfections in the polymer lattice may also contribute to the low mobility in these materials. These sites are caused by side reactions, and the presence of dangling hydrogen bonds caused by imperfections during the chemical synthesis. In principle, such problems can be tackled in the chemistry lab. However problems are likely to exist in such

macromolecular chemistry are inevitable when reactions are scaled up to an industrial level. Some progress has been made with using ladder polymers, where the chemical imperfections have a less detrimental effect on the electrical properties of the polymer. It has been shown that for these polymers, a charge travelling along the chain has two possible conduction routes, along the two strands of conjugation. This can then give rise to the possibility of the charge bypassing a chemical defect on the chain (*Mizes and Conwell*).

Even well ordered pure polymers, where there are no trapping sites, will tend to have lower carrier mobility than ordered crystals. This is due to the formation of polarons. When the charge is added to the chain the lattice relaxes around the charge, resulting in the charge becoming self-localised or self-trapped. Consequently, the self-trapping of charge results in low intrinsic carrier mobility for these polaron species travelling along the polymer backbone. This results in a tendency of these species to accumulate in regions of space charge for the duration of the polaron lifetime.

7.3 Suggestions for future research

The main obstacles to the demonstration of a polymer laser have now been established. The issues of polymer solvency, polaron absorption and low intrinsic carrier mobility must be tackled, for the possibility of a polymer laser to be translated into a working device. There are three possible experimental ways of achieving this:- 1. New film deposition techniques. 2. Modified device structures. 3. The development of novel materials.

7.3.1 Deposition Techniques

The incorporation of two new deposition techniques into the research strategy outlined in this thesis could overcome the problem of the lack of polymers with orthogonal solvency. These techniques are briefly discussed here from the point of view of organic film deposition. Both techniques

remove the need for an existing polymer or small molecule film to be exposed to a solvent and so prevents the degradation of such precursor films.

7.3.1.1 MAPLE

The technique of MAPLE (*Piqué et al.*) (Matrix Assisted Pulsed Laser Evaporation) is a new technique, which has recently been developed by the Naval Research Laboratory in Washington DC. MAPLE can produce high quality polymeric, organic and biomaterial films on various substrates, without the need for solvent contact with the substrate.

The technique consists of freezing a polymeric solution of 1% w/v, in a Teflon container, in liquid nitrogen. The Teflon container is then used as a target in a conventional Pulsed Laser Evaporation set up (see Figure 7.1). The target is rotated throughout this procedure to prevent undue damage due to excessive heating.

Polymeric films have been produced without any noticeable changes in the chemical structure (seen from FTIR spectra) provided the correct solvent has been employed as the matrix (usually a non-chlorinated solvent (*Bubb et al.*)). This technique could easily be used to produce high quality multi-layered devices made from materials of the same solvency characteristics. This technique, while more complicated than spin casting, would be considerably

Figure 7.1 Experimental Setup for Maple Deposition Technique. A UV laser pulse evaporates a frozen polymer solution from a rotating target. The evaporated polymer then diffuses onto the substrate, while the solvent is pumped away. (Copied from the Industrial Physicist, 6, 5 pg.20)

easier to implement than the epitaxial techniques used in the inorganic industry. This may retain a strategic manufacturing advantage for polymeric materials over their inorganic counterparts.

Before applying this technique to device fabrication a detailed comparison between devices fabricated from the MAPLE method and the conventional spincoating method would need to be carried out. The optical, excited state and electrical properties of samples prepared using the MAPLE method would have to be comparable or better than conventional techniques for this method to be of use.

7.3.1.2 Crystal and Epitaxial Film Growth

Inorganic devices are generally made from crystals of GaAs or InGaN. This gives rise to many of the advantages that inorganic materials currently hold over organic materials, such as high mobility and low trap densities.

The fact that inorganic devices are based on materials incorporating a well-defined crystal structure means that species within experiences an ordered, periodic structure. Within this lattice there is a much larger steric hindrance to lattice deformation than there is in their organic counterparts. Polaron absorption is not very different from the ground state absorption band of the material, as the polaron energy levels do not shift very far from the HOMO and LUMO bands. Moreover, the effect of self-trapping is very much reduced and the charge motion is governed by band theory. This means that the mobility is not strongly affected by the lattice deformation.

Despite the recent controversy surrounding the work of *Schön et al.*, the use of molecularly grown organic crystals remains the most likely way of obtaining large, balanced carrier mobilities within organic structures. However, this is merely the first step to opening up possibilities for many new and exciting application and research activities on organic materials. To truly unleash the potential of organic materials it will be necessary to grow

controlled thin film, crystal devices. By modifying the technique of *Kloc et al.*, where the crystal is grown on a heated seed substrate such as HPOG, it may be possible to epitaxially grow single crystal thin films to any desired thickness. If such a technique were to work, it would revolutionise the field of organic devices. It should be noted that although this removes one of the main advantages organics hold over inorganics, i.e. cheap film formation, organics retain other advantages over inorganics such as tunability, and low dielectric constant.

The fabrication of an optimised double hetero-structure organic waveguiding device using this deposition technique would have an excellent chance of overcoming the problems associated with *Schön's* devices. It is quite likely that should such devices could easily be implemented in commercial applications, as the preparation techniques are similar to those currently used in the opto-electronic industry.

7.3.2 Device Structures to circumvent polaron absorption

Some Fabrication procedures, which could be used to overcome the problems associated with developing an electrically pumped device, have been discussed. However, it is possible that by changing the device structure, to spatially decouple the polarons from the emissive excitons within the device, so an all-polymer electrically powered laser device could be prepared.

By preparing an inert substrate (e.g mica) with a highly emissive blue OLED (e.g PFO) on one side and a channel waveguide made with a polymer of high quantum efficiency, which becomes the laser medium (see Figure 7.2). This is analogous to the diode pumped YAG lasers that are commonly used in research labs and the communications industry. The PFO LED can be prepared in a small area, long stripe configuration in order to obtain a large emission brightness as small area devices can display large brightnesses due to less quenching of emission by thermal effects (*Wilkinson et al.*). The stripe forming the LED must be collinear with the channel waveguide containing the laser material. By using a thin mica substrate, it can be ensured that the

Figure 7.2 Schematic showing the proposed device structure for a small area diode pumped channel waveguide; a possible structure to achieve an all-polymer laser device using current materials.

pumping efficiency is large enough so that a large percentage of the emitting excitons in the LED result in an exciton being formed in the channel waveguide. Low loss waveguides ($\sim 0.2\text{dB/cm}$) can be prepared in the channel waveguide configuration, in order to create a low threshold laser device, due to the low optical losses.

The great advantage of this device is that, during operation a minimum of polarons are formed in the laser material. Optical pumping experiments have shown that it is possible to obtain lasing from polymer films. The key to obtaining a working device will undoubtedly be in ensuring sufficient brightness can be obtained from the OLED. The maximum current density obtained by *Wilkinson et al.* in the small area devices was 5.1MA/cm^2 , with an estimated device efficiency of 8%. This means that the peak emitted photon flux is $\sim 10^{24}\text{photons/m}^2\cdot\text{s}$. However, most polymer planar waveguides that exhibit lasing, have a threshold in the region of 0.1J (10ns pulse focussed to an area of $\sim 1.5\text{mm}^2$) (*Diaz-Garcia et al.*), which corresponds to a photon flux of $\sim 10^{25}\text{photons/m}^2\cdot\text{s}$. The threshold photon flux is an order of magnitude greater than that supplied by the small area OLED. However, optimisation of this structure, using charge transport layers to increase the emission from the OLED and channel waveguide structures to

lower the threshold, could make it feasible for lasing to be obtained from such a device.

7.3.3 Design of future polymers

For a polymeric laser to operate, by the direct injection of charge into the laser medium, significant alterations need to be made to the behaviour of the polymeric system. The key difficulty with polymers is that when charge is placed on the chain, it becomes trapped, due to a combination of lattice relaxation and disorder effects. Materials will need to be chemically designed to prevent this from happening.

The solution to this problem is to design polymers, which possess increased stiffness compared to the current PPV type polymers. Ladder polymers provide a clue as to how this may be achieved. The incorporation of the bridge connecting two benzene rings acts to make this polymer a more rigid planar structure than single strand PPV derivatives. If a more complex cage structure were formed from a number of these planar structures, arranged around the axis of the polymer backbone, a structure of considerable order and rigidity could be formed. Such a material would also have multiple strands of conjugation along the polymer backbone, reducing further the effect of chemical defects on the conduction of charge along the polymer. A charge added to this polymer, would have a decreased effect on the bond order of this polymer (since there are more atoms per repeat unit) and the lattice relaxation should be considerably reduced. As a result, this material should retain increased carrier mobility and blue shifted polaron absorption, making it more suitable to be a laser material for an electrically pumped device.

The fabrication of such a material will most likely present considerable difficulties. However, this is the most likely way that the obstacles currently preventing polymers being used in an electrically pumped laser can be overcome. As a result, some consideration should be given to the preparation of this type of material, or a similar material displaying increased order and rigidity.

7.4 Conclusions

It is a dangerous practice to make predictions as to the likelihood, or lack thereof, of fabricating a polymeric laser in the future. The history of science is littered with predictions claiming a certain advance is impossible, only for that very advance to be achieved thereafter. In the case of conjugated polymers, it can be said that it is unlikely that an electrically pumped polymer can be achieved with the materials currently available. This work has shown that to fabricate a polymer laser using a waveguiding double hetero-structure a wide range of properties such as the refractive index, conductivity, mobility, stimulated emission, and excited state absorption need to be determined. It is also of great importance that a range of materials be available to tune these properties so that effective device structures can be designed.

Chemical engineering of the excited state absorption and emission bands to prevent overlap is of key importance in the development of a future laser device. A possible strategy, for the development of more rigid polymeric structures has been suggested as a solution to this problem along with the problem of low intrinsic carrier mobility experienced by current PPV derivatives. The development of an injection polymer laser remains a long-term project. Central to this development process must be the determination of structure-property relationships for material. A strong interaction between the design (numerical modelling), synthesis (chemistry) and characterisation (physics) and device design (engineering) processes is therefore extremely important. Similar global research strategies to that outlined in this thesis must be pursued, in order to change the dream of a polymer laser into reality.

The pessimistic reader (or writer!) should remind himself that only six years ago it was believed that optically pumped lasing in PPV was impossible and that no conjugated polymer could survive a current density of $\sim \text{kA}/\text{cm}^2$. It should be noted that during the lifetime of this thesis advancements in the synthesis of conjugated polymers has facilitated the attainment of these goals.

References

- Bubb, D. M., P.K., W., Horowitz, J. S., Callahan, J. H., Galicia, M., Vertes, A., McGill, R. A., Houser, E. J., Ringeisen, B. R. and Chrisey, D. B. (2002). "The effect of the matrix on film properties in matrix-assisted pulsed laser evaporation." Journal of Applied Physics **91**(4): 2055-8.
- Diaz-Garcia, M. A., Hide, F., Schwartz, B. J., McGehee, M. D., Andersson, M. R. and Heeger, A. J. (1997). ""Plastic" lasers: comparison of gain narrowing with a soluble semiconducting polymer in waveguides and microcavities." Applied Physics Letters **70**(24): 3191-3.
- Kloc, C., Simpkins, P. G., Siegrist, T. and Laudise, R. A. (1997). "Physical vapor growth of centimeter-sized crystals of alpha -hexathiophene." Journal of Crystal Growth **182**(3-4): 416-27.
- Mizes, H. and Conwell, E. (1991). "Conduction in ladder polymers." Physical Review B-Condensed Matter **44**(8): 3963-9.
- Piqué, A., McGill, R. A. and Chrisey, D. B. (2000). "A new way to Deposit Organic Thin Films." The Industrial Physicist **6**(5): 20-3.
- Schön, J. H., Kloc, C., Dodabalapur, A. and Batlogg, B. (2000). "An organic solid state injection laser." Science **289**(5479): 599-601.
- Wilkinson, C. I., Lidzey, D. G., Palilis, L. C., Fletcher, R. B., Martin, S. J., Wang, X. H. and Bradley, D. D. C. (2001). "Enhanced performance of pulse driven small area polyfluorene light emitting diodes." Applied Physics Letters **79**(2): 171-3.

APPENDIX I – PROGRAM FOR MODELLING OF ELLIPSOMETRY RESULTS AND NONLINEAR REGRESSION

In chapter 4, reference was made to the modelling program that was developed in order to fit various different optical models to the ellipsometry data. Due to length restrictions, the program listing has not been included here. Instead, a flow chart is shown outlining the main points involved in the coding of the program. A full version of the program listing is available for download at <http://www.eircom.net/~beltoncr>.

Since the nonlinear regression technique used for this program has also been used for the majority of the data analysis in this thesis, the key points of the Levenberg Marquardt algorithm are also outlined.

The Ellipsometry Modelling Program

The modelling program that is used for the analysis of the ellipsometry data uses the Levenberg Marquardt algorithm `mrqmin()` as the primary element for the fitting of the data. The program opens various user-edited files to obtain starting parameters for the regression function, experimental data and display settings. The program then manages these parameters through the fitting process, under the supervision of the user, and then saves a copy of the final parameters, and the fitted data set when the model is optimised.

The `main()` (see flow chart) function offers the user the choice between regression on experimental data or modelling of a given structure with a specific optical model. The modelling function is not reviewed here as it is only of use at a preliminary stage of data analysis, and has little bearing on the data analysis used in this thesis.

The `regression()` (see flowchart) function, is used to read in the data set to be modelled and the initial parameters for the model, along with various details about the structure of the sample, which is treated as a layered stack of different materials. Most of these materials have known optical constants, which are read (using functions such as `readmaterialfile()`) into a Matrix N, of size number of data points (`ndata`) by number of layers in the stack (`nlayers`). If a layer is unknown and is to be replaced, as an optical model, the positions in N are left blank and an integer of the layer number is retained for later use. The parameters are all arranged in a suitable vector for `mrqmin()` and are sent along with N to the `do_regression()` function.

The `do_regression()` function is essentially a loop type structure, which allows the `mrqmin()` function to iterate. During each iteration, the current parameters are displayed to `<stdout>` and a graph of the experimental data and the current fit, along with the optical constants, are displayed using `gnuplot`. This function also manages the display settings for the `gnuplot` program. (NOTE the `gnuplot` program must be installed on the operating system for the program to display results.)

The operation of the `mrqmin()` and `mrqcof()` functions are described in detail in the next section. These functions require that the model values and the partial derivatives with respect to the parameters be known at all wavelengths. This is carried out by the function `funcs()`. The actual values of $Tan\psi$ and $Cos\Delta$ are calculated from the current set of parameters by the twin functions `func_val_tp()` and `func_val_cd()`. These functions calculate values for the optical constants at the current parameter values and fill in the blank space left in the matrix N for model layers. The matrix N is then used to calculate the reflection coefficients at the interface of each layer. The value for $Tan\psi$ and $Cos\Delta$ can then be determined iteratively using equation 4.23 with the values being returned to `funcs()`.

Flow Chart of Ellipsometry Program

Extracting Parameters by using Curve fitting

In the previous section the twin functions `mrqmin()` and `mrqcof()` were mentioned as integral parts of the ellipsometry modelling program. In fact, these functions have been used to extract model parameters from all of the modelling in this thesis. Consequently, the algorithm and the functions themselves will now be reviewed in detail.

Non-linear Modelling of Data

Given a set of observations y_i , the data is condensed and summarised by fitting it to a “model” that depends on adjustable parameters. The model can

be merely a convenient class of functions, such as the series of Gaussians fitted to the polaron absorption data in section 5.4, and the fit supplies the appropriate coefficients. Other times, the model's parameters come from some underlying physical theory that should describe the data e.g the straight line fits to log-log IV plots of unipolar devices.

The basic approach in all cases is usually the same: A *figure-of-merit function* is chosen as a measure of the agreement between the data and the model with a particular choice of parameters. The merit function should be arranged so that small values represent close agreement. The merit function should also contain some way of comparing the deviation of the model from the data to the experimental noise present in the data. An example is the merit function (equation 4.71) chosen for fitting the ellipsometry data.

The merit function can then be minimized with respect to the parameters of the model, yielding the *best-fit parameters*. This process is thus a problem of minimization in many dimensions. When this has been achieved it is also necessary to establish the accuracy with which the parameters are determined by the data set.

The fitting procedure used in this work is the Levenberg-Marquardt non-linear least squares fitting routine from Numerical Recipes in C : the art of scientific computing by Press. This is robust fitting technique that returns:-

- The Parameters.
- The Covariance Matrix.
- The value of the minimised merit function.

Consider the fitting of a model that depends *nonlinearly* on the set of M unknown parameters a_k where $k=1, 2, \dots, M$. A χ^2 merit function is defined and the best-fit parameters are determined by its minimisation. With

nonlinear dependences, this minimization process must be carried out iteratively. This means that given trial values for the parameters, the fitting procedure returns a parameter set that improves the fit. These improved parameters are then become the trial parameter set for the next iteration of the fitting routine. The procedure is then repeated until χ^2 stops (or effectively stops) decreasing.

If the trial parameters are sufficiently close to the minimum, the χ^2 function can be expected to be locally well approximated by a quadratic form:-

$$\chi^2 \approx \gamma - d \cdot a + \frac{1}{2} a \cdot D \cdot a \quad [\text{AI.1}]$$

where d is an M -vector and D is an $M \times M$ matrix. In this case, the minimised parameters, $a_{\min}$, can be expressed simply in terms of the current trial parameters, a_{curr} :-

$$a_{\min} = a_{\text{curr}} + D^{-1} \cdot [-\nabla \chi^2(a_{\text{curr}})] \quad [\text{AI.2}]$$

This method is known as the *inverse-Hessian* method.

However, if the trial parameters are not close to the minimum the quadratic form is likely to be a poor approximation to the shape of the χ^2 function that is being minimised at a_{curr} . In this case, all that can be achieved is to take a step down the gradient, as in the *method of steepest descent*:-

$$a_{\text{next}} = a_{\text{cur}} - \text{Const} \times \nabla \chi^2(a_{\text{cur}}) \quad [\text{AI.3}]$$

where the constant is small enough not to exhaust the downhill direction.

In order to use these two minimization methods, it must be possible to determine:-

- The gradient of the χ^2 function

➤ The matrix D , which is the second derivative matrix (*Hessian matrix*) of the χ^2 merit function

at any set of parameters a .

The strategy for minimization will then be as follows:-

- For a set of trial parameters evaluate the gradient of χ^2 and the matrix. D .
- Use the inverse Hessian method of to improve the fit
- If this fails to improve the fit use the method of steepest descent
- Set the parameters of the improved fit as the trial parameters and repeat the process.

The key calculations to be carried out here are the evaluation of the gradient of χ^2 and the Hessian matrix D .

Calculation of the Gradient and Hessian

The model to be fitted is given by some user supplied function:-

$$y = y(x; a) \quad [\text{AI.4}]$$

This means that the χ^2 merit function is of the form:-

$$\chi^2(a) = \sum_{i=1}^N \left[\frac{y_i - y(x_i; a)}{\sigma_i} \right]^2 \quad [\text{AI.5}]$$

The components of the gradient of χ^2 with respect to the parameters a are:-

$$\frac{\partial \chi^2}{\partial a_k} = -2 \sum_{i=1}^N \frac{[y_i - y(x_i; a)]}{\sigma_i^2} \frac{\partial y(x_i; a)}{\partial a_k} \quad [\text{AI.6}]$$

where $k=1, 2, \dots, M$. Note that each term of the gradient will be equal to zero at the χ^2 minimum. Taking a further partial derivative gives:-

$$\frac{\partial^2 \chi^2}{\partial a_k \partial a_l} = -2 \sum_{i=1}^N \frac{1}{\sigma_i^2} \left[\frac{\partial y(x_i; a)}{\partial a_k} \frac{\partial y(x_i; a)}{\partial a_l} - [y_i - y(x_i; a)] \frac{\partial^2 y(x_i; a)}{\partial a_k \partial a_l} \right] \quad [\text{AI.7}]$$

The equations for minimisation by the quadratic approximation and the method of steepest descent can then be rewritten, in terms of $\delta a_l = a_{\min} - a_{\text{curr}}$, as the set of linear equations:-

$$\sum_{l=1}^M \alpha_{kl} \delta a_l = \beta_k \quad [\text{AI.8}]$$

for minimisation by the inverse Hessian method (equation AI.2), and:-

$$\delta a_l = \kappa \times \beta_l \quad [\text{AI.9}]$$

which is the the steepest descent formula with κ as a constant (equation AI.3).

Here α_{kl} and β_k are shorthand for the terms:-

$$\beta_k = -\frac{1}{2} \frac{\partial \chi^2}{\partial a_k} \quad \text{and} \quad \alpha_{kl} = \frac{1}{2} \frac{\partial^2 \chi^2}{\partial a_k \partial a_l} \quad [\text{AI.10}]$$

In the context of the least-squares procedure, the matrix $[\alpha]$, equal to one-half times the Hessian matrix, is usually called the *curvature matrix*. The components α_{kl} of the Hessian matrix depends on both the first derivatives and the second derivatives of the basis functions with respect to their parameters (see equation AI.7).

The second derivatives occur because the gradient already has a dependence on $\partial y / \partial a_k$, so the next derivative simply must contain terms involving $\partial^2 y / \partial a_l \partial a_k$. The second derivative term can be dismissed when it is zero, or small enough to be negligible when compared to the term involving the first derivative. It also has an additional possibility of being ignorably small in

practice. This is because the term multiplying the second derivative is $[y_i - y(x_i; a)]$, which, for a successful model, should just be the random measurement error of each point. This error should have an equal distribution of positive and negative signs, over the range of where the model is being fitted. Consequently, the second derivative terms tend to cancel out when summed over i . Indeed inclusion of the second-derivative term in equation AI.7 can be destabilising if the model fits badly or is contaminated by outlier points that are unlikely to be offset by compensating points of opposite sign. Therefore the definition of α_{kl} used from here on is given by the formula:-

$$\alpha_{kl} = \sum_{i=1}^N \frac{1}{\sigma_i^2} \left[\frac{\partial y(x_i; a)}{\partial a_k} \frac{\partial y(x_i; a)}{\partial a_l} \right] \quad \text{[AI.11]}$$

It should be noted that minor (or even major) changes to $[\alpha]$ has no effect on the final set of parameters a that is reached, but affects only the iterative route that is taken in getting there. The condition that $\beta_k=0$ at the χ^2 minimum, for all k , is independent of how $[\alpha]$ is defined.

Levenberg-Marquardt Method

Marquardt presented an elegant method, related to an earlier suggestion of Levenberg, for varying smoothly between the extremes of the inverse-Hessian method and the steepest descent method. As has been seen the steepest descent method is used far from the minimum, switching to the inverse-Hessian method as the minimum is approached. This *Levenberg-Marquardt method* (also called *Marquardt method*) works very well in practice and has become the standard of nonlinear least-squares routines.

The method is based on two elementary insights. Consider the “constant” in used in the steepest descent method (equation AI.3). There is no information about the necessary size of the constant κ . The slope of the function is

constantly varying. Equation AI.3 is only valid over the range, in which the slope is constant. This range is governed by the size of the constant κ . Marquardt's first insight is that the Hessian matrix gives some information about the order-of-magnitude over which the slope can be considered constant. As a result Marquardt incorporated the diagonal elements of this matrix into the the constant κ , which he put equal to $1/\lambda\alpha_{ii}$. This means that by setting $\lambda \gg 1$ it is possible to bring down the size of the step below the extent, which the slope is constant. This means that equation AI.9 is written as:-

$$\delta a_i = \frac{1}{\lambda\alpha_{ii}} \beta_i \quad \text{or} \quad \lambda\alpha_{ii}\delta a_i = \beta_i \quad [\text{AI.12}]$$

It is necessary that α_{ii} be positive, but this is guaranteed by definition (AI.11). Marquardt's second insight is that the inverse Hessian method (equation AI.8) and the steepest descent method (equation AI.9) can be combined if a new matrix α' is defined by the following prescription:-

$$\alpha'_{jj} = \alpha_{jj} (1 + \lambda) \quad [\text{AI.12}]$$

$$\alpha'_{jk} = \alpha_{jk} \quad \text{where} \quad j \neq k$$

and then replace both (equations AI.8 and AI.9) by

$$\sum_{i=1}^M \alpha'_{ki} \delta a_i = \beta_k \quad [\text{AI.14}]$$

When λ is very large, the matrix α' is forced into being *diagonally dominant*, so equation AI.14 becomes identical to equation AI.9. If λ approaches zero, equation AI.14 is the same as equation AI.8.

Given an initial guess for the set of fitted parameters a_k , the Marquardt recipe is then as follows:

- Compute $\chi^2(a)$.
- Pick a modest value for λ , say $\lambda = 0.001$.
- (*) Solve the linear equations AI.14 for δa and evaluate $\chi^2(a + \delta a)$.
- If $\chi^2(a + \delta a) \geq \chi^2(a)$, increase λ by a factor of 10 (or any other substantial factor) and go back to (*) and repeat.
- If $\chi^2(a + \delta a) < \chi^2(a)$, decrease λ by a factor of 10, update the trial solution $a \leftarrow a + \delta a$, and go back to (*) and repeat.

By definition a change in χ^2 by an amount $\ll 1$ is statistically meaningless. Throughout this work when a fit is being performed the procedure is stopped whenever a change in $\chi^2 < 10^{-4}$ occurs. The procedure can be susceptible to returning a local minimum when this criterion for stopping the fitting procedure is applied. For this reason the general practice is to perform the fitting procedure a few times from different initial conditions and ensuring that the same set of final parameters is returned. It is also of great importance that relatively simple models are applied, to the data, with a low number of free parameters. A model with a large number of free parameters usually results in a greater likelihood of local minima occurring and the process of eliminating these and it becomes deleteriously difficult to arrive at the true global minimum.

The numerical routines that are at the center of the fitting procedures in this work are the C functions supplied by the Numerical Recipes book. These functions are available for downloading along with the ellipsometry modeling program from the same web address.

To use the fitting functions the parameters must be arranged into the parameter vector $a[1..ma]$ along with the integer vector $ia[1..ma]$, which must

be input with components one or zero corresponding to whether the respective parameter values are to be fitted for or held fixed at their input values, respectively. The user must supply a function of the form $\text{funcs}(x, a, y, dyda)$, which for input values $x = x_i$ and $a = a$ calculates the model function $y = y(x_i; a)$ and the vector of derivatives $dyda = \partial y / \partial a_k$.

The routine `mrqmin`, which performs one iteration of Marquardt's method, should be placed in a suitable controlling loop. It is first called (once) with `alamda < 0`, which signals the routine to initialize. The variable `alamda` is then set on the first call and all subsequent calls to the suggested value of λ for the next iteration; `a` and `chisq` are always given back as the best parameters found so far. When convergence is deemed satisfactory, `alamda` is set to zero before a final call. The matrices `alpha` and `covar` (which were used as workspace in all previous calls) will then be set to the curvature and covariance matrices for the converged parameter values. The arguments `alpha`, `a`, and `chisq` must not be modified between calls, nor should `alamda` be, except to set it to zero for the final call. When an uphill step is taken, `chisq` and `a` are given back with their input (best) values, but `alamda` is set to an increased value. The routine `mrqmin` uses the routine `mrqcof` for the computation of the matrix $[\alpha]$ (equation AI.11) and vector β (equations AI.6 and AI.10).

be input with components one or zero corresponding to whether the respective parameter values are to be fitted for or held fixed at their input values, respectively. The user must supply a function of the form $\text{funcs}(x,a,y,\text{dyda})$, which for input values $x = x_i$ and $a = a$ calculates the model function $y = y(x_i; a)$ and the vector of derivatives $\text{dyda} = \partial y / \partial a_k$.

The routine `mrqmin`, which performs one iteration of Marquardt's method, should be placed in a suitable controlling loop. It is first called (once) with `alamda < 0`, which signals the routine to initialize. The variable `alamda` is then set on the first call and all subsequent calls to the suggested value of λ for the next iteration; `a` and `chisq` are always given back as the best parameters found so far. When convergence is deemed satisfactory, `alamda` is set to zero before a final call. The matrices `alpha` and `covar` (which were used as workspace in all previous calls) will then be set to the curvature and covariance matrices for the converged parameter values. The arguments `alpha`, `a`, and `chisq` must not be modified between calls, nor should `alamda` be, except to set it to zero for the final call. When an uphill step is taken, `chisq` and `a` are given back with their input (best) values, but `alamda` is set to an increased value. The routine `mrqmin` uses the routine `mrqcof` for the computation of the matrix $[\alpha]$ (equation AI.11) and vector β (equations AI.6 and AI.10).

APPENDIX II – ANALYSIS OF UNCERTAINTY

One of the most important aspects of data analysis is the reporting of the uncertainty in the measurement of parameters. There are two aspects to consider here:-

- The propagation of uncertainties due to calculation of parameters by the use of formulae
- The direct measurement of the uncertainty of a fit parameter

Propagation of Uncertainty

The formulae used in the calculation of parameters in this thesis are reasonably simple and so the propagation of the uncertainty through calculations is a relatively straightforward matter. Equations AII.1 and AII.2 show what the uncertainty, Δy , is for basic algebraic manipulations of experimentally measured parameters a and b with uncertainties Δa and Δb .

$$\text{If } y = a + b \text{ or } y = a - b \text{ then } \Delta y = \Delta a + \Delta b \quad [\text{AII.1}]$$

$$\text{If } y = a.b \text{ or } y = \frac{a}{b} \text{ then } \Delta y = y \left\{ \frac{\Delta a}{a} + \frac{\Delta b}{b} \right\} \quad [\text{AII.2}]$$

It is possible to use equations AII.1 and AII.2 to calculate the uncertainty in any of the formulae used in this thesis for calculation of a given parameter. The formulae for the uncertainty of each calculated parameter in this thesis is given in Table AII.1 along with the page number and equation number used to calculate the parameter.

Uncertainty of Fit Parameters

The extraction of the uncertainty of fit parameters is a relatively straightforward procedure. The curvature matrix contains the information on how much a given parameter affects the curve fit or inversely how accurately

Table AII.1 Table showing the uncertainties due to propagation of errors through formulae used to calculate certain parameters in this thesis. Also shown is the equation number of the formula used in the calculation and the page number that the result of the calculation was reported on. (Continued on next page.)

Uncertainty	Equation	Page	Comment
$\Delta n(\epsilon_c) = \Delta A + \frac{\Delta B}{\lambda_c^2} + \frac{\Delta C}{\lambda_c^4}$	4.61	116-119	λ_c is the Wavelength that corresponds to ϵ_c
$\Delta \gamma = \frac{\epsilon_s - \epsilon_{rel}}{\epsilon_s} \left\{ \frac{\Delta \epsilon_s + \Delta \epsilon_{rel}}{\epsilon_s - \epsilon_{rel}} + \frac{\Delta \epsilon_s}{\epsilon_s} \right\}$	5.11	167	—
$\Delta E_B = \frac{V_B}{d} \left\{ \frac{\Delta V_B}{V_B} + \frac{\Delta d}{d} \right\}$	—	219 & 223	E_B =Breakdown Field V_B =Breakdown Voltage d =device thickness
$\Delta A = l.w \left\{ \frac{\Delta l}{l} + \frac{\Delta w}{w} \right\}$	—	219 & 223	A =Device Area (l, w) l =length w =width
$\Delta n = \frac{9}{8} \frac{eV_o}{ed^2} \left\{ \frac{\Delta V_o}{V_o} + 2 \frac{\Delta d}{d} \right\}$	6.19 & 6.26	225	—
$\Delta \mu_o = \frac{10^I d}{en} \left\{ \Delta I \ln 10 + \frac{\Delta n}{n} + \frac{\Delta d}{d} \right\}$	6.19 & 6.26	225	I is the intercept
$\Delta \mu_{scic} = \frac{8}{9} \frac{10^I d^3}{e} \left\{ \Delta I \ln 10 + 3 \frac{\Delta d}{d} \right\}$	6.25	225	I is the intercept
$\Delta \sigma = 10^I d \left\{ \Delta I \ln 10 + \frac{\Delta d}{d} \right\}$	6.18	225	I is the intercept
$\Delta \eta_{int} = \frac{Le}{6.83Jhc \int_0^\infty \frac{E_F(z) - E_F(z)}{d\lambda} d\lambda} \left\{ \frac{\Delta L}{L} + \frac{\Delta J}{J} \right\}$	6.47	229	—
$\Delta A = \frac{E_i - E_\perp}{E_i} \left\{ \frac{\Delta E_i + \Delta E_\perp}{E_i - E_\perp} + \frac{\Delta E_i}{E_i} \right\}$	(see text)	230	Anisotropy

the data constrains the parameter. As a result, the covariance matrix is defined as the inverse of the curvature matrix. Once the acceptable minimum has been found, the condition $\lambda=0$ is set and the covariance matrix is given by:-

$$C = [\alpha]^{-1} \quad \text{[AII.3]}$$

The covariance matrix gives a measure of the standard errors in the fitted parameters a , with respect to each other. The elements of the covariance matrix are defined as:-

$$C_{kl} = \sigma_k \sigma_l \quad [\text{AII.4}]$$

By this definition, the standard error for each parameter, a_k , is given by the square root of the diagonal elements C_{kk} . It is this uncertainty that is quoted for fit parameters throughout this thesis.

APPENDIX III – LIST OF PUBLICATIONS

“Design and Fabrication of a Waveguiding Organic Double Heterostructure Light-Emitting Device - *A Milestone in the Development of an Electrically Pumped Polymer Laser*”, **Belton C.**, Toussaere E., Krantzilbinder G., Hörhold H-H., Blau W. J., (Accepted for publication in the proceedings of the SPIE OPTO-IRELAND conference in Galway September 2002).

“Spectroscopic Ellipsometry of a conjugated polymer nanotube composite”. **Belton C.**, Toussaere E., Krantzilbinder G., Drury A., Cadek M., Blau W. J., (To be Submitted.)

“Excited state inhibition of luminescence in DPOP-PPV”. **Belton C.**, O'Brien D., Cadby A. J., Lane P., Byrne H. J., Stockmann R., Hörhold H-H., Bradley D. D. C. and Blau W. J.. Synthetic Metals, vol.119, no.1-3, 15 March 2001, pp.567-8.

“Excited-state quenching of a highly luminescent conjugated polymer”. **Belton C.**, O'Brien DF, Blau W. J., Cadby A. J., Lane P. A., Bradley D. D. C., Byrne H.J., Stockmann R. and Hörhold H-H. Applied Physics Letters, vol.78, no.8, 19 Feb. 2001, pp.1059-61.

“Optical gain spectra from doped polymeric waveguides”. Kretsch K. P., **Belton C.**, Lipson S., Blau W. J., Henari F. Z., Pfeiffer S., Tillmann H., and Hörhold H-H. Synthetic Metals, vol.111-112, 1 June 2000, pp.567-70.

“Amplified spontaneous emission and optical gain spectra from stilbenoid and phenylene vinylene derivative model compounds”. Kretsch KP, **Belton C.**, Lipson S., Blau W. J., Henari F. Z. , Rost H., Pfeiffer S., Teuschel A., Tillman H., and Hörhold H-H. Journal of Applied Physics, vol.86, no.11, 1 Dec. 1999, pp.6155-9.